QUICK REFERENCE CARD

Camera Health Platform · Diagnose tab · Dashboard **http://<platform-PC>:5070**

DP WORLD

YOUR DAILY ROUTINE

1
08:45 PRE-CHECK
Console window open. Header grey, not "Server unreachable". Schedule: Next run = today.

2
09:00 RUN
Automatic. Watch the progress card. Press "Show new results" when finished.

3
TRIAGE
Show = Latest per camera · Verdict = No engineer verdict yet. Do No view first, then Worse than last check.

4
VERIFY
Open the picture, choose a verdict, add name + remark (ticket no.), Save.

5
REPORT
Latest per camera → Download report (PDF). Share. Awaiting verification = 0.

WHAT THE STATUSES MEAN

STATUS	USUALLY MEANS	FIRST ACTION
OK	Picture looks normal	Nothing
NO VIEW	No picture: power, cable, network, IP / port / path / password	Ping, Settings › Test capture now, ticket to network / maintenance
TOO DARK	Lights off, IR failed, night shot	Check lighting / IR; if expected → Normal, reason OK
OVEREXPOSED	Sun glare, exposure / iris fault	Check exposure settings, camera position
GREEN/BLUE/RED TINT	Colour fault, IR-cut filter, or a coloured object filling the view	Compare with earlier pictures; coloured object → Normal, OK
DIRTY / BLURRY LENS	Dust, salt, condensation, focus, or an old soft camera	Cleaning ticket; old unit → Normal, Old camera
PARTIAL OCCLUSION	Something covers part of the lens	Remove obstruction, check bracket

WHICH VERDICT?

YOU SEE...	CHOOSE
The problem is real	**Same as detected** + ticket
Fine; older / lower-quality camera	**Normal** › Old camera
Fine; scene caused it (colour, night, sun)	**Normal** › OK
A different real problem	**Normal** › that problem
Not sure	Test capture now / check on site

REMEMBER
Your verdict becomes this camera's baseline and is copied to similar future pictures. You can change it with Update verdict; the newest counts.

TAGS ON A CARD

AUTO-MATCHED	An engineer's earlier verdict was copied (engineer name "auto-match").
WORSE THAN LAST CHECK	Same problem as before but clearly worse. Look again.
detected:...	What the computer found, when a verdict changed the reported status.
Removed	Camera deleted in Settings; history kept.

TWO CONFIDENCE NUMBERS

Detection 50-99.9%	How obvious the problem is. ~60% borderline, 95%+ obvious. Not a probability.
Learned 68-99%	Trust in an automatic copy: 68, 77, 84, 88, 92 ... 99% with each repeat.

QUICK REFERENCE CARD

Filters, reports, cameras and fixes

DP WORLD

USEFUL FILTER COMBINATIONS

TO SEE...	SET
Today's to-do list	Show: Latest per camera · Verdict: No engineer verdict yet
Dead cameras	Show: Latest per camera · Status: No view
Getting worse	Verdict: Worse than last check
Most obvious first	Sort by: Detection confidence · Desc
One camera's history	Camera: … · Show: All inspections · Sort: Time
Check automatic copies	Verdict: Auto-matched · Learned conf. max 80
Last week	From / To (Dubai time)

REPORTS

- **One inspection:** Download report on its card.
- **Everything filtered:** Download report (PDF) in the filter bar (max 2,000 rows).
- **Hand-picked:** tick cards › Download selected as report (PDF).
- **Excel:** Export CSV (all fields, both statuses and confidences).

RUN DIAGNOSIS NOW

Diagnose tab › open **Run diagnosis now** › tick terminals or machines › **Diagnose N cameras**. A progress bar appears; **Stop** removes cameras not yet started.

CAMERAS (SETTINGS)

Add	Settings › Add camera. Required: Terminal, Machine, Camera, IP (add :port if not 554).
Many	Settings › Import from Excel › download template › fill › Import.
Test	Cameras list › Test capture now (result on the Diagnose tab).
Pause	Disable (or untick Daily inspection in Edit).
Remove	Delete keeps history. Re-adding same names re-links it.
Schedule	Settings › Schedule: start time, pause, cameras at once, which terminals, which detections.

QUICK FIXES

PROBLEM	TRY
Server unreachable	Start run.bat on the platform PC; keep the window open.
No results today	Schedule: Daily inspection on? Terminal ticked? PC asleep > 3 h after start? Use Run diagnosis now.
Whole terminal No view	Network issue: inform network team, re-run that terminal.
Same false alarm daily	Give a verdict (Old camera / OK).
A problem type never appears	Switched off? Schedule › Detections.
Wrong verdict saved	Update verdict and save again.
Report refused (too many)	Narrow filters: one terminal, dates, Latest per camera.

DO NOT

close the console window, let the PC sleep before the run, or delete inspections to tidy up — deleting removes pictures and engineer baselines for good.