

CODE

```
#include <Wire.h>

#include <LiquidCrystal_I2C.h>

LiquidCrystal_I2C lcd(0x27, 16, 2);

#define MQ3_PIN A0

#define BUZZER_PIN 5

#define RELAY_PIN 9

#define RED_LED 13

int alcoholthreshold = 400;

void setup() {

  pinMode(MQ3_PIN, INPUT);

  pinMode(BUZZER_PIN, OUTPUT);

  pinMode(RELAY_PIN, OUTPUT);

  pinMode(RED_LED, OUTPUT);

  digitalWrite(RELAY_PIN, HIGH);

  Serial.begin(9600);

  lcd.begin(16, 2);

  lcd.backlight();

  lcd.setCursor(0, 0);

  lcd.print("Alcohol System");

  lcd.setCursor(0, 1);

  lcd.print("Warming up...");

  delay(3000);

  lcd.clear();

}

void loop() {

  int value = analogRead(MQ3_PIN);
```

```
Serial.print("Alcohol level = ");

Serial.println(value);

lcd.setCursor(0, 0);

lcd.print("Level: ");

lcd.print(value);

lcd.print(" ");

if (value >= alcoholthreshold) {

digitalWrite(RELAY_PIN, LOW);

digitalWrite(BUZZER_PIN, HIGH);

digitalWrite(RED_LED, HIGH);

lcd.setCursor(0, 1);

lcd.print("Driver Drunk ");

Serial.println("Alcohol detected!");

}

else {

digitalWrite(RELAY_PIN, HIGH);

digitalWrite(BUZZER_PIN, LOW);

digitalWrite(RED_LED, LOW);

lcd.setCursor(0, 1);

lcd.print("Not Drunk ");

Serial.println("Safe condition");

}

delay(500);

}
```