

Interfacing buzzer to PIC18 Microcontroller to RB3 Port Pin:

```
#include <pic18f4520.h>

#pragma config OSC = HS      //Oscillator Selection
#pragma config WDT = OFF     //Disable Watchdog timer
#pragma config LVP = OFF     //Disable Low Voltage Programming
#pragma config PBADEN = OFF  //Disable PORTB Analog inputs

// Timer0 ISR Definition
void __interrupt () timer0_isr (void)
{
    TMROH = 0X85;           //Reload the timer values after overflow
    TMROL = 0XEE;
    PORTBbits.RB3 = ~PORTBbits.RB3; //Toggle the RB3
    INTCONbits.TMR0IF = 0;   //Reset the timer overflow interrupt flag }
}

// Start of main Program
void main()
{
    ADCON1 = 0x0F; //Configuring the PORTE pins as digital I/O
    TRISBbits.TRISB3 = 0; //Configuring the RB3 as output
    PORTBbits.RB3 = 0; //Setting the initial value
    TOCON = 0x02; //Set the timer to 16-bit,Fosc/4,1:16 pre-scaler
    TMROH = 0x85; //load timer value to generate delay 50 ms
    TMROL = 0xEE;
    INTCONbits.TMR0IF = 0; // Clear Timer0 overflow flag
    INTCONbits.TMR0IE = 1; // TMR0 interrupt enabled
    TOCONbits.TMR0ON = 1; // Start timer0
    INTCONbits.GIE = 1; // Global interrupt enabled
    while(1); //Program execution stays here until the timer overflow interrupt is generate
}
```

OUTPUT:

