






I2C ADDR(7bit): 0x34
U1
AXP2101
VBUS
VMID
VSYS
SW
BAT
BLDOIN
BLDO1
BLDO2
CPULDOS
DLDO1/DC1SW
DLDO2/DC4SW
VBackup
VRTC
PWROK
PWRON
GPIO1
TS
CHGLED
IRQ
SDA
SCL
GND
GND
VIN1
LX1
FB1
VIN2
LX2
FB2
VIN3
LX3
FB3
VIN4
LX4
FB4
ALDOIN
ALDO1
ALDO2
ALDO3
ALDO4
VREF
C1
10uF/10V
C2 2.2uF/10V
L1 WPN201610M1R0MT
C8 22uF 6.3V
C3 22uF 6.3V
C9 10uF/10V
L2 WPN201610M1R0MT
C10 2.2uF/10V
C14 2.2uF/10V
L3 WPN201610M1R0MT
C15 22uF 6.3V
C16 2.2uF/10V
C19 2.2uF/10V
C20 2.2uF/6.3V
R29 10K/1%
R30 10K/1%
R15 10K/1%
R1 2K/1%
R38 510R
R39 510R
C18 1nF/50V
C97 1nF/50V
C4 2.2uF/6.3V
C5 2.2uF/10V
C6 2.2uF/10V
C7 2.2uF/10V
C11 2.2uF/10V
C12 2.2uF/10V
C13 2.2uF/10V
C17 2.2uF/10V
D7 PTVSLC3D3V3B
D1 NC
D2 NC
LED1 RED
S1 SMT_SW_TS_015
S2 SMT_SW_TS_015
J5 PIN2 PIN1 SMT_HDR_2x1.25mm
VBUS
VDD_3V3
VDD_3V3_SD
VBAT
VDD_1V8
VDDA_3V3
VDDCAM_3V3
VCC_BL
VCC_3V3
RTC_VDD
DVDD
AVDD
AXP_PS
AXP_PG
AXP_CHG_LED
PWR_KEY
AXP_WAKEUP
BUS_OUT
I2C_SYS_SDA
I2C_SYS_SCL
I2C NEED REVERSED
GND



VDD_3V3
C21
2.2uF/10V
GND
R2
10K/1%
AXP_PG
C23
1uF/10V
D3
1N4148WS
R5
270K/1%
C22
10uF/10V
R3
680K/1%
D5
1N4148WS
R7
10K/1%
R8
10K/1%
U2
LMV331
R4
10K/1%
ESP_BOOT
LED2
GREEN
R10
2K/1%
USB_DU_N
R25
22R/1%
USB_D_N
USB_DU_P
R47
22R/1%
USB_D_P
VUSB
J1
VCC DP1
CC1 DP2
CC2 DN1
GNDDN2
SHELL
R6
5.1K/1%
R9
5.1K/1%
USB-TYPEC
D4
ESD5Z3V3
D6
ESD5Z3V3
J6
PIN4
PIN3
PIN2
PIN1
HDR4接插件-2MM
C123
22uF 6.3V
AXP_PS
L5
WPN3012H2R2MT
U3
LX
OUT
IN
FB
SGND
PGND
EN
SY7088
C24
22uF 6.3V
C25
22uF 6.3V
C26
22uF 6.3V
BUS_5V
R11
15K/1%
R12
4.7K/1%
R13
47R
R14
10K/1%
C29
1uF/10V
BOOST_EN
C27
22uF 6.3V
C28
22uF 6.3V
U16
MPU6886
I2C_SYS_SCL
I2C_SYS_SDA
C80
2.2uF/10V
C98
470nF/25V
C100
0.47uF/50V
I2C ADDR(7bit): 0x68
RTC_VDD
D8
1N5819
R16
100R
C30
6pF/50V
C32
6pF/50V
Y1
TXC/9H0320
U4
OSCI
INT
SCL
SDA
OSCO
VDD
CLKOUT
VSS
BM8563
AXP_WAKEUP
C33
1uF/10V
C34
22uF 6.3V
BAT1/NC
XH414HG-IV01E


U5
ESP32-S3
LNA_IN
CHIP_PU
VDD_SPI
SPIHD
SPIWP
SPICS0
SPICLK
SPIQ
SPID
XTAL_P
XTAL_N
VDD3P3
VDD3P3_RTC
VDD3P3_CPU
VDDA1
VDDA2
GND
GPIO0
GPIO1
GPIO2
GPIO3
GPIO4
GPIO5
GPIO6
GPIO7
GPIO8
GPIO9
GPIO10
GPIO11
GPIO12
GPIO13
GPIO14
XTAL_32K_P
XTAL_32K_N
GPIO17
GPIO18
GPIO19
GPIO20
GPIO21
SPICS1
SPICLK_N
SPICLK_P
GPIO33
GPIO34
GPIO35
GPIO36
GPIO37
GPIO38
MTCK
MTDO
MTDI
MTMS
U0TXD
U0RXD
GPIO45
GPIO46
ESP_LNA
AXP_PG
FLASH_VCC
FLASH_HD
FLASH_WP
FLASH_CS0
FLASH_CLK
FLASH_Q
FLASH_D
XTAL_40M_P
XTAL_40M_N
VDDP_3V3
VDD_3V3
GND
ESP_BOOT
BUS_PA_SCL
BUS_PA_SDA
LCD_CS
TF_CS
BUS_G5
BUS_G6
BUS_G7
BUS_PB_IN
BUS_PB_OUT
BUS_ADC1
I2C_SYS_SCL
I2C_SYS_SDA
I2S_DATO
I2S_DATI
CAM_D6
CAM_D7
BUS_PC_TX
BUS_PC_RX
USB_DU_N
USB_DU_P
I2C_INT
FLASH_CS1
CAM_D8
CAM_D9
I2S_WCK
I2S_BCK
SPI_MISO
SPI_SCK
SPI_MOSI
CAM_HREF
CAM_D2
CAM_D3
CAM_D4
CAM_D5
BUS_U0TXD
BUS_U0RXD
CAM_PCLK
CAM_VSYNC
I2S_MCLK
R49
10k/1%
R48
499R/1%
VSPI: 0=3.3V 1=1.8V
UART_PRINT
R33
22nH
C44
12pF
X1
40Mhz/10ppm/20pF/2520
C51
12pF
C68
1.8nH
C69
2.7pF
C86
2.4pF
R35
0R
R36
NC
L9
NC
C121
NC
J4
IPEX
ANT1
PROANT440
U6
GD25Q128/W25Q128/128Mbit/3.3V
VCC
GND
nCS
CLK
DI/IO0
DO/IO1
nWP/IO2
nHOLD/IO3
C35
4.7uF/10V
C36
470nF/10V
U7
ESPSRAM
nCS
VDD
VSS
SI/SIO0
SO/SIO1
SIO2
SIO3
SCLK
C37
4.7uF/10V
C38
470nF/10V
R20
2.2k/1%
R32
2.2k/1%
L4
2.0nH
C110
470nF/25V
C122
4.7uF/10V
C39
4.7uF/10V
C41
4.7uF/10V
C42
4.7uF/10V
C31
22uF 6.3V
C119
22uF 6.3V
C45
10nF/50V
C46
470nF/25V
C48
470nF/25V
C49
470nF/25V
C50
470nF/25V
C120
22uF 6.3V


I2C ADDR(7bit): 0x36
U8
AW88298
AXP_PS
AW_PVDD
VDD_1V8
VDD_3V3
GND
SPK_VON
SPK_VOP
L6
WPN201610M1R0MT
FB1
FB2
C52 0.1nF/25V
C58 0.1nF/25V
AW_INT
AW_RST
I2C_SYS_SDA
I2C_SYS_SCL
I2S_BCK
I2S_WCK
I2S_DATO
C53 22uF 6.3V
C54 22uF 6.3V
C55 22uF 6.3V
C56 22uF 6.3V
C57 100nF/50V
C59 10uF/25V
C60 10uF/25V
VDDA_3V3
GNDA
C66 100nF/50V
C67 100nF/50V
C99 2.2uF/10V
C61 100nF/50V
C62 2.2uF/10V
C63 100nF/50V
C64 2.2uF/10V
C65 2.2uF/10V
I2C ADDR(7bit): 0x40
U9
ES7210
R34 51R/1%
ESP_BOOT
I2S_DATI
ES_INT
I2C_SYS_SDA
I2C_SYS_SCL
R22 0R
MIC1_N
MIC1_P
MIC2_P
MIC2_N
AEC_P
AEC_N
C102
R40 150K/1%
C103 1uF/10V 22pF/50V
R41 NC
C104
R42 150K/1%
C105 1uF/10V 22pF/50V
R43 NC
VBIAS_MIC
C70 1uF/10V
C71 1uF/10V
C72 1uF/10V
C73 1uF/10V
C74 1uF/10V
C75 1uF/10V
C76 1uF/10V
HZ1005U102TFB01
L7
L8
U12
U13
MSM381A3729H9BPC
C87
C88 1uF/10V
C89 1uF/10V
C90 100nF/50V
C91 1uF/10V
C92
C93 1uF/10V
C94 1uF/10V
C95 100nF/50V
C96 1uF/10V
22pF/25V


I2C ADDR(7bit): 0x58
J2
AFC34-S24FIA-00
VDDCAM_3V3
VDD_3V3
C101 4.7uF/10V
C77 2.2uF/10V
C78 100nF/50V
R37 10K/1%
R31 51R/1%
CAM_MCLK
C114 10nF/50V
C115 470nF/25V
X2 20MHz ±25ppm 3.3V
U10
AW9523B
TOUCH_RST
BUS_OUT_EN
AW_RST
ES_INT
TF_SW
USB_OTG_EN
CAM_RST
LCD_RST
TOUCH_INT
AW_INT
BOOST_EN
AXP_PG
I2C_INT
I2C_SYS_SCL
I2C_SYS_SDA
R24 10K/1%
R27 10K/1%
R26 10K/1%
R23 10K/1%
AVDD
DVDD
C126 4.7uF/10V
C127 4.7uF/10V
C81 22uF 6.3V
C82 2.2uF/10V
C83 2.2uF/10V
LCD1
M5_LCD_10P
SPI_MOSI
SPI_SCK
LCD_CS
LCD_RST
SPI_MISO
VCC_BL
R18 10K/1%
R19 10K/1%
R21 10K/1%
BUS1
M5.BUS
BUS_ADC1
BUS_PB_IN
AXP_PG
BUS_G5
BUS_PB_OUT
VCC_3V3
BUS_U0RXD
BUS_U0TXD
BUS_PC_RX
BUS_PC_TX
I2C_SYS_SDA
I2C_SYS_SCL
BUS_PA_SDA
BUS_PA_SCL
BUS_G6
BUS_G7
I2S_DATO
ESP_BOOT
I2S_DATI
BUS_OUT
VBAT
U11
MicroSD-SPI
TF_CS
SPI_MOSI
VDD_3V3_SD
SPI_SCK
SPI_MISO
R28 10K/1%
TF_SW
CTP1
M5_TOUCH_8P
J3
GH2.0-4P
C116 470nF/25V
C84 2.2uF/10V
C85 22uF 6.3V
GND


Boost
OTG
USB
PMU
C117
BUS_5V
U14
VIN
VOUT
EN
RSET
GND
470nF/25V
BUS_OUT_EN
R17
60K/1%
ME1502AM5G
(EN高使能)
C118
22uF 6.3V
BUS_OUT
C106
470nF/25V
U17
VUSB
USB_OTG_EN
R44
C111
AXP_PS
C124
220uF/6.3V/6.3x4.3/6R3AVEA221M0645
C125
C108
U19
R46
30K/1%
ME1502CM5G
(EN低使能)
C113
VBUS
U18
C112
C107
R45
PHD1
PHD2
PHD3
phd_2.1mm
phd_3mm


VDD_3V3
VDD_3V3
R?
15KΩ
R?
15KΩ
R50
2.2k/1%
SDO=GND 0x68
SDO=VDDIO 0x69
U15
SA0
I2C_SYS_SDA
I2C_SYS_SCL
1
14
13
4
9
6
7
8
5
12
2
3
11
10
BMM_SDA
BMM_SCL
BMI270
GND
VDD_3V3
VDD_3V3
C43
100nF/25V
C40
100nF/25V
GND
GND
GND
C1
U20
BMM150
E1
D2
E3
D4
E5
A1
B2
A3
B4
A5
BMM_SCL
BMM_SDA
VDD_3V3
VDD_3V3
C79
100nF/25V
C5
C47
100nF/25V
GND
GND
GND
GND
GND