

Partner: Symetrix
Model: Edge/Radius
Device Type: Digital Signal Processor



GENERAL INFORMATION

SIMPLWINDOWS NAME:	Symetrix Command Processor IP v3.0
CATEGORY:	Mixer
VERSION:	3.0
SUMMARY:	<p>This module controls all TCP/IP communication with the Symetrix Edge and Radius.</p>
GENERAL NOTES:	<p>This module controls all TCP/IP communication with the Symetrix Edge and Radius.</p> <p>There are 200 serial outputs on this module, one for each of up to 200 control modules. All responses from the device are processed by this module and sent to the appropriate serial output for a specific control module (e.g. volume control, button press, dialer, etc).</p> <p>When the Initialize input on the module is pulsed, the module will send out initialization strings to each of the To_ModuleX outputs asking for the module's type and associated controller numbers. The control modules will transmit that information back to the command processor module on the To_Command_Processor output.</p> <p>The individual control modules can be connected consecutively or in groups with empty gaps between the module connections. Depending on how you make your connections, you should choose the appropriate setting for the Initialization Control parameter.</p> <p>Connecting your modules consecutively and selecting the "Stop Init After 10 No Response" option will result in the fastest initialization time because it will stop initializing after 10 consecutive module connections do not respond. This is also the most efficient method for the command processor as it will only sort responses against the outputs that are used.</p> <p>If you choose to connect your control modules in groups, choose the appropriate setting for the Initialization Control parameter.</p> <p>Setting the Initialization Control parameter to "Initialize All Outputs" will ensure that all outputs are checked on initialization however it will add time to the initialization process and potentially make the module operate less efficiently in sorting responses from the device.</p> <p>Control modules with single controller number parameters (Volume, Button Push, and Input Output Select) will flag that single controller number value for sorting of received responses.</p> <p>Control modules with multiple controller number parameters (ATI Single Line Dial, VOIP Single Line Dial, and Controller Receiver) will examine the full range of controller numbers and will direct responses within that range to the module using that range. Because of this, it is important to set up controller numbers for these modules sequentially – or if controller numbers are skipped they should not be used for other functions controlled by the Crestron system.</p>
CRESTRON HARDWARE REQUIRED:	Ethernet capable processor
SETUP OF CRESTRON HARDWARE:	TCP/IP Port: 48631

Partner: Symetrix
Model: Edge/Radius
Device Type: Digital Signal Processor



VENDOR FIRMWARE:	2.868
------------------	-------

PARAMETERS:

Initialization_Control

Setting to "Initialize All Outputs" will send initialization commands to all To Module outputs during the initialization process. Setting to "Stop Init After 10 No Response" will send initialization commands to the To Module outputs until 10 consecutive module connections do not respond. Default is "Initialize All Outputs".

See General Notes section for more detail on these settings.

CONTROL:

Initialize

D

Pulse to initialize the communications between all of the Symetrix modules being used in the Crestron program. This input is locked out for 5 seconds after the Crestron processor boots up to allow the individual control modules to initialize their values. After the lockout you can pulse this input at any time. Or you could put a one (1) on this input and the initialization will trigger after the lockout time.

TCP_IP_Client_Connect_FB

D

Digital signal to be connected to the Connect-F output on a TCP/IP Client symbol.

TCP_IP_Client_Status

A

Analog signal to be connected to the status output on a TCP/IP Client symbol.

From_Device

S

Serial signal to be routed from the RX\$ output on a TCP/IP Client symbol.

From_Modules

S

Serial signal to be routed from all Symetrix control modules in the program.

FEEDBACK:

Initialize_Is_Busy

D

High to indicate that the module is busy initializing communications with the other Symetrix control modules.

TCP_IP_Client_Connect

D

Digital signal to be connected to the Connect input on a TCP/IP Client symbol.

To_Device

S

Serial signal to be routed to the TX\$ input on a TCP/IP Client symbol.

To_ModuleX

S

Serial signal to be routed to the From_Command_Processor input on a single Symetrix control module.

Partner: Symetrix
Model: Edge/Radius
Device Type: Digital Signal Processor

**TESTING:**

OPS USED FOR TESTING:	PRO2: 4.008.0008 CP3: 1.009.0029
SIMPL WINDOWS USED FOR TESTING:	4.02.53
CRES DB USED FOR TESTING:	47.05.002.01
DEVICE DATABASE:	60.02.001.00
SYMBOL LIBRARY USED FOR TESTING:	906
SAMPLE PROGRAM:	Symetrix ATI IP Demo v3.0 CP3 Symetrix ATI IP Demo v3.0 Pro2 Symetrix VOIP IP Demo v3.0 CP3 Symetrix VOIP IP Demo v3.0 Pro2
REVISION HISTORY:	v3.0 – Initial Release – named as v3.0 to avoid confusion with earlier module versions provided by Symetrix.