

Troubleshooting - USB Fiber Network Adapter Does Not Work on IGEL OS

You use fibre-to-USB adaptors with your IGEL OS 12 devices. IGEL OS can see the adaptor, but no network traffic is transmitted.

Problem

Some USB ethernet fiber adaptors work with 4.4.x kernel but not with newer ones.

Solution

As of IGEL OS 12.7.1, you can activate the asix_thirdparty driver to get some fibre USB ethernet adapters to work.

1. In the Profile Configurator, create a profile for IGEL OS Base System. For more information on profile creation, see [How to Create and Assign Profiles in the IGEL UMS Web App](#).
2. Go to **System > Registry** and enable the following registry key:

Parameter	Use thirdparty asix kernel module.
Registry	<code>network.drivers.asix.prefer_thirdpart</code>
Range	[Auto] [Yes] [No]
Value	Auto

The screenshot shows the 'Profile Configurator Advanced Setup' window. The 'System' tab is selected and highlighted with a red box. In the left sidebar, the 'Registry' section is also highlighted with a red box. The main pane displays a tree view of system settings under 'network.drivers.asix.prefer_thirdparty'. The 'prefer_thirdparty' item is selected. A dropdown menu is open, showing options: 'Auto', 'Yes', and 'No'. A red arrow points to the 'Yes' option. At the bottom, there are buttons for 'App Selector', 'Cancel', 'Save', and 'Save and Close'.

Accessories User Interface Network Devices Security **System**

Time and Date
Remote Management
Remote Access
Logging
Power Options
System Customization
Update
Registry
Notification

network.drivers.asix.prefer_thirdparty

- network
 - applet
 - dhcp
 - dhcp6
 - dns
 - drivers
 - asix
 - prefer_thirdparty**
 - broadcom
 - igb
 - r8162
 - r8169
 - realtek

Use thirdparty asix kernel module.

Auto
Yes
No

App Selector Cancel Save Save and Close