
Compander user guide

Compander is an FFGL plugin for Resolume Arena and Avenue, and an OpenFX plugin for DaVinci Resolve, Vegas, Nuke and Natron, that pushes your picture through an analogue radio mic's companding circuit.



Rendered by the plugin's own offline harness in a headless GL context rather than captured from Resolume. Actual frames through the shipped shaders, on a synthetic scene built to make companding measurable: a flat band, hard vertical edges, two one-pixel combs at ninety degrees to each other, and a ramp.

A wireless microphone link can't carry the dynamic range of what's sent down it. So the transmitter squashes it (pre-emphasis to lift the quiet top end above the link's noise, then a compressor that halves the signal's excursion in dB) and the receiver does the exact opposite. In between sits a link with a noise floor, a ceiling, and no opinion about either.

```
in → EMPHASIS → COMPRESS → [ link: level, ceiling, noise ] → EXPAND → DE-EMPHASIS → out
```

Get every stage right and almost nothing happens, which is rather the idea: a working radio mic sounds like a cable. Everything this plugin is for comes from the two ends failing to cancel.

The idea that makes it a video effect rather than an audio compressor pointed at a picture: **a compander's attack and release, applied to a picture, is a distance along the scan.** A signal on a wire has one axis, time, and when that signal is a picture, time is the scan: left to right, line after line.

> **Before you rely on this:** the signal model is verified numerically. The compander's round trip cancels to **three millionths of a decibel** wherever its gain law is unbounded, a flat field comes back **byte-identical** through a matched pair, and the envelope detector the GPU runs is checked against a strictly serial implementation of the same law (one that could never run on a GPU), which it agrees with to float precision. All 24 controls are confirmed to change the picture and no two presets render the same frame.
>
> It's been **loaded into Resolume Arena 7.27.1, put on a layer and run on real footage**, with its controls, groups and factory presets read back out of the running host.
>
> Still open: **no audio spectrum has ever reached it.** The audio-reactive controls are wired up and Resolume recognises them, but they've never been driven; see Audio reactivity for the one-line way to check them on your own rig. The OpenFX build has only ever been driven by a test probe and has **never been opened in Resolve**. Try it on a spare layer before you put it in a show.
>
> It's at v0.1.4, whose OpenFX build now tells the host that its output changes from frame to frame (the noise floor moves), so a host that caches by that flag re-renders it. This codebase was created with AI assistance, directed and reviewed by a human author.

Installing

Drop the plugin into Resolume's FFGL folder and restart Resolume:

```
macOS    ~/Documents/Resolume Arena/Extra Effects/
         (or /Users/Shared/Resolume Arena/Extra Effects/)
Windows  %USERPROFILE%\Documents\Resolume Arena\Extra Effects\
```

Avenue uses the same layout under its own folder name. Compander then shows up in the effects browser under **Video Effects**.

The macOS builds are **Developer ID-signed and notarised**, so the bundle just loads, with nothing to clear and no `xattr` step. The Windows builds aren't code-signed, but plugin files aren't gated the way `.exe` files are, so Resolume loads them normally.

OpenFX hosts (Resolve, Vegas, Nuke, Natron)

Copy `Compander.ofx.bundle` into the OFX plugin directory:

```
macOS    /Library/OFX/Plugins/
Windows  C:\Program Files\Common Files\OFX\Plugins\
Linux    /usr/OFX/Plugins/
```

It shows up under **Stoatworks**. ⚠️ The OpenFX build has never been opened in a real host: it's built, it loads under a test probe, and that's all that's established.

The one control that matters most

Time Constant is the compander's attack and release, and on a picture that's a *distance*. The active picture is 52 microseconds of a 64 microsecond line, so:

Time Constant	at 1920 wide	what you see
0.2 µs	7 samples	haloing tight to every edge
5 µs	185 samples	a smear off the side of things
60 µs	about a line	streaks pulling down the frame
2 ms	about 37 lines	broad vertical banding
20 ms	half a frame	the whole picture pumping

Two things about it are on purpose and worth knowing, because they're what make it read as a circuit rather than a filter:

- **It trails to the right.** The detector can only know what has already gone past, so a bright object drags its gain change out behind it and leaves its left-hand edge alone.
- **It wraps line to line.** A bright object at the end of one line affects the start of the next, because that's where the signal was a moment ago.

The processing is horizontal and there's no vertical equivalent. A link carries one signal with one frequency axis: a vertical edge is a high frequency to a transmitter, and a horizontal edge isn't a frequency at all. It's the next line.

The controls

Signal

- **Sidechain:** where the compressor's control signal comes from. *Picture* is the circuit as built. *Audio* hands it a real spectrum instead. *Picture × Audio* is both, and it's the one that survives a whole show because it still follows the footage.
- **Chroma:** whether the colour crossed the link. At **0** the colour difference bypassed it and comes back at the amplitude it left at, so lifting a shadow *desaturates* it: one channel was companded and the colour wasn't, which is the radio mic reading. At **1** the whole colour is carried through together, so saturation holds while brightness moves, which is the video link reading.

Encode

- **Compress:** the ratio at the transmitter, 1:1 to 4:1. The two-to-one that essentially every analogue wireless system used sits at **one third** of the travel.
- **Emphasis:** pre-emphasis, 0 to 12 dB of lift on the detail band, so quiet high-frequency content sits above the link's noise instead of under it.

Link

- **Link Level:** gain into the link, ±12 dB, applied **before** the noise. The noise floor stays where it is while the signal moves relative to it, so this is a signal-to-noise control before it is a level control. Centre is an aligned pair.
- **Noise:** the link's own noise floor, and it matters. Companding exists to hide a noise floor, and without one the decode stage has nothing to show for itself. Turning it to zero to see the companding on its own is a perfectly reasonable thing to do; it just isn't the default.
- **Headroom:** where the link clips. **Runs backwards**: higher is *less* headroom, so it reads the way a drive control should.

Decode

- **Expand:** the ratio at the receiver, 1:1 to 1:4. Match it to Compress and the round trip nearly cancels. That's what a working link does; everything interesting is a departure from it.
- **Tilt:** the mismatch between the transmitter's emphasis network and the receiver's. Centre is matched. At the **top** there's no de-emphasis at all and everything the transmitter lifted stays lifted: hard, glassy, edges ringing. At the **bottom** the signal is de-emphasised twice: soft, smeared, detail sucked out of anything fine.

Detector

- **Time Constant:** see above.
- **Pivot:** the level the law pivots about. Signal at the pivot passes at unity through both ends whatever the ratio, so this is the one brightness where the round trip is exact, and everything either side of it is where the character is.
- **Max Gain:** the most boost the compressor will ever apply, 0 to 48 dB. A real circuit's boost runs out, or it would be amplifying nothing but its own noise floor. This decides **how far into the shadows the effect reaches**, and it's why dark parts of a picture stop lifting rather than lifting forever.

Audio

- **Audio:** Resolume's own audio-source picker (Local / Composition / External). This is the spectrum the sidechain reads.
- **Audio Amount:** how hard that envelope drives the compressor.
- **Audio Band:** which part of the spectrum drives it, from the bottom of the band to the top. It's a *lean*, two octaves wide, not a filter: a narrow window on 64 bins tracks one drum rather than the music.

- **Audio Tilt:** how much the spectrum's brightness pushes Tilt on top of its own setting. It rides on the Tilt control rather than replacing it, so a tilt you've set is kept and the music moves it.

Output

- **Mix:** wet/dry against the untouched input.

Preset

Ten real systems, named for what they are rather than for whose trademark they are:

Preset	What it is
Two-to-One VCA	The one almost everything was: broadband, 2:1, moderate pre-emphasis, fast enough that the gain change hugs the edges.
High Density	The quieter, more ambitious end of the same generation — a gentler ratio carrying a much deeper emphasis network, and a slower detector.
Digital Hybrid	A compander emulated in arithmetic rather than built out of a VCA, so it tracks almost perfectly. Nearly transparent on purpose: start here before breaking something deliberately.
Diversity Fade	A receiver on the wrong side of the room. Six dB down into the link with the noise floor where it always was, so the shadows breathe.
Cheap Handheld	Over-compressed, out of headroom, with the two ends set to ratios that do not match. Nothing ever quite comes back.
Tape Luma	Not a microphone at all: the luma channel of a consumer tape format, which used the same trick. Very heavy pre-emphasis into a hard white clip.
Satellite Link	A video up-link. Composite through one emphasis network, so the colour moves with the picture.
ENG Microwave	The same idea in a truck, done worse — further down into the link, noisier, and de-emphasising slightly harder than the transmitter emphasised.
Encode Only	Half the chain. Compressed and emphasised with nothing to undo either: flat, lifted out of the shadows, edges ringing.
Decode Only	The other half. A decoder handed material that was never encoded: contrasty, blacks crushed, fine detail sucked out.

Picking a preset sets the controls below it. Editing any of them afterwards falls back to **Custom**; the preset is a starting point, not a mode.

⚠️ `High Density` **is an impression, not a measurement.** The real two-band systems split the signal and compand the halves against different laws; this plugin has one band, and the preset gets near the character by leaning the emphasis harder and slowing the detector.

Recipes

A link that's only just working. Start at *Digital Hybrid*, then pull **Link Level** down two or three dB. The picture stays where it is and the shadows start to breathe, because the expander is restoring the noise and the picture by different amounts.

Analogue video, not analogue audio. *Tape Luma*, then take **Chroma** to 0 if it isn't there already. The colour did go somewhere else in those formats, and the desaturation as shadows lift is the give-away.

The smear. Any preset, then walk **Time Constant** up past halfway. Watch the right-hand side of anything bright: the gain change trails off it and leaves the left edge alone. That asymmetry is what an ordinary glow or blur can't do.

Something breaking on cue. *Cheap Handheld* with **Mix** on a fader. The mismatch is worst on high-contrast content, so it hits hardest just when the footage does.

Restraint. *Digital Hybrid* at **Mix** 0.3 is a grade rather than an effect: it tightens shadows and puts a little life in the top end without announcing itself.

Audio reactivity

Set **Sidechain** to *Audio* or *Picture × Audio*, then choose a source on the **Audio** control (Local / Composition / External) just as you would for any Resolume audio-reactive parameter.

A compander is a circuit whose gain is driven by an audio envelope, so this is the circuit being fed the kind of signal it was built for, with the picture standing in for the carrier. **The audio drives the encode end only.** A real receiver's expander knows nothing about what the transmitter's VCA was being fed, and that's the interesting behaviour rather than a simplification: drive both ends and the round trip cancels and the picture merely gets louder; drive one and the link mistracks in time with the music.

⚠️ **This is the least-tested part of the plugin.** It's never been driven by a live spectrum.

If it seems to do nothing, the usual cause is the audio source picker pointing at something silent. The plugin can't tell that apart from a quiet track, so it says which in its log. Look for one line:

```
audio input active: 64 bins, envelope 0.31, balance -0.12
```

If that line never appears, no spectrum is arriving and the problem is upstream of the plugin. Check, in this order: that the composition and the layer aren't muted (they're separate volumes, and both must be up), and that **Resolume has a real audio device**. An install whose output is routed to a virtual sink with no input device configured has no live audio bus to analyse, and nothing will ever reach an audio-reactive parameter, this plugin's or anyone else's.

```
macOS    ~/Library/Logs/compander/compander.YYYY-MM-DD.log
Windows  %USERPROFILE%\compander\logs\
```

Performance

About **0.7 to 1.1 ms a frame at 1920×1080** on an Apple M4 Max, and the cost tracks **Time Constant**: a short setting needs a handful of detector passes and only the longest settings need the full count. If you're tight for headroom, a shorter Time Constant is the cheaper one.

The chain runs at full resolution in one channel (a link carried one signal), and the detector runs at quarter width, which is where the saving is.

Troubleshooting

The effect does nothing at all. Check the log. A shader that won't compile looks just like this, and the log names the stage, the compiler's complaint and the source it refers to.

It's very subtle. Check **Mix**, then **Noise**: with no noise in the link the decode stage has nothing to reveal, and a matched pair is *meant* to be nearly transparent. Try *Cheap Handheld* to confirm the plugin is doing anything at all, then come back.

Everything is crushed to black. Expand is high with **Compress** low: a decoder handed material that was never encoded. That's *Decode Only*, and it's a real look, but if you didn't mean it, match the two ratios.

The picture got brighter and flatter. The opposite: **Compress** high with **Expand** low.

Highlights have hard flat tops. Headroom is running the encoded signal into the link's ceiling. Remember the control runs backwards, so turn it *down* for more headroom.

Licence

MIT. Source at https://github.com/stoatworks-labs/compander.