
Otter EDID Editor user guide

Otter EDID Editor is a browser EDID editor for event video. Build an EDID from a resolution and a refresh rate, or edit every field by hand, then see which processors will actually take it, and in which mode.

Nothing's uploaded. There's no backend to upload it to.



> **Before you rely on this:** the timing engine is checked against published VESA DMT values, and the DisplayID layout against the Linux kernel's own parser.
>
> **The hardware table is vendor paperwork, cited per claim, and has not been tried against any hardware. No hardware has ever been fed an EDID this tool produced.** Treat a verdict as a shortlist.
>
> Built with AI assistance, directed and reviewed by a human author.

Three modes

Simple. Type a resolution and a refresh rate, name it, press Calculate. You get a complete, valid EDID 1.4: the mode as a detailed timing, a range-limits descriptor **sized to it**, the name where every input menu will read it, and a CTA-861 extension carrying the VIC when the mode has one.

Advanced. Every field. Identity, video input definition, chromaticity, established and standard timings, all four descriptors, the CTA-861 extension (video and audio descriptors, HDMI and HDMI Forum vendor blocks, HDR static metadata, colorimetry, 4:2:0 maps) and a DisplayID 2.0 extension.

Mosaic. For frame-synced output from a Mac across several plugs. Give the whole canvas, the grid (**2 × 1** or **2 × 2**) and the rate. You get **one EDID per plug**: load `left.bin` on the input the Mac's left-hand output feeds and `right.bin` on the other (for 2 × 2, `tile_r1_c1.bin` is the top left). Each carries a DisplayID Tiled Display Topology block. A Mac that finds matching blocks on its outputs joins them into **one display**, drives them together, and the seams don't tear. If the Mac lists the plugs as separate displays, they haven't bonded and aren't in sync.

- Up to **6144 wide** bonds on any recent macOS; up to **12288** needs **macOS 27**.
- Each plug is at most 6144 wide. Three or four across never bonds on a Mac.
- A second mosaic on the same Mac needs a different **mosaic number**, because the Mac groups plugs by it.

The layout copies, byte for byte, reference files that have bonded on macOS 26 and 27. Otter hasn't loaded its own files into a Mac.

All three modes name the EDID, and all three show the same two answers on the right.

The two answers

What the mode costs, and the smallest interface that carries it. Pixel clock, raster, line rate and payload, then the minimum HDMI version (1.0–1.2, 1.3/1.4, 2.0, or which FRL rate), the minimum DisplayPort rate at 4 and 2 lanes, and whether DVI needs one link or two.

Which hardware takes it. Twenty-one models across the major event-video vendors, each answering **yes / conditional / no**, and **where the answer is conditional, the capacity mode you have to configure to get it**:

- A **LiveCore dual-link input costs you the neighbouring input.**
- A **Barco E2 Gen 1** does 4K60 only across two cables.
- A **Barco E2 Gen 2 quad card** is four WQXGA inputs **or** two UHD60 ones.
- An **Aquilon DisplayPort card** is four DP 1.2 ports **or** two DP 1.4 ports, and **DP 1.4 preempts ports 2 and 4.**

Every device carries its sources, quoted, with the date they were read. That's what to check before a purchase decision rests on a row.

DSC and variable refresh

Both are toggles, and **both are real**: they change the bandwidth arithmetic, they change which interface version is required, and they're written into the EDID.

Turning DSC on correctly makes every HDMI 2.0 and earlier input say no, because DSC travels only over a fixed-rate link. That's just how DSC works.

Import

Open a `.bin`, or paste a hex dump from anywhere: `xrandr`, `edid-decode`, `xxd`, a C header, a bare hex string.

A bad checksum is reported, not refused. The dump off a misbehaving device is the one you most need to look at, and a tool that won't open it is no use at the one moment it matters.

If something is unexpected

Symptom	Cause
Every HDMI input says no after I enabled DSC	Correct. DSC needs a fixed-rate link.
A device says "conditional"	It takes the mode only in a particular capacity mode — the answer names which.
An imported EDID has a checksum error	Reported deliberately rather than refused. Look at it.
A verdict disagrees with a manufacturer	Every row carries its source and the date it was read. Check it — the table is paperwork, not measurement.
The processor rejected an EDID this built	Possible, and untested — no hardware has ever been fed one of these.

Not affiliated with Analog Way, Barco, PixelHue, Brompton, NovaStar, disguise or Green Hippo. Product names appear only to state compatibility.