Page: 27/51 **Table 3-1 Cortex-M0+ instruction summary (continued)**

Operation	Description	Assembler	Cycles
Logical	AND	ANDS Rd, Rd, Rm	1
	Exclusive OR	EORS Rd, Rd, Rm	1
	OR	ORRS Rd, Rd, Rm	1
	Bit clear	BICS Rd, Rd, Rm	1
	Move NOT	MVNS Rd, Rm	1
	AND test	TST Rn, Rm	1

add the **S**
nstructions
orted on **RP2040**
S suffix.
orted in
ode.

Subtract	Lo and Lo	SUBS Rd, Rn, Rm	1
	3-bit immediate	SUBS Rd, Rn, #<imm>	1
	8-bit immediate	SUBS Rd, Rd, #<imm>	1
	With carry	SBCS Rd, Rd, Rm	1
	Immediate from SP	SUB SP, SP, #<imm>	1
	Negate	RSBS Rd, Rn, #0	1
Multiply	Multiply	MULS Rd, Rm, Rd	1 or 32[a]

Page: 27/51 **Table 3-1 Cortex-M0+ instruction summary (continued)**

Operation	Description	Assembler	Cycles
Shift	Logical shift left by immediate	LSLS Rd, Rm, #<shift>	1
	Logical shift left by register	LSLS Rd, Rd, Rs	1
	Logical shift right by immediate	LSRS Rd, Rm, #<shift>	1
	Logical shift right by register	LSRS Rd, Rd, Rs	1
	Arithmetic shift right	ASRS Rd, Rm, #<shift>	1
	Arithmetic shift right by register	ASRS Rd, Rd, Rs	1
Rotate	Rotate right by register	RORS Rd, Rd, Rs	1

ıe **S**
:tions
. on **RP2040**
ix.
in

Syntax: `<instruction>{<cond>}{S} Rd, Rn, N`

ADC	add two 32-bit values and carry	$Rd = Rn + N +$ carry
ADD	add two 32-bit values	$Rd = Rn + N$
RSB	reverse subtract of two 32-bit values	$Rd = N - Rn$
RSC	reverse subtract with carry of two 32-bit values	$Rd = N - Rn -$!(carry flag)
SBC	subtract with carry of two 32-bit values	$Rd = Rn - N -$!(carry flag)
SUB	subtract two 32-bit values	$Rd = Rn - N$

Condition Code	Interpretation	Status Flag State
EQ	Equal / equals zero	Z set
NE	Not equal	Z clear
CS / HS	Carry set / unsigned higher or same	C set
CC / LO	Carry clear / unsigned lower	C clear
MI	Minus / negative	N set
PL	Plus / positive or zero	N clear
VS	Overflow	V set
VC	No overflow	V clear
HI	Unsigned higher	C set and Z clear
LS	Unsigned lower or same	C clear or Z set
GE	Signed greater than or equal	N equals V
LT	Signed less than	N is not equal to V
GT	Signed greater than	Z clear and N equals V
LE	Signed less than or equal	Z set or N is not equal to V
AL	Always (optional)	Any

Table 3-1 Cortex-M0+ instruction summary

Operation	Description	Assembler	Cycles
Move	8-bit immediate	MOVS Rd, #<imm>	1
	Lo to Lo	MOVS Rd, Rm	1
	Any to Any	MOV Rd, Rm	1
	Any to PC	MOV PC, Rm	2
Add	3-bit immediate	ADDS Rd, Rn, #<imm>	1
	All registers Lo	ADDS Rd, Rn, Rm	1
	Any to Any	ADD Rd, Rd, Rm	1
	Any to PC	ADD PC, PC, Rm	2
	8-bit immediate	ADDS Rd, Rd, #<imm>	1
	With carry	ADCS Rd, Rd, Rm	1
	Immediate to SP	ADD SP, SP, #<imm>	1
	Form address from SP	ADD Rd, SP, #<imm>	1
	Form address from PC	ADR Rd, <label>	1

the S suffix
nstructions.
valid for
y the instructions
S suffix
d.

Branch	Conditional	B<cc> <label>	1 or 2[e]
	Unconditional	B <label>	2
	With link	BL <label>	3
	With exchange	BX Rm	2
	With link and exchange	BLX Rm	2

ge: 28/51

cycles if the
ch is taken,
cycle if
taken.

Compare	Compare	CMP Rn, Rm	1
	Negative	CMN Rn, Rm	1
	Immediate	CMP Rn, #<imm>	1

ge: 26/51