# Notation

Rubem Vasconcelos Pacelli
rubem.engenharia@gmail.com

Department of Teleinformatics Engineering,
Federal University of Ceará.
Fortaleza, Ceará, Brazil.

Version: May 3, 2023

## Contents

**1 Font notation**

**2 Signals and functions**
- 2.1 Time indexing
- 2.2 Common signals
- 2.3 Common functions
- 2.4 Operations and symbols
- 2.5 Transformations

**3 Probability, statistics, and stochastic processes**
- 3.1 Operators and symbols
- 3.2 Stochastic processes
- 3.3 Functions
- 3.4 Distributions

**4 Machine learning, optimization theory, and statistical signal processing**
- 4.1 Derivative terms
- 4.2 Estimated terms
- 4.3 Signals, (hyper)parameters, system performance, and criteria

**5 Linear Algebra**
- 5.1 Common matrices and vectors
- 5.2 Indexing
- 5.3 General operations
- 5.4 Operations with matrices and tensors
- 5.5 Operations with vectors
- 5.6 Decompositions
- 5.7 Spaces and sets

5.8 Set operations . . . . . . . . . . . . . . . . . . . . . . . . . . . . . .
5.9 Inequalities . . . . . . . . . . . . . . . . . . . . . . . . . . . . . .

**6 Communication systems**
6.1 Symbols . . . . . . . . . . . . . . . . . . . . . . . . . . . . . .
6.2 Fading multipath channels . . . . . . . . . . . . . . . . . . . . . . . .

**7 Discrete mathematics**
7.1 Quantifiers, inferences . . . . . . . . . . . . . . . . . . . . . . . .
7.2 Propositional Logic . . . . . . . . . . . . . . . . . . . . . . . . . .
7.3 Operations . . . . . . . . . . . . . . . . . . . . . . . . . . . . . .

**8 Electromagnetic waves**

**9 Calculus**

**10 Generic mathematical symbols**

**11 Abbreviations**

# 1 Font notation

| | |
|---|---|
| $a, b, c, \ldots, A, B, C, \ldots$ | Scalars |
| $\mathbf{a}, \mathbf{b}, \mathbf{c}, \ldots$ | Vectors |
| $\mathbf{A}, \mathbf{B}, \mathbf{C}, \ldots$ | Matrices |
| $\mathcal{A}, \mathcal{B}, \mathcal{C}, \ldots$ | Tensors |
| $A, B, C, \ldots, \mathcal{A}, \mathcal{B}, \mathcal{C}, \ldots, \mathbb{A}, \mathbb{B}, \mathbb{C}, \ldots$ test | Sets |

# 2 Signals and functions

## 2.1 Time indexing

| | |
|---|---|
| $x(t)$ | Continuous-time $t$ |
| $x[n], x[k], x[m], x[i], \ldots$ $x_n, x_k, x_m, x_i, \ldots$ $x(n), x(k), x(m), x(i), \ldots$ | Discrete-time $n, k, m, i, \ldots$ (parenthesis should be adopted only if there are no continuous-time signals in the context to avoid ambiguity) |
| $x\left[((n-m))_N\right], x\left((n-m)\right)_N$ | Circular shift in $m$ samples within a $N$-samples window [11, 17] |

## 2.2 Common signals

| | |
|---|---|
| $\delta(t)$ | Delta function |
| $\delta[n], \delta_{i,j}$ | Kronecker function $(n = i - j)$ |
| $h(t), h[n]$ | Impulse response (continuous and discrete time) |
| $\tilde{x}[n], \tilde{x}(t)$ | Periodic discrete- or continuous-time signal |
| $\hat{x}[n], \hat{x}(t)$ | Estimate of $x[n]$ or $x(t)$ |
| $\dot{x}[m]$ | Interpolation of $x[n]$ |

## 2.3 Common functions

| | |
|---|---|
| $\mathcal{O}(\cdot), O(\cdot)$ | Big-O notation |
| $\Gamma(\cdot)$ | Gamma function |
| $Q(\cdot)$ | Quantization function |
| $I_\alpha(\cdot)$ | Modified Bessel function of the first kind and order $\alpha$ |
| $\left(\begin{array}{c} n \\ k \end{array}\right)$ | Binomial coefficient |

## 2.4 Operations and symbols

| | |
|---|---|
| $f : A \to B$ | A function $f$ whose domain is $A$ and codomain is $B$ |
| $\mathbf{f} : A \to \mathbb{R}^n$ | A vector-valued function $\mathbf{f}$, i.e., $n \geq 2$ |
| $f^n, x^n(t), x^n[k]$ | $n$th power of the function $f$, $x[n]$ or $x(t)$ |
| $f^{(n)}, x^{(n)}(t)$ | $n$th derivative of the function $f$ or $x(t)$ |
| $f', f^{(1)}, x'(t)$ | 1th derivative of the function $f$ or $x(t)$ |
| $f'', f^{(2)}, x''(t)$ | 2th derivative of the function $f$ or $x(t)$ |
| $\arg\max_{x \in \mathcal{A}} f(x)$ | Value of $x$ that minimizes $x$ |
| $\arg\min_{x \in \mathcal{A}} f(x)$ | Value of $x$ that minimizes $x$ |
| $f(\mathbf{x}) = \inf_{\mathbf{y} \in \mathcal{A}} g(\mathbf{x}, \mathbf{y})$ | Infimum, i.e., $f(\mathbf{x}) = \min\{g(\mathbf{x}, \mathbf{y}) \mid \mathbf{y} \in \mathcal{A} \wedge (\mathbf{x}, \mathbf{y}) \in \mathrm{dom}\,(g)\}$, which is the greatest lower bound of this set [3] |
| $f(\mathbf{x}) = \sup_{\mathbf{y} \in \mathcal{A}} g(\mathbf{x}, \mathbf{y})$ | Supremum, i.e., $f(\mathbf{x}) = \max\{g(\mathbf{x}, \mathbf{y}) \mid \mathbf{y} \in \mathcal{A} \wedge (\mathbf{x}, \mathbf{y}) \in \mathrm{dom}\,(g)\}$, which is the least upper bound of this set [3] |
| $f \circ g$ | Composition of the functions $f$ and $g$ |
| $*$ | Convolution (discrete or continuous) |
| $\circledast, \textcircled{N}$ | Circular convolution [7, 17] |

## 2.5 Transformations

| | |
|---|---|
| $W_N$ | Twiddle factor, $e^{-j\frac{2\pi}{N}}$ [11] |
| $\mathcal{F}\{\cdot\}$ | Fourier transform |
| $\mathcal{L}\{\cdot\}$ | Laplace transform |
| $\mathcal{Z}\{\cdot\}$ | $z$-transform |
| $\hat{x}(t), \hat{x}[n]$ | Hilbert transform of $x(t)$ or $x[n]$ |
| $X(s)$ | Laplace transform of $x(t)$ |
| $X(f)$ | Fourier transform (FT) (in linear frequency, Hz) of $x(t)$ |
| $X(j\omega)$ | Fourier transform (FT) (in angular frequency, rad/sec) of $x(t)$ |
| $X(e^{j\omega})$ | Discrete-time Fourier transform (DTFT) of $x[n]$ |

| | |
|---|---|
| $X[k], X(k), X_k$ | Discrete Fourier transform (DFT) or fast Fourier transform (FFT) of $x[n]$, or even the Fourier series (FS) of the periodic signal $x(t)$ |
| $\tilde{X}[k], \tilde{X}(k), \tilde{X}_k$ | Discrete Fourier series (DFS) of $\tilde{x}[n]$ |
| $X(z)$ | $z$-transform of $x[n]$ |

# 3 Probability, statistics, and stochastic processes

## 3.1 Operators and symbols

| | |
|---|---|
| $\mathrm{E}[\cdot], \mathbf{E}[\cdot], E[\cdot], \mathbb{E}[\cdot]$ | Statistical expectation operator [6, 16] |
| $\mathrm{E}_u[\cdot], \mathbf{E}_u[\cdot], E_u[\cdot], \mathbb{E}_u[\cdot]$ | Statistical expectation operator with respect to $u$ |
| $\langle\cdot\rangle$ | Ensamble average |
| $\mathrm{var}[\cdot], \mathrm{VAR}[\cdot]$ | Variance operator [2, 10, 15, 19] |
| $\mathrm{var}_u[\cdot][\cdot], \mathrm{VAR}_u[\cdot]$ | Variance operator with respect to $u$ |
| $\mathrm{cov}[\cdot], \mathrm{COV}[\cdot]$ | Covariance operator [2] |
| $\mathrm{cov}_u[\cdot], \mathrm{COV}_u[\cdot]$ | Covariance operator with respect to $u$ |
| $\mu_x$ | Mean of the random variable $x$ |
| $\boldsymbol{\mu}_\mathbf{x}, \mathbf{m}_\mathbf{x}$ | Mean vector of the random variable $\mathbf{x}$ [4] |
| $\mu_n$ | $n$th-order moment of a random variable |
| $\sigma_x^2, \kappa_2$ | Variance of the random variable $x$ |
| $\mathcal{K}_x, \mu_4$ | Kurtosis (4th-order moment) of the random variable $x$ |
| $\kappa_n$ | $n$th-order cumulant of a random variable |
| $\rho_{x,y}$ | Pearson correlation coefficient between $x$ and $y$ |
| $a \sim P$ | Random variable $a$ with distribution $P$ |
| $\mathcal{R}$ | Rayleigh's quotient |

## 3.2 Stochastic processes

| | |
|---|---|
| $r_x(\tau), R_x(\tau)$ | Autocorrelation function of the signal $x(t)$ or $x[n]$ [16] |

| | |
|---|---|
| $S_x(f), S_x(j\omega)$ | Power spectral density (PSD) of $x(t)$ in linear $(f)$ or angular $(\omega)$ frequency |
| $S_{x,y}(f), S_{x,y}(j\omega)$ | Cross PSD of $x(t)$ and $y(t)$ in linear or angular $(\omega)$ frequency |
| $\mathbf{R_x}$ | (Auto)correlation matrix of $\mathbf{x}(n)$ |
| $r_{x,d}(\tau), R_{x,d}(\tau)$ | Cross-correlation between $x[n]$ and $d[n]$ or $x(t)$ and $d(t)$ [16] |
| $\mathbf{R_{xy}}$ | Cross-correlation matrix of $\mathbf{x}(n)$ and $\mathbf{y}(n)$ |
| $\mathbf{p}_{\mathbf{x}d}$ | Cross-correlation vector between $\mathbf{x}(n)$ and $d(n)$ [**dinizAdaptiveFiltering1997**] |
| $c_x(\tau), C_x(\tau)$ | Autocovariance function of the signal $x(t)$ or $x[n]$ [16] |
| $\mathbf{C_x}, \mathbf{K_x}, \mathbf{\Sigma_x}, \mathrm{cov}\,[\mathbf{x}]$ | (Auto)covariance matrix of $\mathbf{x}$ [10, 15, 19, 25] |
| $c_{xy}(\tau), C_{xy}(\tau)$ | Cross-covariance function of the signal $x(t)$ or $x[n]$ [16] |
| $\mathbf{C_{xy}}, \mathbf{K_{xy}}, \mathbf{\Sigma_{xy}}$ | Cross-covariance matrix of $\mathbf{x}$ and $\mathbf{y}$ |

## 3.3 Functions

| | |
|---|---|
| $Q(\cdot)$ | $Q$-function, i.e., $P\left[\mathcal{N}(0,1) > x\right]$ [19] |
| $\mathrm{erf}(\cdot)$ | Error function [19] |
| $\mathrm{erfc}(\cdot)$ | Complementary error function i.e., $\mathrm{erfc}(x) = 2Q(\sqrt{2}x) - \mathrm{erf}(x)$ [19] |
| $P[A]$ | Probability of the event or set $A$ [15] |
| $p(\cdot), f(\cdot)$ | Probability density function (PDF) or probability mass function (PMF) [15] |
| $p(x \mid A)$ | Conditional PDF or PMF [15] |
| $F(\cdot)$ | Cumulative distribution function (CDF) |
| $\Phi_x(\omega), M_x(j\omega), E\left[e^{j\omega x}\right]$ | First characteristic function (CF) of $x$ [19, 24] |
| $M_x(t), \Phi_x(-jt), E\left[e^{tx}\right]$ | Moment-generating function (MGF) of $x$ [19, 24] |
| $\Psi_x(\omega), \ln \Phi_x(\omega), \ln E\left[e^{j\omega x}\right]$ | Second characteristic function |
| $K_x(t), \ln E\left[e^{tx}\right], \ln M_x(t)$ | Cumulant-generating function (CGF) of $x$ [10] |

## 3.4 Distributions

| | |
|---|---|
| $\mathcal{N}(\mu, \sigma^2)$ | Gaussian distribution of a random variable with mean $\mu$ and variance $\sigma^2$ |
| $\mathcal{CN}(\mu, \sigma^2)$ | Complex Gaussian distribution of a random variable with mean $\mu$ and variance $\sigma^2$ |
| $\mathcal{N}(\boldsymbol{\mu}, \boldsymbol{\Sigma})$ | Gaussian distribution of a vector random variable with mean $\boldsymbol{\mu}$ and covariance matrix $\boldsymbol{\Sigma}$ |
| $\mathcal{CN}(\boldsymbol{\mu}, \boldsymbol{\Sigma})$ | Complex Gaussian distribution of a vector random variable with mean $\boldsymbol{\mu}$ and covariance matrix $\boldsymbol{\Sigma}$ |
| $\mathcal{U}(a, b)$ | Uniform distribution from $a$ to $b$ |
| $\chi^2(n), \chi_n^2$ | Chi-square distribution with $n$ degree of freedom (assuming that the Gaussians are $\mathcal{N}(0, 1)$) |
| $\mathrm{Exp}(\lambda)$ | Exponential distribution with rate parameter $\lambda$ |
| $\Gamma(\alpha, \beta)$ | Gamma distribution with shape parameter $\alpha$ and rate parameter $\beta$ |
| $\Gamma(\alpha, \theta)$ | Gamma distribution with shape parameter $\alpha$ and scale parameter $\theta = 1/\beta$ |
| $\mathrm{Nakagami}(m, \boldsymbol{\Omega})$ | Nakagami-m distribution with shape parameter or fading figure $m$ and spread, scale, or shape parameter $\boldsymbol{\Omega}$ |
| $\mathrm{Rayleigh}(\sigma)$ | Rayleigh distribution with scale parameter $\sigma$ |
| $\mathrm{Rayleigh}(\boldsymbol{\Omega})$ | Rayleigh distribution with the second moment $\boldsymbol{\Omega} = E\left[x^2\right] = 2\sigma^2$ |
| $\mathrm{Rice}(s, \sigma)$ | Rice distribution with noncentrality parameter $s$ and $\sigma$. $s^2$ represent the specular component power |
| $\mathrm{Rice}(A, K)$ | Rice distribution with Rice factor $K = s^2/2\sigma^2$ and scale parameter $A = s^2 + 2\sigma^2$ |

# 4 Machine learning, optimization theory, and statistical signal processing

## 4.1 Derivative terms

| | |
|---|---|
| $\boldsymbol{\nabla} f, \mathbf{g}$ | Gradient descent vector |

| | |
|---|---|
| $\boldsymbol{\nabla}_x f, \mathbf{g}_x$ | Gradient descent vector with respect $x$ [2] |
| $\mathbf{J}$ | Jacobian matrix |
| $\mathbf{H}$ | Hessian matrix |

## 4.2 Estimated terms

| | |
|---|---|
| $\mathbf{g}$ (or $\hat{\mathbf{g}}$ if the gradient vector is $\mathbf{g}$) | Stochastic gradient descent (SGD), i.e., instantaneous approximation of gradient descent vector |
| $\hat{x}(t)$ or $\hat{x}[n]$ | Estimate of $x(t)$ or $x[n]$ |
| $\hat{\boldsymbol{\mu}}_x, \hat{\mathbf{m}}_x$ | Sample mean of $x[n]$ or $x(t)$ |
| $\hat{\boldsymbol{\mu}}_{\mathbf{x}}, \hat{\mathbf{m}}_{\mathbf{x}}$ | Sample mean vector of $\mathbf{x}[n]$ or $\mathbf{x}(t)$ |
| $\hat{r}_x(\tau), \hat{R}_x(\tau)$ | Estimated autocorrelation function of the signal $x(t)$ or $x[n]$ |
| $\hat{S}_x(f), \hat{S}_x(j\omega)$ | Estimated power spectral density (PSD) of $x(t)$ in linear $(f)$ or angular $(\omega)$ frequency |
| $\hat{\mathbf{R}}_{\mathbf{x}}$ | Sample (auto)correlation matrix |
| $\hat{r}_{x,d}(\tau), \hat{R}_{x,d}(\tau)$ | Estimated cross-correlation between $x[n]$ and $d[n]$ or $x(t)$ and $d(t)$ |
| $\hat{S}_{x,y}(f), \hat{S}_{x,y}(j\omega)$ | Estimated cross PSD of $x(t)$ and $y(t)$ in linear or angular $(\omega)$ frequency |
| $\hat{\mathbf{R}}_{\mathbf{xy}}$ | Sample cross-correlation matrix of $\mathbf{R}_{\mathbf{xy}}$ |
| $\hat{c}_x(\tau), \hat{C}_x(\tau)$ | Estimated autocovariance function of the signal $x(t)$ or $x[n]$ |
| $\hat{\mathbf{C}}_{\mathbf{x}}, \hat{\mathbf{K}}_{\mathbf{x}}, \hat{\boldsymbol{\Sigma}}_{\mathbf{x}}$ | Sample (auto)covariance matrix |
| $\hat{c}_{xy}(\tau), \hat{C}_{xy}(\tau)$ | Estimated cross-covariance function of the signal $x(t)$ or $x[n]$ |
| $\hat{\mathbf{C}}_{\mathbf{xy}}, \hat{\mathbf{K}}_{\mathbf{xy}}, \hat{\boldsymbol{\Sigma}}_{\mathbf{xy}}$ | Sample cross-covariance matrix |
| $\hat{\mathbf{H}}$ | Estimate of the Hessian matrix |

## 4.3 Signals, (hyper)parameters, system performance, and criteria

| | |
|---|---|
| $\mathbf{x}(n), \mathbf{x}_n$ | Input signal |
| $\mathbf{y}(n), \mathbf{y}_n$ | Output signal |
| $\hat{\mathbf{y}}(n), \hat{\mathbf{y}}_n$ | Alternative output signal |
| $d(n), d_n$ | Desired label (in case of supervised learning) |

| | |
|---|---|
| $\hat{\mathbf{y}}(n), \hat{\mathbf{y}}_n$ | Alternative desired signal if the output is $\mathbf{y}(n), \mathbf{y}_n$ |
| $\mathbf{w}(n), \mathbf{w}_n, \boldsymbol{\theta}(n), \boldsymbol{\theta}_n$ | Parameters, coefficients, or weights vector |
| $\mathbf{w}_o, \mathbf{w}^\star, \boldsymbol{\theta}_o, \boldsymbol{\theta}^\star$ | Optimum value of the parameters, coefficients, or weights vector |
| $\mathbf{W}$ | Matrix of the weights |
| $\eta$ | Learning rate hyperparameter |
| $J(\cdot), \mathcal{E}(\cdot)$ | Cost-function or objective function |
| $\Lambda(\cdot)$ | Likelihood function |
| $\Lambda_l(\cdot)$ | Log-likelihood function |
| $\hat{\rho}_{x,y}$ | Estimated Pearson correlation coefficient between $x$ and $y$ |
| $\rho$ | Distance of the margin of separation between two classes (Support Vector Machine, SVM) |
| $g(\cdot)$ | Discriminant function, i.e., $g(\mathbf{w}^\star) = 0$ |

# 5 Linear Algebra

## 5.1 Common matrices and vectors

| | |
|---|---|
| $\mathbf{W}, \mathbf{D}$ | Diagonal matrix |
| $\mathbf{P}$ | Projection matrix; Permutation matrix |
| $\mathbf{J}$ | Jordan matrix |
| $\mathbf{L}$ | Lower matrix |
| $\mathbf{U}$ | Upper matrix |
| $\mathbf{C}$ | Cofactor matrix |
| $\mathbf{C}_\mathbf{A}, \mathrm{cof}\,(\mathbf{A})$ | Cofactor matrix of $\mathbf{A}$ |
| $\mathbf{S}$ | Symmetric matrix |
| $\mathbf{Q}$ | Orthogonal matrix |
| $\mathbf{I}_N$ | $N \times N$-dimensional identity matrix |
| $\mathbf{0}_{M\times N}$ | $M \times N$-dimensional null matrix |
| $\mathbf{0}_N$ | $N$-dimensional null vector |
| $\mathbf{1}_{M\times N}$ | $M \times N$-dimensional ones matrix |
| $\mathbf{1}_N$ | $N$-dimensional ones vector |
| $\mathbf{0}$ | Null matrix, vector, or tensor (dimensionality understood by context) |
| $\mathbf{1}$ | Ones matrix, vector, or tensor (dimensionality understood by context) |

## 5.2 Indexing

| | |
|---|---|
| $x_{i_1,i_2,\ldots,i_N}, [\mathcal{X}]_{i_1,i_2,\ldots,i_N}$ | Element in the position $(i_1, i_2, \ldots, i_N)$ of the tensor $\mathcal{X}$ |
| $\mathcal{X}^{(n)}$ | $n$th tensor of a nontemporal sequence |
| $\mathbf{x}_n, \mathbf{x}_{:n}$ | $n$th column of the matrix $X$ |
| $\mathbf{x}_{n:}$ | $n$th row of the matrix $X$ |
| $\mathbf{x}_{i_1,\ldots,i_{n-1},:,i_{n+1},\ldots,i_N}$ | Mode-$n$ fiber of the tensor $\mathcal{X}$ |
| $\mathbf{x}_{:,i_2,i_3}$ | Column fiber (mode-1 fiber) of the thrid-order tensor $\mathcal{X}$ |
| $\mathbf{x}_{i_1,:,i_3}$ | Row fiber (mode-2 fiber) of the thrid-order tensor $\mathcal{X}$ |
| $\mathbf{x}_{i_1,i_2,:}$ | Tube fiber (mode-3 fiber) of the thrid-order tensor $\mathcal{X}$ |
| $\mathbf{X}_{i_1,:,:}$ | Horizontal slice of the thrid-order tensor $\mathcal{X}$ |
| $\mathbf{X}_{:,i_2,:}$ | Lateral slices slice of the thrid-order tensor $\mathcal{X}$ |
| $\mathbf{X}_{i_3}, \mathbf{X}_{:,:,i_3}$ | Frontal slices slice of the thrid-order tensor $\mathcal{X}$ |

## 5.3 General operations

| | |
|---|---|
| $\langle \mathbf{a}, \mathbf{b} \rangle, \mathbf{a}^\top \mathbf{b}, \mathbf{a} \cdot \mathbf{b}$ | Inner or dot product |
| $\mathbf{a} \circ \mathbf{b}, \mathbf{a}\mathbf{b}^\top$ | Outer product |
| $\otimes$ | Kronecker product |
| $\odot$ | Hadamard (or Schur) (elementwise) product |
| $.^{\odot n}$ | $n$th-order Hadamard power |
| $.^{\odot \frac{1}{n}}$ | $n$th-order Hadamard root |
| $\oslash$ | Hadamard (or Schur) (elementwise) division |
| $\diamond$ | Khatri-Rao product |
| $\otimes$ | Kronecker Product |
| $\times_n$ | $n$-mode product |

## 5.4 Operations with matrices and tensors

| | |
|---|---|
| $\mathbf{A}^{-1}$ | Inverse matrix |
| $\mathbf{A}^{+}, \mathbf{A}^{\dagger}$ | Moore-Penrose left pseudoinverse |
| $\mathbf{A}^{\top}$ | Transpose |

| | |
|---|---|
| $\mathbf{A}^{-\top}$ | Transpose of the inverse, i.e., $\left(\mathbf{A}^{-1}\right)^{\top} = (\mathbf{A}^{\top})^{-1}$ [8, 18] |
| $\mathbf{A}^{*}$ | Complex conjugate |
| $\mathbf{A}^{\mathsf{H}}$ | Hermitian |
| $\lVert\mathbf{A}\rVert_{\mathrm{F}}$ | Frobenius norm |
| $\lVert\mathbf{A}\rVert$ | Matrix norm |
| $\lvert\mathbf{A}\rvert$, $\det(\mathbf{A})$ | Determinant |
| $\mathrm{diag}(\mathbf{A})$ | The elements in the diagonal of $\mathbf{A}$ |
| $\mathbf{E}[\mathbf{A}]$ | Vectorization: stacks the columns of the matrix $\mathbf{A}$ into a long column vector |
| $\mathbf{E}_d[\mathbf{A}]$ | Extracts the diagonal elements of a square matrix and returns them in a column vector |
| $\mathbf{E}_l[\mathbf{A}]$ | Extracts the elements strictly below the main diagonal of a square matrix in a column-wise manner and returns them into a column vector |
| $\mathbf{E}_u[\mathbf{A}]$ | Extracts the elements strictly above the main diagonal of a square matrix in a column-wise manner and returns them into a column vector |
| $\mathbf{E}_b[\mathbf{A}]$ | Block vectorization operator: stacks square block matrices of the input into a long block column matrix |
| $\mathrm{unvec}(\mathbf{A})$ | Reshapes a column vector into a matrix |
| $\mathrm{tr}\{\mathbf{A}\}$ | trace |
| $\mathbf{X}_{(n)}$ | $n$-mode matricization of the tensor $\mathcal{X}$ |

## 5.5 Operations with vectors

| | |
|---|---|
| $\lVert\mathbf{a}\rVert$ | $l_1$ norm, 1-norm, or Manhatan norm |
| $\lVert\mathbf{a}\rVert$, $\lVert\mathbf{a}\rVert_2$ | $l_2$ norm, 2-norm, or Euclidean norm |
| $\lVert\mathbf{a}\rVert_p$ | $l_p$ norm, $p$-norm, or Minkowski norm |
| $\lVert\mathbf{a}\rVert_\infty$ | $l_\infty$ norm, $\infty$-norm, or Chebyshev norm |
| $\mathrm{diag}(\mathbf{a})$ | Diagonalization: a square, diagonal matrix with entries given by the vector $\mathbf{a}$ |

## 5.6 Decompositions

| | |
|---|---|
| $\mathbf{\Lambda}$ | Eigenvalue matrix [23] |
| $\mathbf{Q}$ | Eigenvectors matrix; Orthogonal matrix of the QR decomposition[23] |
| $\mathbf{R}$ | Upper triangular matrix of the QR decomposition[23] |
| $\mathbf{U}$ | Left singular vectors[23] |
| $\mathbf{U}_r$ | Left singular nondegenerated vectors |
| $\mathbf{\Sigma}$ | Singular value matrix |
| $\mathbf{\Sigma}_r$ | Singular value matrix with nonzero singular values in the main diagonal |
| $\mathbf{\Sigma}^+$ | Singular value matrix of the pseudoinverse [23] |
| $\mathbf{\Sigma}_r^+$ | Singular value matrix of the pseudoinverse with nonzero singular values in the main diagonal |
| $\mathbf{V}$ | Right singular vectors [23] |
| $\mathbf{V}_r$ | Right singular nondegenerated vectors |
| $\operatorname{eig}(\mathbf{A})$ | Set of the eigenvalues of $\mathbf{A}$ [5, 15, 18] |
| $[\![\mathbf{A}, \mathbf{B}, \mathbf{C}, \ldots]\!]$ | CANDECOMP/PARAFAC (CP) decomposition of the tensor $\mathcal{X}$ from the outer product of column vectors of $\mathbf{A}$, $\mathbf{B}$, $\mathbf{C}$, ... |
| $[\![\boldsymbol{\lambda}; \mathbf{A}, \mathbf{B}, \mathbf{C}, \ldots]\!]$ | Normalized CANDECOMP/PARAFAC (CP) decomposition of the tensor $\mathcal{X}$ from the outer product of column vectors of $\mathbf{A}$, $\mathbf{B}$, $\mathbf{C}$, ... |

## 5.7 Spaces and sets

| | |
|---|---|
| $\operatorname{span}\{\mathbf{a}_1, \mathbf{a}_2, \ldots, \mathbf{a}_n\}$ | Vector space spanned by the argument vectors [8] |
| $\mathrm{C}(\mathbf{A})$, columnspace$(\mathbf{A})$, range$(\mathbf{A})$, $\operatorname{span}\{\mathbf{A}\}$, image$(\mathbf{A})$ | Columnspace, range or image, i.e., the space $\operatorname{span}\{\mathbf{a}_1, \mathbf{a}_2, \ldots, \mathbf{a}_n\}$, where $\mathbf{a}_i$ is the ith column vector of the matrix $\mathbf{A}$ [16, 23] |
| $\mathrm{C}(\mathbf{A}^{\mathsf{H}})$ | Row space (also called left columnspace) [16, 23] |
| $\mathrm{N}(\mathbf{A})$, nullspace$(\mathbf{A})$, null$(\mathbf{A})$, kernel$(\mathbf{A})$ | Nullspace (or kernel space) [16, 23, 24] |
| $\mathrm{N}(\mathbf{A}^{\mathsf{H}})$ | Left nullspace |
| $\operatorname{rank}\mathbf{A}$ | Rank, that is, $\dim(\operatorname{span}\{\mathbf{A}\}) = \dim(\mathrm{C}(\mathbf{A}))$ [16] |

| | |
|---|---|
| nullity $(\mathbf{A})$ | Nullity of $\mathbf{A}$, i.e., $\dim(\mathrm{N}(\mathbf{A}))$ |
| $\{1, 2, \ldots, n\}$ | Discrete set containing the integer elements $1, 2, \ldots, n$ |
| $U$ | Universe |
| $2^A$ | Power set of $A$ |
| $\mathbb{R}$ | Set of real numbers |
| $\mathbb{C}$ | Set of complex numbers |
| $\mathbb{Z}$ | Set of integer number |
| $\mathbb{B} = \{0, 1\}$ | Boolean set |
| $\varnothing$ | Empty set |
| $\mathbb{N}$ | Set of natural numbers |
| $\mathbb{K} \in \{\mathbb{R}, \mathbb{C}\}$ | Real or complex space (field) |
| $\mathbb{K}^{I_1 \times I_2 \times \cdots \times I_N}$ | $I_1 \times I_2 \times \cdots \times I_N$-dimensional real (or complex) space |
| $\mathbb{K}_+$ | Nonnegative real (or complex) space [3] |
| $\mathbb{K}_{++}$ | Positive real (or complex) space, i.e., $\mathbb{K}_{++} = \mathbb{K}_+ \setminus \{\mathbf{0}\}$ [3] |
| $\mathbb{S}^n, \mathcal{S}^n$ | Conic set of the symmetric matrices in $\mathbb{R}^{n \times n}$ [3] |
| $\mathbb{S}^n_+, \mathcal{S}^n_+$ | Conic set of the symmetric positive semidefinite matrices in $\mathbb{R}^{n \times n}$ [3] |
| $\mathbb{S}^n_{++}, \mathcal{S}^n_{++}$ | Conic set of the symmetric positive definite matrices in $\mathbb{R}^{n \times n}$, i.e., $\mathbb{S}^n_{++} = \mathbb{S}^n_+ \setminus \{\mathbf{0}\}$ [3] |
| $\mathbb{H}^n$ | Set of all hermitian matrices in $\mathbb{C}^{n \times n}$ |
| $[a, b]$ | Closed interval of a real set from $a$ to $b$ |
| $(a, b)$ | Opened interval of a real set from $a$ to $b$ |
| $[a, b), (a, b]$ | Half-opened intervals of a real set from $a$ to $b$ |
| conv $C$ | Convex hull |
| aff $C$ | Affune hull |
| $\mathcal{R}$ | Ray |
| $\mathcal{H}$ | Hyperplane |
| $\mathcal{H}_+, \mathcal{H}_-$ | Positive/negative halfspace |
| $B(\mathbf{x}_c, r)$ | Euclidean ball with radium $r$ and centered at $\mathbf{x}_c$ |
| $\mathcal{E}$ | Ellipsoid |
| $C$ | Norm cone |
| $K$ | Proper cone |
| $K^*$ | Dual cone |

| | |
|---|---|
| $\mathcal{P}$ | Polyhedra |
| $S$ | Simplex |
| $C_\alpha$ | $\alpha$-sublevel set |
| epi $f$ | Epigraph of the function $f$ |
| hypo $f$ | Hypograph of the function $f$ |

## 5.8 Set operations

| | |
|---|---|
| $A + B$ | Set addition (Minkowski sum), i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} = \mathbf{x} + \mathbf{y},\ \forall\ \ \mathbf{x} \in \mathcal{X} \wedge \mathbf{y} \in \mathcal{Y}\}$ [13] |
| $A - B$ | Minkowski difference, i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} = \mathbf{x} - \mathbf{y},\ \forall\ \ \mathbf{x} \in \mathcal{X} \wedge \mathbf{y} \in \mathcal{Y}\}$ |
| $A \ominus B$ | Pontryagin difference, i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} + \mathbf{y} \in \mathcal{X},\ \forall\ \ \mathbf{y} \in \mathcal{Y}\}$ [13] |
| $A \setminus B, A - B$ | Set difference or set subtraction, i.e., $A \setminus B = \{x \mid x \in A \wedge x \notin B\}$ the set containing the elements of $A$ that are not in $B$ [21] |
| $A \cup B$ | Set of union |
| $A \cap B$ | Set of intersection |
| $A \times B$ | Cartesian product |
| $A^n$ | $\underbrace{A \times A \times \cdots \times A}_{n \text{ times}}$ |
| $A^\perp$ | Orthogonal complement of $A$, e.g., $\mathrm{N}(\mathbf{A}) = \mathrm{C}(\mathbf{A}^\top)^\perp$ [3] |
| $\mathbf{a} \perp \mathbf{b}$ | $\mathbf{a}$ is orthogonal to $\mathbf{b}$ |
| $\mathbf{a} \not\perp \mathbf{b}$ | $\mathbf{a}$ is not orthogonal to $\mathbf{b}$ |
| $A \oplus B$ | Direct sum, i.e., each $\mathbf{v} \in \{\sum \mathbf{a}_i \mid \mathbf{a}_i \in S_i, i = 1, \ldots, k\}$ has a unique representation of $\sum \mathbf{a}_i$ with $\mathbf{a}_i \in S_i$. That is, they expand to a space. Note that $\{S_i\}$ might not be orthogonal each other [8] |
| $A \overset{\perp}{\oplus} B$ | Direct sum of two space that are orthogonal and span a $n$-dimensional space, e.g., $\mathrm{C}(\mathbf{A}^\top) \overset{\perp}{\oplus} \mathrm{C}(\mathbf{A}^\top)^\perp = \mathbb{R}^n$ (this decomposition of $\mathbb{R}^n$ is called the orthogonal decomposition induced by $\mathbf{A}$) [3] |
| $\bar{A}, A^c$ | Complement set (given $U$) |
| $\#A, \lvert A \rvert$ | Cardinality |

| | |
|---|---|
| $a \in A$ | $a$ is element of $A$ |
| $a \notin A$ | $a$ is not element of $A$ |

### 5.9 Inequalities

| | |
|---|---|
| $\mathcal{X} \leq 0$ | Nonnegative tensor |
| $\mathbf{a} \preceq_K \mathbf{b}$ | Generalized inequality meaning that $\mathbf{b}-\mathbf{a}$ belongs to the conic subset $K$ in the space $\mathbb{R}^n$[3] |
| $\mathbf{a} \prec_K \mathbf{b}$ | Strict generalized inequality meaning that $\mathbf{b}-\mathbf{a}$ belongs to the interior of the conic subset $K$ in the space $\mathbb{R}^n$[3] |
| $\mathbf{a} \preceq \mathbf{b}$ | Generalized inequality meaning that $\mathbf{b}-\mathbf{a}$ belongs to the nonnegative orthant conic subset, $\mathbb{R}^n_+$, in the space $\mathbb{R}^n$.[3] |
| $\mathbf{a} \prec \mathbf{b}$ | Strict generalized inequality meaning that $\mathbf{b}-\mathbf{a}$ belongs to the positive orthant conic subset, $\mathbb{R}^n_{++}$, in the space $\mathbb{R}^n$[3] |
| $\mathbf{A} \preceq_K \mathbf{B}$ | Generalized inequality meaning that $\mathbf{B}-\mathbf{A}$ belongs to the conic subset $K$ in the space $\mathbb{S}^n$[3] |
| $\mathbf{A} \prec_K \mathbf{B}$ | Strict generalized inequality meaning that $\mathbf{B}-\mathbf{A}$ belongs to the interior of the conic subset $K$ in the space $\mathbb{S}^n$[3] |
| $\mathbf{A} \preceq \mathbf{B}$ | Generalized inequality meaning that $\mathbf{B}-\mathbf{A}$ belongs to the positive semidefinite conic subset, $\mathbb{S}^n_+$, in the space $\mathbb{S}^n$[3] |
| $\mathbf{A} \prec \mathbf{B}$ | Strict generalized inequality meaning that $\mathbf{B}-\mathbf{A}$ belongs to the positive orthant conic subset, $\mathbb{S}^n_{++}$, in the space $\mathbb{S}^n$[3] |

# 6 Communication systems

### 6.1 Symbols

| | |
|---|---|
| $B$ | One-sided bandwidth of the transmitted signal, in Hz |

| | |
|---|---|
| $W$ | One-sided bandwidth of the transmitted signal, in rad/s |
| $x_i$ | Real or in-phase part of $x$ |
| $x_q$ | Imaginary or quadrature part of $x$ |
| $f_c, f_{RF}$ | Carrier frequency (in Hertz) |
| $f_L$ | Carrier frequency in L-band (in Hertz) |
| $f_{IF}$ | Intermediate frequency (in Hertz) |
| $f_s$ | Sampling frequency or sampling rate (in Hertz) |
| $T_s$ | Sampling time interval/duration/period |
| $R$ | Bit rate |
| $T$ | Bit interval/duration/period |
| $T_c$ | Chip interval/duration/period |
| $T_{sy}, T_{sym}$ | Symbol/signaling[19] interval/duration/period |
| $s_{RF}$ | Transmitted signal in RF |
| $s_{FI}$ | Transmitted signal in FI |
| $s, s_l$ | Lowpass (or baseband) equivalent signal or envelope complex of transmitted signal |
| $r_{RF}$ | Received signal in RF |
| $r_{FI}$ | Received signal in FI |
| $r, r_l$ | Lowpass (or baseband) equivalent signal or envelope complex of received signal |
| $\phi$ | Signal phase |
| $\phi_0$ | Initial phase |
| $\eta_{RF}, w_{RF}$ | Noise in RF |
| $\eta_{FI}, w_{FI}$ | Noise in FI |
| $\eta, w$ | Noise in baseband |
| $\tau$ | Timing delay |
| $\Delta\tau$ | Timing error (delay - estimated) |
| $\varphi$ | Phase offset |
| $\Delta\varphi$ | Phase error (offset - estimated) |
| $f_d$ | Linear Doppler frequency |
| $\Delta f_d$ | Frequency error (Doppler frequency - estimated) |
| $\nu$ | Angular Doppler frequency |
| $\Delta\nu$ | Frequency error (Doppler frequency - estimated) |
| $\gamma, A$ | Transmitted signal amplitude |

| | |
|---|---|
| $\gamma_0, A_0$ | Combined effect of the path loss and antenna gain |

## 6.2 Fading multipath channels

| | |
|---|---|
| $t \overset{\mathcal{F}}{\leftrightarrow} \lambda$ | Support temporal of the signal. $\lambda$ is obtained after taking the Fourier transform on $t$. |
| $\tau \overset{\mathcal{F}}{\leftrightarrow} f$ | Second support temporal of the signal ($c(t)$ varies with with the input at the time $\tau$). $f$ is obtained after taking the Fourier transform on $\tau$. |
| $c(t, \tau)$ | Complex envelope of the channel response at the time $t$ due to an impulse applied at the $t - \tau$ |
| $C(f, t)$ | Transfer function of $c(t, \tau)$ in $\tau$ |
| $\alpha(t, \tau)$ | Attenuation of $c(t, \tau)$, i.e., $c(t, \tau) = \alpha(t, \tau)e^{e\pi f_c \tau}$ |
| $R_c(\tau_1, \tau_2, \Delta t)$ | Autocorrelation function of $c(t, \tau)$, i.e., $R_c(\tau_1, \tau_2, \Delta t) = \mathrm{E}\left[c^*(t, \tau_1), c^*(t + \Delta t, \tau_2)\right]$ |
| $R_c(\tau, \Delta t)$ | Autocorrelation function of $c(t, \tau)$ assuming uncorrelated scattering |
| $R_c(\tau)$, $R_c(\tau, \Delta t)\big\rvert_{\Delta t=0}$ | Multipath intensity profile or delay power spectrum |
| $R_C(\Delta f, \Delta t), R_C(f_1, f_2; \Delta t)$, $\mathrm{E}\left[C(f_1, t), C(f_2, t + \Delta t)\right]$, $\mathcal{F}_\tau\left\{R_c(\tau, \Delta t)\right\}$ | Spaced-frequency, spaced-time correlation function ($\Delta f = f_2 - f_1$) |
| $R_C(\Delta f)$, $R_C(\Delta f, \Delta t)\big\rvert_{\Delta t=0}$, $\mathcal{F}\left\{R_c(\tau)\right\}$ | Spaced-frequency correlation function |
| $(\Delta f)_c$ | Coherence bandwidth of $c(t)$, that is, the frequency interval in which $R_C(\Delta f)$ is nonzero |
| $T_m$ | Multipath spread of the channel, that is, the time interval in which $R_c(\tau)$ is nonzero ($T_m \approx 1/(\Delta f)_c$) |
| $R_C(\Delta t)$, $R_C(\Delta f, \Delta t)\big\rvert_{\Delta f=0}$ | Spaced-time correlation function |
| $S_C(\lambda), \mathcal{F}\left\{R_C(\Delta t)\right\}$ | Doppler power spectrum |
| $(\Delta t)_c$ | Coherence time of $c(t)$, that is, the time interval in which $R_C(\Delta t)$ is nonzero |

| | |
|---|---|
| $B_m$ | Multipath spread of the channel, that is, the frequency interval in which $S_c(\lambda)$ is nonzero ($B_d \approx 1/(\Delta t)_c$) |
| $S_C(\tau, \lambda), \mathcal{F}_{\Delta f, \Delta t}\{R_C(\Delta f, \Delta t)\}$ | Scattering function |

# 7 Discrete mathematics

## 7.1 Quantifiers, inferences

| | |
|---|---|
| $\forall$ | For all (universal quantifier) [9] |
| $\exists$ | There exists (existential quantifier) [9] |
| $\nexists$ | There does not exist [9] |
| $\exists!$ | There exist an unique [9] |
| $\in$ | Belongs to [9] |
| $\notin$ | Does not belong to [9] |
| $\because$ | Because [9] |
| $\mid, :$ | Such that, sometimes that parantheses is used [9] |
| $,, (\cdot)$ | Used to separate the quantifier with restricted domain from the its scope, e.g., $\forall \quad x < 0 \left(x^2 > 0\right)$ or $\forall \quad x < 0, x^2 > 0$ [9] |
| $\therefore$ | Therefore [9] |

## 7.2 Propositional Logic

| | |
|---|---|
| $\neg a$ | Logical negation of $a$ [21] |
| $a \wedge b$ | Conjunction (logical AND) operator between $a$ and $b$[21] |
| $a \vee b$ | Disjunction (logical OR) operator between $a$ and $b$[21] |
| $a \oplus b$ | Exclusive OR (logical XOR) operator between $a$ and $b$[21] |
| $a \rightarrow b$ | Implication (or conditional) statement[21] |
| $a \leftrightarrow b$ | Bi-implication (or biconditional) statement, i.e., $(a \rightarrow b) \wedge (b \rightarrow a)$ [21] |
| $a \equiv b, a \iff b, a \Leftrightarrow b$ | Logical equivalence, i.e., $a \leftrightarrow b$ is a tautology[21] |

### 7.3 Operations

| | |
|---|---|
| $\lvert a \rvert$ | Absolute value of $a$ |
| log | Base-10 logarithm or decimal logarithm |
| ln | Natual logarithm |
| $\mathrm{Re}\{x\}$ | Real part of $x$ |
| $\mathrm{Im}\{x\}$ | Imaginary part of $x$ |
| $\angle\cdot$ | Phase (complex argument) |
| $x \bmod y$ | Remainder, i.e., $x - y\lfloor x/y \rfloor$, for $y \neq 0$ |
| $x \operatorname{div} y$ | Quotient [21] |
| $x \equiv y \pmod{m}$ | Congruent, i.e., $m \backslash (x - y)$ [21] |
| $\mathrm{frac}(x)$ | Fractional part, i.e., $x \bmod 1$ [9] |
| $a \backslash b$, $a \mid b$ | $b$ is a positive integer multiple of $a$, i.e., $\exists\, n \in \mathbb{Z}_{++} \mid b = na$ [9, 21] |
| $a \not\backslash b$, $a \nmid b$ | $b$ is not a positive integer multiple of $a$, i.e., $\nexists\, n \in \mathbb{Z}_{++} \mid b = na$ [9, 21] |
| $\lceil\cdot\rceil$ | Ceiling operation [9] |
| $\lfloor\cdot\rfloor$ | Floor operation [9] |

# 8 Electromagnetic waves

| | |
|---|---|
| $\mathbf{\Phi}$ | Electric flux (scalar) (in V m) |
| $\mathbf{J}$ | Electric current density vector (in $\mathrm{A/m^2}$) |
| $\mathbf{H}$ | Magnetic field vector (in A/m) |
| $\mathbf{B}$ | Magnetic flux density vector (in $\mathrm{Wb/m^2} = \mathrm{T}$) |
| $q$ | Electric charge strength/magnitude (in C) |
| $\rho$ | Electric charge density (for volumes) (in $\mathrm{C/m^3}$) |
| $\rho_s$ | Electric charge density (for surface) (in $\mathrm{C/m^2}$) |
| $\rho_l$ | Electric charge density (for volumes) (in C/m) |
| $\mathbf{f}$ | Electrostatic force (Coulomb force), (in $\mathrm{kg\,m/s^2}$) |
| $\varepsilon$ | Electric permittivity(in F/m) [20] |
| $\varepsilon_r$ | Relative electric permittivity or dielectric constant (in F/m) [20] |

| | |
|---|---|
| $\varepsilon_0$ | Electric permittivity in vacuum, $8.854 \times 10^{-12}$ F/m [20] |
| $\mathbf{E}$ | Electric field vector (in V/m) |
| $\mathbf{D}$ | Electric flux density, electric displacement, or electric induction vector (in $C/m^2$) |
| $\mathbf{P}$ | Electric polarization of the material (in $C/m^2$) |
| $\chi_e$ | Electric susceptibility (for linear and isotropic materiais) |
| $\mu$ | Magnetic permeability |
| $\mu_0$ | Magnetic permeability in vacuum |

# 9 Calculus

| | |
|---|---|
| $\nabla$ | Vector differential operator (Nabla symbol), i.e., $\nabla f$ is the gradient of the scalar-valued function $f$, i.e., $f : \mathbb{R}^n \to \mathbb{R}$ |
| $t, (u, v)$ | Parametric variables commonly used, $t$ for one variable, $(u, v)$ for two variables[22] |
| $\mathbf{r}(t)$ | Vector position $(x(t), y(t), z(t))$ parametrized by $t$[22] |
| $\mathbf{r}'(t)$ | First derivative of $\mathbf{r}(t)$, i.e., the tangent vector of the curve $(x(t), y(t), z(t))$ [22] |
| $\mathbf{T}(t), \mathbf{u}(t)$ | Tangent unit vector of $\mathbf{r}(t)$, i.e., $\mathbf{u}(t) = \mathbf{r}'(t)/\lvert\mathbf{r}'(t)\rvert$[14, 22] |
| $\mathbf{n}(t), \left(\frac{y'(t)}{\lvert\mathbf{r}'(t)\rvert}, -\frac{x'(t)}{\lvert\mathbf{r}'(t)\rvert}\right)$ | Normal vector of $\mathbf{r}(t)$, i.e., $\mathbf{n}(t) \perp \mathbf{T}(t)$[22] |
| $C$ | Contour that traveled by $\mathbf{r}(t)$, for $a \leq t \leq b$ [22] |
| $L, L(C)$ | Total length of the contour $C$ (which can be defined the vector $\mathbf{r}$, parametrized by $t$), i.e., $L_C = \int_a^b \lvert\mathbf{r}'(t)\rvert \, \mathrm{d}t$[22] |
| $s(t)$ | Length of the arc, which can be defined by the vector $\mathbf{r}$ and $t$, that is, $s(t) = \int_a^t \lvert\mathbf{r}'(u)\rvert \, \mathrm{d}u$ $(s(b) = L)$[22] |

| | |
|---|---|
| $\mathrm{d}s$ , $\mathrm{d}l$ | Differential operator of the length of the contour $C$, i.e., $\mathrm{d}s = \lvert\mathbf{r}'(t)\rvert\,\mathrm{d}t$. It is also denoted by $\mathrm{d}l$ [20] |
| $\int_C f(\mathbf{r})\,\mathrm{d}s$ , $\int_a^b f(\mathbf{r}(t))\lvert\mathbf{r}'(t)\rvert\,\mathrm{d}t$ | Line integral of the function $f : \mathbb{R}^n \to \mathbb{R}$ along the contour $C$ [1, 22] |
| $\int_C \mathbf{F}\cdot\mathrm{d}\mathbf{r}$ , $\int_a^b \mathbf{F}(\mathbf{r}(t))\cdot\mathbf{r}'(t)\,\mathrm{d}t$ , $\int_C \mathbf{F}\cdot\mathbf{T}\,\mathrm{d}s$ | Line integral of vector field $\mathbf{F}$ along the contour $C$ [1, 22] |
| $\int_{\mathbf{a}}^{\mathbf{b}} \mathbf{F}$, $\int_{\mathbf{a}}^{\mathbf{b}} \mathbf{F}\cdot\mathrm{d}\mathbf{r}$ | Alternative notation to the line integral, where the parametric variable $t$ goes from $a$ to $b$, making $r$ goes from $\mathbf{r}(a) = \mathbf{a}$ to $\mathbf{r}(b) = \mathbf{b}$ [1] |
| $\oint_C$, $\oint_C$ | Closed line integral along the contour $C$ |
| $\mathbf{r}(u, v)$ | Vector position $(x(u, v), y(u, v), z(u, v))$ parametrized by $(u, v)$ |
| $\mathbf{r}_u$ | $(\partial x/\partial u, \partial y/\partial u, \partial z/\partial u)$ |
| $\mathbf{r}_v$ | $(\partial x/\partial v, \partial y/\partial v, \partial z/\partial v)$ |
| $\mathrm{d}A$ | Differential operator of a 2D area (denoted by $D$ or $R$) in the $\mathbb{R}^2$ domain. This differential operator can be solved in different ways (rectangular, polar, cylindric, etc) [22] |
| $D, R$ | Integration domain in which $\mathrm{d}A$ is integrated, i.e., $\iint_D f\,\mathrm{d}A$ [22] |
| $S$ | Smooth surface $S$, i.e., a 2D area in a 3D space ($\mathbb{R}^3$ domain) |
| $\mathrm{d}S$ , $\lvert\mathbf{r}_u \times \mathbf{r}_v\rvert\,\mathrm{d}A$ | Differential operator of a 2D area in a 3D domain (an surface). Note that $\mathrm{d}S = \lvert\mathbf{r}_u \times \mathbf{r}_v\rvert\,\mathrm{d}A$ should be accompanied with the change of the integration interval(from $S$ to $D$) |
| $A(S)$, $\iint_S \mathrm{d}S$ , $\iint_D \lvert\mathbf{r}_u \times \mathbf{r}_v\rvert\,\mathrm{d}A$ | Area of the surface $S$ parametrized by $(u, v)$, in which $\mathrm{d}A$ is the area defined in the $D$ domain (which is form by the $u$-by-$v$ graph) |
| $\mathrm{d}V$ | Differential operator of a shape volume (denoted by $E$) in $\mathbb{R}^3$ domain, i.e., $\iiint_E \mathrm{d}V = V$ |
| $E$ | Integration domain in which $\mathrm{d}V$ is integrated, i.e., $\iiint_E f\,\mathrm{d}V$ [22] |

| | |
|---|---|
| $V, \iint_D f \, \mathrm{d}A \, , \iiint_E f \, \mathrm{d}V$ | Volume of the function $f$ over the regions $D$ (in the case of double integrais) or $E$ (in the case of triple integrais) |
| $\iint_S f \, \mathrm{d}S \, , \iint_D f \lvert \mathbf{r}_u \times \mathbf{r}_v \rvert \, \mathrm{d}A$ | Surface integral over $S$ |
| $\mathbf{n}(u, v), \frac{\mathbf{r}_u(u,v) \times \mathbf{r}_v(u,v)}{\lvert \mathbf{r}_u(u,v) \times \mathbf{r}_v(u,v) \rvert}$ | Normal vector of of the smooth surface $S$ |
| $\iint_S \mathbf{F} \cdot \mathbf{n} \, \mathrm{d}S \, , \iint_S \mathbf{F} \cdot \mathrm{d}\mathbf{S} \, ,$ $\iint_D \mathbf{F} \cdot (\mathbf{r}_u \times \mathbf{r}_v) \, \mathrm{d}A$ | Flux integral of vector field $\mathbf{F}$ through the smooth surface $S$ ($\mathbf{n} \, \mathrm{d}S \triangleq \mathrm{d}\mathbf{S}$) |
| $\nabla \times \mathbf{F}$, curl $\mathbf{F}$ | Curl (rotacional) of the vector field $\mathbf{F}$ |
| $\nabla \cdot \mathbf{F}$, div $\mathbf{F}$ | Divercence of the vector field $\mathbf{F}$ |
| $\nabla^2 f, \nabla \cdot (\nabla f), \Delta f,$ $\partial^2 f/\partial x^2 + \partial^2 f/\partial y^2 + \partial^2 f/\partial z^2$ | Scalar Laplacian operator (performed on a scalar-valued function $f : \mathbb{R}^n \to \mathbb{R}$) |
| $\nabla^2 \mathbf{F}, \nabla \times \nabla \times \mathbf{F} - \nabla(\nabla \cdot \mathbf{F}), \Delta \mathbf{F},$ $(\partial^2 \mathbf{F}/\partial x^2, \partial^2 \mathbf{F}/\partial y^2, \partial^2 \mathbf{F}/\partial z^2)$ | Vector Laplacian operator (performed on a vector field, i.e., a vector-valued function, $\mathbf{F} : \mathbb{R}^n \to \mathbb{R}^n$). $\nabla^2$ denotes the scalar (vector) Laplacian if the function is scalar-valued (vector-valued) |

# 10 Generic mathematical symbols

| | |
|---|---|
| $\blacksquare$ | Q.E.D. |
| $\triangleq$ | Equal by definition |
| $:=, \leftarrow$ | Assignment [21] |
| $\neq$ | Not equal |
| $\infty$ | Infinity |
| $j$ | $\sqrt{-1}$ |

# 11 Abbreviations

PS: Only names of techniques and algorithms or usual abbreviations are considered.

| | |
|---|---|
| wrt. | With respect to |
| st. | Subject to |
| iff. | If and only if |
| EVD | Eigenvalue decomposition, or eigendecomposition [16] |
| SVD | Singular value decomposition |
| CP | CANDECOMP/PARAFAC |

| | |
|---|---|
| SGD | Stochastic gradient descent |
| SVM | Support vector machine |
| BPNN | Backpropagation neural network [12] |
| RBF | Radial basis function |

# References


[1] TM Apostol. *Calculus, 2nd Edn., Vol. 2*. 1967.

[2] Christopher M Bishop and Nasser M Nasrabadi. *Pattern Recognition and Machine Learning*. Vol. 4. 4. Springer, 2006.

[3] Stephen Boyd, Stephen P. Boyd, and Lieven Vandenberghe. *Convex Optimization*. Cambridge university press, 2004.

[4] Robert Grover Brown and Patrick YC Hwang. "Introduction to Random Signals and Applied Kalman Filtering: With MATLAB Exercises and Solutions". In: *Introduction to random signals and applied Kalman filtering: with MATLAB exercises and solutions* (1997).

[5] Rama Chellappa and Sergios Theodoridis. *Signal Processing Theory and Machine Learning*. Academic Press, 2014. ISBN: 0-12-396502-0.

[6] Paulo SR Diniz. *Adaptive Filtering: Algorithms and Practical Implementation*. Nowell, MA: Kluwer Academic Publishers, 2002.

[7] Paulo SR Diniz, Eduardo AB Da Silva, and Sergio L Netto. *Digital Signal Processing: System Analysis and Design*. Cambridge University Press, 2010. ISBN: 1-139-49157-1.

[8] Gene H Golub and Charles F Van Loan. *Matrix Computations*. JHU press, 2013. ISBN: 1-4214-0859-7.

[9] Ronald L Graham et al. "Concrete Mathematics: A Foundation for Computer Science". In: *Computers in Physics* 3.5 (1989), pp. 106–107. ISSN: 0894-1866.

[10] Simon S Haykin. *Adaptive Filter Theory*. Pearson Education India, 2002. ISBN: 81-317-0869-1.

[11] Vinay K Ingle and John G Proakis. *Digital Signal Processing Using MATLAB*. Cole Publishing Company, 2000.

[12] Yu Jiao, John J Hall, and Yu T Morton. "Automatic Equatorial GPS Amplitude Scintillation Detection Using a Machine Learning Algorithm". In: *IEEE Transactions on Aerospace and Electronic Systems* 53.1 (2017), pp. 405–418. ISSN: 0018-9251.

[13] Basil Kouvaritakis and Mark Cannon. "Model Predictive Control". In: *Switzerland: Springer International Publishing* 38 (2016).

[14] Erwin Kreyszig, K Stroud, and G Stephenson. *Advanced Engineering Mathematics*. Vol. 9. John Wiley & Sons, Inc. 9 th edition, 2006 Page 2 of 6 Teaching methods ..., 2008.

[15] Alberto Leon-Garcia. *Probability, Statistics, and Random Processes for Electrical Engineering*. 3rd ed. edição. Upper Saddle River, NJ: Prentice Hall, 2007. ISBN: 978-0-13-147122-1.

[16] Josef Nossek. *Adaptive and Array Signal Processing*. 2015.

[17] Alan V. Oppenheim and Ronald W. Schafer. *Discrete-Time Signal Processing: International Edition*. 3ª edição. Upper Saddle River Munich: Pearson, Nov. 12, 2009. ISBN: 978-0-13-206709-6.

[18] Kaare Brandt Petersen and Michael Syskind Pedersen. "The Matrix Cookbook". In: *Technical University of Denmark* 7.15 (2008), p. 510.

[19] John Proakis and Masoud Salehi. *Digital Communications*. 5th ed. edição. Boston: Mc Graw Hill, Jan. 1, 2007. ISBN: 978-0-07-295716-7.

[20] Simon Ramo, John R Whinnery, and Theodore Van Duzer. *Fields and Waves in Communication Electronics*. John Wiley & Sons, 1994. ISBN: 81-265-1525-2.

[21] Kenneth H Rosen. "Discrete Mathematics and Its Applications (7Th Editio)". In: *William C Brown Pub* (2011).

[22] James Stewart. *Calculus*. Cengage Learning, 2011. ISBN: 1-133-17069-2.

[23] Gilbert Strang et al. *Introduction to Linear Algebra*. Vol. 3. Wellesley-Cambridge Press Wellesley, MA, 1993.

[24] Sergios Theodoridis. *Machine Learning: A Bayesian and Optimization Perspective*. 2nd ed. Academic Pr, 2020. ISBN: 978-0-12-818803-3.

[25] Harry L Van Trees. *Optimum Array Processing: Part IV of Detection, Estimation, and Modulation Theory*. John Wiley & Sons, 2002. ISBN: 0-471-09390-4.