

# Notation

Rubem Vasconcelos Pacelli  
rubem.engenharia@gmail.com

Department of Teleinformatics Engineering,  
Federal University of Ceará.  
Fortaleza, Ceará, Brazil.

Version: May 2, 2023

## Contents

### 1 Font notation

### 2 Signals and functions

- 2.1 Time indexing . . . . .
- 2.2 Common signals . . . . .
- 2.3 Common functions . . . . .
- 2.4 Operations and symbols . . . . .
- 2.5 Transformations . . . . .

### 3 Probability, statistics, and stochastic processes

- 3.1 Operators and symbols . . . . .
- 3.2 Stochastic processes . . . . .
- 3.3 Functions . . . . .
- 3.4 Distributions . . . . .

### 4 Statistical signal processing and machine learning

- 4.1 Statistical and estimated terms . . . . .
- 4.2 Weights, classes, discriminants, hyperparameters, and system performance . . . . .

### 5 Linear Algebra

- 5.1 Common matrices and vectors . . . . .
- 5.2 Indexing . . . . .
- 5.3 General operations . . . . .
- 5.4 Operations with matrices and tensors . . . . .
- 5.5 Operations with vectors . . . . .
- 5.6 Decompositions . . . . .
- 5.7 Spaces . . . . .
- 5.8 Inequalities . . . . .

<b>6</b>	<b>Communication systems</b>	
6.1	Symbols	.....
6.2	Fading multipath channels	.....
<b>7</b>	<b>Discrete mathematics</b>	
7.1	Set theory	.....
7.2	Quantifiers, inferences	.....
7.3	Propositional Logic	.....
7.4	Operations	.....
<b>8</b>	<b>Electromagnetic waves</b>	
<b>9</b>	<b>Calculus</b>	
<b>10</b>	<b>Generic mathematical symbols</b>	
<b>11</b>	<b>Abbreviations</b>	

## 1 Font notation

$a, b, c, \dots, A, B, C, \dots$	Scalars
$\mathbf{a}, \mathbf{b}, \mathbf{c}, \dots$	Vectors
$\mathbf{A}, \mathbf{B}, \mathbf{C}, \dots$	Matrices
$\mathcal{A}, \mathcal{B}, \mathcal{C}, \dots$	Tensors
$A, B, C, \dots, \mathcal{A}, \mathcal{B}, \mathcal{C}, \dots, \mathbb{A}, \mathbb{B}, \mathbb{C}, \dots$	Sets

## 2 Signals and functions

### 2.1 Time indexing

$x(t)$	Continuous-time $t$
$x[n], x[k], x[m], x[i], \dots$ $x_n, x_k, x_m, x_i, \dots$ $x(n), x(k), x(m), x(i), \dots$	Discrete-time $n, k, m, i, \dots$ (parenthesis should be adopted only if there are no continuous-time signals in the context to avoid ambiguity)
$x[((n-m))_N], x((n-m))_N$	Circular shift in $m$ samples within a $N$ -samples window [11, 17]

### 2.2 Common signals

$\delta(t)$	Delta function
$\delta[n], \delta_{i,j}$	Kronecker function ( $n = i - j$ )
$h(t), h[n]$	Impulse response (continuous and discrete time)
$\tilde{x}[n], \tilde{x}(t)$	Periodic discrete- or continuous-time signal
$\hat{x}[n], \hat{x}(t)$	Estimate of $x[n]$ or $x(t)$
$\dot{x}[m]$	Interpolation of $x[n]$

### 2.3 Common functions

$\mathcal{O}(\cdot), \mathcal{O}(\cdot)$	Big-O notation
$\Gamma(\cdot)$	Gamma function
$\mathcal{Q}(\cdot)$	Quantization function
$I_\alpha(\cdot)$	Modified Bessel function of the first kind and order $\alpha$
$\binom{n}{k}$	Binomial coefficient

## 2.4 Operations and symbols

$f : A \rightarrow B$	A function $f$ whose domain is $A$ and codomain is $B$
$\mathbf{f} : A \rightarrow \mathbb{R}^n$	A vector-valued function $\mathbf{f}$ , i.e., $n \geq 2$
$f^n, x^n(t), x^n[k]$	$n$ th power of the function $f$ , $x[n]$ or $x(t)$
$f^{(n)}, x^{(n)}(t)$	$n$ th derivative of the function $f$ or $x(t)$
$f', f^{(1)}, x'(t)$	1th derivative of the function $f$ or $x(t)$
$f'', f^{(2)}, x''(t)$	2th derivative of the function $f$ or $x(t)$
$\arg \max_{x \in \mathcal{A}} f(x)$	Value of $x$ that minimizes $x$
$\arg \min_{x \in \mathcal{A}} f(x)$	Value of $x$ that minimizes $x$
$f(\mathbf{x}) = \inf_{\mathbf{y} \in \mathcal{A}} g(\mathbf{x}, \mathbf{y})$	Infimum, i.e., $f(\mathbf{x}) = \min \{g(\mathbf{x}, \mathbf{y}) \mid \mathbf{y} \in \mathcal{A} \wedge (\mathbf{x}, \mathbf{y}) \in \text{dom}(g)\}$ , which is the greatest lower bound of this set [3]
$f(\mathbf{x}) = \sup_{\mathbf{y} \in \mathcal{A}} g(\mathbf{x}, \mathbf{y})$	Supremum, i.e., $f(\mathbf{x}) = \max \{g(\mathbf{x}, \mathbf{y}) \mid \mathbf{y} \in \mathcal{A} \wedge (\mathbf{x}, \mathbf{y}) \in \text{dom}(g)\}$ , which is the least upper bound of this set [3]
$f \circ g$	Composition of the functions $f$ and $g$
$*$	Convolution (discrete or continuous)
$\oplus, \textcircled{\mathbb{N}}$	Circular convolution [7, 17]

## 2.5 Transformations

$W_N$	Twiddle factor, $e^{-j\frac{2\pi}{N}}$ [11]
$\mathcal{F}\{\cdot\}$	Fourier transform
$\mathcal{L}\{\cdot\}$	Laplace transform
$\mathcal{Z}\{\cdot\}$	$z$ -transform
$\hat{x}(t), \hat{x}[n]$	Hilbert transform of $x(t)$ or $x[n]$
$X(s)$	Laplace transform of $x(t)$
$X(f)$	Fourier transform (FT) (in linear frequency, Hz) of $x(t)$
$X(j\omega)$	Fourier transform (FT) (in angular frequency, rad/sec) of $x(t)$
$X(e^{j\omega})$	Discrete-time Fourier transform (DTFT) of $x[n]$

$X[k], X(k), X_k$	Discrete Fourier transform (DFT) or fast Fourier transform (FFT) of $x[n]$ , or even the Fourier series (FS) of the periodic signal $x(t)$
$\tilde{X}[k], \tilde{X}(k), \tilde{X}_k$	Discrete Fourier series (DFS) of $\tilde{x}[n]$
$X(z)$	$z$ -transform of $x[n]$

### 3 Probability, statistics, and stochastic processes

#### 3.1 Operators and symbols

$\mathbf{E}[\cdot], \mathbf{E}[\cdot], E[\cdot], \mathbb{E}[\cdot]$	Statistical expectation operator [6, 16]
$\mathbf{E}_u[\cdot], \mathbf{E}_u[\cdot], E_u[\cdot], \mathbb{E}_u[\cdot]$	Statistical expectation operator with respect to $u$
$\langle \cdot \rangle$	Ensamble average
$\text{var}[\cdot], \text{VAR}[\cdot]$	Variance operator [2, 10, 15, 19]
$\text{var}_u[\cdot][\cdot], \text{VAR}_u[\cdot]$	Variance operator with respect to $u$
$\text{cov}[\cdot], \text{COV}[\cdot]$	Covariance operator [2]
$\text{cov}_u[\cdot], \text{COV}_u[\cdot]$	Covariance operator with respect to $u$
$\mu_x$	Mean of the random variable $x$
$\boldsymbol{\mu}_x, \mathbf{m}_x$	Mean vector of the random variable $\mathbf{x}$ [4]
$\mu_n$	$n$ th-order moment of a random variable
$\sigma_x^2, \kappa_2$	Variance of the random variable $x$
$\mathcal{K}_x, \mu_4$	Kurtosis (4th-order moment) of the random variable $x$
$\kappa_n$	$n$ th-order cumulant of a random variable
$\rho_{x,y}$	Pearson correlation coefficient between $x$ and $y$
$a \sim P$	Random variable $a$ with distribution $P$
$\mathcal{R}$	Rayleigh's quotient

#### 3.2 Stochastic processes

$r_x(\tau), R_x(\tau)$	Autocorrelation function of the signal $x(t)$ or $x[n]$ [16]
------------------------	--

$S_x(f), S_x(j\omega)$	Power spectral density (PSD) of $x(t)$ in linear ( $f$ ) or angular ( $\omega$ ) frequency
$S_{x,y}(f), S_{x,y}(j\omega)$	Cross PSD of $x(t)$ and $y(t)$ in linear or angular ( $\omega$ ) frequency
$\mathbf{R}_x$	(Auto)correlation matrix of $\mathbf{x}(n)$
$r_{x,d}(\tau), R_{x,d}(\tau)$	Cross-correlation between $x[n]$ and $d[n]$ or $x(t)$ and $d(t)$ [16]
$\mathbf{R}_{xy}$	Cross-correlation matrix of $\mathbf{x}(n)$ and $\mathbf{y}(n)$
$\mathbf{p}_{xd}$	Cross-correlation vector between $\mathbf{x}(n)$ and $d(n)$ [dinizAdaptiveFiltering1997]
$c_x(\tau), C_x(\tau)$	Autocovariance function of the signal $x(t)$ or $x[n]$ [16]
$\mathbf{C}_x, \mathbf{K}_x, \mathbf{\Sigma}_x, \text{cov}[\mathbf{x}]$	(Auto)covariance matrix of $\mathbf{x}$ [10, 15, 19, 25]
$c_{xy}(\tau), C_{xy}(\tau)$	Cross-covariance function of the signal $x(t)$ or $x[n]$ [16]
$\mathbf{C}_{xy}, \mathbf{K}_{xy}, \mathbf{\Sigma}_{xy}$	Cross-covariance matrix of $\mathbf{x}$ and $\mathbf{y}$

### 3.3 Functions

$Q(\cdot)$	$Q$ -function, i.e., $P[\mathcal{N}(0, 1) > x]$ [19]
$\text{erf}(\cdot)$	Error function [19]
$\text{erfc}(\cdot)$	Complementary error function i.e., $\text{erfc}(x) = 2Q(\sqrt{2}x) - \text{erf}(x)$ [19]
$P[A]$	Probability of the event or set $A$ [15]
$p(\cdot), f(\cdot)$	Probability density function (PDF) or probability mass function (PMF) [15]
$p(x   A)$	Conditional PDF or PMF [15]
$F(\cdot)$	Cumulative distribution function (CDF)
$\Phi_x(\omega), M_x(j\omega), E[e^{j\omega x}]$	First characteristic function (CF) of $x$ [19, 24]
$M_x(t), \Phi_x(-jt), E[e^{tx}]$	Moment-generating function (MGF) of $x$ [19, 24]
$\Psi_x(\omega), \ln \Phi_x(\omega), \ln E[e^{j\omega x}]$	Second characteristic function
$K_x(t), \ln E[e^{tx}], \ln M_x(t)$	Cumulant-generating function (CGF) of $x$ [10]

### 3.4 Distributions

$\mathcal{N}(\mu, \sigma^2)$	Gaussian distribution of a random variable with mean $\mu$ and variance $\sigma^2$ . The same notation can be used to denote a real-valued white Gaussian process with mean equal to $\mu$ and power spectral density equal to $N_0/2$ , e.g., $s(t) \sim \mathcal{N}(\mu, N_0/2)$
$\mathcal{CN}(\mu, \sigma^2)$	Complex Gaussian distribution of a random variable with mean $\mu$ and variance $\sigma^2$ . The same notation can be used to denote a complex-valued white Gaussian process with mean equal to $\mu$ and power spectral density equal to $N_0$ , e.g., $s(t) \sim \mathcal{CN}(\mu, N_0)$
$\mathcal{N}(\mathbf{\mu}, \mathbf{\Sigma})$	Gaussian distribution of a vector random variable with mean $\mathbf{\mu}$ and covariance matrix $\mathbf{\Sigma}$
$\mathcal{CN}(\mathbf{\mu}, \mathbf{\Sigma})$	Complex Gaussian distribution of a vector random variable with mean $\mathbf{\mu}$ and covariance matrix $\mathbf{\Sigma}$
$\mathcal{U}(a, b)$	Uniform distribution from $a$ to $b$
$\chi^2(n), \chi_n^2$	Chi-square distribution with $n$ degree of freedom (assuming that the Gaussians are $\mathcal{N}(0, 1)$ )
$\text{Exp}(\lambda)$	Exponential distribution with rate parameter $\lambda$
$\Gamma(\alpha, \beta)$	Gamma distribution with shape parameter $\alpha$ and rate parameter $\beta$
$\Gamma(\alpha, \theta)$	Gamma distribution with shape parameter $\alpha$ and scale parameter $\theta = 1/\beta$
$\text{Nakagami}(m, \Omega)$	Nakagami-m distribution with shape parameter or fading figure $m$ and spread, scale, or shape parameter $\Omega$
$\text{Rayleigh}(\sigma)$	Rayleigh distribution with scale parameter $\sigma$
$\text{Rayleigh}(\Omega)$	Rayleigh distribution with the second moment $\Omega = E[x^2] = 2\sigma^2$
$\text{Rice}(s, \sigma)$	Rice distribution with noncentrality parameter $s$ and $\sigma$ . $s^2$ represent the specular component power
$\text{Rice}(A, K)$	Rice distribution with Rice factor $K = s^2/2\sigma^2$ and scale parameter $A = s^2 + 2\sigma^2$

## 4 Statistical signal processing and machine learning

### 4.1 Statistical and estimated terms

$\nabla f, \mathbf{g}$	Gradient descent vector
$\nabla_x f, \mathbf{g}_x$	Gradient descent vector with respect $x$
$\mathbf{g}$ (or $\hat{\mathbf{g}}$ if the gradient vector is $\mathbf{g}$ )	Stochastic gradient descent (SGD)
$\Lambda(\cdot)$	Likelihood function
$\Lambda_l(\cdot)$	Log-likelihood function
$\hat{x}(t)$ or $\hat{x}[n]$	Estimate of $x(t)$ or $x[n]$
$\hat{\mu}_x, \hat{\mathbf{m}}_x$	Sample mean of $x[n]$ or $x(t)$
$\hat{\mu}_{\mathbf{x}}, \hat{\mathbf{m}}_{\mathbf{x}}$	Sample mean vector of $\mathbf{x}[n]$ or $\mathbf{x}(t)$
$\hat{r}_x(\tau), \hat{R}_x(\tau)$	Estimated autocorrelation function of the signal $x(t)$ or $x[n]$
$\hat{S}_x(f), \hat{S}_x(j\omega)$	Estimated power spectral density (PSD) of $x(t)$ in linear ( $f$ ) or angular ( $\omega$ ) frequency
$\hat{\mathbf{R}}_{\mathbf{x}}$	Sample (auto)correlation matrix
$\hat{r}_{x,d}(\tau), \hat{R}_{x,d}(\tau)$	Estimated cross-correlation between $x[n]$ and $d[n]$ or $x(t)$ and $d(t)$
$\hat{S}_{x,y}(f), \hat{S}_{x,y}(j\omega)$	Estimated cross PSD of $x(t)$ and $y(t)$ in linear or angular ( $\omega$ ) frequency
$\hat{\mathbf{R}}_{\mathbf{xy}}$	Sample cross-correlation matrix of $\mathbf{R}_{\mathbf{xy}}$
$\hat{c}_x(\tau), \hat{C}_x(\tau)$	Estimated autocovariance function of the signal $x(t)$ or $x[n]$
$\hat{\mathbf{C}}_{\mathbf{x}}, \hat{\mathbf{K}}_{\mathbf{x}}, \hat{\Sigma}_{\mathbf{x}}$	Sample (auto)covariance matrix
$\hat{c}_{xy}(\tau), \hat{C}_{xy}(\tau)$	Estimated cross-covariance function of the signal $x(t)$ or $x[n]$
$\hat{\mathbf{C}}_{\mathbf{xy}}, \hat{\mathbf{K}}_{\mathbf{xy}}, \hat{\Sigma}_{\mathbf{xy}}$	Sample cross-covariance matrix
$\mathbf{J}$	Jacobian matrix
$\mathbf{H}$	Hessian matrix
$\hat{\mathbf{H}}$	Estimate of the Hessian matrix

### 4.2 Weights, classes, discriminants, hyperparameters, and system performance

$\mathbf{w}, \boldsymbol{\theta}$	Parameters, coefficients, or weights vector
-----------------------------------	---



$\mathbf{w}_o, \mathbf{w}^*, \boldsymbol{\theta}_o, \boldsymbol{\theta}^*$	Optimum value of the parameters, coefficients, or weights vector
$\mathbf{W}$	Matrix of the weights
$\eta$	Learning rate hyperparameter
$J(\cdot), \mathcal{E}(\cdot)$	Cost-function or objective function
$\hat{\rho}_{x,y}$	Estimated Pearson correlation coefficient between $x$ and $y$
$d(n), d_n$	Desired label (in case of supervised learning)
$\rho$	Distance of the margin of separation between two classes (Support Vector Machine, SVM)
$g(\cdot)$	Discriminant function, i.e., $g(\mathbf{w}^*) = 0$

## 5 Linear Algebra

### 5.1 Common matrices and vectors

$\mathbf{W}, \mathbf{D}$	Diagonal matrix
$\mathbf{P}$	Projection matrix; Permutation matrix
$\mathbf{J}$	Jordan matrix
$\mathbf{L}$	Lower matrix
$\mathbf{U}$	Upper matrix
$\mathbf{C}$	Cofactor matrix
$\mathbf{C}_A, \text{cof}(\mathbf{A})$	Cofactor matrix of $\mathbf{A}$
$\mathbf{S}$	Symmetric matrix
$\mathbf{Q}$	Orthogonal matrix
$\mathbf{I}_N$	$N \times N$ -dimensional identity matrix
$\mathbf{0}_{M \times N}$	$M \times N$ -dimensional null matrix
$\mathbf{0}_N$	$N$ -dimensional null vector
$\mathbf{1}_{M \times N}$	$M \times N$ -dimensional ones matrix
$\mathbf{1}_N$	$N$ -dimensional ones vector
$\mathbf{0}$	Null matrix, vector, or tensor (dimensionality understood by context)
$\mathbf{1}$	Ones matrix, vector, or tensor (dimensionality understood by context)

### 5.2 Indexing

$x_{i_1, i_2, \dots, i_N}, [\mathcal{X}]_{i_1, i_2, \dots, i_N}$	Element in the position $(i_1, i_2, \dots, i_N)$ of the tensor $\mathcal{X}$
$\mathcal{X}^{(n)}$	$n$ th tensor of a nontemporal sequence
$\mathbf{x}_n, \mathbf{X}_{:,n}$	$n$ th column of the matrix $X$
$\mathbf{x}_{n,:}$	$n$ th row of the matrix $X$
$\mathbf{X}_{i_1, \dots, i_{n-1}, :, i_{n+1}, \dots, i_N}$	Mode- $n$ fiber of the tensor $\mathcal{X}$
$\mathbf{x}_{:, i_2, i_3}$	Column fiber (mode-1 fiber) of the thrid-order tensor $\mathcal{X}$
$\mathbf{x}_{i_1, :, i_3}$	Row fiber (mode-2 fiber) of the thrid-order tensor $\mathcal{X}$
$\mathbf{x}_{i_1, i_2, :}$	Tube fiber (mode-3 fiber) of the thrid-order tensor $\mathcal{X}$
$\mathbf{X}_{i_1, :, :}$	Horizontal slice of the thrid-order tensor $\mathcal{X}$
$\mathbf{X}_{:, i_2, :}$	Lateral slices slice of the thrid-order tensor $\mathcal{X}$
$\mathbf{X}_{i_3}, \mathbf{X}_{:, :, i_3}$	Frontal slices slice of the thrid-order tensor $\mathcal{X}$

### 5.3 General operations

$\langle \mathbf{a}, \mathbf{b} \rangle, \mathbf{a}^\top \mathbf{b}, \mathbf{a} \cdot \mathbf{b}$	Inner or dot product
$\mathbf{a} \circ \mathbf{b}, \mathbf{a} \mathbf{b}^\top$	Outer product
$\otimes$	Kronecker product
$\odot$	Hadamard (or Schur) (elementwise) product
$\cdot^{\odot n}$	$n$ th-order Hadamard power
$\cdot^{\odot \frac{1}{n}}$	$n$ th-order Hadamard root
$\oslash$	Hadamard (or Schur) (elementwise) division
$\diamond$	Khatri-Rao product
$\otimes$	Kronecker Product
$\times_n$	$n$ -mode product

### 5.4 Operations with matrices and tensors

$\mathbf{A}^{-1}$	Inverse matrix
$\mathbf{A}^+, \mathbf{A}^\dagger$	Moore-Penrose left pseudoinverse
$\mathbf{A}^\top$	Transpose
$\mathbf{A}^{-\top}$	Transpose of the inverse, i.e., $(\mathbf{A}^{-1})^\top = (\mathbf{A}^\top)^{-1}$ [8, 18]
$\mathbf{A}^*$	Complex conjugate

$\mathbf{A}^H$	Hermitian
$\ \mathbf{A}\ _F$	Frobenius norm
$\ \mathbf{A}\ $	Matrix norm
$ \mathbf{A} , \det(\mathbf{A})$	Determinant
$\text{diag}(\mathbf{A})$	The elements in the diagonal of $\mathbf{A}$
$\mathbf{E}[\mathbf{A}]$	Vectorization: stacks the columns of the matrix $\mathbf{A}$ into a long column vector
$\mathbf{E}_d[\mathbf{A}]$	Extracts the diagonal elements of a square matrix and returns them in a column vector
$\mathbf{E}_l[\mathbf{A}]$	Extracts the elements strictly below the main diagonal of a square matrix in a column-wise manner and returns them into a column vector
$\mathbf{E}_u[\mathbf{A}]$	Extracts the elements strictly above the main diagonal of a square matrix in a column-wise manner and returns them into a column vector
$\mathbf{E}_b[\mathbf{A}]$	Block vectorization operator: stacks square block matrices of the input into a long block column matrix
$\text{unvec}(\mathbf{A})$	Reshapes a column vector into a matrix
$\text{tr}\{\mathbf{A}\}$	trace
$\mathbf{X}_{(n)}$	$n$ -mode matricization of the tensor $\mathcal{X}$

## 5.5 Operations with vectors

$\ \mathbf{a}\ $	$l_1$ norm, 1-norm, or Manhattan norm
$\ \mathbf{a}\ , \ \mathbf{a}\ _2$	$l_2$ norm, 2-norm, or Euclidean norm
$\ \mathbf{a}\ _p$	$l_p$ norm, $p$ -norm, or Minkowski norm
$\ \mathbf{a}\ _\infty$	$l_\infty$ norm, $\infty$ -norm, or Chebyshev norm
$\text{diag}(\mathbf{a})$	Diagonalization: a square, diagonal matrix with entries given by the vector $\mathbf{a}$

## 5.6 Decompositions

$\mathbf{\Lambda}$	Eigenvalue matrix <a href="#">[23]</a>
--------------------	--

$\mathbf{Q}$	Eigenvectors matrix; Orthogonal matrix of the QR decomposition[23]
$\mathbf{R}$	Upper triangular matrix of the QR decomposition[23]
$\mathbf{U}$	Left singular vectors[23]
$\mathbf{U}_r$	Left singular nondegenerated vectors
$\mathbf{\Sigma}$	Singular value matrix
$\mathbf{\Sigma}_r$	Singular value matrix with nonzero singular values in the main diagonal
$\mathbf{\Sigma}^+$	Singular value matrix of the pseudoinverse [23]
$\mathbf{\Sigma}_r^+$	Singular value matrix of the pseudoinverse with nonzero singular values in the main diagonal
$\mathbf{V}$	Right singular vectors [23]
$\mathbf{V}_r$	Right singular nondegenerated vectors
$\text{eig}(\mathbf{A})$	Set of the eigenvalues of $\mathbf{A}$ [5, 15, 18]
$\llbracket \mathbf{A}, \mathbf{B}, \mathbf{C}, \dots \rrbracket$	CANDECOMP/PARAFAC (CP) decomposition of the tensor $\mathcal{X}$ from the outer product of column vectors of $\mathbf{A}, \mathbf{B}, \mathbf{C}, \dots$
$\llbracket \boldsymbol{\lambda}; \mathbf{A}, \mathbf{B}, \mathbf{C}, \dots \rrbracket$	Normalized CANDECOMP/PARAFAC (CP) decomposition of the tensor $\mathcal{X}$ from the outer product of column vectors of $\mathbf{A}, \mathbf{B}, \mathbf{C}, \dots$

## 5.7 Spaces

$\text{span}\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_n\}$	Vector space spanned by the argument vectors [8]
$\mathbf{C}(\mathbf{A}), \text{columnspace}(\mathbf{A}), \text{range}(\mathbf{A}), \text{span}\{\mathbf{A}\}, \text{image}(\mathbf{A})$	Columnspace, range or image, i.e., the space $\text{span}\{\mathbf{a}_1, \mathbf{a}_2, \dots, \mathbf{a}_n\}$ , where $\mathbf{a}_i$ is the $i$ th column vector of the matrix $\mathbf{A}$ [16, 23]
$\mathbf{C}(\mathbf{A}^H)$	Row space (also called left column space) [16, 23]
$\mathbf{N}(\mathbf{A}), \text{nullspace}(\mathbf{A}), \text{null}(\mathbf{A}), \text{kernel}(\mathbf{A})$	Nullspace (or kernel space) [16, 23, 24]
$\mathbf{N}(\mathbf{A}^H)$	Left nullspace
$\text{rank } \mathbf{A}$	Rank, that is, $\dim(\text{span}\{\mathbf{A}\}) = \dim(\mathbf{C}(\mathbf{A}))$ [16]

nullity ( $\mathbf{A}$ )	Nullity of $\mathbf{A}$ , i.e., $\dim(\mathbf{N}(\mathbf{A}))$
$\mathbf{a} \perp \mathbf{b}$	$\mathbf{a}$ is orthogonal to $\mathbf{b}$
$\mathbf{a} \not\perp \mathbf{b}$	$\mathbf{a}$ is not orthogonal to $\mathbf{b}$

## 5.8 Inequalities

$\mathcal{X} \leq 0$	Nonnegative tensor
$\mathbf{a} \preceq_K \mathbf{b}$	Generalized inequality meaning that $\mathbf{b} - \mathbf{a}$ belongs to the conic subset $K$ in the space $\mathbb{R}^n$ [3]
$\mathbf{a} \prec_K \mathbf{b}$	Strict generalized inequality meaning that $\mathbf{b} - \mathbf{a}$ belongs to the interior of the conic subset $K$ in the space $\mathbb{R}^n$ [3]
$\mathbf{a} \preceq \mathbf{b}$	Generalized inequality meaning that $\mathbf{b} - \mathbf{a}$ belongs to the nonnegative orthant conic subset, $\mathbb{R}_+^n$ , in the space $\mathbb{R}^n$ [3]
$\mathbf{a} \prec \mathbf{b}$	Strict generalized inequality meaning that $\mathbf{b} - \mathbf{a}$ belongs to the positive orthant conic subset, $\mathbb{R}_{++}^n$ , in the space $\mathbb{R}^n$ [3]
$\mathbf{A} \preceq_K \mathbf{B}$	Generalized inequality meaning that $\mathbf{B} - \mathbf{A}$ belongs to the conic subset $K$ in the space $\mathbb{S}^n$ [3]
$\mathbf{A} \prec_K \mathbf{B}$	Strict generalized inequality meaning that $\mathbf{B} - \mathbf{A}$ belongs to the interior of the conic subset $K$ in the space $\mathbb{S}^n$ [3]
$\mathbf{A} \preceq \mathbf{B}$	Generalized inequality meaning that $\mathbf{B} - \mathbf{A}$ belongs to the positive semidefinite conic subset, $\mathbb{S}_+^n$ , in the space $\mathbb{S}^n$ [3]
$\mathbf{A} \prec \mathbf{B}$	Strict generalized inequality meaning that $\mathbf{B} - \mathbf{A}$ belongs to the positive orthant conic subset, $\mathbb{S}_{++}^n$ , in the space $\mathbb{S}^n$ [3]

## 6 Communication systems

### 6.1 Symbols

$B$	One-sided bandwidth of the transmitted signal, in Hz
-----	--

$W$	One-sided bandwidth of the transmitted signal, in rad/s
$x_i$	Real or in-phase part of $x$
$x_q$	Imaginary or quadrature part of $x$
$f_c, f_{RF}$	Carrier frequency (in Hertz)
$f_L$	Carrier frequency in L-band (in Hertz)
$f_{IF}$	Intermediate frequency (in Hertz)
$f_s$	Sampling frequency or sampling rate (in Hertz)
$T_s$	Sampling time interval/duration/period
$R$	Bit rate
$T$	Bit interval/duration/period
$T_c$	Chip interval/duration/period
$T_{sy}, T_{sym}$	Symbol/signaling[19] interval/duration/period
$s_{RF}$	Transmitted signal in RF
$s_{FI}$	Transmitted signal in FI
$s, s_l$	Lowpass (or baseband) equivalent signal or envelope complex of transmitted signal
$r_{RF}$	Received signal in RF
$r_{FI}$	Received signal in FI
$r, r_l$	Lowpass (or baseband) equivalent signal or envelope complex of received signal
$\phi$	Signal phase
$\phi_0$	Initial phase
$\eta_{RF}, w_{RF}$	Noise in RF
$\eta_{FI}, w_{FI}$	Noise in FI
$\eta, w$	Noise in baseband
$\tau$	Timing delay
$\Delta\tau$	Timing error (delay - estimated)
$\varphi$	Phase offset
$\Delta\varphi$	Phase error (offset - estimated)
$f_d$	Linear Doppler frequency
$\Delta f_d$	Frequency error (Doppler frequency - estimated)
$\nu$	Angular Doppler frequency
$\Delta\nu$	Frequency error (Doppler frequency - estimated)
$\gamma, A$	Transmitted signal amplitude

$\gamma_0, A_0$	Combined effect of the path loss and antenna gain
-----------------	---

## 6.2 Fading multipath channels

$t \xleftrightarrow{\mathcal{F}} \lambda$	Support temporal of the signal. $\lambda$ is obtained after taking the Fourier transform on $t$ .
$\tau \xleftrightarrow{\mathcal{F}} f$	Second support temporal of the signal ( $c(t)$ varies with the input at the time $\tau$ ). $f$ is obtained after taking the Fourier transform on $\tau$ .
$c(t, \tau)$	Complex envelope of the channel response at the time $t$ due to an impulse applied at the $t - \tau$
$C(f, t)$	Transfer function of $c(t, \tau)$ in $\tau$
$\alpha(t, \tau)$	Attenuation of $c(t, \tau)$ , i.e., $c(t, \tau) = \alpha(t, \tau)e^{e\pi f_c \tau}$
$R_c(\tau_1, \tau_2, \Delta t)$	Autocorrelation function of $c(t, \tau)$ , i.e., $R_c(\tau_1, \tau_2, \Delta t) = E [c^*(t, \tau_1), c^*(t + \Delta t, \tau_2)]$
$R_c(\tau, \Delta t)$	Autocorrelation function of $c(t, \tau)$ assuming uncorrelated scattering
$R_c(\tau), R_c(\tau, \Delta t) _{\Delta t=0}$	Multipath intensity profile or delay power spectrum
$R_C(\Delta f, \Delta t), R_C(f_1, f_2; \Delta t),$ $E [C(f_1, t), C(f_2, t + \Delta t)],$ $\mathcal{F}_\tau \{R_c(\tau, \Delta t)\}$	Spaced-frequency, spaced-time correlation function ( $\Delta f = f_2 - f_1$ )
$R_C(\Delta f), R_C(\Delta f, \Delta t) _{\Delta t=0}, \mathcal{F} \{R_c(\tau)\}$	Spaced-frequency correlation function
$(\Delta f)_c$	Coherence bandwidth of $c(t)$ , that is, the frequency interval in which $R_C(\Delta f)$ is nonzero
$T_m$	Multipath spread of the channel, that is, the time interval in which $R_c(\tau)$ is nonzero ( $T_m \approx 1/(\Delta f)_c$ )
$R_C(\Delta t), R_C(\Delta f, \Delta t) _{\Delta f=0}$	Spaced-time correlation function
$S_C(\lambda), \mathcal{F} \{R_C(\Delta t)\}$	Doppler power spectrum
$(\Delta t)_c$	Coherence time of $c(t)$ , that is, the time interval in which $R_C(\Delta t)$ is nonzero

$B_m$	Multipath spread of the channel, that is, the frequency interval in which $S_c(\lambda)$ is nonzero ( $B_d \approx 1/(\Delta t)_c$ )
$S_C(\tau, \lambda), \mathcal{F}_{\Delta f, \Delta t} \{R_C(\Delta f, \Delta t)\}$	Scattering function

## 7 Discrete mathematics

### 7.1 Set theory

$A + B$	Set addition (Minkowski sum), i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} = \mathbf{x} + \mathbf{y}, \forall \mathbf{x} \in \mathcal{X} \wedge \mathbf{y} \in \mathcal{Y}\}$ [13]
$A - B$	Minkowski difference, i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} = \mathbf{x} - \mathbf{y}, \forall \mathbf{x} \in \mathcal{X} \wedge \mathbf{y} \in \mathcal{Y}\}$
$A \ominus B$	Pontryagin difference, i.e., $\{\mathbf{v} \in \mathbb{R}^n \mid \mathbf{v} + \mathbf{y} \in \mathcal{X}, \forall \mathbf{y} \in \mathcal{Y}\}$ [13]
$A \setminus B, A - B$	Set difference or set subtraction, i.e., $A \setminus B = \{x \mid x \in A \wedge x \notin B\}$ the set containing the elements of $A$ that are not in $B$ [21]
$A \cup B$	Set of union
$A \cap B$	Set of intersection
$A \times B$	Cartesian product
$A^n$	$\underbrace{A \times A \times \dots \times A}_{n \text{ times}}$
$A^\perp$	Orthogonal complement of $A$ , e.g., $N(\mathbf{A}) = C(\mathbf{A}^\top)^\perp$ [3]
$A \oplus B$	Direct sum, i.e., each $\mathbf{v} \in \{\sum \mathbf{a}_i \mid \mathbf{a}_i \in S_i, i = 1, \dots, k\}$ has a unique representation of $\sum \mathbf{a}_i$ with $\mathbf{a}_i \in S_i$ . That is, they expand to a space. Note that $\{S_i\}$ might not be orthogonal each other [8]
$A \overset{\perp}{\oplus} B$	Direct sum of two space that are orthogonal and span a $n$ -dimensional space, e.g., $C(\mathbf{A}^\top) \overset{\perp}{\oplus} C(\mathbf{A}^\top)^\perp = \mathbb{R}^n$ (this decomposition of $\mathbb{R}^n$ is called the orthogonal decomposition induced by $\mathbf{A}$ ) [3]
$A, A^c$	Complement set (given $U$ )
$\#A,  A $	Cardinality
$a \in A$	$a$ is element of $A$



$a \notin A$	$a$ is not element of $A$
$\{1, 2, \dots, n\}$	Discrete set containing the integer elements $1, 2, \dots, n$
$U$	Universe
$2^A$	Power set of $A$
$\mathbb{R}$	Set of real numbers
$\mathbb{C}$	Set of complex numbers
$\mathbb{Z}$	Set of integer number
$\mathbb{B} = \{0, 1\}$	Boolean set
$\emptyset$	Empty set
$\mathbb{N}$	Set of natural numbers
$\mathbb{K} \in \{\mathbb{R}, \mathbb{C}\}$	Real or complex space (field)
$\mathbb{K}^{I_1 \times I_2 \times \dots \times I_N}$	$I_1 \times I_2 \times \dots \times I_N$ -dimensional real (or complex) space
$\mathbb{K}_+$	Nonnegative real (or complex) space [3]
$\mathbb{K}_{++}$	Positive real (or complex) space, i.e., $\mathbb{K}_{++} = \mathbb{K}_+ \setminus \{\mathbf{0}\}$ [3]
$\mathbb{S}^n, \mathcal{S}^n$	Conic set of the symmetric matrices in $\mathbb{R}^{n \times n}$ [3]
$\mathbb{S}_+^n, \mathcal{S}_+^n$	Conic set of the symmetric positive semidefinite matrices in $\mathbb{R}^{n \times n}$ [3]
$\mathbb{S}_{++}^n, \mathcal{S}_{++}^n$	Conic set of the symmetric positive definite matrices in $\mathbb{R}^{n \times n}$ , i.e., $\mathbb{S}_{++}^n = \mathbb{S}_+^n \setminus \{\mathbf{0}\}$ [3]
$\mathbb{H}^n$	Set of all hermitian matrices in $\mathbb{C}^{n \times n}$
$[a, b]$	Closed interval of a real set from $a$ to $b$
$(a, b)$	Opened interval of a real set from $a$ to $b$
$[a, b), (a, b]$	Half-opened intervals of a real set from $a$ to $b$

## 7.2 Quantifiers, inferences

$\forall$	For all (universal quantifier) [9]
$\exists$	There exists (existential quantifier) [9]
$\nexists$	There does not exist [9]
$\exists!$	There exist an unique [9]
$\in$	Belongs to [9]
$\notin$	Does not belong to [9]
$\therefore$	Because [9]

$ , :$	Such that, sometimes that parantheses is used [9]
$,, (\cdot)$	Used to separate the quantifier with restricted domain from the its scope, e.g., $\forall x < 0 (x^2 > 0)$ or $\forall x < 0, x^2 > 0$ [9]
$\therefore$	Therefore [9]

### 7.3 Propositional Logic

$\neg a$	Logical negation of $a$ [21]
$a \wedge b$	Conjunction (logical AND) operator between $a$ and $b$ [21]
$a \vee b$	Disjunction (logical OR) operator between $a$ and $b$ [21]
$a \oplus b$	Exclusive OR (logical XOR) operator between $a$ and $b$ [21]
$a \rightarrow b$	Implication (or conditional) statement [21]
$a \leftrightarrow b$	Bi-implication (or biconditional) statement, i.e., $(a \rightarrow b) \wedge (b \rightarrow a)$ [21]
$a \equiv b, a \iff b, a \Leftrightarrow b$	Logical equivalence, i.e., $a \leftrightarrow b$ is a tautology [21]

### 7.4 Operations

$ a $	Absolute value of $a$
$\log$	Base-10 logarithm or decimal logarithm
$\ln$	Natural logarithm
$\operatorname{Re}\{x\}$	Real part of $x$
$\operatorname{Im}\{x\}$	Imaginary part of $x$
$\angle \cdot$	Phase (complex argument)
$x \bmod y$	Remainder, i.e., $x - y \lfloor x/y \rfloor$ , for $y \neq 0$
$x \operatorname{div} y$	Quotient [21]
$x \equiv y \pmod{m}$	Congruent, i.e., $m \mid (x - y)$ [21]
$\operatorname{frac}(x)$	Fractional part, i.e., $x \bmod 1$ [9]
$a \setminus b, a \mid b$	$b$ is a positive integer multiple of $a$ , i.e., $\exists n \in \mathbb{Z}_{++} \mid b = na$ [9, 21]
$a \nmid b, a \nmid b$	$b$ is not a positive integer multiple of $a$ , i.e., $\nexists n \in \mathbb{Z}_{++} \mid b = na$ [9, 21]

$[\cdot]$	Ceiling operation [9]
$[\cdot]$	Floor operation [9]

## 8 Electromagnetic waves

$\Phi$	Electric flux (scalar) (in V m)
$\mathbf{J}$	Electric current density vector (in A/m <sup>2</sup> )
$\mathbf{H}$	Magnetic field vector (in A/m)
$\mathbf{B}$	Magnetic flux density vector (in Wb/m <sup>2</sup> = T)
$q$	Electric charge strength/magnitude (in C)
$\rho$	Electric charge density (for volumes) (in C/m <sup>3</sup> )
$\rho_s$	Electric charge density (for surface) (in C/m <sup>2</sup> )
$\rho_l$	Electric charge density (for volumes) (in C/m)
$\mathbf{f}$	Electrostatic force (Coulomb force), (in kg m/s <sup>2</sup> )
$\varepsilon$	Electric permittivity(in F/m) [20]
$\varepsilon_r$	Relative electric permittivity or dielectric constant (in F/m) [20]
$\varepsilon_0$	Electric permittivity in vacuum, $8.854 \times 10^{-12}$ F/m [20]
$\mathbf{E}$	Electric field vector (in V/m)
$\mathbf{D}$	Electric flux density, electric displacement, or electric induction vector (in C/m <sup>2</sup> )
$\mathbf{P}$	Electric polarization of the material (in C/m <sup>2</sup> )
$\chi_e$	Electric susceptibility (for linear and isotropic materials)
$\mu$	Magnetic permeability
$\mu_0$	Magnetic permeability in vacuum

## 9 Calculus

$\nabla$	Vector differential operator (Nabla symbol), i.e., $\nabla f$ is the gradient of the scalar-valued function $f$ , i.e., $f : \mathbb{R}^n \rightarrow \mathbb{R}$
$t, (u, v)$	Parametric variables commonly used, $t$ for one variable, $(u, v)$ for two variables[22]
$\mathbf{r}(t)$	Vector position $(x(t), y(t), z(t))$ parametrized by $t$ [22]
$\mathbf{r}'(t)$	First derivative of $\mathbf{r}(t)$ , i.e., the tangent vector of the curve $(x(t), y(t), z(t))$ [22]
$\mathbf{T}(t), \mathbf{u}(t)$	Tangent unit vector of $\mathbf{r}(t)$ , i.e., $\mathbf{u}(t) = \mathbf{r}'(t)/ \mathbf{r}'(t) $ [14, 22]
$\mathbf{n}(t), \left( \frac{y'(t)}{ \mathbf{r}'(t) }, -\frac{x'(t)}{ \mathbf{r}'(t) } \right)$	Normal vector of $\mathbf{r}(t)$ , i.e., $\mathbf{n}(t) \perp \mathbf{T}(t)$ [22]
$C$	Contour that traveled by $\mathbf{r}(t)$ , for $a \leq t \leq b$ [22]
$L, L(C)$	Total length of the contour $C$ (which can be defined the vector $\mathbf{r}$ , parametrized by $t$ ), i.e., $L_C = \int_a^b  \mathbf{r}'(t)  dt$ [22]
$s(t)$	Length of the arc, which can be defined by the vector $\mathbf{r}$ and $t$ , that is, $s(t) = \int_a^t  \mathbf{r}'(u)  du$ ( $s(b) = L$ )[22]
$ds, dl$	Differential operator of the length of the contour $C$ , i.e., $ds =  \mathbf{r}'(t)  dt$ . It is also denoted by $dl$ [20]
$\int_C f(\mathbf{r}) ds, \int_a^b f(\mathbf{r}(t)) \mathbf{r}'(t)  dt$	Line integral of the function $f : \mathbb{R}^n \rightarrow \mathbb{R}$ along the contour $C$ [1, 22]
$\int_C \mathbf{F} \cdot d\mathbf{r}, \int_a^b \mathbf{F}(\mathbf{r}(t)) \cdot \mathbf{r}'(t) dt, \int_C \mathbf{F} \cdot \mathbf{T} ds$	Line integral of vector field $\mathbf{F}$ along the contour $C$ [1, 22]
$\int_a^b \mathbf{F}, \int_a^b \mathbf{F} \cdot d\mathbf{r}$	Alternative notation to the line integral, where the parametric variable $t$ goes from $a$ to $b$ , making $r$ goes from $\mathbf{r}(a) = \mathbf{a}$ to $\mathbf{r}(b) = \mathbf{b}$ [1]
$\oint_C, \oint_C$	Closed line integral along the contour $C$
$\mathbf{r}(u, v)$	Vector position $(x(u, v), y(u, v), z(u, v))$ parametrized by $(u, v)$
$\mathbf{r}_u$	$(\partial x / \partial u, \partial y / \partial u, \partial z / \partial u)$
$\mathbf{r}_v$	$(\partial x / \partial v, \partial y / \partial v, \partial z / \partial v)$

$dA$	Differential operator of a 2D area (denoted by $D$ or $R$ ) in the $\mathbb{R}^2$ domain. This differential operator can be solved in different ways (rectangular, polar, cylindric, etc) [22]
$D, R$	Integration domain in which $dA$ is integrated, i.e., $\iint_D f dA$ [22]
$S$	Smooth surface $S$ , i.e., a 2D area in a 3D space ( $\mathbb{R}^3$ domain)
$dS,  \mathbf{r}_u \times \mathbf{r}_v  dA$	Differential operator of a 2D area in a 3D domain (an surface). Note that $dS =  \mathbf{r}_u \times \mathbf{r}_v  dA$ should be accompanied with the change of the integration interval(from $S$ to $D$ )
$A(S), \iint_S dS, \iint_D  \mathbf{r}_u \times \mathbf{r}_v  dA$	Area of the surface $S$ parametrized by $(u, v)$ , in which $dA$ is the area defined in the $D$ domain (which is form by the $u$ -by- $v$ graph)
$dV$	Differential operator of a shape volume (denoted by $E$ ) in $\mathbb{R}^3$ domain, i.e., $\iiint_E dV = V$
$E$	Integration domain in which $dV$ is integrated, i.e., $\iiint_E f dV$ [22]
$V, \iint_D f dA, \iiint_E f dV$	Volume of the function $f$ over the regions $D$ (in the case of double integrals) or $E$ (in the case of triple integrals)
$\iint_S f dS, \iint_D f  \mathbf{r}_u \times \mathbf{r}_v  dA$	Surface integral over $S$
$\mathbf{n}(u, v), \frac{\mathbf{r}_u(u, v) \times \mathbf{r}_v(u, v)}{ \mathbf{r}_u(u, v) \times \mathbf{r}_v(u, v) }$	Normal vector of of the smooth surface $S$
$\iint_S \mathbf{F} \cdot \mathbf{n} dS, \iint_S \mathbf{F} \cdot d\mathbf{S}, \iint_D \mathbf{F} \cdot (\mathbf{r}_u \times \mathbf{r}_v) dA$	Flux integral of vector field $\mathbf{F}$ through the smooth surface $S$ ( $\mathbf{n} dS \triangleq d\mathbf{S}$ )
$\nabla \times \mathbf{F}, \text{curl } \mathbf{F}$	Curl (rotacional) of the vector field $\mathbf{F}$
$\nabla \cdot \mathbf{F}, \text{div } \mathbf{F}$	Divergence of the vector field $\mathbf{F}$
$\nabla^2 f, \nabla \cdot (\nabla f), \Delta f, \partial^2 f / \partial x^2 + \partial^2 f / \partial y^2 + \partial^2 f / \partial z^2$	Scalar Laplacian operator (performed on a scalar-valued function $f : \mathbb{R}^n \rightarrow \mathbb{R}$ )
$\nabla^2 \mathbf{F}, \nabla \times \nabla \times \mathbf{F} - \nabla(\nabla \cdot \mathbf{F}), \Delta \mathbf{F}, (\partial^2 \mathbf{F} / \partial x^2, \partial^2 \mathbf{F} / \partial y^2, \partial^2 \mathbf{F} / \partial z^2)$	Vector Laplacian operator (performed on a vector field, i.e., a vector-valued function, $\mathbf{F} : \mathbb{R}^n \rightarrow \mathbb{R}^n$ ). $\nabla^2$ denotes the scalar (vector) Laplacian if the function is scalar-valued (vector-valued)

## 10 Generic mathematical symbols

■	Q.E.D.
$\triangleq$	Equal by definition
$:=, \leftarrow$	Assignment [21]
$\neq$	Not equal
$\infty$	Infinity
$j$	$\sqrt{-1}$

## 11 Abbreviations

PS: Only names of techniques and algorithms or usual abbreviations are considered.

wrt.	With respect to
st.	Subject to
iff.	If and only if
EVD	Eigenvalue decomposition, or eigen-decomposition [16]
SVD	Singular value decomposition
CP	CANDECOMP/PARAFAC
SGD	Stochastic gradient descent
SVM	Support vector machine
BPNN	Backpropagation neural network [12]
RBF	Radial basis function

## References

- [1] TM Apostol. *Calculus, 2nd Edn., Vol. 2*. 1967.
- [2] Christopher M Bishop and Nasser M Nasrabadi. *Pattern Recognition and Machine Learning*. Vol. 4. 4. Springer, 2006.
- [3] Stephen Boyd, Stephen P. Boyd, and Lieven Vandenberghe. *Convex Optimization*. Cambridge university press, 2004.
- [4] Robert Grover Brown and Patrick YC Hwang. “Introduction to Random Signals and Applied Kalman Filtering: With MATLAB Exercises and Solutions”. In: *Introduction to random signals and applied Kalman filtering: with MATLAB exercises and solutions* (1997).
- [5] Rama Chellappa and Sergios Theodoridis. *Signal Processing Theory and Machine Learning*. Academic Press, 2014. ISBN: 0-12-396502-0.
- [6] Paulo SR Diniz. *Adaptive Filtering: Algorithms and Practical Implementation*. Nowell, MA: Kluwer Academic Publishers, 2002.

- [7] Paulo SR Diniz, Eduardo AB Da Silva, and Sergio L Netto. *Digital Signal Processing: System Analysis and Design*. Cambridge University Press, 2010. ISBN: 1-139-49157-1.
- [8] Gene H Golub and Charles F Van Loan. *Matrix Computations*. JHU press, 2013. ISBN: 1-4214-0859-7.
- [9] Ronald L Graham et al. “Concrete Mathematics: A Foundation for Computer Science”. In: *Computers in Physics* 3.5 (1989), pp. 106–107. ISSN: 0894-1866.
- [10] Simon S Haykin. *Adaptive Filter Theory*. Pearson Education India, 2002. ISBN: 81-317-0869-1.
- [11] Vinay K Ingle and John G Proakis. *Digital Signal Processing Using MATLAB*. Cole Publishing Company, 2000.
- [12] Yu Jiao, John J Hall, and Yu T Morton. “Automatic Equatorial GPS Amplitude Scintillation Detection Using a Machine Learning Algorithm”. In: *IEEE Transactions on Aerospace and Electronic Systems* 53.1 (2017), pp. 405–418. ISSN: 0018-9251.
- [13] Basil Kouvaritakis and Mark Cannon. “Model Predictive Control”. In: *Switzerland: Springer International Publishing* 38 (2016).
- [14] Erwin Kreyszig, K Stroud, and G Stephenson. *Advanced Engineering Mathematics*. Vol. 9. John Wiley & Sons, Inc. 9 th edition, 2006 Page 2 of 6 Teaching methods ..., 2008.
- [15] Alberto Leon-Garcia. *Probability, Statistics, and Random Processes for Electrical Engineering*. 3rd ed. edição. Upper Saddle River, NJ: Prentice Hall, 2007. ISBN: 978-0-13-147122-1.
- [16] Josef Nosssek. *Adaptive and Array Signal Processing*. 2015.
- [17] Alan V. Oppenheim and Ronald W. Schaffer. *Discrete-Time Signal Processing: International Edition*. 3<sup>a</sup> edição. Upper Saddle River Munich: Pearson, Nov. 12, 2009. ISBN: 978-0-13-206709-6.
- [18] Kaare Brandt Petersen and Michael Syskind Pedersen. “The Matrix Cookbook”. In: *Technical University of Denmark* 7.15 (2008), p. 510.
- [19] John Proakis and Masoud Salehi. *Digital Communications*. 5th ed. edição. Boston: Mc Graw Hill, Jan. 1, 2007. ISBN: 978-0-07-295716-7.
- [20] Simon Ramo, John R Whinnery, and Theodore Van Duzer. *Fields and Waves in Communication Electronics*. John Wiley & Sons, 1994. ISBN: 81-265-1525-2.
- [21] Kenneth H Rosen. “Discrete Mathematics and Its Applications (7Th Edition)”. In: *William C Brown Pub* (2011).
- [22] James Stewart. *Calculus*. Cengage Learning, 2011. ISBN: 1-133-17069-2.
- [23] Gilbert Strang et al. *Introduction to Linear Algebra*. Vol. 3. Wellesley-Cambridge Press Wellesley, MA, 1993.

- [24] Sergios Theodoridis. *Machine Learning: A Bayesian and Optimization Perspective*. 2nd ed. Academic Pr, 2020. ISBN: 978-0-12-818803-3.
- [25] Harry L Van Trees. *Optimum Array Processing: Part IV of Detection, Estimation, and Modulation Theory*. John Wiley & Sons, 2002. ISBN: 0-471-09390-4.