

7. RETRIVE

```
#include <ThingSpeak.h>

#include <ESP8266WiFi.h>

#include <Wire.h>

const char ssid[] = "powerakk";
const char pass[] = "kumaranil";
int statusCode = 0;
WiFiClient client;
unsigned long ChannelID = 1932043;
const char * myCounterReadAPIKey = "TEUW37GZWJDCPYMW";
const int FieldNumber1 = 1;
const int FieldNumber2 = 2;

void setup() {
  Serial.begin(9600);
  Serial.begin(9600);
  WiFi.begin(ssid, pass);
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(500);
    Serial.print(".");
  }
  Serial.println("WiFi connected");
  Serial.println(WiFi.localIP());
  ThingSpeak.begin(client);
  delay(1000);
}

void loop() {
```

```
    long humidity = ThingSpeak.readLongField(ChannelID, FieldNumber1,
myCounterReadAPIKey);

    statusCode = ThingSpeak.getLastReadStatus();

    if
(statusCode == 200)
{
    Serial.print("% RH= ");

    Serial.println(humidity);

}
else
{
    Serial.println("Unable to read channel data or No internet");

}

delay(1000);

long temp = ThingSpeak.readLongField(ChannelID, FieldNumber2,
myCounterReadAPIKey);

statusCode = ThingSpeak.getLastReadStatus();

if (statusCode == 200)
{
    Serial.print( "Temperature in degree celcius= ");

    Serial.println(temp);

}
else
{
    Serial.println("Unable to read channel data or No internet");

}

delay(15000);

}
```