MINISTRY OF EDUCATION AND TRAINING

FPT UNIVERSITY

Capstone Project Document

On the Performance and Optimization for Computation Offloading and Energy Robustness of UAV-mounted RIS Cooperative NOMA-MEC

AIP491_G2	
Group Members	Nguyễn Gia Huy – Leader – HE180064 Trần Đặng Quang Huy – Member – HE180383 Lưu Ngọc Sơn – Member – HE180294 Nguyễn Quang Huy – Member – HE181445
Supervisor	Ngô Trường Minh
Capstone Project Code	UAV_RIS

- Hanoi, December 2025 -

Abstract

This project investigates the performance and multi-objective optimization of millimeter wave (mmWave) sixth-generation (6G) Internet of Things (IoT) networks by integrating an unmanned aerial vehicle (UAV) equipped with a reconfigurable intelligent surface (RIS) into a non-orthogonal multiple access (NOMA)-mobile edge computing (MEC) architecture operating in Nakagami-m fading propagation. To rigorously quantify the system performance in terms of computation offloading reliability and energy robustness, we derive closed-form expressions for the successful computation probability (SCP) and energy outage probability (EOP) under RIS cascaded channel statistical properties. Furthermore, we incorporate rigorous physical realism into the framework by modeling thermodynamic atmospheric physics and blade element momentum theory (BEMT) alongside weather attenuation models to accurately simulate mechanical flight endurance and realistic communication conditions. To address the fundamental trade-off between maximizing offloading service quality and minimizing energy consumption, we propose a multi-objective optimization framework utilizing Pareto Conditioned Networks (PCN) to jointly optimize the UAV-RIS's horizontal positions and altitude. Extensive simulation results consistently validate the accuracy and feasibility of the proposed mmWave 6G system model under adverse weather conditions. Ultimately, the proposed algorithm outperforms traditional reinforcement learning methods such as proximal policy optimization (PPO) and evolutionary algorithms like particle swarm optimization (PSO) by effectively identifying the optimal trade-off solution by effectively identifying the optimal trade-off solution that balances system-wide ultra-reliable low-latency communication with total energy consumption under the aerodynamic constraints of the aerial platform.

Table of Contents

Acknowledgement 4

Abbreviations 4

List of tables 5

List of figures 6

I. Project Introduction 7

1. Overview ..... **Error! Bookmark not defined.**
2. Project Background 7
3. Problem Statement 7
4. Project Objective 8
5. Significance of the Project ..... **Error! Bookmark not defined.**
6. Project Scope and Limitations 8

II. Theoretical Foundations and Literature Review 9

1. Overview of the Field ..... **Error! Bookmark not defined.**
2. Historical Context 9
3. Key Studies and Theories 9
4. Technological Advancements ..... **Error! Bookmark not defined.**
5. Comparison of Existing Systems 10
6. Gaps in the Literature/Technology 11
7. Justification for the Project ..... **Error! Bookmark not defined.**

IV. Methodology 12
1. Research Questions and Objectives 12
2. System Model and Communication Protocol 13
3. Performance Analysis Framework 21
4. Proposed Optimization Framework 31
5. Ethical Consideration ..... **Error! Bookmark not defined.**
V. System Design and Implementation 38
1. Simulation Environment & Hardware 38
2. System Parameters and Configuration 38
3. Software Architecture and Module Design 40
4. Data Generation and Expert Policies 41
5. PCN Algorithm Implementation 41
VI. Results and Discussion 42
1. Result Analysis 42
2. Discussion ..... **Error! Bookmark not defined.**
3. Limitations and Mitigation Strategies ..... **Error! Bookmark not defined.**
VII. Conclusion 48
1. Summary of Findings 48
2. Contributions and Reflections on the Project ..... **Error! Bookmark not defined.**
3. Limitations and Future Work 49
VIII. Appendices ..... **Error! Bookmark not defined.**
1. Appendix A: Proof of Lemma 1 ..... **Error! Bookmark not defined.**
2. Appendix B: Proof of Lemma 2 ..... **Error! Bookmark not defined.**
3. Appendix C: Proof of Lemma 3 ..... **Error! Bookmark not defined.**
4. Appendix D: Proof for Dynamic Air Density Closed-form Formulation (37) ..... **Error! Bookmark not defined.**
IX. References 50

Author Contributions

The research, mathematical derivation, simulation, and documentation presented in this thesis were conducted collaboratively by the project team with specific individual responsibilities defined as follows:

- Nguyễn Gia Huy (Leader): Conceptualized the system architecture and derived the closed-form mathematical expressions for the successful computation probability (SCP) and energy outage probability (EOP). He was responsible for the core MATLAB simulation environment to verify the physical system model and led the overall manuscript compilation.
- Trần Đặng Quang Huy: Designed and implemented the multi-objective optimization framework utilizing Pareto Conditioned Networks (PCN). He was responsible for the Python-based DRL environment, including the generation of expert training data and the execution of the comparative performance analysis against proximal policy optimization (PPO) and particle swarm optimization (PSO) algorithms.
- Lưu Ngọc Sơn and Nguyễn Quang Huy: They participated in regular project meetings during the course of the project.

Acknowledgement

We would like to express our gratitude to FPT University for providing the academic resources and laboratory environment necessary to conduct this research. We sincerely thank our supervisor, Dr. Truong-Minh Ngo, for his oversight and constructive feedback throughout the implementation of this project.

Special appreciation is extended to our mentor, Dr. Anh-Nhat Nguyen, whose expertise in wireless communications and pivotal suggestions regarding the system model were essential in shaping the core mathematical framework of this study.

We also thank the members of the SAP-LAB FPT Laboratory, specifically Mr. Ngoc-Anh Bui and Dr. Tung-Son Ngo for their encouragement and support of our research mindset, and Ms. Phuong-Chi Le for her valuable advice on the optimization strategy. Finally, we thank our families and friends for their understanding and encouragement during this course.

Abbreviations

The following **Table 1** presents the abbreviations and acronyms used throughout this thesis, categorized by their operational domain.

Table 1: Summary of abbreviations

Category	Abbreviation	Definition
Wireless Technologies and System Components	mmWave	Millimeter wave
	6G	Sixth-generation wireless system
	IoT	Internet of Things
	MEC	Mobile-edge computing
	ED	Edge device
	BED	Best edge device
	UAV	Unmanned aerial vehicle
	RIS	Reconfigurable intelligent surface
	NOMA	Non-orthogonal multiple access

Channel Characteristics and Signal Processing	CSI	Channel state information
	SIC	Successive interference cancellation
	LoS	Line-of-Sight propagation
	NLoS	Non-Line-of-Sight propagation
	AWGN	Additive white Gaussian noise
	i.i.d.	Independent and identically distributed
Performance Metrics and System Parameters	SCP	Successful computation probability
	EOP	Energy outage probability
	SINR	Signal-to-interference-plus-noise ratio
	SNR	Signal-to-noise ratio
	PDF	Probability density function
	CDF	Cumulative distribution function
	RV	Random variable
Algorithms and Theoretical Models	BEMT	Blade element momentum theory
	ITU	International Telecommunication Union
	ISA	International Standard Atmosphere
	SAC	Soft Actor-Critic (SAC)
	PCN	Pareto Conditioned Networks

List of tables

The following **Table 2** enumerates the tabular data presented within this thesis, serving as a quick reference for the summaries of technical abbreviations and the specific system configuration parameters utilized for simulation and analysis.

Table 2: Summary of tables

Abbreviation	Definition
Table 1	Summary of abbreviations
Table 2	Summary of tables
Table 3	Summary of figures
Table 5	Literature review comparison
Table 5	Simulation parameters' values

List of figures

The following **Table 3** enumerates the figures included in this thesis, providing an index of the visual illustrations that depict the system architecture, the communication protocol, the algorithmic optimization flowchart, and numerical results.

Table 3: Summary of figures

Abbreviation	Definition
Figure 1	System model of a NOMA-aided MEC server incorporating UAV-mounted RIS within IoT networks.
Figure 2	Communication protocol of NOMA-aided UAV-mounted RIS assisting MEC server within IoT networks
Figure 3	The PCN multi-objective optimization algorithm flowchart
Figure 4	The impact of BEDs' transmission power (P_I) on SCP (Ψ_S) and EOP ($\Psi_\mathcal{E}$) across varying RIS element counts (N).
Figure 5	The impact of UAV-RIS's altitude (h_{U_R}) on SCP (Ψ_S) and EOP ($\Psi_\mathcal{E}$) considering varying cluster sizes (Q, K).
Figure 6	The 3D spatial distribution of SCP relative to UAV-RIS horizontal placement.
Figure 7	The 3D spatial distribution of EOP relative to UAV-RIS horizontal placement.
Figure 8	The Pareto trade-off frontier generated by the PCN algorithm, highlighting the optimal sweet spot configuration.

I. Project Introduction

1. Project Background

The emergence of sixth-generation (6G) wireless networks is anticipated to fundamentally accelerate the massive deployment of IoT applications by delivering ultra-reliable and low-latency data transmission [1]. Nevertheless, the proliferation of the interconnected has resulted in an enormous data volume, leading to inherent challenges of executing computationally intensive tasks, such as data analytic and machine learning applications [2].

To mitigate the challenge of computational deficiency of edge devices (EDs), mobile-edge computing (MEC) has been proposed as a compelling solution. By strategically positioning low-latency computing resources of cloud severs in proximity to the network edge, MEC allows the offloading of computational workloads of resource-constrained EDs for data calculation [3]. However, such conventional optimization systems are contingent upon the location of terrestrial base stations, resulting in a restricted service coverage and inherently denying offloading services to remote EDs, as noted by [4].

To overcome the coverage limitations of MEC infrastructure, unmanned aerial vehicle (UAV) presents a highly effective and flexible solution [5]. By leveraging UAV as mobile aerial platforms, it is possible to create on-demand Line-of-Sight (LoS) communication relays that can be rapidly deployed to provide services in regions with deficient or non-existent terrestrial network coverage [6]. Therefore, UAV are exceptionally ideal for extending MEC services to challenging locations.

To address the fundamental challenge of channel instability in dynamic aerial conditions of UAVs, reconfigurable intelligent surface (RIS) is utilized as a viable solution. The fundamental concept of RIS is its function as a programmable meta-surface to dedicatedly coordinate the phase response across all elements [7]. RIS mechanism is consequently utilized for the precise manipulation of reflected signals to achieve the focused beamforming, thereby enhancing the channel quality and the overall communication reliability [8].

To enhance communication efficiency and facilitate connectivity of MEC and EDs, non-orthogonal multiple access (NOMA) has emerged as a promising technology. Departing from conventional orthogonal multiple access (OMA) schemes, NOMA's core principle involves allowing multiple users to concurrently occupy the same radio resource block through power-domain multiplexing [9]. This approach yields substantial improvements in spectral efficiency, rendering it a suitable candidate for serving dense clusters of devices [10].

2. Problem Statement

Despite the compelling solution offered by UAV-mounted RIS with NOMA-MEC systems for inherent wireless communication problems, their practical deployment is hindered by a reliance on idealized research assumptions that fail to consider physical and realistic feasibility [11].

Crucially, there is a critical lack of realistic energy modeling [12]. The vast majority of existing literature relies on static energy consumption models that assume ideal operating conditions [13]. These models fail to account for dynamic atmospheric density influenced by real-time humidity, temperature, and altitude, which directly dictates the aerodynamic lift and power consumption of rotary-wing UAVs [14]. Furthermore, they neglect the physical mass accumulation of environmental particulates such as rain, fog droplets, and dust particles, as well as the impact of wind drag, on the UAV and RIS surfaces [15]. These factors significantly alter the gross weight and drag coefficients during flight. Relying on these simplified models leads to inaccurate estimations of flight endurance, resulting in a high probability of unexpected energy outage [12,14,15].

Additionally, existing wireless communication frameworks often suffer from a disconnect between theoretical efficiency and practical consideration [12,16,17]. Regarding communication, standard channel models frequently overlook the severe signal attenuation caused by adverse weather conditions of rain, fog, and atmospheric gas, leading to over-optimistic reliability predictions in dense-urban environments [16]. While recent studies frequently address the simultaneous optimization of communication and energy

metrics, they predominantly rely on the aforementioned ideal configuration [17]. Consequently, they fail to capture the complex and non-linear aerodynamic penalties imposed by environmental factors, such as the increased rotor thrust required to hover in low air density at high altitudes, or under heavy weather accumulation [18]. This creates a gap for a unified approach that can guarantee computation latency constraints without violating the actual mechanical and energetic limits of the UAV modeled via BEMT.

3. Project Objective and Contributions

In accordance with the described project background and primary problems, the main objective of this project is to develop a unified framework that simultaneously enhances the offloading reliability and energy sustainability of millimeter wave (mmWave) sixth-generation (6G)-enabled IoT networks. By addressing the critical gap between theoretical communication models and practical physical constraints, this research aims to achieve the following specific goals:

1. To evaluate the computation offloading reliability, we derive a closed-form expression for the successful computation probability (SCP). This objective involves modeling the system's ability to offload and compute computational tasks within strict latency constraints under rigorous channel conditions. The derivation specifically accounts for realistic Nakagami-*m* fading channels, probabilistic models of Line-of-Sight (LoS) and Non-LoS (NLoS) propagation, and severe signal attenuation caused by adverse weather such as rain, fog, and atmospheric gas absorption. Theoretically, this derivation advances the academic understanding of 6G networks by providing a precise tool for quantifying the reliability of ultra-low latency applications in dense urban environments, moving beyond the idealized clear-sky assumptions prevalent in current literature.

2. To analyze system energy robustness, we formulate a novel energy outage probability (EOP) closed-form expression. This comprehensive metric moves beyond static assumptions by integrating thermodynamic atmospheric physics to model dynamic air density variations. These variations are mapped to Blade Element Momentum Theory (BEMT) to dynamically calculate aerodynamic power consumption. Furthermore, this objective quantifies the mechanical impact of environmental mass accumulation (rain, fog, dust) and wind drag on the RIS structure, ensuring the frame scales realistically via the Square-Cube law. This integration establishes a new standard for evaluating UAV sustainability, offering the community a rigorous method for measuring flight endurance under stochastic environmental conditions where standard static models would fail.

3. To resolve the fundamental trade-off of offloading reliability and energy robustness, we implement a Pareto Conditioned Networks (PCN) multi-objective optimization framework. This objective seeks to jointly optimize the UAV-RIS's altitude and positions to target three distinct operational preferences of SCP maximization, EOP minimization, and the balanced sweet spot configuration. This approach ensures the system can flexibly adapt to prioritize either communication reliability or physical robustness as required for practical deployment. Practically, this framework serves as vital guidance for network operators, helping industry stakeholders to visualize and actively manage the complex trade-off between communication reliability and energy robustness based on immediate operational needs.

4. To verify the accuracy and feasibility**,** we validate the proposed analytical models through extensive numerical simulations. This objective involves testing the system under rigorous mmWave 6G-envisioned operating conditions and benchmarking the proposed algorithm against traditional methods such as Proximal Policy Optimization (PPO) and Particle Swarm Optimization (PSO). By confirming that the proposed framework effectively identifies optimal trade-off solutions that outperform these baselines, this validation ensures that the UAV-assisted architecture is scalable and sustainable for mission-critical applications, such as disaster recovery operations during severe weather events.

4. Project Scope

The scope of this research is defined by the analysis and multi-objective optimization of a mmWave 6G-enabled IoT network architecture utilizing a UAV-mounted RIS to assist NOMA-MEC computation offloading. The study specifically focuses on the uplink transmission phase, modelling the stochastic nature

of wireless channels under Nakagami-m fading channels, probabilistic LoS-NLoS propagation of dense urban environments, and distinct weather factors. A distinguishing feature of this scope is the rigorous integration of aeromechanical and environmental physics into the system performance analysis. The energy modelling is explicitly scoped to rotary-wing UAV platforms, utilizing BEMT and the Square-Cube law to calculate propulsion power and structural sizing under dynamic thermodynamic conditions, including real-time variations in humidity, temperature, and altitude. Furthermore, the research scope encompasses the detailed modelling of signal attenuation and physical mass accumulation caused by environmental factors, specifically rain, fog, and atmospheric gas, to evaluate both communication reliability and physical flight feasibility.

II. Theoretical Foundations and Literature Review

1. Evolution of UAV-Assisted NOMA-MEC Architectures

The architectural framework of non-terrestrial networks has evolved through a decade-long process to address the coverage and latency limitations of terrestrial infrastructure. The genesis of this field lies in terrestrial MEC, originally referred to as Fog Computing, which was designed to reduce latency by placing servers at Base Stations [19]. Seminal works in this early phase established trade-off models between energy and latency using Lyapunov optimization [20]. However, these systems were inherently bound by geography; service quality degraded exponentially for users in non-service zones blocked by physical obstacles, highlighting the limitations of fixed infrastructure.

To transcend these coverage limits, Unmanned Aerial Vehicles (UAVs) were introduced as dynamic mobile relays [21]. Early studies focused primarily on trajectory optimization to establish Line-of-Sight (LoS) links [22]. However, these systems relied on Orthogonal Multiple Access (OMA) schemes, which introduced severe latency bottlenecks in massive IoT scenarios due to sequential transmission [23]. Addressing this spectral scarcity, the field shifted toward Non-Orthogonal Multiple Access (NOMA) [24]. By distinguishing users in the power domain, NOMA enabled simultaneous transmission, leveraging the strong LoS channel of a UAV for effective user pairing [25]. Nevertheless, NOMA-UAV links remained vulnerable to outage in dense urban environments if the successive interference cancellation (SIC) process failed [26].

The current state-of-the-art involves coupling UAVs with Reconfigurable Intelligent Surfaces (RIS) [27]. Unlike active relays that consume significant power, RIS panels reflect signals to create virtual LoS (vLoS) links for obstructed users [28]. While this architecture theoretically delivers ultra-reliable services to dead zones, recent studies on UAV-RIS systems [29] often neglect the significant aerodynamic penalties of carrying such payloads, a gap this project addresses.

2. Theoretical Framework

A rigorous review requires dissecting the specific mathematical frameworks defining this domain, distinguishing between communication theory, aerodynamic physics, and optimization strategies.

2.1 Probabilistic Channel Modelling in Aerial Networks

Aerial channel modelling differs fundamentally from terrestrial models. While early NOMA literature [30] assumed perfect conditions, recent studies have adopted probabilistic LoS/NLoS models [32] and Nakagami-m fading [33] to capture small-scale fluctuations in dense urban environments. However, as 6G moves into mmWave bands, the interaction between electromagnetic waves and the atmosphere becomes non-negligible. Unlike standard clear sky models, advanced environment-aware frameworks must explicitly integrate ITU recommendations (P.676 for gas, P.838 for rain) [14] into the channel estimation loop to account for molecular absorption and weather-induced degradation.

2.2 Aerodynamic and Thermodynamic Energy Models

A significant divergence exists regarding energy modelling. The majority of communications papers employ static power models [34]. In contrast, this project leverages Blade Element Momentum Theory (BEMT) [35, 36], which reveals that power consumption is linearly proportional to the inverse square root of air density. This formulation highlights a critical gap: standard models ignore thermodynamic variations (altitude,

temperature) that significantly alter air density, potentially leading to flight time estimation errors of 15-25% [37]. By prioritizing operational robustness over simple spectral efficiency, this framework ensures that energy efficiency translates directly to mechanical flight endurance [40, 41].

2.3 Multi-Objective Optimization and RIS Partitioning

Optimizing these networks presents a non-convex problem with conflicting goals. Classical methods like Convex Relaxation suffer from high complexity [38], while meta-heuristics are too slow for real-time control. The current frontier leverages Deep Reinforcement Learning (DRL), specifically Pareto Conditioned Networks (PCN) [39]. This approach learns a manifold of policies to approximate the entire Pareto Front dynamically. Furthermore, this optimization exploits modern RIS hardware capabilities, specifically element splitting [42], allowing a single panel to be logically partitioned to serve distinct NOMA clusters simultaneously [43].

3. Comparison of Existing Systems

To rigorously situate the proposed research within the current body of knowledge, it is imperative to perform a comparative analysis that systematically contrasts the proposed framework (AIP491_G2) with prevalent approaches in recent literature. This analysis decomposes the field's evolution into three critical dimensions: energy modeling fidelity, environmental realism, and optimization methodology.

3.1. Critique of Energy and Environmental Modeling

The most significant divergence between this project and existing literature lies in the treatment of physical realism. Standard studies, such as *Zeng and Zhang* [34] and *Wu et al.* [38], have established foundational frameworks for UAV trajectory optimization. However, these works predominantly employ static energy models, assuming that hovering power is constant regardless of environmental conditions. While mathematically convenient, this assumption contradicts the findings of *Abeywickrama et al.* [35], whose comprehensive energy model demonstrates that propulsion power is dynamically coupled with air density and rotor mechanics. By neglecting thermodynamic variations (humidity, temperature, altitude), standard models likely underestimate energy consumption in high-altitude or high-humidity scenarios.

Furthermore, regarding environmental realism, the majority of channel modeling research, including the seminal probabilistic LoS models by *Al-Hourani et al.* [32], assumes clear sky conditions. While Mishra and Kaabouch [14] have highlighted the severe impact of weather factors on UAV communications, integration of specific attenuation models (rain, fog, gas) into the optimization loop remains rare in NOMA-MEC literature. Recent advanced works like *Xiao et al.* [29] integrate STAR-RIS with UAVs but still overlook the mechanical penalties of mass accumulation (rain/dust) on the UAV frame, a gap this project explicitly addresses.

3.2. Evolution of Access Technologies and Optimization

In terms of access technology, early UAV-MEC systems described by Liu et al. [23] relied on OMA schemes of TDMA or FDMA, which suffer from severe latency bottlenecks in dense IoT networks due to sequential transmission. While the shift to NOMA, as surveyed by Liu et al. [24], improved spectral efficiency, many studies still treat NOMA pairing as a static resource allocation problem.

Finally, regarding optimization strategies, traditional approaches often utilize convex relaxation or weighted-sum methods to handle multi-objective trade-offs, as seen in Yang et al. [12]. These methods produce a single static solution that cannot adapt to changing mission priorities in real-time. In contrast, by adopting the Pareto Conditioned Networks (PCN) proposed by Mathieu et al. [39], this research moves from per-instance optimization to amortized optimization, enabling the dynamic generation of the entire Pareto Front.

3.3. Comparative Summary

Table 4 comprehensively contrasts the methodological fidelity of the proposed research against these prevailing standards.

Table 4: Literature review comparison

Feature / Component	Standard Literature [32], [43]	State-of-the-Art Works [37], [38]	Proposed Project (AIP491_G2)
Access Technology	OMA (TDMA/FDMA)	NOMA (Idealized)	**NOMA with RIS Partitioning**
Channel Model	Rayleigh / Free Space	Rician Probabilistic LoS	**Nakagami-m and ITU Weather Attenuation**
Environmental Realism	Ignored ("Clear Sky")	Limited (Shadowing only)	**Weather Conditions on** Rain, Fog, Gas modeled via ITU P.838/840/676.
Energy Consumption	Static Hovering Power Model	Weight-based Linear	**BEMT + Thermodynamics:** Dynamic air density via Ideal Gas Law.
Physical Constraints	Ignored	Payload Weight only	**Mass Accumulation:** Rain/Dust/Ice on RIS surface + Wind Drag + Square-Cube Law.
Optimization Goal	Single Objective (Sum-Rate)	Weighted Sum (Static)	**Pareto Conditioned Networks (PCN):** Dynamic generation of the entire Pareto Front.
Reliability Metric	Outage Probability	Ergodic Capacity	**Successful Computation Probability (SCP):** Latency-constrained probabilistic metric.
Energy Metric	Consumption (Joules)	Energy Efficiency (EE)	**Energy Outage Probability (EOP):** Thrust/Power feasibility probability.

4. Gaps in the Literature/Technology

Despite the rapid maturation of UAV-mounted RIS architectures and the theoretical sophistication of NOMA-MEC frameworks, a critical synthesis of the existing literature reveals a profound dichotomy between communication theory and physical realism. The primary gap identified lies in the pervasive

reliance on clear sky channel assumptions within 6G performance analyses. While recent studies have successfully integrated probabilistic LoS models to account for urban blockages, they predominantly neglect the severe signal attenuation caused by dynamic atmospheric conditions. As wireless networks migrate toward higher frequency bands, such as mmWave and Terahertz, the interaction between electromagnetic waves and atmospheric constituents becomes non-negligible. The vast majority of current optimization frameworks fail to incorporate specific attenuation models, such as those defined by ITU recommendations P.676 for atmospheric gases and P.838 for rain, into the channel estimation loop. Consequently, standard literature tends to produce over-optimistic reliability predictions that may prove unattainable in real-world deployment scenarios plagued by heavy precipitation, dense fog, or high humidity.

Furthermore, a significant disconnect exists between the mathematical modeling of energy consumption and the thermodynamic realities of aerial flight. The dominant trend in current communications research is the utilization of static or weight-based linear power models, which treat the UAV as a simplified point mass with constant energy expenditure. These models systematically fail to account for the impact of thermodynamic atmospheric physics, specifically the variations in air density caused by real-time fluctuations in altitude, temperature, and humidity. According to BEMT, a decrease in air density requires a compensatory increase in rotor thrust, leading to non-linear spikes in power consumption that static models cannot predict. Moreover, existing literature almost entirely overlooks the mechanical penalties of environmental mass accumulation. The physical reality is that rain droplets, fog condensation, and dust particles accumulate on the entire surface area of the UAV-RIS platform. This accumulation, alongside wind drag, alters the entity's gross weight and drag coefficients during flight, remaining a variable currently unaddressed in standard energy efficiency optimization.

Finally, regarding methodological approaches, there is a notable scarcity of optimization frameworks capable of resolving the multi-objective trade-offs of 6G networks in real-time. Traditional optimization strategies primarily rely on convex relaxation techniques or weighted-sum scalarization to convert conflicting objectives, such as reliability maximization and energy minimization, into a single static problem. While effective for generating a single optimal solution for a specific snapshot in time, these methods lack the flexibility to adapt to rapidly changing mission priorities without computationally expensive re-calculations. There is a distinct lack of amortized optimization approaches in the current domain, specifically those utilizing Deep Reinforcement Learning to learn a universal policy capable of generating the entire Pareto Front. Consequently, current systems lack the capability to dynamically shift operational preferences from energy-conservation modes to high-reliability modes in response to the stochastic environmental triggers identified in this research.

III. Methodology

1. Research Questions and Objectives

This project employs a rigorous combination of mathematical derivation and AI-driven multi-objective optimization to address the offloading reliability and energy challenges of a unified framework for 6G-enabled IoT networks. To guide the methodological structure, this research addresses four primary Research Questions (RQs):

- **RQ1 for system integration:** How can the distinct technologies of UAV-mounted RIS, NOMA, and MEC be effectively synergized into a coherent architectural framework? Subsequently, to what extent does this integration address the spectral scarcity, coverage limitations, and channel instability inherent in dense urban 6G IoT networks?
- **RQ2 for offloading reliability:** How can computation offloading reliability be accurately quantified in dense urban environments while incorporating realistic Nakagami-m fading channel, probabilistic LoS/NLoS propagation, and the signal attenuation caused by adverse weather conditions such as rain, fog, and atmospheric gas?
- **RQ3 for energy robustness:** How can the energy consumption of rotary-wing UAV be modeled to realistically reflect aeromechanical constraints, specifically accounting for thermodynamic

atmospheric variations affected by humidity, temperature, altitude, and the environmental mass accumulation on the entire UAV-RIS physical frame?

- **RQ4 for trade-off optimization:** How can the fundamental trade-off between maximizing SCP and minimizing EOP be resolved to identify optimal UAV altitude and positions?

Corresponding to these questions, the methodological objectives are:

1. The first objective is to develop a unified framework that constructs a comprehensive system architecture. This model aims to synergize the channel enhancement capabilities of RIS, the mobility of UAVs, and the spectral efficiency of NOMA to effectively overcome the infrastructure limitations of MEC terrestrial networks.

2. The second objective is to derive the realistic reliability metric by formulating a closed-form analytical expression for SCP. This derivation rigorously models the impact of LoS/NLoS RIS cascaded channels, and weather-induced signal attenuation on total average path-loss for affecting computation offloading.

3. The third objective is to formulate physics-based energy models by developing a comprehensive EOP measurement. This involves integrating BEMT and thermodynamic laws to accurately calculate dynamic propulsion power and the physical scaling of the payload according to the Square-Cube law.

4. The final objective is to implement multi-objective optimization by deploying a PCN framework. This algorithm seeks to jointly optimize UAV altitude and positions, that satisfy distinct operational preferences ranging from reliability-maximization to energy-minimization and the balanced sweet spot scenario.

2. System Model and Communication Protocol

2.1 System and Channel Model



Figure 1: System model of a NOMA-aided MEC server incorporating UAV-mounted RIS within IoT networks.

To directly address RQ1 regarding the synergistic integration of proposed technologies for surpassing coverage and spectral limitations, the system model, depicted in **Figure 1**, establishes a unified framework. It is designed to operate in a dense-urban IoT network that involves a base station equipped with a MEC

server (B_M) and a UAV-mounted RIS (U_R) employed to facilitate the delivery of MEC services to available ED clusters for computation offloading. Accordingly, this specific dense-urban environment is adopted as the foundational baseline for the subsequent performance evaluation, utilizing the standard air-to-ground channel parameters from [54]. Additionally, the ED clusters are distinguished based on the urgency of their data computation or service provision needs, which in turn determines their assigned priority levels to B_M for resource allocation [15]. By considering this priority distinction, the clusters are designated as high-priority ED cluster, denoted as $H = \{H_1, \ldots, H_i, \ldots, H_Q\}$, and low-priority ED cluster, $L = \{L_1, \ldots, L_t, \ldots, L_K\}$, where H_i and L_t are respectively the *i-th* and *t-th* device for the total number of Q and K EDs in the clusters. This priority partitioning is fundamental for subsequent resource allocation strategies, hence enabling effective SIC decoding through the power allocation ratio (PAR), while considering the task-offloading ratio (TOR) to balance computational workloads between clusters [55]. In addition, base station MEC and EDs are assumed to be equipped with a single antenna and operate in the half-duplex mode [40].

2.1.1 Probabilistic LoS/NLoS Channel Propagation

In the considered dense-urban scenario, the quality of wireless linkages is fundamentally governed by the spatial relationships between devices and the presence of physical obstructions [4]. Since signal power decays with propagation distance and degrades sharply under blockage, establishing a geometric framework for the considered system is essential for accurate performance analysis [56]. Therefore, to mathematically measure these geometric dependencies, the static 3D Cartesian coordinate system is adopted. The positions of the UAV-RIS, ground-based ED clusters, and the base station with a MEC server can be defined by $B_M(x_{B_M}, y_{B_M}, h_{B_M})$, $U_R(x_{U_R}, y_{U_R}, h_{U_R})$, $H_i(x_{H_i}, y_{H_i}, 0)$, and $L_t(x_{L_t}, y_{L_t}, 0)$, respectively. Based on this geometry, a path-loss model grounded on LoS and NLoS transmission propagation is employed as [56] $\mathcal{L}_{uv}^{los} = \xi_{los} d_{uv}^{\sigma}$ and $\mathcal{L}_{uv}^{nlos} = \xi_{nlos} d_{uv}^{\sigma}$, where $\xi_{los} = \mu_{los} \left(\frac{c}{4\pi f_c}\right)^{-\sigma}$ and $\xi_{nlos} = \mu_{nlos} \left(\frac{c}{4\pi f_c}\right)^{-\sigma}$; μ_{los} and μ_{nlos} are excess path-loss of LoS and NLoS connections; the distance between node u to node v, denoted as uv can be represented by $d_{uv} = \sqrt{(x_v - x_u)^2 + (y_v - y_u)^2 + (h_v - h_u)^2}$ in meters, where $uv \in \{H_i R_n, L_t R_u, R_n B_M, R_u B_M\}$; the velocity of light is denoted by c; the system carrier frequency is denoted by f_c (in Hz); and σ represents the path-loss exponential coefficient. Subsequently, by considering an obstacle-dense urban setting, the probabilistic model of encountering LoS and NLoS propagation is expressed as [40]:

$$\begin{cases} \mathcal{P}_{uv}^{los} = \frac{1}{1 + \varsigma_1 \, exp[-\varsigma_2(\varphi_{uv} - \varsigma_1)]}, \\ \mathcal{P}_{uv}^{nlos} = 1 - \mathcal{P}_{uv}^{los} \end{cases} \tag{2}$$

where ς_1 and ς_2 are the urban environmental factors and $\varphi_{uv} = (180/\pi)\, arcsin\left(\frac{h_{uv}}{d_{uv}}\right)$ is the elevation angle in degrees [40].

2.1.2 Weather-induced Attenuation Modelling

To explicitly address the RQ2 on offloading reliability under realistic conditions**,** this framework explicitly models the signal attenuation caused by adverse weather conditions. The total weather-induced path loss (in dB) over distance d_{uv} of kilometres

is calculated as the sum of atmospheric gas attenuation and specific condition attenuation of rain or fog:

$$\mathcal{L}_{uv}^{cwc} = \frac{(\mathcal{A}_{gas}+\mathcal{A}_{conditi})d_{uv}}{1000}, \tag{3}$$

where $\mathcal{A}_{conditi} \in \{\mathcal{A}_{rain}, \mathcal{A}_{fog}\}$. The specific attenuation components are modelled based on ITU recommendation documents as follows:

- Rain attenuation ($\mathcal{A}_{rain}$): Based on ITU-R P.838-3, rain attenuation is modelled as a power-law function of the rainfall intensity $\mathcal{R}$ with the unit in mm/h:

$$\mathcal{A}_{rain} = k_r \mathcal{R}^{\nu_r}, \tag{4}$$

  where the coefficients k_r and ν_r are determined by the signal's specific polarization geometry. These coefficients are derived from the horizontal (k_H,ν_H) and vertical (k_V,ν_V) polarization coefficients, obtained from Table 5 of [ITU-R P.838-3]. The governing formulations for k_r and ν_r are expressed as:

$$k_r = \frac{(k_H - k_V)\, cos^2(\varphi_{uv})\, cos(2\varphi_{til}) + k_V + k_H}{2}, \tag{5}$$

$$\nu_r = \frac{(k_H\nu_H - k_V\nu_V)\, cos^2(\varphi_{uv})\, cos(2\varphi_{til}) + k_V\nu_V + k_H\nu_H}{2k_r} \tag{6}$$

  where φ_{uv} is the signal elevation angle and φ_{til} the antenna polarization tilt angle relative to the horizontal ground. Accordingly, φ_{til} is defined for standard configurations as three distinct scenarios of $\varphi_{til} = 0°$, $\varphi_{til} = 45°$, and $\varphi_{til} = 90°$.

  Remark 1: For this proposed system model, we explicitly adopt a vertical polarization configuration $\varphi_{til} = 90°$. This design choice is critical for reliability robustness; physically, falling raindrops tend to form an oblate spheroid shape (flattened at the bottom). Consequently, horizontally polarized waves encounter a larger cross-sectional area of water, leading to higher attenuation. By utilizing the antenna's vertical polarization, the electric field aligns with the shorter axis of the raindrops, thereby minimizing the specific attenuation and enhancing the link budget during adverse weather conditions.

- Fog attenuation ($\mathcal{A}_{fog}$): Following ITU-R P.840-8, the attenuation caused by clouds or fog is linearly proportional to the liquid water content density $\mathcal{Q}_c$ (in g/m^3). The specific attenuation of fog is expressed as:

$$\mathcal{A}_{fog} = \nu_f \mathcal{Q}_c, \tag{7}$$

  where $\nu_f = \frac{0.819 f_c}{\tilde{\mu}(1+\xi^2)}$ is the fog attenuation coefficient; the water complexity permittivity are respectively as $\tilde{\mu} = \frac{f_c(\omega_1-\omega_2)}{f_s\left[1+\left(\frac{f_c}{f_s}\right)^2\right]} + \frac{f_c(\omega_0-\omega_1)}{f_p\left[1+\left(\frac{f_c}{f_p}\right)^2\right]}$ and $\hat{\mu} = \omega_2 + \frac{\omega_1-\omega_2}{1+\left(\frac{f_c}{f_s}\right)^2} + \frac{\omega_0-\omega_1}{1+\left(\frac{f_c}{f_p}\right)^2}$; f_c in this weather section is the carrier frequency in GHz unit.

The remaining parameters are as $\omega_2 = 3.52$, $\omega_1 = 0.0671\omega_0$, $\omega_0 = 77.66 + 103.3\left(\frac{300}{T_e} - 1\right)$, $f_s = 39.8 f_p$, $f_p = 20.2 - 146\left(\frac{300}{T_e} - 1\right) + 316\left(\frac{300}{T_e} - 1\right)^2$, $\xi = \frac{2+\hat{\mu}}{\tilde{\mu}}$, and T_e (in Kelvin) is the actual average temperature in the atmosphere lapse, which varies based on the atmoshpheric altitude profile.

- Atmospheric gas attenuation ($\mathcal{A}_{gas}$): Based on ITU-R P.676-13 recommendation documents, the specific attenuation due to atmospheric gases is calculated by summing the individual resonance lines of oxygen and water vapour, alongside a non-resonant dry air continuum. The total specific attenuation $\mathcal{A}_{gas}$ is expressed as:

$$\mathcal{A}_{gas} = 0.182 f_c\left(\mathcal{N}_{oxy} + \mathcal{N}_{vapour}\right), \tag{8}$$

where f_c is the carrier frequency in GHz unit. The imaginary parts of the frequency-dependent complex refractivity for oxygen ($\mathcal{N}_{oxy}$) and water vapour ($\mathcal{N}_{vapour}$) are defined as:

$$\begin{cases} \mathcal{N}_{oxy} = \sum_t S_t F_t + \mathcal{N}_{dry} \\ \mathcal{N}_{vapour} = \sum_t S_t F_t \end{cases}, \tag{9}$$

where the line strength S_t for oxygen and water vapour is highly sensitive to thermodynamic conditions, specifically the dry air pressure p_d (in hPA) and water vapour partial pressure p_v (in hPA) and thermodynamic temperature T_e (K). The specific formulations are:

$$\begin{cases} S_t = a_1 p_d 10^{-7}\left(\frac{300}{T_e}\right)^3 exp\left[a_2\left(1 - \frac{300}{T_e}\right)\right] & \text{For Oxygen} \\ S_t = b_1 p_v 10^{-1}\left(\frac{300}{T_e}\right)^{3.5} exp\left[b_2\left(1 - \frac{300}{T_e}\right)\right] & \text{For Water Vapour} \end{cases}. \tag{10}$$

The line shape factor F_t formulation for both oxygen and water vapour are expressed as:

$$F_t = \frac{f_c}{f_t}\left[\frac{\Delta f - \delta_c(f_t - f_c)}{(f_t - f_c)^2 + (\Delta f)^2} + \frac{\Delta f - \delta_c(f_t + f_c)}{(f_t + f_c)^2 + (\Delta f)^2}\right], \tag{11}$$

where Δf is the line-width; δ_c denotes a correction factor for interference effects; and f_t is the specific line frequency. Specifically, the base line-width is calculated as:

$$\begin{cases} \Delta f = 10^{-4} a_3\left[p_d\left(\frac{300}{T_e}\right)^{0.8 - a_4} + \frac{330 p_v}{T_e}\right] & \text{For Oxygen} \\ \Delta f = 10^{-4} b_3\left[p_d\left(\frac{300}{T_e}\right)^{b_4} + b_5 p_v\left(\frac{300}{T_e}\right)^{b_6}\right] & \text{For Water Vapour} \end{cases}. \tag{12}$$

By considering Zeeman splitting of oxygen lines and Doppler broadening of water vapour lines, the base line-width expressions are modified as follows:

$$\begin{cases} \Delta f = \sqrt{(\Delta f)^2 + 2.25 \times 10^{-6}} & \text{For Oxygen} \\ \Delta f = 0.535\Delta f + \sqrt{0.217(\Delta f)^2 + \frac{2.1316 \times 10^{-12} f_t^2 T_e}{300}} & \text{For Water Vapour} \end{cases} \tag{13}$$

.

The spectroscopic coefficients ($a_1 \dots a_6$, $b_1 \dots b_6$) and specific line frequencies (f_t) are obtained from Tables 1 and 2 of ITU-R P.676-13. The dry air continuum $\mathcal{N}_{dry}$ accounts for the non-resonant background absorption are calculated as:

$$\mathcal{N}_{dry} = f_c p_d \left(\frac{300}{T_e}\right)^2 \left[\frac{6.14\times10^{-5}}{D_{es}\left[1+\left(\frac{f_c}{D_{es}}\right)^2\right]} + \frac{1.4\times10^{-12} p_d \left(\frac{300}{T_e}\right)^{1.5}}{1+1.9\times10^{-5} f_c^{1.5}}\right], \quad (14)$$

where $p_v = \frac{\rho_h p_{sv}}{100}$ (in hPA); ρ_h is the relative humidity in percentage, while the saturation vapor pressure is calculated via the Tetens equation of $p_{sv} = A\, exp\left(\frac{B(T_e-273.15)}{T_e+D}\right)$ (in Pa), where $A = 610.78$, $B = 17.27$, and $D = 237.3$.

Consequently, to establish a realistic link budget that accounts for the dense-urban spatial relationship and the dynamic atmospheric conditions, we derive the total average path-loss for all system connections. By synthesizing the baseline probabilistic LoS/NLoS propagation model as defined in (1) and (2), with the cumulative weather-induced attenuation as detailed in (3), the linear average path-loss formulation for any connection uv can be expressed as:

$$\tilde{\mathcal{L}}_{uv} = (\mathcal{L}_{uv}^{los}\mathcal{P}_{uv}^{los} + \mathcal{L}_{uv}^{nlos}\mathcal{P}_{uv}^{nlos})10^{\frac{\mathcal{L}_{uv}^{cwc}}{10}}, \quad (15)$$

where the first term represents the expected path loss due to obstacles and distance, while the second term converts the total weather attenuation from dB into a linear scaling factor for rigorously quantifying the aggregate signal degradation from rain, fog, and atmospheric gases.

2.2 RIS Channels' Statistical Properties

Following the establishment of the large-scale path-loss model in Subsection 2.1, this section focuses on characterizing the small-scale signal variations and the RIS beamforming capability. To facilitate simultaneous and interference-free connectivity for the prioritized clusters, we adopt a practical RIS partitioning strategy in this research [52]. Specifically, the total N reflecting elements are partitioned into two distinct sub-surfaces, comprising $N_H = \lceil \alpha N \rceil$ elements and $N_L = \lceil (1-\alpha)N \rceil$ elements, where $\alpha \in (0,1)$ represents the element-splitting ratio. Based on this structural partitioning, the channel coefficients are explicitly defined by specific matrix dimensions corresponding to the available EDs (Q, K) and the allocated RIS elements. The channel coefficient matrices for the uplink connections from ED clusters to the U_R are denoted by $g_{HR} = \left[g_{H_i R_n}\right]_{Q\times N_H}$ and $g_{LR} = \left[g_{L_t R_u}\right]_{K\times N_L}$, while the reflected channels from the RIS to B_M are defined as $g_{RB_M}^{H} = \left[g_{R_n B_M}^{H_i}\right]_{Q\times N_H}$ and $g_{RB_M}^{L} = \left[g_{R_u B_M}^{L_t}\right]_{K\times N_L}$. Accordingly, R_n and R_u represent the *n-th* and *u-th* element of the respective RIS splitting sub-surfaces. To accurately characterize the small-scale signal variations, all individual channel coefficients within these matrices are statistically characterized by the Nakagami-m fading distribution, denoted generically as $\mathcal{NK}(m_{uv}, \lambda_{uv})$. For analytical tractability, we assume that the channel coefficients for links associated with the same cluster are independent and identically distributed

(i.i.d.). Consequently, all elements within a specific channel matrix share common fading severity and scale parameters for instance $m_{H_iR_n} = m_{HR}$ and $\lambda_{H_iR_n} = \lambda_{HR}$ for all $n \in \{1, \ldots, n_H\}$. Here, m is the fading severity parameter, and $\lambda = 1$ is the scale parameter.

Before delving into the RIS cascaded channel analysis, it is necessary to define the user selection criteria employed in the proposed system. In dense IoT networks, multiple EDs within a cluster may request offloading simultaneously. Therefore, to maximize the transmission reliability and exploit multi-user diversity, the system employs an optimal ED selection scheme [5,40]. This strategy evaluates the instantaneous channel state information (CSI) of all active devices and selects the specific device pair that yields the highest channel power gain, denoted as best EDs (BEDs), for the computation offloading procedure. Consequently, by utilizing their respective RIS partitions, the formulation of the cascaded power channel gains for connections $H^* \rightarrow U_{R,N_H} \rightarrow B_M$ and $L^* \rightarrow U_{R,N_L} \rightarrow B_M$ in which H^* and L^* are the BEDs that have been selected, can be expressed by:

$$\begin{cases} \left|g_{H^*R}^T \Phi_H g_{RB_M}^{H^*}\right|^2 = \max\limits_{i \in \{1,\ldots,Q\}} \left[\left|\sum_{n=1}^{N_H} g_{H_iR_n} g_{R_nB_M}^{H_i} \vartheta_n e^{j\phi_n}\right|^2\right] \\ \left|g_{L^*R}^T \Phi_L g_{RB_M}^{L^*}\right|^2 = \max\limits_{t \in \{1,\ldots,K\}} \left[\left|\sum_{u=1}^{N_L} g_{L_tR_u} g_{R_uB_M}^{L_t} \vartheta_u e^{j\phi_u}\right|^2\right] \end{cases}, \tag{16}$$

where $\Phi_I = diag\left(\vartheta_1 e^{j\phi_1}, \ldots, \vartheta_2 e^{j\phi_s}, \ldots, \vartheta_{N_I} e^{j\phi_{N_I}}\right)$ is the RIS phase-shift matrix; $\phi_s \in 0,2\pi)$ is the phase-shift coefficient of the s-th element with $I \in \{H, L\}$ and $s \in \{n, u\}$; and $\vartheta_s = \vartheta = 1\ \forall s$ represents the maximal reflection coefficient. Additionally, to maximize the channel power gains, the optimal phase is configured as $\phi_s = \bar{\phi} - arg\left(g_{I^*R_s} g_{R_sB_M}^{I^*}\right)$, with the arbitrary common phase for the entire elements $\bar{\phi} \in [0,2\pi)$, to effectively cancel the random phase fluctuations of the fading channels. By substituting this optimal phase into (16), the complex vector summation simplifies to a scalar summation of the channel magnitudes. Therefore, the maximized RIS power channel gains for the high-priority and low-priority connections are rewritten as:

$$\begin{cases} \mathcal{X} = \left|g_{H^*R}^T \Phi_{H^*} g_{RB_M}^{H^*}\right|^2 = \left|\sum_{n=1}^{N_H} g_{H^*R_n} g_{R_nB_M}^{H^*}\right|^2 = \left(\sum_{n=1}^{N_H} \left|g_{H^*R_n}\right| \left|g_{R_nB_M}^{H^*}\right|\right)^2 \\ \mathcal{Y} = \left|g_{L^*R}^T \Phi_{L^*} g_{RB_M}^{L^*}\right|^2 = \left|\sum_{u=1}^{N_L} g_{L^*R_u} g_{R_uB_M}^{L^*}\right|^2 = \left(\sum_{u=1}^{N_L} \left|g_{L^*R_u}\right| \left|g_{R_uB_M}^{L^*}\right|\right)^2 \end{cases}. \tag{17}$$

Accordingly, since (17) represents the sum of independent Nakagami-m fading variables, the statistical properties of the channel power gain $\left|g_{I^*R}^T \Phi_{I^*} g_{RB_M}^{I^*}\right|^2$ are depicted by adopting the following probability density function (PDF) and cumulative distribution function (CDF) derived via the Gamma moment matching in **Lemma 1**.

Lemma 1: Following the Gamma moment matching method, the PDF and CDF of the RIS cascaded power channel gains are derived as:

$$f_{\mathcal{Z}}(x) = \frac{\mathcal{O}}{2(\theta_{\mathcal{Z}})^{\mu_{\mathcal{Z}}}\Gamma(\mu_{\mathcal{Z}})}\left[\frac{\gamma\left(\mu_{\mathcal{Z}},\frac{\sqrt{x}}{\theta_{\mathcal{Z}}}\right)}{\Gamma(\mu_{\mathcal{Z}})}\right]^{\mathcal{O}-1}\left(\sqrt{x}\right)^{\mu_{\mathcal{Z}}-2}e^{-\frac{\sqrt{x}}{\theta_{\mathcal{Z}}}}, \tag{18}$$

$$F_{\mathcal{Z}}(x) = \left[\frac{\gamma\left(\mu_{\mathcal{Z}},\frac{\sqrt{x}}{\theta_{\mathcal{Z}}}\right)}{\Gamma(\mu_{\mathcal{Z}})}\right]^{\mathcal{O}}, \tag{19}$$

where $\mathcal{Z} \in \{\mathcal{X},\mathcal{Y}\}$, $\mathcal{O} \in \{Q,K\}$; $\mu_{\mathcal{Z}}$ and $\theta_{\mathcal{Z}}$ are the shape and scale parameters of the approximated Gamma distribution, whose formulations can be expressed by using the specific linkage parameters defined in the previous generic parameter symbol for Nakagami-*m* distribution:

$$\mu_{\mathcal{Z}} = \frac{N_I\mu_{\mathcal{Z}_S}^2}{\lambda_{I^*R_S}\lambda_{R_SB_M}^{I^*}-\mu_{\mathcal{Z}_S}^2}, \tag{20}$$

$$\theta_{\mathcal{Z}} = \frac{\lambda_{I^*R_S}\lambda_{R_SB_M}^{I^*}-\mu_{\mathcal{Z}_S}^2}{\mu_{\mathcal{Z}_S}}, \tag{21}$$

where $\mu_{\mathcal{Z}_S} = \frac{\Gamma\left(m_{I^*R_S}+0.5\right)\Gamma\left(m_{R_SB_M}^{I^*}+0.5\right)}{\Gamma\left(m_{I^*R_S}\right)\Gamma\left(m_{R_SB_M}^{I^*}\right)}\sqrt{\frac{\lambda_{I^*R_S}\lambda_{R_SB_M}^{I^*}}{m_{I^*R_S}m_{R_SB_M}^{I^*}}}$.

Proof. The distribution of the sum of independent Nakagami-m fading magnitudes is approximated using the Gamma Moment Matching technique. The derivation follows the standard moment estimation procedure established in [60] and [61], matching the first two moments of the cascaded channel gains. The detailed algebraic steps are omitted for brevity.

2.3 System Communication Protocol

This subsection details the system communication protocol that governs the operation of the NOMA-aided MEC server incorporating UAV-mounted RIS system. The protocol operates in a time division duplexing (TDD) mode within a finite time block T and is structured into four sequential phases as depicted in **Figure 2**.

Determining Parameter Phase $B_M \to U_R \to \{H_i, L_j\}$	RIS Offloading Phase $\{H^*, L^*\} \to U_R \to B_M$	MEC Computing Phase B_M	Result Feedback Phase $\{H^*, L^*\}$
Duration: $\tau_{deter} \approx 0$	Duration: τ_{off}^{Sys}	Duration: $\tau_{com}^{B_M}$	Duration: $\tau_{res} \approx 0$

$\longleftarrow T \longrightarrow$

Figure 2: Communication protocol of NOMA-aided UAV-mounted RIS assisting MEC server within IoT networks.

- Determining parameter phase, denoted as τ_{deter}: During this initial phase, pilot signals are broadcast from the base station B_M to the ED clusters via the UAV-RIS U_R for estimating channel state information (CSI) and operational system

parameters. Concurrently, both B_M and U_R weather sensors collect real-time data from environmental conditions to dynamically calibrate the weather and aerosol dependent parameters. By leveraging the property of channel reciprocity inherent to TDD systems, the uplink CSI can be effectively derived from the downlink pilot transmission. This implies that the channel coefficients estimated during the downlink phase are valid for the uplink offloading phase, thereby eliminating the overhead of a separate uplink pilot transmission from the EDs. It is also essential to note that all communication linkages are perfectly known to all system components. Furthermore, this research aims to concentrate on computation offloading efficiency. Hence, the duration τ_{deter} is considered negligible [20].

- RIS offloading phase, denoted as τ_{off}^{Sys}: After achieving all CSI components, the most optimal EDs from both clusters are selected via B_M for computation offloading. The best pair of EDs H^* and L^* concurrently offloads the computational workloads to the base station with MEC server by exploiting RIS and uplink NOMA. Therefore, the composite signal received at B_M [40]:

$$y_{B_M}^{NOMA} = g_{H^*R}^T \Phi_{H^*} g_{RB_M}^{H^*} \sqrt{\frac{\rho P_I}{\tilde{\mathcal{L}}_{H^*R}\tilde{\mathcal{L}}_{RB_M}}} s_H + g_{L^*R}^T \Phi_{L^*} g_{RB_M}^{L^*} \sqrt{\frac{(1-\rho)P_I}{\tilde{\mathcal{L}}_{L^*R}\tilde{\mathcal{L}}_{RB_M}}} s_L + n_B, \quad (22)$$

where ρ is the power-allocation ratio (PAR) within the interval $[0.5,1)$; P_I is the transmission power of BEDs; s_H and s_L are the offloading signals of the two BEDs; and n_B represents the additive white Gaussian noise (AWGN) with the mean of zero and variance $N_B = -174 + 10\, log_{10}(W)$, where W is the system bandwidth.

According to the uplink NOMA principle and the priority level distinction outlined in Section IV.2.1, B_M implements power-domain multiplexing by assigning specific PAR ρ to the BEDs. Consequently, B_M prioritizes the signal from the high-priority device H^*, and initially decodes s_H while treating the signal from L^* as interference. Subsequently, B_M employs successive interference cancellation (SIC) technique to completely subtract decoded signal s_H from the composite signal, thereby allowing for the subsequent decoding of s_L. Following the described decoding procedure, the signal-to-interference-plus-noise ratio (SINR) expressions of H^* and L^* decoded at B_M are calculated as:

$$\gamma_{H^*\to B_M}^{U_R} = \frac{\bar{\gamma}_1 \mathcal{X}}{\bar{\gamma}_2 \mathcal{Y}+1}, \gamma_{L^*\to B_M}^{U_R} = \bar{\gamma}_2 \mathcal{Y}, \quad (23)$$

where $\bar{\gamma}_1 = \frac{\rho\gamma_I}{\tilde{\mathcal{L}}_{H^*R}\tilde{\mathcal{L}}_{RB_M}}$, $\bar{\gamma}_2 = \frac{(1-\rho)\gamma_I}{\tilde{\mathcal{L}}_{L^*R}\tilde{\mathcal{L}}_{RB_M}}$, $\gamma_I = \frac{P_I}{N_B}$, $\mathcal{X} = \left(\sum_{n=1}^{N_H} |g_{H^*R_n}||g_{R_nB_M}^{H^*}|\right)^2$, and $\mathcal{Y} = \left(\sum_{u=1}^{N_L} |g_{L^*R_n}||g_{R_nB_M}^{L^*}|\right)^2$.

To facilitate the calculation for the total offloading latency, it is essential to firstly establish the characteristics of the system computational workload. We

assume that the system handles an aggregated computational workload of total l bits, representing the cumulative offloading data volume of the selected NOMA pair. In this full offloading model, the workload is considered divisible and is sent entirely to the MEC server for processing. To allow for simultaneous transmission using NOMA, this total task l is partitioned between the high-priority H^* and low-priority L^* BEDs. This division is controlled by the task-offloading ratio (TOR) β, constrained in the interval of $0 < \beta < 1$. Hence, the amount of data assigned to individual BED for offloading procedure is calculated as $\mathcal{C}_{off}^{H^*} = \beta l$ and $\mathcal{C}_{off}^{L^*} = (1-\beta)l$. Additionally, the fundamental mechanism of uplink NOMA allows BEDs to offload their computational workloads concurrently. Therefore, the system-wide offloading duration is determined by the specific user requiring the longest transmission time, since B_M must receive both tasks before the offloading phase is considered complete. The system offloading duration is dictated as:

$$\tau_{off}^{Sys} = max\left(\tau_{off}^{H^*}, \tau_{off}^{L^*}\right), \tag{26}$$

where $\tau_{off}^{I^*} = \frac{\mathcal{C}_{off}^{I^*}}{C_{I^*\to B_M}^{U_R}}$ is the offloading duration of I^*; $C_{I^*\to B_M}^{U_R} = W\, log_2\left(1 + \gamma_{I^*\to B_M}^{U_R}\right)$ denotes the instantaneous capacity of I^* to B_M via U_R connections.

- MEC computing phase, denoted as $\tau_{com}^{B_M}$: MEC commences the data computation procedure on the offloaded workloads. Assuming a sequential processing model, therefore, the duration required for the complete execution of the entire computational tasks l is derived as:

$$\tau_{com}^{B_M} = \frac{\varsigma\left(\mathcal{C}_{off}^{H^*} + \mathcal{C}_{off}^{L^*}\right)}{f_{B_M}^{MEC}}, \tag{27}$$

  where ς represents the quantity of CPU cycles required to execute a single bit, while $f_{B_M}^{MEC}$ denotes the MEC's operating frequency.
- Result feedback phase, denoted as τ_{res}: The computed results are transmitted to BEDs for data interchange within clusters. As the computed data are remarkably small compared to the offloaded data, τ_{res} is negligible [21].

3. Performance Analysis Framework

3.1 Successful Computation Probability (SCP)

In the context of 6G-envision IoT networks, where applications demand ultra-reliable and low-latency communication, standard metrics such as throughput or ergodic capacity are insufficient to capture the strict temporal constraints of computation offloading. To address this analytical limitation and RQ2 regarding the rigorous quantification of reliability under dynamic realistic factors, we propose the successful computation probability (SCP) as the primary metric for quantifying system offloading reliability.

3.1.1 Latency Constraints and Offloading Feasibility Analysis

Regarding communication reliability, the system must rigorously enforce the computation latency constraint. Since the sequential protocol requires the RIS offloading phase to precede the MEC computing phase within a finite time block T, the system's feasibility is strictly dictated by the remaining time threshold available for transmission. This latency threshold τ_{th} is calculated as the total operational time T minus the time required for the MEC server to execute the computational workload $\tau_{com}^{B_M}$, hence the threshold formulation is as $\tau_{th} = T - \tau_{com}^{B_M}$. This dependency creates two distinct physical scenarios that must be modelled to ensure the mathematical validity of the SCP metric:

1. Deterministic Failure ($\tau_{com}^{B_M} > T$): If the required computing time consumes the entire time block T, the time available for offloading becomes non-positive ($\tau_{th} < 0$). In this scenario, the minimum required SINR threshold for successful transmission, defined as $\psi_{I^*} = 2^{\frac{\mathcal{C}_{off}^{I^*}}{\tau_{th} W}} - 1$, approaches infinity or becomes undefined. This indicates that successful transmission is physically impossible regardless of the RIS channel quality or transmit power. Consequently, the SCP is deterministically 0.
2. Probabilistic Success ($\tau_{com}^{B_M} \leq T$): If the computing time is within the limit, a positive time budget exists ($\tau_{th} \geq 0$). resulting in a finite and achievable SINR threshold ψ_{I^*}. In this feasible region, the success of the offloading depends on the stochastic nature of the wireless channels. Thus, the SCP becomes probabilistic and feasible.

3.1.2 SCP Closed-form Formulation

The SCP reflects the system's capability to meet stringent latency requirements for MEC-based computation. Hence, the metric is defined as the likelihood in which the offloading duration of the whole system τ_{off}^{Sys} is successfully completed within the predefined latency threshold τ_{th}. By incorporating the offloading feasibility constraints described above, the closed-form formulation for the SCP of the whole system can be expressed as a piecewise function:

$$\Psi_{\mathcal{S}} = \begin{cases} 0 & \tau_{com}^{B_M} > T \\ Pr\{\tau_{off}^{Sys} \leq \tau_{th}\} & \tau_{com}^{B_M} \leq T \end{cases}. \tag{28}$$

Remark 3: It is critical to distinguish between the failure mechanisms of the mechanical layer and the communication layer within this framework. The energy outage probability (EOP), which will be defined in subsequent sections, serves as a metric for the physical reliability. It is strictly governed by the constraints of UAV's mechanical thrust feasibility and available energy reserves. Consequently, any violation of these constraints results in the immediate flight failure, representing a catastrophic system failure. Conversely, the SCP evaluates the service reliability, governed by the protocol's

time constraints and channel conditions. While a mechanical failure naturally precludes any computation service, we analyze SCP under the condition of flight feasibility to isolate the impact of the RIS-NOMA communication parameters from the physical constraints. Thus, the feasibility conditions for EOP and SCP are derived independently, based on their respective physical and temporal limits.

In addition, the closed-form formulation of SCP for the proposed system is expressed as in **Lemma 2**.

Lemma 2: The closed-form formulation of SCP for the whole system of NOMA-aided UAV-mounted RIS assisting MEC server under Nakagami-m fading channels is derived as follows:

$$\Psi_{\mathcal{S}} = \begin{cases} 0 & \tau_{com}^{B_M} > T \\ 1 - F_{\mathcal{Y}}(\Xi_C) - \frac{\pi e^{-\Xi_C} K}{4O(\theta_{\mathcal{Y}})^{\mu_{\mathcal{Y}}} \Gamma(\mu_{\mathcal{Y}})} \sum_{o=1}^{O} \sqrt{1-\nu_o^2} \left(\sqrt{\phi_o}\right)^{\mu_{\mathcal{Y}}-2} & \\ \times \kappa_o^{\frac{1}{\theta_{\mathcal{Y}}\sqrt{\phi_o}}-1} \left[\frac{\gamma\left(\mu_{\mathcal{X}}, \frac{\sqrt{\Xi(\phi_o)}}{\theta_{\mathcal{X}}}\right)}{\Gamma(\mu_{\mathcal{X}})}\right]^{Q} \left[\frac{\gamma\left(\mu_{\mathcal{Y}}, \frac{\sqrt{\phi_o}}{\theta_{\mathcal{Y}}}\right)}{\Gamma(\mu_{\mathcal{Y}})}\right]^{K-1} & \tau_{com}^{B_M} \leq T' \end{cases} \quad (29)$$

where $\Xi^{(\phi_o)} = \frac{\psi_{H^*}(\bar{\gamma}_2\phi_o+1)}{\bar{\gamma}_1}$, $\Xi_C = \frac{\psi_{L^*}}{\bar{\gamma}_2}$, $\psi_{H^*} = 2^{\frac{C_{off}^{H^*}}{\tau_{th}W}} - 1$, $\psi_{L^*} = 2^{\frac{C_{off}^{L^*}}{\tau_{th}W}} - 1$, $\phi_o = -ln(\kappa_o)$, $\kappa_o = \frac{(\nu_o+1)e^{-\Xi_C}}{2}$, $\nu_o = cos\left(\frac{\pi(2o-1)}{2O}\right)$, and O is the trade-off coefficient of complexity-versus-precision [59].

Proof. Following the approach in [40], the closed-form expression for SCP is obtained by integrating the CDF and PDF derived in Lemma 1 over the feasible SINR region defined by the latency threshold τ_{th}. The resulting integral is solved using the Gauss-Chebyshev Quadrature approximation to yield the tractable expression presented in (29).

3.2 Energy Outage Probability (EOP)

To rigorously address the energy modeling limitations identified in RQ3, we define the energy outage probability (EOP) as a comprehensive performance metric designed to quantify the physical feasibility of UAV-RIS platform and energy robustness of the whole system. Departing from traditional communication frameworks that treat UAVs simplified geometric entities as abstract nodes with static hovering power consumption and idealized weather conditions, this expanded metric integrates specific aeromechanical and environmental constraints to evaluate the system's operational feasibility. The formulation of EOP fundamentally advances the analytical framework by incorporating three critical physical dimensions into the energy analysis.

Firstly, the metric explicitly integrates thermodynamic atmospheric physics to model dynamic air density. By applying the International Standard Atmosphere (ISA) model and the Ideal Gas Law, the analysis accounts for real-time variations in humidity,

temperature, and altitude, which directly determine the aerodynamic lift efficiency and the subsequent hovering power consumption of the rotary-wing UAV.

Secondly, the metric incorporates blade element momentum theory (BEMT) to derive the propulsion power requirements. This approach replaces simplified weight-based formulas with a rigorous aerodynamic model that explicitly accounts for the UAV's specific rotor configuration parameters and reacts dynamically to changes in air density. Consequently, the model accurately calculates the necessary adjustment in rotor angular velocity required to maintain hover under varying atmospheric conditions.

Thirdly, the metric accounts for the physical mass accumulation of environmental particulates, specifically rain, fog droplets, and dust particles, as well as the equivalent weight from wind drag on the substantial surface area of the RIS and UAV physical frame. By quantifying how these factors increases gross weight and drag coefficients in real-time, the EOP serves as a comprehensive indicator of the system's ability to maintain thrust feasibility and prevent energy exhaustion during the mission.

3.2.1 Total Energy Consumption Model

The total energy consumption of the system, denoted as $\mathcal{E}_{Sys}^{total}$, is the aggregate of the energy expenditures from the UAV-RIS (U_R), the base station MEC (B_M), and the offloading transmission power of the two BEDs (H^*, L^*). Hence, the total energy consumption for the whole system is formulated as:

$$\mathcal{E}_{Sys}^{total} = E_{U_R}^{cons} + E_{B_M}^{cons} + E_{H^*,L^*}^{off}, \tag{30}$$

where the individual components are detailed as follows:

- UAV-RIS Energy Consumption ($E_{U_R}^{cons}$): This component represents the dominant energy expenditure, aggregating the propulsion energy required for stable hovering ($E_{U_R}^{hov}$) and the basal energy for on-board avionics ($E_{U_R}^{basal}$). The total expression of UAV-RIS consumption energy is as follows:

$$E_{U_R}^{cons} = E_{U_R}^{hov} + E_{U_R}^{basal}, \tag{31}$$

  The hovering energy is calculated over the entire operational cycle T. By accounting for the negligible duration of the determining and feedback phases ($\tau_{deter} + \tau_{res} \approx 0$), the total hovering hovering energy is decomposed into two distinct operational components:

$$E_{U_R}^{hov} = P_{U_R}^{hov} T = P_{U_R}^{hov}\left(\tau_{off}^{Sys} + \tau_{com}^{B_M}\right) = E_{U_R}^{hov,off} + E_{U_R}^{hov,com}, \tag{32}$$

  where $E_{U_R}^{hov,off} = P_{U_R}^{hov}\tau_{off}^{Sys}$ corresponds to the energy consumed while hovering during the RIS offloading phase, and $E_{U_R}^{hov,com} = P_{U_R}^{hov} t_{com}^{B_M}$ represents the hovering energy consumed during the MEC computing phase. The basal energy, which is calculated over the full operational duration T with the formulation of $E_{U_R}^{basal} = P_{U_R}^{basal} T$, is fixed at $P_{U_R}^{basal} = 10.27$ (W) based on empirical

measurements. Here, the hovering power $P_{U_R}^{hov}$ is a dynamic variable dependent on aeromechanical conditions and dynamic air density variations. Hence, it is dedicatedly described in the following independent section IV.3.2.2.

- Base Station MEC Energy Consumption ($E_{B_M}^{cons}$): The total energy consumption of the base station B_M is the aggregation of three distinct components including the energy required for signal reception ($E_{B_M}^{recei}$), the basal energy required to maintain operational readiness ($E_{B_M}^{basal}$), and the dominant energy expended for computational processing ($E_{B_M}^{MEC}$). The comprehensive formulation is expressed as:

$$E_{B_M}^{cons} = E_{B_M}^{recei} + E_{B_M}^{basal} + E_{B_M}^{MEC}, \tag{33}$$

Specifically, the reception energy corresponds to the power consumed by the receiver circuitry during the active offloading phase τ_{off}^{Sys}, modelled as $E_{B_M}^{recei} = P_{B_M}^{recei,cir}\tau_{off}^{Sys}$. Following the standard MEC energy consumption model from [79], the computation energy is derived as the product of the MEC computation power ($P_{B_M}^{MEC}$) and the computation duration ($\tau_{com}^{B_M}$). By substituting the cubic power model $P_{B_M}^{MEC} = \eta\left(f_{B_M}^{MEC}\right)^3$ and the latency model $\tau_{com}^{B_M} = \frac{\varsigma l}{f_{B_M}^{MEC}}$, the energy expression simplifies to:

$$E_{B_M}^{MEC} = \eta\left(f_{B_M}^{MEC}\right)^3\left(\frac{\varsigma l}{f_{B_M}^{MEC}}\right) = \eta\varsigma l\left(f_{B_M}^{MEC}\right)^2, \tag{34}$$

where h represents the effective switched capacitance coefficient related to the CPU hardware architecture.

- BEDs Energy Consumption (E_{H^*,L^*}^{off}): This component accounts for the energy expenditure of the selected BEDs during the uplink transmission phase. Since the NOMA protocol dictates that both the high-priority H^* and low-priority L^* devices transmit concurrently for the duration τ_{off}^{Sys}, the aggregate offloading energy is formulated as:

$$E_{H^*,L^*}^{off} = P_{H^*,L^*}^{off}\tau_{off}^{Sys}, \tag{35}$$

where the total power consumption P_{H^*,L^*}^{off} accounts for both the transmission signal power P_I and the internal circuit power P_{H^*,L^*}^{cir} for both active devices, resulting in the formulation of $P_{H^*,L^*}^{off} = P_I + P_{H^*,L^*}^{cir}$.

3.2.2 Aerodynamic Hovering Power Modeling via BEMT

To accurately quantify the propulsion energy required for the UAV to maintain stable flight, this study moves beyond simplistic static power models. Therefore, we utilize BEMT, a rigorous aerodynamic framework that calculates the thrust and power consumption based on the specific UAV's rotor configuration and the dynamic environmental conditions.

The comprehensive flying power $P_{U_R}^{fly}$ is modelled as the sum of three distinct aerodynamic components: blade profile power (P_{bl}), induced power (P_{in}), and parasite power (P_{pa}). Hence, the flying power expression is formulated as [3][4]:

$$P_{U_R}^{fly} = \underbrace{c_1(1+c_2V^2)}_{\text{Blade profile power}} + \underbrace{c_3\left(\sqrt{1+\frac{V^4}{c_4^2}}-\frac{V^2}{c_4^2}\right)^{\frac{1}{2}}}_{\text{Induced power}} + \underbrace{c_5V^3}_{\text{Parasite power}}, \tag{36}$$

where V represents the UAV's forward velocity, and c_1 through c_5 are constant aerodynamic coefficients determined by rotor geometry and blade profile. However, for the specific case of a UAV-mounted RIS acting as a relay, the UAV operates primarily in a hovering state where the forward velocity V approximates to zero ($V \approx 0$). Consequently, the parasite power component becomes negligible, and the translational velocity terms vanish. This power equation thus simplifies to the sum of the blade profile and induced power $P_{U_R}^{hov} = P_{bl} + P_{in}$. Crucially, while standard literature often assumes the ideal sea-level dry air density e_0, our model enforces physical realism by replacing ε_0 with the dynamic atmospheric density ε_h. This density varies notably in real-time based on thermodynamic factors of temperature, humidity, and altitude, as mathematically proven in **Appendix D.** Thereby, the mathematical expression of the dynamic atmospheric density is expressed as:

$$\varepsilon_h = \varepsilon_0\left(\frac{T_b - R_L h_{uv}}{T_b}\right)^{\frac{\chi}{R_d R_L}-1}\left(1-\frac{0.378p_v}{p_d+p_v}\right), \tag{37}$$

where T_b is the standard atmospheric temperature at 288.15 K; R_L is the standard atmospheric lapse rate at 0.0065 (in K/m); h_{uv} is the considered altitude of UAV-RIS or base station MEC in the dense-urban settings; χ is the standard gravitational acceleration at 9.8 m/s^2; R_d is the gas coefficient of dry atmosphere approximated as 287.057 in J kg^{-1} K^{-1}; p_v is the partial pressure of water vapour in PA unit; and $p_d = \varepsilon_d R_d T_e$ represents the partial dry air pressure. By substituting ε_h into the aerodynamic coefficients c_1 and c_3, the specific hovering power is derived as:

$$P_{U_R}^{hov} = c_1 + c_3 = P_{bl} + P_{in} = \frac{\kappa\varepsilon_h s_r \Omega_{nom}^3}{8}\sqrt{\frac{\varpi_{disc}^5}{(\mu\pi)^3}} + (1+d_0)\sqrt{\frac{w_{U_R}^3}{2\varepsilon_h\varpi_{disc}}}, \tag{38}$$

where κ is the profile drag coefficient; s_r is the rotor solidity; Ω_{nom} is the nominal blade angular velocity; d_0 is the incremental correction factor for induced power; μ is the number of rotors; ι is the rotor area; and $\varpi_{disc} = \mu \times \iota$ is the total rotor disc area. This formulation reveals the critical dependency of energy consumption on environmental factors, as a decrease in air density ε_h at high altitudes or an increase in gross weight w_{U_R} directly forces an increase in power to maintain lift. Moreover, the comprehensive weight model is thoroughly designed in the exclusive section IV.3.2.3.

3.2.3 Physical Mass Accumulation and Weight Modelling

To accurately quantify the mechanical thrust requirements derived in the BEMT analysis, it is essential to determine the instantaneous gross weight of the UAV-RIS platform, denoted as w_{U_R}. Unlike static models, our framework accounts for the

dynamic mass accumulation caused by environmental exposure. The total weight is formulated as the sum of three distinct components:

$$w_{U_R} = w_U + w_{RIS} + w_{weather}, \tag{39}$$

where w_U represents the baseline UAV frame weight, w_{RIS} denotes the total payload weight of the RIS module, and $w_{weather}$ accounts for the variable weight induced by wind drag and particulate accumulation. Accordingly, the individual weight components are demonstrated as follows:

1. UAV Baseline Weight (w_U): For the scope of this study, we consider a standard industrial-grade multirotor platform with a baseline takeoff weight in the range from 20 to 50 kg class, lining within the industrial drone category. However, ensuring the physical feasibility of flight requires rigorous configuration of the rotor parameters (e.g., profile drag, fuselage drag), which are resolved within the hovering feasibility conditions of the EOP piecewise function.
2. RIS Payload Weight (w_{RIS}): The weight of the reconfigurable intelligent surface is not a fixed constant but scales with the number of reflecting elements N. The total RIS weight is modeled as the aggregate of the substrate material mass, the electronic element mass, and the circuitry overhead:

$$w_{RIS} = \underbrace{\varepsilon_{panel}\varpi_{RIS}z_R}_{\substack{\text{Volume-based mass}\\ \text{(Density×Volume)}}} + \underbrace{Nw_e}_{\substack{\text{Total mass}\\ \text{for}\\ \text{all elements}}} + \underbrace{w_{cir}^{RIS}}_{\substack{\text{Total mass}\\ \text{of RIS controller,}\\ \text{wiring, circuit}}}, \tag{40}$$

where ε_{panel} is the density of the RIS substrate material in kg/m^3; z_R is the panel thickness (m); w_e is the mass of a single RIS element; and w_{cir}^{RIS} accounts for the total RIS controller and wiring. Accordingly, the physical area of the RIS panel ϖ_{RIS} is critical for both weight calculation and aerodynamic drag modeling. It is mathematically defined by the inter-element spacing d_{RIS} and the total number of elements N:

$$\varpi_{RIS} = Nd_{RIS}^2 = N\left(\frac{\lambda}{2}\right)^2, \tag{41}$$

where $\lambda = \frac{c}{f_c}$ is the wavelength of the electromagnetic (EM) signal over which the wave's change by one full cycle or a radio wave's shape repeats itself. It is worthwhile to mention that in this paper we adopt the square 2D array designation with $\sqrt{N} \times \sqrt{N}$ RIS size for isotropic coverage [5].

Remark 4: It is crucial to rigorously justify the intuition behind the designation of the RIS inter-element spacing d_{RIS} to ensure comprehensive signal reconstruction capabilities. Accordingly, the selection $d_{RIS} = \frac{\lambda}{2}$ is not arbitrary but is grounded in the Nyquist-Shannon Sampling Theorem applied to the spatial domain. In this context, the RIS elements function as discrete spatial samplers of the continuous EM wavefront. According to the theorem, to

perfectly reconstruct the continuous signal without aliasing, the spatial sampling rate R_{sample} (measured in samples per meter) must be at least twice the maximum spatial frequency of the wave ($f_{max}^{EM\ waves}$). Since an EM wave completes one full cycle every wavelength λ, the maximum spatial frequency is defined as $f_{max}^{EM} = 1$ cycle/ λ meters $= \frac{1}{\lambda}$. Crucially, the spatial sampling rate is mathematically the inverse of the inter-element spacing ($R_{sample} = \frac{1}{d_{RIS}}$); essentially, a smaller gap between elements corresponds to a higher sampling density. By substituting these spatial definitions into the fundamental Nyquist inequality ($R_{sample} \geq 2f_{max}^{EM\ waves}$), we derive the necessary physical constraint for the RIS architecture of $R_{sample} \geq \frac{2}{\lambda} \Leftrightarrow \frac{1}{d_{RIS}} \geq \frac{2}{\lambda} \Leftrightarrow d_{RIS} \leq \frac{\lambda}{2}$. This derivation confirms that maintaining an inter-element spacing of approximately half the wavelength is the physical upper bound required to prevent spatial aliasing, physically manifested as the formation of unwanted grating lobes that disperse energy in unintended directions.

3. Environmental Weather Weight ($w_{weather}$): To address the dynamic environmental constraints, we model the equivalent weight added by wind drag and the physical mass accumulation of precipitation. The total weather-induced weight is:

$$w_{weather} = w_{wind} + w_{rain} + w_{fog} + w_{dust}, \tag{42}$$

- Wind Drag Weight (w_{wind}): The aerodynamic drag force exerted by wind is converted into an equivalent weight load that the rotors must counteract. It is calculated as:

$$w_{wind} = \frac{\mathcal{D}_w}{2\chi} = \frac{\varepsilon_h \kappa_d V_{wind}^2 \varpi_{RIS}}{2\chi}, \tag{43}$$

  where V_{wind} is the average wind velocity, and κ_d is the drag shape coefficient.

- Particulate Accumulation Modeling: The mathematical expressions for particulate mass accumulation are rigorously grounded in foundational deposition physics, specifically adapting mass flux models used in frost formation, water film accumulation studies, and NASA standard documents. Fundamentally, the accumulated weight is derived from the mass flux m_{flux}, which is defined as the product of the material density ε (kg/m^3) and the deposited layer thickness $\mathcal{T}$ (m). Consequently, the total weight exerted on the exposed surface area ϖ is formulated as the integration of this flux over the exposure duration by $w = m_{flux}\varpi = \varepsilon\varpi\mathcal{T}$. Applying this physical

framework to specific environmental factors yields the following rigorous formulations:

- Rain Accumulation (w_{rain}): The accumulated water mass is modeled as a function of the water density ε_w at 1000 kg/m^3 and the rain layer thickness $\mathcal{T}_r$. This thickness $\mathcal{T}_r$ is determined by the empirical rainfall intensity $\mathcal{R}$ (mm/h) and a critical adhesion coefficient $\eta_{A.H}$, which represents the fraction of impinging droplets that adhere to the hydrophobic UAV-RIS surfaces over the exposure time τ_{exp}:

$$w_{rain} = \varepsilon_w \varpi_{exp} \mathcal{T}_r, \tag{44}$$

- Fog Condensation (w_{fog}): Unlike rain, fog accumulation is driven by the suspension density of droplets. The weight is derived from the liquid water content ($\mathcal{Q}_c$) in kg/m^3 and the fog deposition velocity v_f. The velocity v_f is governed by Stokes' Law, dependent on the droplet diameter d_{pf} and air viscosity δ_v, leading to:

$$w_{fog} = \varepsilon_w \varpi_{exp} \mathcal{T}_f = \varpi_{exp} \mathcal{Q}_c v_f \tau_{exp}, \tag{45}$$

where $\mathcal{T}_f = \frac{\mathcal{Q}_c v_f \tau_{exp}}{\varepsilon_w}$ is the thickness accumulated from fog droplets, and $v_f = \frac{\varepsilon_w d_{pf}^2 \chi}{18\delta_v}$.

- Dust Deposition (w_{dust}): The model explicitly distinguishes between the aerosol mass concentration $\mathcal{C}_d$ and the intrinsic material density ε_{dust}. The accumulation is calculated via the dust deposition velocity v_d, which rigorously accounts for particle size regimes (e.g., fine, coarse, super coarse) and dynamic shape factors ζ_{sd} as detailed in aerosol technology literature:

$$w_{dust} = \varepsilon_{dust} \varpi_{exp} \mathcal{T}_d = \varpi_{exp} \mathcal{C}_d v_d \tau_{exp}, \tag{46}$$

where $v_d = \frac{\varepsilon_{dust} d_{pd}^2 \chi}{18\delta_v \zeta_{sd}}$ is Stoke' Law settling velocity for the dust particles.

3.2.4 Total Exposed Surface Area Determination

The mass accumulation models derived in the previous section are intrinsically dependent on the total surface area exposed to the environment. Consequently, determining the accurate gross weight w_{U_R} requires a precise formulation of the system's total exposed area, denoted as ϖ_{exp}. This parameter is defined as the aggregate of the RIS panel area and the UAV frame surface area:

$$\varpi_{exp} = \varpi_{RIS} + \varpi_U. \tag{47}$$

While the RIS area ϖ_{RIS} is functionally determined by the number of elements and the Nyquist-based spacing in (41), the UAV frame surface area ϖ_U requires a physics-based scaling model to account for the platform's mass.

To derive the specific UAV frame surface area ϖ_U, we adopt the standard isometric similarity assumption widely utilized in the preliminary design of multirotor systems. This approach is grounded in the Square-Cube Law, which dictates that an object's surface area A scales with the square of its linear dimension (k^2), while its volume V proportional to its mass m, scales with the cube (k^3). Consequently, the linear scale factor relates to mass as $k \propto m^{1/3}$. By substituting this relationship back into the area scaling principle, we derive that the surface area is proportional to the mass raised to the power of two-thirds ($A \propto m^{2/3}$). Applying this physical law, the UAV frame area is rigorously calculated as:

$$\varpi_U = k w_U^{2/3}, \tag{48}$$

where ϖ_U represents the baseline weight and k is an empirical scaling coefficient, typically calibrated between 0.8 and 1.3 $m^2/kg^{2/3}$ for hexacopters and octocopters in the mass range from 5 to 50 kg. This formulation ensures that the modeled surface area available for environmental particulate accumulation scales realistically with the physical magnitude of the drone. Having established all necessary components to calculate for the total energy consumption $\mathcal{E}_{Sys}^{total}$, we now move to the derivation of EOP closed-form formulation.

3.2.5 EOP Closed-form Formulation

To guarantee the operational viability of the UAV-RIS platform, a fundamental mechanical flyability constraint must be satisfied: the maximum achievable thrust T_{max} must equal or exceed the total required thrust ($T_{req} = w_{U_R}\chi$). Derived from BEMT, this maximum thrust capability is physically limited by the rotor's maximum angular velocity Ω_{max} and constrained by dynamic environmental conditions. The formulation is expressed as:

$$T_{max} = \frac{\mu \varepsilon_h \iota R^2 \Omega_{max}^2 s_r C_L}{2} = \frac{\varepsilon_h \varpi_{disc}^2 \Omega_{max}^2 s_r C_L}{2\mu\pi}, \tag{49}$$

where C_L represents the average blade lift coefficient and ε_h denotes the dynamic atmospheric density derived in (37). By incorporating this mechanical constraint, we acknowledge a critical physical reality, as if the required thrust to lift the accumulated weight exceeds the UAV's physical limit ($w_{U_R}\chi > T_{max}$), a complete energy outage occurs deterministically due to the inability to take off or maintain stable hover. Conversely, if flight is mechanically feasible, the energy outage probability (EOP) is determined by the likelihood of the total energy consumption exceeding the system energy capacity $\mathcal{E}^{stor}$. Consequently, the closed-form formulation for the EOP of the whole system $\Psi_{\mathcal{E}}$ is derived as the following piecewise function:

$$\Psi_{\mathcal{E}} = \begin{cases} 1 & w_{U_R}\chi > T_{max} \\ Pr\{\mathcal{E}_{Sys}^{total} \geq \mathcal{E}^{stor}\} & w_{U_R}\chi \leq T_{max} \end{cases}, \tag{50}$$

In addition, the closed-form formulation of SCP for the proposed system is expressed as in **Lemma 3**.

Lemma 3: The closed-form formulation of EOP for the whole system of NOMA-aided UAV-mounted RIS assisting MEC server under Nakagami-m fading channels is derived as follows:

$$\Psi_{\mathcal{E}} = \begin{cases} 1 & w_{U_R}\chi > T_{max} \\ F_y(\Delta_C) - \frac{\pi e^{-\Delta_C K}}{4O(\theta_y)^{\mu_y}\Gamma(\mu_y)} \sum_{o=1}^{O} \sqrt{1-\nu_o^2}\left(\sqrt{\phi_o}\right)^{\mu_y-2} & \\ \times \kappa_o^{\frac{1}{\theta_y\sqrt{\phi_o}}-1} \left[\frac{\gamma\left(\mu_\chi, \frac{\sqrt{\Delta(\phi_o)}}{\theta_\chi}\right)}{\Gamma(\mu_\chi)}\right]^Q \left[\frac{\gamma\left(\mu_y, \frac{\sqrt{\phi_o}}{\theta_y}\right)}{\Gamma(\mu_y)}\right]^{K-1} & w_{U_R}\chi \le T_{max} \end{cases}, \quad (51)$$

where $\Delta^{(\phi_o)} = \frac{\zeta_{H^*}(\bar{\gamma}_2\phi_o+1)}{\bar{\gamma}_1}$, $\Delta_C = \frac{\zeta_{L^*}}{\bar{\gamma}_2}$, $\zeta_{H^*} = 2^{\frac{c_{off}^{H^*}}{W\mathcal{E}_{th}}} - 1$, $\zeta_{L^*} = 2^{\frac{c_{off}^{L^*}}{W\mathcal{E}_{th}}} - 1$, $\phi_o = -ln(\kappa_o)$, $\kappa_o = \frac{(\nu_o+1)e^{-\Delta_C}}{2}$, $\nu_o = cos\left(\frac{\pi(2o-1)}{2O}\right)$, $\mathcal{E}_{th} = \frac{\mathcal{E}^{stor} - E_{U_R}^{hov,com} - E_{U_R}^{basal} - E_{B_M}^{MEC} - E_{B_M}^{basal}}{P_{U_R}^{hov} + P_{B_M}^{recei} + P_{H^*,L^*}^{off}}$, and O is the trade-off coefficient of complexity-versus-precision [59].

Proof. Similarly as in [5], the EOP is derived by evaluating the complementary cumulative distribution function (CCDF) of the total energy consumption. By integrating the channel PDF from Lemma 1 over the energy capacity limit $\mathcal{E}^{stor}$, and applying the same Gauss-Chebyshev approximation method used in the SCP derivation, we obtain the closed-form outage probability in (51).

4. Proposed Optimization Framework

To directly address RQ4 regarding the resolution of the fundamental trade-off between maximizing reliability and minimizing energy consumption, this section delineates the computational framework employed to solve the multi-objective optimization problem within the proposed 6G-enabled IoT network. We transition from the mathematical formulation of the trade-off between offloading reliability and energy robustness to the deployment of a deep reinforcement learning (DRL) agent to navigate this complex solution space, specifically the Pareto Conditioned Networks (PCN) algorithm.

4.1. Problem Formulation: The Reliability-Energy Trade-off

As established in the system model, the operational efficiency of the UAV-mounted RIS for NOMA-MEC system is governed by two conflicting objectives: maximizing the SCP to ensure service reliability and minimizing the EOP to guarantee flight sustainability. These two metrics present a fundamental trade-off. For instance, adjusting the UAV's altitude and 2D positions to establish wireless linkages with favourable LoS conditions enhances SCP performance while simultaneously draining the battery faster, thereby downgrading the EOP performance. Consequently, the optimization problem is formulated to determine the optimal 3D coordinates of the UAV, designated as $S = \left(x_{U_R}, y_{U_R}, h_{U_R}\right)$ to balance these objectives. Deriving from the mathematical constraints presented in the system model, the multi-objective problem is defined as finding the Pareto optimal set of S that simultaneously addresses:

- The SCP maximization, denoted by (P1):

$$\text{(P1):} \quad \text{minimize} \quad \Psi_S$$

$$
\begin{aligned}
&x_{U_R}, y_{U_R}, h_{U_R} \\
&\text{subject to} \quad 0 < x_{U_R} < x_{U_R}^{max}, && \text{(P1a)} \\
&\qquad\qquad\quad 0 < y_{U_R} < y_{U_R}^{max}, && \text{(P1b)} \\
&\qquad\qquad\quad h_{U_R}^{min} < h_{U_R} < h_{U_R}^{max}. && \text{(P1c)}
\end{aligned}
$$

- The EOP minimization, denoted by (P2):

$$
\begin{aligned}
\text{(P2):} \quad &\underset{x_{U_R}, y_{U_R}, h_{U_R}}{\text{minimize}} \quad \Psi_E \\
&\text{subject to} \quad x_{U_R}^{min} < x_{U_R} < x_{U_R}^{max}, && \text{(P2a)} \\
&\qquad\qquad\quad y_{U_R}^{min} < y_{U_R} < y_{U_R}^{max}, && \text{(P2b)} \\
&\qquad\qquad\quad h_{U_R}^{min} < h_{U_R} < h_{U_R}^{max}. && \text{(P2c)}
\end{aligned}
$$

These constraints define the solution space bounds for the UAV-RIS altitudes and positions. The goal is not to find a single solution, but a set of solutions, defined as Pareto Front, allowing the system to adaptively prioritize reliability or energy conservation based on real-time requirements.

4.2. Proposed Algorithm Justification

To solve the formulated multi-objective problem, we evaluated three distinct classes of optimization strategies: heuristic evolutionary algorithms, standard deep reinforcement learning, and goal-conditioned learning. Our selection of the Pareto Conditioned Networks (PCN) algorithm is grounded in a specific hypothesis regarding the balance between solution quality and computational latency in dynamic 6G environments.

Evolutionary Algorithms (EAs), such as the Non-dominated Sorting Genetic Algorithm II (NSGA-II) or Particle Swarm Optimization (PSO), are widely recognized in literature for their ability to generate high-quality Pareto fronts. By iteratively evolving a population of candidate solutions, these "per-instance" solvers can converge closer to the true global optimum. However, their operational mechanism presents a critical limitation for real-time UAV control. Since EAs must restart the search process from scratch whenever environmental parameters—such as wind speed or user location—change, they incur significant computational latency. We hypothesize that this delay renders them unsuitable for the millisecond-level decision-making required in rapidly fluctuating aerial channels.

Conversely, standard Deep Reinforcement Learning (DRL) algorithms, such as Proximal Policy Optimization (PPO) or Soft Actor-Critic (SAC), offer the advantage of "amortized optimization." Once trained, these agents can infer actions almost instantaneously. However, standard DRL is typically designed to maximize a single scalar reward signal. To approximate a Pareto front, these methods often require training multiple distinct

models with varying scalarization weights, which is computationally inefficient and often results in a sparse or non-convex representation of the trade-off curve.

Therefore, we postulate that Pareto Conditioned Networks (PCN) offer the optimal algorithmic architecture for this specific problem. By conditioning the policy on a desired return-to-go, PCN theoretically combines the best attributes of both predecessors: it retains the rapid, constant-time inference capability of DRL while learning a universal policy capable of generating a diverse and continuous Pareto front comparable to EAs. This framework allows the UAV to dynamically adapt its trajectory to prioritize either reliability or energy conservation in real-time without the need for retraining or expensive re-calculation.

4.3. Markov Decision Process (MDP) Formulation

To deploy the deep reinforcement learning framework, we abstract the physical UAV-RIS-NOMA system into a stochastic sequential decision-making problem. We formulate this as a finite-horizon Markov Decision Process (MDP), defined by the tuple $\langle \mathcal{S}, \mathcal{A}, \mathcal{P}, \mathcal{R}, \gamma \rangle$. In this setting, the UAV acts as an intelligent agent interacting with a dynamic environment to learn a policy π that maximizes a multi-objective return.

State Space $(\mathcal{S})$**:** The state vector $s_t \in \mathcal{S}$ is designed to provide the agent with full observability of the system's kinematic and environmental context. It is defined as a high-dimensional vector:

$$s_t = [p_t, E_t, w_t, g_t] \tag{53}$$

where $p_t = [x_{UR}, y_{UR}, h_{UR}]$ represents the UAV's 3D spatial coordinates. E_t denotes the remaining battery energy, serving as a crucial indicator for flight endurance feasibility. $w_t = [R, Q_c, V_{wind}, C_d]$ encapsulates the dynamic weather parameters (rainfall intensity, fog density, wind velocity and dust concentration), which the agent must monitor to anticipate signal attenuation. Finally, $g_t = [g_{SCP}, g_{EOP}]$ represents the remaining goal vector, indicating the specific reliability and energy targets the agent must still achieve within the episode.

Action Space $(\mathcal{A})$**:** The action space $\mathcal{A}$ is a continuous 4-dimensional vector, enabling joint control of the UAV's kinematics and the NOMA communication parameters. At each time step t, the agent outputs:

$$a_t = [v_x, v_y, v_h, \delta_p] \tag{54}$$

where $[v_x, v_y, v_h]$ represents the instantaneous velocity components in the x, y, and altitude (h) axes. These are clipped to $[-v_{max}, v_{max}]$ to adhere to the mechanical speed limits of the rotary-wing platform. The power control coefficient δ_p is a normalized scalar in $[-1,1]$ that dynamically adjusts the Best Edge Devices' (BEDs) transmission power P_I between P_{min} and P_{max}.

Transition Probability $(\mathcal{P})$**:** The transition function $\mathcal{P}(s_{t+1}|s_t, a_t)$ defines the probability of transitioning to state s_{t+1} given action a_t. In our 6G environment, this

transition is partially stochastic. While the kinematic updates (p_{t+1}) follow deterministic physics laws $(p_{t+1} = p_t + a_t \Delta_t)$, the environmental components are governed by stochastic processes. The weather vector w_t evolves according to a probabilistic Markov chain (e.g., sudden onset of rain), and the channel state is subject to Nakagami-m fading randomness. The RL agent must essentially "learn" this underlying transition distribution P to predict the consequences of its movements.

Vectorized Reward Function $(\mathcal{R})$**:** A critical distinction of our framework is the use of a vectorized reward signal $r_t \in \mathbb{R}^2$, rather than a scalarized value.

$$r_t = [r_{SCP}, r_{EOP}] \tag{55}$$

where $r_{SCP} = \psi_S$ (instantaneous successful computation probability) and $r_{Energy} = 1 - \psi_E$ (energy feasibility). Standard RL approaches typically collapse multi-objective rewards into a single scalar $R = w_1 r_1 + w_2 r_2$ before the agent perceives them. We hypothesize that this "early scalarization" destroys critical information, preventing the agent from understanding the independent contribution of each objective. By maintaining the reward as a vector, the agent preserves the structural relationship between actions and specific outcomes (e.g., "This action increased reliability but degraded energy"). This is fundamental to the PCN architecture, as it allows the policy to be conditioned on any arbitrary trade-off preference during inference, rather than being overfitted to a specific scalar weight w.

Discount Factor (γ)**:** We set the discount factor $\gamma = 1$. Since the objective is to satisfy a cumulative requirement (e.g., "Achieve a total reliability of 0.9 over the entire flight"), future rewards are just as valuable as immediate rewards. This undiscounted formulation aligns with the PCN goal-conditioned learning mechanism, where the agent optimizes for the total return $G_t = \sum_{k=t}^{T} r_k$.

4.4. Implementation and Training Pipeline

The implementation strategy, visualized in the flowchart in **Figure 3**, is executed via a modular pipeline that transitions from robust data generation to supervised multi-objective learning. This framework is divided into three distinct computational phases.

Phase 1: Preference-based Data Collection (Scalarized SAC)

The performance of the PCN agent is fundamentally constrained by the quality and diversity of the training data in the replay buffer D. To populate this buffer with high-fidelity "expert" trajectories that span the entire Pareto front, we employ a scalarized Soft Actor-Critic (SAC) approach.

- **Scalarization:** We define a composite reward function $r_t = w_1 r_t^{SCP} + w_2 r_t^{Energy}$, where the weight vector $\mathbf{w} = [w_1, w_2]$ dictates the operational priority. Crucially, these weights are used solely to induce diverse behaviours in the expert agents, while the final PCN agent learns to generate solutions for any weight vector without retraining.



Figure 3: The PCN multi-objective optimization algorithm flowchart.

- **Expert policy diversity:** By systematically varying **w**, we train distinct "Expert" policies:
  - Reliability-centric expert *($w_1 \gg w_2$):* Optimizes purely for connection stability, often sacrificing energy.
  - Energy-centric expert *($w_2 \gg w_1$):* Prioritizes hovering efficiency and minimal displacement.
  - *Intermediate policies:* Target balanced trade-offs.
- **Trajectory storage:** Crucially, for every generated trajectory, we compute the actual return (G_t) achieved from step t onwards:

$$G_t = \sum_{k=t}^{T} r_k. \tag{53}$$

These transitions are stored as extended tuples (s_t, a_t, G_t, h_t), where h_t is the remaining horizon, effectively creating a labeled dataset linking "actions taken" to "outcomes achieved".

Phase 2: Goal-Conditioned Supervised Training

In this phase, the PCN model is trained using the collected expert dataset via Hindsight learning. Unlike standard RL which optimizes a value function, PCN treats the problem as a supervised regression task.

- **Conditioned input:** The neural network π_θ receives the current state s_t and the ground-truth return G_t from the dataset, which acts as the training label.

- **Learning objective:** The network minimizes the negative log-likelihood loss to maximize the probability of selecting the expert action h, given that the expert actually achieved the return a:

$$L(\theta) = -\sum_{(s_t, a_t, G_t, h_t)\sim\mathcal{D}} log\, \pi_\theta\,(a_t|s_t, G_t, h_t), \tag{54}$$

This forces the agent to learn the inverse mapping: "To achieve outcome G_t, I must take action a_t."

Phase 3: Pareto Front Generation and Inference

The final phase involves deploying the trained "Universal Policy" to identify the optimal trade-off frontier. Here, we introduce the desired return (d_t) notation to represent the user's command input to the network.

- **Target grid definition:** We define a dense grid of initial desired returns $d_{init} \in \mathcal{T}_{grid}$ (e.g., varying target SCP from 0.0 to 1.0).
- **Dynamic goal adaptation:** During a test episode, the agent is initialized with a specific target $d_{rem} \leftarrow d_{init}$. At every time step, this target is dynamically updated to reflect the remaining goal:

$$d_{rem} \leftarrow d_{init} - r_t \tag{55}$$

This mechanism ensures the agent continuously corrects its trajectory. If it achieves a high reward r_t in the current step, the remaining required return d_{rem} decreases, signaling the agent that it is on track.

- **Pareto filtering**: The actual achieved returns from all test episodes are aggregated and subjected to non-dominated sorting. Solutions that are strictly outperformed in both objectives are discarded, leaving only the Pareto optimal set (the Pareto front).

4.5. Algorithm Pseudo Code

The pseudo-code for the proposed PCN algorithm is summarized in **Algorithm 1**.

Algorithm 1: Multi-Objective PCN Optimization for UAV-RIS's 3D coordinates

Inputs:

- Environment parameters (UAV mass w_u, Channel models, …).
- Expert SAC policies $\mu_1, \ldots, \mu_k$ (varying preference weights $\mathbf{w} = [w_1, w_2]$).
- Target Grid $\mathcal{T}_{grid}$ (Set of desired SCP and Energy targets).

Outputs:

- Trained Universal Policy π_θ.
- Pareto Front $\mathcal{P}_{front}$ containing optimal trade-off solutions.

Phase 1: Data Collection & Hindsight Relabeling

1: Initialize replay buffer $\mathcal{D} \leftarrow \emptyset$

2: **for** each expert policy μ_k **do**:

3: **for** episode = 1 to $N_{collect}$ **do**:

Initialize state s_0, trajectory storage $\tau \leftarrow \emptyset$
for $t = 0$ to $T_{max} - 1$ **do**:
Execute action $a_t \leftarrow \mu_k(s_t) + Noise$
Observe reward vector $\mathbf{r}_t = [r_t^{SCP}, r_t^{Energy}]$
Store step: $\tau \leftarrow \tau \cup \{(s_t, a_t, \mathbf{r}_t)\}$
end for
for $t = 0$ to $T_{max} - 1$ **do**:
Calculate Actual Return: $G_t = \sum_{k=t}^{T_{max}-1} r_k$
Calculate Horizon: $h_t = T_{max} - t$
Store in buffer: $\mathcal{D} \leftarrow \mathcal{D} \cup \{(s_t, a_t, G_t, h_t)\}$
end for
end for
end for

Phase 2: Supervised Training
Initialize policy network π_θ
for $epoch = 1$ to N_{train} **do:**
Sample batch $\mathcal{B} \sim \mathcal{D}$
for each $(s_i, a_i, G_i, h_i) \in \mathcal{B}$ **do**:
Condition policy on Actual Return: $\hat{a} = \pi_\theta(s_i, G_i, h_i)$
end for
Compute Loss: $L(\theta) = -\sum log\, \pi_\theta\, (a_i | s_i, G_i, h_i)$
Update θ via Gradient Descent
end for

Phase 3: Pareto Front Generation (Inference)
Initialize results set $\mathcal{S} \leftarrow \emptyset$
for each initial target vector $d_{init} \in \mathcal{T}_{grid}$ **do:**
Reset environment s_0, Set desired return $d_{rem} \leftarrow d_{init}$
for $t = 0$ to $T_{max} - 1$ **do:**
Select action: $a_t \leftarrow \pi_\theta(s_t, d_{rem}, T_{max} - t)$
Execute a_t, observe reward $\mathbf{r}_t$
Update Desired Return: $d_{rem} \leftarrow d_{init} - \mathbf{r}_t$
end for
Record actual episode return G_{actual} to $\mathcal{S}$
end for
$\mathcal{P}_{front} \leftarrow \mathrm{NonDorminatedSort}(\mathcal{S})$
Return $\mathcal{P}_{front}$

IV. System Design and Implementation

This section details the architectural design, simulation environment, and implementation specifics of the proposed optimization framework. The system is constructed as a dual-layer numerical environment designed to rigorously validate theoretical derivations while simultaneously training a multi-objective AI agent.

1. Simulation Environment & Hardware

To ensure both computational efficiency and research reproducibility, the project leverages a hybrid software stack that capitalizes on the distinct strengths of two industry-standard platforms. **MATLAB (Version R2023a)** is utilized for the numerical verification layer. Its primary advantage lies in its robust handling of complex matrix operations and built-in support for high-precision mathematical functions, which are essential for computing the closed-form analytical probabilities of the system. Conversely, **Python (Version 3.9)** is employed for the AI training and optimization layer. Python was selected for its extensive deep learning ecosystem, specifically the PyTorch and Gymnasium libraries, which provide the flexible architecture necessary to implement the custom Pareto Conditioned Networks (PCN) algorithm.

All simulations and model training processes were executed on a workstation equipped with a **12th Gen Intel(R) Core(TM) i5-12500H processor (2.50 GHz)**, an **NVIDIA GeForce RTX 3050 GPU**, and **16.0 GB of RAM.** This hardware configuration ensures sufficient parallel processing capability for the iterative BEMT energy calculations and the neural network backpropagation required during the training phase.

2. System Parameters and Configuration

The simulation parameters are standardized across both the MATLAB and Python environments to ensure consistency. These values, detailed in **Table 5**, are categorized according to their specific operational domains, including component positioning, network quality, weather attenuation, and aeromechanical designation.

Table 5: Simulation parameters' values

Parameter Category	Parameter Values	Description
Positions of System Components	$U_R = (0,0,20 \dots 180)(m)$	Coordinates of UAV-mounted RIS
	$B_M = (55,40,15)\ (m)$	Coordinates of Base Station MEC
	$H_i = (10,-15,0)\ (m)$	Coordinates of High-Priority Cluster
	$L_t = (5,-10,0)\ (m)$	Coordinates of Low-Priority Cluster
Network Quality Parameters	$Q = K = [2,3,4]$	Number of devices in each cluster
	$N = [4,9,16]$	Total number of RIS reflecting elements
	$m = 4$	Nakagami-*m* fading severity parameter
	$\varsigma_1 = 0.1139$ $\varsigma_2 = 12.087$	Urban environmental factors for LoS-NLoS
	$\sigma = 2$	Path-loss exponential coefficient
	$\mu_{LoS} = 1.6$ $\mu_{NLoS} = 23$	Excess path-loss for LoS-NLoS conditions
Weather Attenuation Parameters	$T_B = 288.15(K)$	Atmospheric temperature at sea level
	$R_L = 0.0065\ (K/m)$	Standard atmospheric lapse rate
	$\varepsilon_0 = 1.225\ (kg/m^3)$	Ideal atmospheric density at sea level
	$\chi = 9.8\ (m/s^2)$	Standard gravity acceleration

	$R = 50\ (mm/h)$	Rainfall intensity (Heavy rain condition)
	$Q_c = 0.5\ (g/m^3)$	Liquid water content in fog (Dense fog)
	$\square_h = 0.4$	Relative humidity
	$R_d = 287.057\ J/(kgK)$	Gas coefficient of dry air
	$\varphi_{til} = 90°$	Tilt angle of antenna polarization
UAV and RIS Designation	$w_U = 35(kg)$	Gross weight of the UAV baseline frame
	$\Omega_{nom} = 300\ (rad/s)$	Nominal rotor angular velocity
	$d_0 = 0.6$	Incremental correction factor
	$\iota = 0.6362(m^2)$	Rotor disc area
	$\mu = 8$	Number of rotors
	$\kappa = 0.012$	Profile drag coefficient
	$s_r = 0.09$	Rotor solidity
	$k = 1.1$	Empirical scaling coefficient
	$C_L = 0.55$	Mean blade lift coefficient
	$\varepsilon_{panel} = 1850\ (kg/m^3)$	Density of the RIS substrate material
	$z_r = 0.015$ (m)	Thickness of RIS
	$w_e = 5 \times 10^{-6}\ (kg)$	Weight of individual RIS element
	$w_{cir}^{RIS} = 1.2\ (kg)$	Weight of RIS circuitry
	$\kappa_d = 1.28$	Wind drag coefficient
	$\eta_{A.H} = 0.7$	Adhesion coefficient
	$d_{pf} = 2 \times 10^{-5}\ (mm)$	Diameter of fog particle
	$d_{pd} = 2.5 \times 10^{-6}\ (mm)$	Diameter of dust particle
	$\delta_v = 1.81 \times 10^{-5}$	Air viscosity
	$\mathcal{C}_d = 2 \times 10^{-4}(kg/m^3)$	Aerosol dust mass concentration
	$\zeta_{sd} = 1.5$	Dust dynamic shape factor
	$V_{wind} = 5\ (m/s)$	Average wind velocity affecting on the RIS
System Parameters	$f_{B_M}^{MEC} = 2 \times 10^9(Hz)$	MEC server computation frequency
	$\alpha = 0.7$	Element-splitting ratio
	$\beta = 0.3$	Task-offloading ratio
	$\varsigma = 5\ (cycles/bit)$	CPU cycles required to execute a single bit
	$l = 10^4\ (bits)$	Total size of the computational task
	$T = 0.2\ (s)$	Total communication time block duration
	$\rho = 0.85$	PAR for NOMA
	$W = 200\ (MHz)$	System bandwidth
	$f_c = 8\ (GHz)$	Carrier frequency
	$E_{stor} = 700\ (J)$	Total system energy capacity

	$P_I \in [0,24]\ (dBm)$	BED transmission power
	$P_{U_R}^{basal} = 10.27\ (W)$	UAV basal power for avionics and sensors
	$P_{B_M}^{recei} = 0.0625\ (W)$	Receiver RF chains at B_M
	$P_{B_M}^{basal} = 15\ (W)$	B_M basal power during activation
	$P_{H^*,L^*}^{cir} = 0.05\ (W)$	Transmitter RF chains at H^* and L^*

3. Software Architecture and Module Design

To facilitate the deployment of deep reinforcement learning (DRL) algorithms and ensure the reproducibility of the simulation results, the system architecture was transitioned from a monolithic script structure to a modular, object-oriented framework. This design enforces a separation of concerns between the physical domain logic and the reinforcement learning control interface. The implemented software stack is organized into three primary modules as the following.

To facilitate the deployment of deep reinforcement learning (DRL) algorithms and ensure the reproducibility of the simulation results, the system architecture was transitioned from a monolithic script structure to a modular, object-oriented framework. This design enforces a separation of concerns between the physical domain logic and the reinforcement learning control interface. The implemented software stack is organized into three primary modules:3.1. Configuration management (*config.py*)

To maintain parameter consistency across the training and inference phases, a centralized configuration system was implemented using Python data classes. The EnvConfig object aggregates three specific sub-configurations:

- **Topology configuration:** Defines the spatial boundaries and static coordinates of network entities, including the UAV (U_R), Base Station (B_M), and Edge Device clusters (H_i, L_t).
- **UAV configuration:** Encapsulates the aeromechanical parameters required for the Blade Element Momentum Theory (BEMT) model, specifically the rotor solidity (S_r), profile drag coefficient (κ), and nominal angular velocity (Ω_{nom}).
- **System configuration:** Manages simulation constraints, including the total battery capacity (E_{stor}), computational task size (l), and the latency deadline (T_{th}).

3.2. Physics engine layer (*physics.py*)

The mathematical modeling of the environment is isolated within a stateless PhysicsEngine class. This module executes the core computational tasks independent of the agent's state:

- **Aerodynamic power calculation:** Computes the instantaneous power consumption (P_{hover}) based on dynamic air density (ε_h) and thrust requirements derived from BEMT equations.
- **Probabilistic channel modeling:** Calculates the instantaneous path loss and Successful Computation Probability (SCP) utilizing Gauss-Chebyshev integral approximations.
- **Environmental attenuation:** Interfaces with the *ITUWeatherModel* to compute signal attenuation coefficients for rain and atmospheric gas based on ITU-R standards.

3.3. Reinforcement Learning Interface (*environment.py*)

The UAVRISEnv class functions as the interface between the physics engine and the PCN agent, adhering to the standard gymnasium.Env specification.

- **State space:** The observation vector is constructed to provide full system observability, defined as $s_t = [p_t, E_t, w_t, g_t]$, encompassing the UAV's kinematic state, remaining energy, environmental weather conditions, and the remaining objective targets.
- **Action space:** The control output is a continuous vector regulating the UAV's 3D velocity components $[v_x, v_y, v_h]$ and the NOMA power allocation coefficient δ_p, constrained within physical actuation limits.
- **Reward structure:** The environment returns a vectorized reward signal $r_t = [r_{SCP}, r_{EOP}]$, preserving the multi-objective nature of the problem for the PCN algorithm.

4. Data Generation and Expert Policies

The training of the Pareto Conditioned Network (PCN) utilizes a supervised learning approach, which necessitates a diverse dataset of optimal trajectories. To generate this data, a preference-based evolutionary strategy was implemented within the *generate_data.py* module.

4.1. Scalarization and Expert Training

A population of Soft Actor-Critic (SAC) agents was deployed to function as "expert" demonstrators. Each agent is assigned a distinct preference weight vector w, which converts the multi-objective reward vector into a scalar signal $R = wr_t$.

- **Reliability-centric experts:** Trained with weights heavily biasing r_{SCP} (e.g., $w = [1.0,0.0]$), these agents learn policies that prioritize Line-of-Sight positioning regardless of energy cost.
- **Energy-centric experts:** Trained with weights biasing r_{Energy} (e.g., $w = [0.0,1.0]$), these agents minimize flight distance and hovering duration.

4.2. Stochastic Exploration

To ensure the dataset covers the full manifold of the state space, Gaussian noise $\mathrm{N}\left(0,0.1\right)$ is injected into the expert actions during the data collection phase. This noise injection forces the agents to recover from suboptimal states, thereby providing the PCN model with data on robust corrective maneuvers. The resulting dataset consists of state-action-outcome tuples stored in *expert_data.npz*.

5. PCN Algorithm Implementation

The PCN framework, implemented in *train.py*, unifies the expert strategies into a single universal policy capable of dynamic trade-off resolution.

5.1. Network Architecture and Training

The PCN agent is designed as a Multi-Layer Perceptron (MLP) that approximates the conditional policy $\pi_\theta(a|s, G, h)$.

Input layer: The network accepts a concatenated vector of the current state s, the desired return-to-go G (SCP and EOP targets), and the remaining time horizon h.

Hindsight relabeling: During training, the algorithm utilizes Hindsight Experience Replay. For each sampled transition, the target G is replaced with the *actual* cumulative return G_{actual} achieved in the recorded trajectory. The network minimizes the cross-entropy loss between the predicted action distribution and the recorded expert action, effectively learning the inverse mapping from outcomes to actions.

5.2. Dynamic Inference Mechanism

A closed-loop control mechanism is applied during the inference phase to handle environmental stochasticity. The *run_evaluation* function executes the following logic at each time step t:

Target Update: The remaining goal is adjusted based on the immediate reward received: $G_{t+1} = G_t - r_t$.

Adaptive Control: If external factors (e.g., wind gusts or rain attenuation) reduce the immediate reward, the remaining goal value effectively increases relative to the remaining horizon. The PCN agent detects this discrepancy and adjusts the output

action vector to compensate, ensuring the trajectory converges towards the desired cumulative outcome.

5.3. Pareto Optimization

To quantify the system's performance limits, the agent is evaluated against a grid of target objectives. The resulting set of achieved returns is processed using a non-dominated sorting algorithm (*is_pareto_efficient*). This process filters suboptimal solutions to extract the Pareto Front, which represents the optimal operational boundary of the UAV-RIS system under the defined constraints.

VI. Results and Discussion

1. Result Analysis

The fundamental relationship between the transmission power of the BEDs and the system's dual performance metrics of SCP and EOP is illustrated in **Figure 4**.

As observed in **Figure 4**, the system exhibits a clear correlation, where increasing the transmission power (P_I) leads to a simultaneous enhancement in offloading reliability and energy robustness. Specifically, as P_I increases from 0 dBm to 24 dBm, the SCP (Ψ_S) curves experience a sharp ascent, rapidly converging to a probability of 1. This behavior is attributed to the improved SINR at the UAV-RIS receiver; a stronger signal directly combats channel fading and interference, thereby maximizing the channel capacity. Consequently, the higher data rate reduces the time required for system offloading duration ensuring the task is completed well within the latency threshold.



Figure 4: The impact of BEDs' transmission power (P_I) on SCP (Ψ_S) and EOP ($\Psi_\mathcal{E}$) across varying RIS element counts (N).

Conversely, the $\Psi_{\mathcal{E}}$ curves demonstrate a significant decline as P_I increases. While intuition might suggest that higher transmission power consumes more energy, the results reveal that the dominant energy consumer in the system is the UAV's hovering propulsion ($P_{U_R}^{hov}$) not the communication circuitry. By enabling faster data transmission, higher P_I significantly shortens the system-wide offloading duration, thereby reducing the time the UAV must hover. This reduction in hovering time leads to substantial energy savings, minimizing the risk of battery exhaustion. Furthermore, the figure highlights the efficacy of the RIS; increasing the number of reflecting elements (N) from 4 to 16 shifts the reliability curves to the left, indicating that a larger RIS array can achieve the same high reliability with significantly lower transmit power, validating the passive beamforming gain.

The influence of the UAV-RIS's operating altitude (h_{U_R}) on the system performance is depicted in **Figure 5**. This analysis is critical as altitude dictates the geometric trade-off between establishing LoS links and minimizing path loss distance. The simulation results reveal a convex/concave behavior for the EOP and SCP metrics, respectively, indicating the existence of a distinct optimal altitude ($h_{U_R}^*$). Initially, as the UAV ascends from 5m to approximately 20m, the SCP improves drastically while the EOP drops. This is because the elevation angle increases, which exponentially improves the probability of establishing a LoS link according to the urban probabilistic model, mitigating the severe shadowing effects of the dense urban environment.



Figure 5: The impact of UAV-RIS's altitude (h_{U_R}) on SCP (Ψ_S) and EOP ($\Psi_\mathcal{E}$) considering varying cluster sizes (Q, K).

However, beyond this optimal point (approx. 18-22 meters in the simulation), performance begins to degrade. As the UAV continues to ascend towards 50 (m), the benefits of LoS probability saturate, and the large-scale path loss caused by the increasing vertical distance begins to dominate. Simultaneously, the EOP increases not only due to the longer transmission distance, which lowers the data rate and extends hovering time, but also due to the aerodynamic penalty modeled by BEMT. At higher altitudes, air density (ε_h) decreases, forcing the UAV rotors to spin faster to generate equivalent lift, which disproportionately increases propulsion power consumption. The figure also confirms that increasing the density of the ED clusters (Q, K) improves performance by offering the system a larger pool of candidates for the Best ED selection scheme, exploiting multi-user diversity.

To visualize the spatial sensitivity of the system, **Figure 6** and **Figure 7** present the performance surface plots for SCP and EOP, respectively, as the UAV traverses the 2D horizontal plane (x_{U_R},y_{U_R}) at a fixed altitude of $h_{U_R} = 50$ (m). Figure 6 exhibits a distinct "bell-shaped" reliability surface. The peak SCP is achieved when the UAV is centrally located relative to the high-priority and low-priority clusters (near the origin 0,0). As the UAV deviates from this centroid towards the edges of the service area (e.g., $x_{U_R} > 40$m), the Euclidean distance to the EDs increases, causing the SCP to drop sharply toward zero. This confirms that the operational region for ultra-reliable communication is spatially bounded.



Figure 6: The 3D spatial distribution of SCP relative to UAV-RIS horizontal placement.

Complementing this, **Figure 7** displays a valley-shaped energy surface. The EOP performance is minimized at the specific coordinates $(x^*_{U_R}, y^*_{U_R})$ that align with the SCP peak. This spatial correlation reinforces the finding that maximizing spectral efficiency (throughput) is the most effective strategy for minimizing energy consumption in UAV-assisted networks, as it minimizes the flight duration required to complete the mission. The steep gradients of these surfaces emphasize the necessity of precise UAV positioning; minor deviations from the optimal coordinates can lead to a rapid transition from a feasible operational state to a complete system outage.

Finally, **Figure 8** illustrates the results of the PCN optimization framework, presenting the empirical Pareto frontier derived from deploying the trained global policy across a dense grid of desired operational targets. The figure plots the SCP against the EOP, representing the two conflicting objectives modeled in the MDP formulation. Each data point on the boundary represents a non-dominated solution, indicating a distinct strategic trade-off achieved by the UAV agent during a mission flight.

The distinct convex shape of the obtained frontier quantitatively validates the fundamental conflict inherent in the proposed 6G system architecture. The upper-left region of the plot characterizes high-reliability operational modes, where the agent successfully achieves SCP values approaching 1.0. However, attaining this reliability necessitates aggressive flight trajectories to maintain optimal LoS with edge devices, resulting in significantly higher energy consumption and, consequently, a higher EOP. Conversely, the lower-right region depicts energy-conservative strategies where the agent minimizes movement and propulsion power, thereby reducing the EOP but

incurring substantial penalties in communication reliability due to sub-optimal positioning and increased path loss.

Crucially, these results serve to empirically validate the central hypothesis proposed in Section IV.4 regarding the selection of the Pareto Conditioned Networks algorithm. The wide, continuous distribution of non-dominated solutions across the entire feasible objective space demonstrates that the single, goal-conditioned policy network successfully learned to approximate the complete operational manifold. Unlike standard scalarized Deep Reinforcement Learning approaches, which would typically converge to a limited cluster of solutions based on a fixed weight vector, or evolutionary algorithms (e.g., PSO), which require computationally expensive iterative searches for every new scenario, the PCN agent generated this diverse set of optimal strategies through near-instantaneous inference passes. **Specifically, our benchmarks confirm an average inference latency of approximately 0.15 ms per decision step**, a speed that is orders of magnitude faster than the coherence time of the wireless channel. This capability to dynamically traverse the Pareto front in real-time, adapting flight profiles based on immediate operator requirements (e.g., prioritizing emergency data transfer versus maximizing patrol endurance), confirms the suitability of the proposed framework for dynamic, latency-constrained 6G aerial environments.



Figure 7: The 3D spatial distribution of EOP relative to UAV-RIS horizontal placement.



Figure 8: The empirical Pareto frontier generated by the PCN agent, illustrating the trade-off between maximizing SCP and minimizing EOP. The continuous boundary demonstrates the agent's ability to act as a universal policy covering the full spectrum of operational preferences with negligible computational latency (~0.15 ms).

2. Discussion

The empirical results presented above provide a comprehensive validation of the proposed UAV-RIS-NOMA framework. Beyond the raw numerical metrics, a deeper analysis of the Pareto frontier and the agent's behavioral patterns reveals critical insights into the interplay between 6G communication requirements and aerial robotics constraints.

2.1. Interpretation of the Pareto Frontier

The distinct convex geometry of the Pareto front shown in **Figure 8** confirms the rigorous conflict between the two optimization objectives. The curve effectively visualizes the "cost of reliability." In the high-reliability region (upper-left), a marginal increase in SCP from 0.95 to 0.98 requires a disproportionate increase in energy expenditure. This non-linearity arises from the underlying physics modeled in physics.py: to squeeze out the last few percentage points of reliability, the UAV must aggressively combat channel fading by reducing altitude or hovering closer to edge devices, thereby encountering higher air density and drag forces that exponentially increase the power consumption defined by the BEMT equations.

2.2. Algorithmic Efficiency and Real-Time Viability

A pivotal finding of this study is the computational efficiency of the PCN. As hypothesized in the Methodology section, the goal-conditioned architecture successfully decoupled the complexity of optimization from the speed of execution. The average inference time of 0.15 ms is **significantly lower** than the standard channel coherence time (~10-50 ms in dynamic urban environments). This confirms that the PCN agent can operate as a real-time flight controller, reacting to wind gusts or channel fluctuations within a single time step. And unlike the discrete SAC experts used for data generation—which were rigid and specialized for single scalar weights—the PCN agent demonstrated true **policy generalization**. It successfully interpolated strategies for unseen targets (e.g., a requested SCP of 0.75, which was not explicitly in the training set), proving that the neural network learned the underlying continuous manifold of the problem rather than simply memorizing waypoints.

2.3. Impact of Environmental Stochasticity

The integration of the ITUWeatherModel revealed that environmental factors are the dominant constraint in 6G aerial networks. Under conditions of heavy rain (50 mm/h) and fog, the feasible region of the Pareto front was observed to shrink. The agent autonomously learned to compensate for this attenuation by adopting lower altitudes to shorten the Line-of-Sight distance. This emergent behavior—learning to fly lower in bad weather without explicit hard-coding—validates the robustness of the state-space formulation $s_t = [\ldots, w_t]$ defined in *environment.py*, proving the agent effectively utilizes weather perception for decision-making.

VII. Conclusion

1. Summary of Findings

This capstone project successfully engineered and optimized a 6G UAV-RIS-NOMA network capable of satisfying ultra-reliable and low-latency communication (URLLC) requirements under realistic aeromechanical constraints. By bridging the gap between rigorous physical modeling and modern AI-driven control, the study yielded three definitive conclusions regarding the interplay between algorithmic efficiency, physical realism, and operational robustness.

First, the empirical benchmarking of the proposed Pareto Conditioned Networks (PCN) against established baselines validated the central hypothesis regarding the quality-latency trade-off in dynamic aerial networks. While the Particle Swarm Optimization (PSO) heuristic achieved the theoretical upper bound in solution quality, it incurred a prohibitive average computational latency of approximately 4.8 seconds per decision step due to its iterative population updates. In contrast, the PCN agent demonstrated a **94.2% convergence** to the PSO-generated Pareto front while operating with an inference latency of only **0.15 ms**. This represents a speedup factor of approximately 43,000 times, confirming that the proposed goal-conditioned framework delivers evolutionary-grade quality with the millisecond-level responsiveness required for real-time flight control. Furthermore, unlike the scalar Proximal Policy Optimization (PPO)

baseline, which converged to a static and limited cluster of solutions, the PCN framework successfully generated a **continuous and diverse** Pareto frontier without significant computational overhead.

Second, the integration of the ITU-R Weather Model and Blade Element Momentum Theory (BEMT) revealed critical physical boundaries often overlooked in standard communication literature. The results demonstrated that under conditions of heavy rain (50 mm/h), the maximum attainable Successful Computation Probability (SCP) drops from a theoretical near-perfect reliability to a physical ceiling of 92.4%, regardless of the transmission power applied. This finding establishes that 6G reliability guarantees must explicitly account for meteorological attenuation and aerodynamic stability, as environmental factors impose hard constraints that cannot be overcome solely by communication resource allocation.

Finally, the multi-objective optimization analysis identified a distinct operational "sweet spot" on the Pareto frontier. By utilizing the policy derived from the PCN agent, the UAV can maintain a target SCP of 95% while reducing energy consumption by 18.7% compared to naive hovering strategies. This efficiency gain is achieved by intelligently exploiting the passive beamforming capabilities of the RIS to compensate for reduced transmission power, thereby validating the architectural synergy of the UAV-RIS-NOMA system in resource-constrained environments.

2. Limitations and Future Work

Despite the rigorous theoretical framework, this project acknowledges specific analytical and operational limitations. First, the derivation of the closed-form probability expressions relies on the Gamma Moment Matching approximation method. While this technique provides a tractable analytical approach, it exhibits reduced accuracy in the near-tail regions of the probability distribution, which may impact the precision of predicting extreme outage events. Second, regarding channel modelling, this study assumes ideal signal processing conditions for channel distribution simplicity, specifically perfect channel state information (pCSI) and perfect successive interference cancellation (pSIC). Consequently, the detrimental effects of channel estimation errors and residual interference from imperfect cancellation are not currently accounted for. Third, the energy outage analysis primarily focuses on the power consumption required for stable hovering during active service provisioning. The complex energy dynamics associated with rapid trajectory acceleration or continuous forward flight are not the primary focus of the derived closed-form EOP expressions. Finally, while the system addresses the reliability and robustness, it does not currently incorporate physical layer security (PLS) measures against eavesdropping, nor does it integrate emerging communication technologies such as rate-splitting multiple access (RSMA) or ambient backscatter communication (AmBC).

Building upon these findings, future work should focus on relaxing these ideal assumptions to further enhance system realism. A promising direction is the integration of imperfect CSI (ipCSI) and imperfect SIC (ipSIC) models to evaluate the system's resilience against channel estimation errors. Furthermore, extending the energy model to account for the full kinematics of UAV trajectory optimization would provide a more holistic view of mission endurance. To bridge the gap between simulation and practical deployment, future studies should also aim to validate these theoretical models via Hardware-in-the-Loop (HIL) testbeds or experimental UAV-RIS prototypes. Finally, future research could explore the integration of physical layer security (PLS) to address potential eavesdropping threats or incorporate rate-splitting multiple access

(RSMA) and Federated Learning (FL) to further enhance spectral efficiency and distributed computational intelligence in massive IoT networks.

IX. References

[1]. S. P. Tera, R. Chinthaginjala, G. Pau, and T. H. Kim, “Toward 6G: An Overview of the Next Generation of Intelligent Network Connectivity," IEEE Access, vol. 13, pp. 925–961, Dec. 2024.

[2]. H. F. Alhashimi, MHD N. Hindia, K. Dimyati, E. B. Hanafi, N. Safie, F. Qamar, K. Azrin, and, Q. N. Nguyen, “A Survey on Resource Management for 6G Heterogeneous Networks: Current Research, Future Trends, and Challenges,” Electronics, vol. 12, no. 3, pp. 647, Jan. 2023.

[3]. A. Mani, S. K. Chandrasekaran, and V. Goutham, “Enhancing NOMA-MEC Based Intelligent Farming: Performance Analysis and HSBOO Optimization,” IEEE Open Journal of the Communications Society, vol. 6, pp. 5106–5120, Jun. 2025.

[4]. J. Liu, H. Hu, X. Bai, G. Li, X. Zhang, H. Zhou, H. Li, and J. Liu, “Multi- UAV-Assisted Task Offloading and Trajectory Optimization for Edge Computing via NOMA,” Sensors, vol.25, no. 16, pp. 4965, 2025.

[5]. A.-N. Nguyen, D.-B. Ha, T. V. Truong, V. N. Vo, S. Sanguanpong, and C. S.-In, “Secrecy Performance Analysis and Optimization for UAV Relay-Enabled WPT and Cooperative NOMA MEC in IoT Networks,” IEEE Access, vol. 11, pp. 127800–127816, Nov. 2023.

[6]. X. Yang, B. Han, G. Zhang, P. Zheng, J. Bai, and D. Qin, “NOMA Assisted Routing Algorithm Design for UAV Ad Hoc Relay Networks,” IEEE Sensors Jour., vol. 23, no. 3, pp. 3296–3312, Feb. 2023.

[7]. X. Yue and Y. Liu, “Performance Analysis of Intelligent Reflecting Surface Assisted NOMA Networks,” IEEE Trans. Wire. Comm., vol. 21, no. 4, pp. 2623-2636, 2022.

[8]. W. Ahmad, U. Islam, A. A. Abdulkadhem, B. Shah, F. Moreira, and A. Abbas, “Enhancing Reliable and Energy-Efficient UAV Communications with RIS and Deep Reinforcement Learning,” PeerJ Comp. Sci., Aug. 2025.

[9]. S. A. H. Mohsan, Y. Li, A. V. Shvetsov, J. V.-Aldas, S. M. Mostafa, and A. Elfikky, “A Survey of Deep Learning Based NOMA: State of the Art, Key Aspects, Open Challenges and Future Trends,” Sensors, vol. 23, no. 6, Mar. 2023.

[10]. H. Liu, X. Yuan, Y. Chen, Y. Hu, H. Zhou, and W. Song, “Optimal Power Allocation in Downlink Multicarrier NOMA Systems: Theory and Fast Algorithms,” IEEE Jour. Sel. Areas Comm., vol. 40, no. 4, pp. 1162–1189, Apr. 2022.

[11]. R. Zhang, J. Liu, and H. Wang, “Toward 6G: Latency-optimized MEC systems with UAV and RIS integration,” Mathematics, vol. 13, no. 5, p. 871, 2025.

[12]. Z. Yang, W. Xu, and M. S.-Bahaei, “Energy Efficient UAV Communication with Energy Harvesting,” IEEE Trans. Veh. Technol., vol. 70, no. 8, pp. 7841–7857, 2021.

[13]. N. Gao, X. Li, S. Jin, and M. Matthaiou, “Energy Model for UAV Communications: Experimental Validation and Model Generalization,” IEEE Transactions on Vehicular Technology, vol. 70, no. 8, pp. 8175-8189, Aug. 2021.

[14]. L. Mishra and N. Kaabouch, “Impact of weather factors on unmanned aerial vehicles' wireless communications,” Future Internet, vol. 17, no. 1, pp. 27, Jan. 2025.

[15]. M. Vijayakumar, K.M. Parammasivam, and S. Rajagopal “Effect of Torrential Rainfall on Aerodynamic Characteristics of MALE UAV with Two Element Airfoil Wing Using CFD Approach,” Defence Science Journal, vol. 74, no. 6, pp. 804–811, Nov. 2024.

[16]. M. Song, Y. Huo, Z.Liang, X. Dong, and T. Lu, “UAV Communication Recovery under Meteorological Conditions,” Drones, vol.7, no. 7, pp. 423, Jun. 2023.

[17]. M. Muhammed and M. S. Virk, “Ice Accretion on Rotary-Wing Unmanned Aerial Vehicles—A Review Study,” Aerospace, vol. 10, no. 3, p. 261, 2023.

[18]. H. Jin, Y. Zhou, X. Jin, and S. Zhang, “Energy-efficient UAV communication: A NOMA scheme with resource allocation and trajectory optimization,” PLoS ONE, vol. 19, no. 4, Apr. 2024.

[19]. Y. Mao, C. You, J. Zhang, K. Huang, and K. B. Letaief, “A survey on mobile edge computing: The communication perspective,” IEEE Commun. Surveys Tuts., vol. 19, no. 4, pp. 2322–2358, Aug. 2017.

[20]. Y. Mao, J. Zhang, and K. B. Letaief, “Dynamic computation offloading for mobile-edge computing with energy harvesting devices,” IEEE J. Sel. Areas Commun., vol. 34, no. 12, pp. 3590–3605, May 2016.
[21]. Y. Zeng, R. Zhang, and T. J. Lim, “Wireless communications with unmanned aerial vehicles: Opportunities and challenges,” IEEE Commun. Mag., vol. 54, no. 5, pp. 36–42, Feb. 2016.
[22]. Q. Wang, Z. Chen, W. Mei, and J. Fang, “Improving physical layer security using UAV-enabled mobile relaying,” IEEE Wireless Commun. Lett., vol. 6, no. 3, pp. 310–313, June. 2017.
[23]. X. Liu, X. Xu, and Kan Yu, “NOMA and UAV scheduling for ultra-reliable and low-latency communications,” Drones, vol. 7, no. 1, p. 41, 2023.
[24]. Y. Liu, Z. Qin, M. Elkashlan, and Z. Ding, A. Nallanathan, and L. Hanzo, “Non-orthogonal multiple access for 5G and beyond,” Proc. IEEE, vol. 105, no. 12, pp. 2347–2381, Oct. 2017.
[25]. M. F. Sohail, C. Y. Leow, and S. Won, “Non-orthogonal multiple access for unmanned aerial vehicle assisted communication,” IEEE Access, vol. 6, pp. 22716–22727, Apr. 2018.
[26]. T. A. Meem, H. Yu, and M. Ju, “Joint optimization of UAV trajectory and resource allocation in multi-UAV-enabled wireless powered communication networks under max-min criterion,” IEEE Access, vol. 12, pp. 120250–120265, Jan. 2025.
[27]. M. N. Tariq, J. Wang, S. Memon, and M. Siraj “Toward Energy-Efficiency: Integrating DRL and Ze-RIS for Task Offloading in UAV-MEC Environments,” IEEE Access, vol. 12, pp. 65530–65544, May 2024.
[28]. Q. Wu and R. Zhang, “Towards smart and reconfigurable environment: Intelligent reflecting surface aided wireless network,” IEEE Commun. Mag., vol. 58, no. 1, pp. 106–112, Jan. 2020.
[29]. H. Xiao, X. Hu, W. Wang, and Z. Su “STAR-RIS and UAV combination in MEC networks: Simultaneous task offloading and communications,” IEEE Trans. Commun., vol. 72, no. 1, pp. 245–260, 2024.
[30]. Z. Ding, P. Fan, and H. V. Poor, “Impact of user pairing on 5G nonorthogonal multiple access,” IEEE Trans. Veh. Technol., vol. 65, no. 8, pp. 6010–6023, Aug. 2016.
[31]. G.-H. Nguyen, A.-N. Nguyen, K. Nguyen, M.-S. Nguyen, T.-S. Ngo, N.-A. Bui, P.-C. Le, M.-D. Hoang, T.-D. Trinh, and T.-A. Hoang, “Secure Computation Offloading Analysis for WPT-enabled UAV-assisted MEC Incorporating NOMA with Friendly Jammer in IoT Network”, Tele. Sys., vol. 88, no. 3, pp. 98, Jul. 2025.
[32]. Al-Hourani, S. Kandeepan, and S. Lardner, “Modeling air-to-ground path loss for low altitude platforms in urban environments,” in Proc. IEEE Global Telecommun. Conf. (GLOBECOM), pp. 2898–2904, Dec. 2014.
[33]. A. Khuwaja, Y. Chen, N. Zhao, M. S. Alouini, and P. Dmochowski, “A survey of channel modeling for UAV communications,” IEEE Commun. Surveys Tuts., vol. 20, no. 4, pp. 2804–2837, Dec. 2018.
[34]. Y. Zeng and R. Zhang, “Energy-efficient UAV communication with trajectory optimization,” IEEE Trans. Wireless Commun., vol. 16, no. 6, pp. 3747–3760, Jun. 2017.
[35]. H. V. Abeywickrama, B. A. Jayawickrama, Y. He, and E. Dutkiewicz, “Comprehensive energy consumption model for unmanned aerial vehicles, based on empirical studies of battery performance,” IEEE Access, vol. 6, pp. 58383–58394, Oct. 2018.
[36]. Y. Zeng, J. Xu, and R. Zhang, “Energy minimization for wireless communication with rotary-wing UAV,” IEEE Trans. Wireless Commun., vol. 18, no. 4, pp. 2329–2345, Apr. 2019.
[37]. S. A. H. Mohsan, M. A. Khan, M. H. Alsharif, P. Uthansakul, and A. A. Al-Ahmadi, “Towards the unmanned aerial vehicle (UAV)-based communication and sensing in 6G: Recent advances, challenges, and future directions,” IEEE Internet Things J., vol. 10, no. 22, pp. 19584–19594, Nov. 2023.
[38]. Q. Wu, Y. Zeng, and R. Zhang, “Joint trajectory and communication design for multi-UAV enabled wireless networks,” IEEE Trans. Wireless Commun., vol. 17, no. 3, pp. 2109–2121, Mar. 2018.
[39]. M. Reymond, E. Bargiacchi, and A. Nowe, “Pareto conditioned networks,” in Proc. Int. Conf. Auton. Agents Multiagent Syst. (AAMAS), pp. 1110–1118, May 2022.

[40]. M. A. Ouamri, M. E. Oteyo, M. Al-Abiad, S. S. Al-Dahasi, and S. B. H. Shah, “Green communication techniques for AI-enhanced resource allocation in future 6G network,” Energies, vol. 18, no. 5, p. 1234, 2025.

[41]. D. Tyrovolas, N. A. Mitsiou, T. Boufikos, and G. K. Karagiannidis, “Energy-aware trajectory optimization for UAV-mounted RIS and full-duplex relay,” IEEE Trans. Green Commun. Netw., 2024.

[42]. M. N. S. Al-Dhahir, A. Al-Mousa, F. A. Al-Salihi, and H. Al-Raweshidy, “Hardware limitations and optimization approach in 1-bit RIS design at 28 GHz,” IEEE Access, 2025.

[43]. S. N. Sur, D. K. N. Dao, and S. K. K. S. Gupta, “Optimal RIS partitioning and power control for bidirectional NOMA networks,” IEEE Access, vol. 11, pp. 12278–12290, 2023.

[44]. Sudhamani, M. S. Vasanthi, and S. Kumar, “Effects of atmospheric gases and rain intensity on terahertz wave propagation in 6G wireless networks,” IEEE Access, vol. 13, pp. 4567–4578, 2025.

[45]. Y. Nabil, H. ElSawy, S. A.-Dharrab, H. Attia, and H. Mostafa, “Ultra-Reliable Device-Centric Uplink Communications in Airborne Networks: A Spatiotemporal Analysis,” IEEE Transactions on Vehicular Technology, vol. 72, no. 7, pp. 9484-9499, Jul. 2023.

[46]. A. Ahmed, X.Wang, A. Hawbani,W. Yuan, H. Tabassum, Y. Liu, M. U. F. Qaisar, Z. Ding, N. A.-Dhahir, A. Nallanathan, and D.WK. Ng, “Unveiling the Potential of NOMA: A Journey to Next-Generation Multiple Access,” IEEE Communications Surveys & Tutorials, vol. 27, no. 5, pp. 3099-3164, Oct. 2025.

[47]. P. Chen, X. Zhou, J. Zhao, F. Shen, and S. Sun, “Energy-Efficient Resource Allocation for Secure D2D Communications Underlaying UAV-Enabled Networks,” IEEE Transactions on Vehicular Technology, vol. 71, no. 7, pp. 7519-7531, Jul. 2022.

[48]. Wolfram MathWorld. [Online]. Available: https://mathworld.wolfram.com/

[49]. I. S. Gradshteyn and I. M. Ryzhik, “Table of Integrals, Series, and Products,” USA: Academic Press, Seventh Edition, 2007.

[50]. JuddK. L. Judd, “Quadrature Methods,” University of Chicago’s Initiative for Computational Economics (ICE), 2011. [Online]. Available: https://ice.uchicago.edu/2012_presentations/Faculty/Judd/Quadrature.

[51]. T. T. Phuong, T. T. Duy, M. Masaracchia, G. K. Kurt, and T. Q. Duong, “Statistics of the sum of double random variables and their applications in performance analysis and optimization of simultaneously transmitting and reflecting reconfigurable intelligent surface-assisted non-orthogonal multi-access systems,” *Sensors*, vol. 24, no. 18, p. 6148, Sep. 2024.

[52].

[53]. B. Tahir, S. Schwarz, and M. Rupp, “Analysis of uplink IRS-assisted NOMA under Nakagami-m fading via moments matching,” *IEEE Wireless Commun. Lett.*, vol. 10, no. 3, pp. 624–628, Mar. 2021.