

### Description

The 6004 analogue addressable control and indicating equipment forms the central part of a fire detection and alarm system. The fully networkable 2-wire 6004 is compatible with Numens wired devices and can also be connected to wireless devices when used with wireless nodes.

Default configuration programming facilitates out-of-box installation and rapid commissioning. A powerful and versatile cause-and-effect PC-based programming tool enables rapid customization with software for sites that require special operating features.

The 6004 comes standard with features that allows flexibility and expandability.

The 6004 control and indicating equipment provides fire detection and alarm system designers with a premium product for life safety and property protection applications.

### Features

- Wired loops and wireless loops are both available
- Networkable, up to 12 control panels
- Supports up to 125 addressable devices per loop
- 3 Access Levels
- 128 configurable detection zones
- Automatic device detection on start-up
- Automatic device type-code verification
- 2 independently programmable non-addressable audio/visual alarm device output circuits
- 2 unmonitored Fire Alarm Condition relay outputs
- 1 unmonitored Fault Condition relay output
- High contrast backlit LCD display provides 4 rows of 40 characters
- 16 detection zone fire alarm LED indicators
- Configurable alarm output activation delay timer to (up to 10 min)
- 32 addressable audio/visual alarm devices per loop
- Day/night mode configurable
- Manual activation of alarm devices
- Supervised auxiliary DC 24 V output
- 3000 event history log
- Optional detection zone N/O and N/C relay outputs
- Optional remote LED detection zone displays
- RS-232 port to support GSM mobile telephone network module or Wi-Fi access point module
- Multiple language support
- Attractive designer enclosure available in white
- Surface mounting
- Rugged metal enclosure
- Easy installation



6004 addressable control and indicating equipment

### Compliance

6004 control and indicating equipment have the following compliance <sup>a</sup>.

|           | EN 54-2 <sup>b</sup> | EN 54-4 <sup>c</sup> | CE <sup>d</sup> |
|-----------|----------------------|----------------------|-----------------|
| 6004-01   | ✓                    | ✓                    | ✓               |
| 6004-01/E | ✓                    | ✓                    | ✓               |
| 6004-03   | ✓                    | ✓                    | ✓               |
| 6004-03/W | ✓                    | ✓                    | ✓               |

<sup>a</sup> Third-party assessment has not been undertaken.

<sup>b</sup> EN 54-2 Control and indicating equipment

<sup>c</sup> EN 54-4 Power supply equipment

<sup>d</sup> Conformité Européenne

### Accessories

The following accessories are compatible with 6004 control and indicating equipment.

| Description                                                                | Part Number | Datasheet |
|----------------------------------------------------------------------------|-------------|-----------|
| Control and indicating equipment 1-loop expansion card <sup>a</sup>        | 6001-06     | —         |
| Control and indicating equipment wireless loop expansion card <sup>a</sup> | 6004-04     | —         |
| Network interface card                                                     | 6001-03     | 31-0048   |
| Remote LED display card, 16 indicators                                     | 6001-04     | 31-0049   |
| Detection zone 8-relay output card                                         | 6001-07     | 31-0052   |
| Wi-Fi interface module                                                     | 685-001     | 31-0100   |
| GSM module                                                                 | 623-001     | 31-0107   |
| Programming tool                                                           | —           | —         |

<sup>a</sup> Compatible with 6004-01/E control and indicating equipment

## Specifications

| Device Loops                                            | 6004-01                                | 6004-01/E          | 6004-03 | 6004-03/W            |
|---------------------------------------------------------|----------------------------------------|--------------------|---------|----------------------|
| Addressable loops                                       | 1                                      | 1, expandable to 2 | 2       | 1 wired + 1 wireless |
| Number of connected devices per loop                    | 125                                    |                    |         |                      |
| Loop current (max)                                      | 400 mA                                 |                    |         |                      |
| Wireless loop current (max)                             | 1000mA                                 |                    |         |                      |
| Loop monitoring                                         | Open- and short-circuit                |                    |         |                      |
| Wireless Transmission Path                              |                                        |                    |         |                      |
| Maximum number of wireless nodes (per loop)             | 32                                     |                    |         |                      |
| Wireless node ID range                                  | 0 ~ 31                                 |                    |         |                      |
| Wireless radio interconnection operating frequencies    | 433 MHz, 868 MHz, 915 MHz              |                    |         |                      |
| Number of selectable radio channels                     | 24X3                                   |                    |         |                      |
| Alarms                                                  |                                        |                    |         |                      |
| Configurable audio/visual alarm groups (max)            | 512                                    |                    |         |                      |
| Non-addressable audio/visual alarm device driver        | 800 mA                                 |                    |         |                      |
| Non-addressable audio/visual alarm end-of-line resistor | 10 kΩ                                  |                    |         |                      |
| Alarm zone monitoring                                   | Open- and short-circuit                |                    |         |                      |
| Alarm zone voltage (max)                                | DC 27.5 V                              |                    |         |                      |
| Alarm zone fuse                                         | 1.1 A resettable (electronic fuse)     |                    |         |                      |
| Delayed alarm output timer (max)                        | 10 min                                 |                    |         |                      |
| Ancillary Outputs                                       |                                        |                    |         |                      |
| Repeater panel serial port                              | RS-485                                 |                    |         |                      |
| Network CIE serial port                                 | RS-485                                 |                    |         |                      |
| Zone indicators and relay serial port                   | TTL                                    |                    |         |                      |
| Ancillary modules port                                  | RS-232                                 |                    |         |                      |
| PC connection port                                      | RS-232 DB9 socket                      |                    |         |                      |
| Number of programmable output relays                    | 2                                      |                    |         |                      |
| Ancillary fire C/O relay                                | 2 x (1.0 A @ DC 30 V / 1 A @ AC 240 V) |                    |         |                      |
| Ancillary fault N/C relay                               | 1.0 A @ DC 30 V / 1 A @ AC 240 V       |                    |         |                      |
| Auxiliary supply                                        | DC 28 V @ 200 mA                       |                    |         |                      |
| Power Supply                                            |                                        |                    |         |                      |
| Operating voltage                                       | AC (85 ~ 260) V / 50/60 Hz             |                    |         |                      |
| Mains supply current limit                              | 1.5 A @ AC 230 V                       |                    |         |                      |
| Mains supply fuse                                       | 4 A / AC 250 V slow blow (20 mm)       |                    |         |                      |
| Mains supply fault threshold voltage                    | ≤ AC 60 V                              |                    |         |                      |
| Power supply                                            | 2.2 A @ DC 28 V                        |                    |         |                      |
| Standby battery capacity (2 × DC 12 V)                  | 7.2 Ah                                 |                    |         |                      |
| Maximum battery current draw                            | 1.5 A @ maximum operating temperature  |                    |         |                      |
| Battery fuse                                            | 2 A resettable (electronic fuse)       |                    |         |                      |
| Battery fault threshold voltage                         | < DC 20 V                              |                    |         |                      |
| Quiescent current                                       | 230 mA @ DC 27.6 V(No wireless node)   |                    |         |                      |
| Miscellaneous                                           |                                        |                    |         |                      |
| Event history log                                       | 3000 events                            |                    |         |                      |
| Number of networked panels                              | 12                                     |                    |         |                      |
| Terminal wiring                                         | (0.4 ~ 2.5) mm <sup>2</sup>            |                    |         |                      |
| Operating temperature                                   | (-5 ~ +40) °C                          |                    |         |                      |
| Operating humidity                                      | (0 ~ 95) % RH, non-condensing          |                    |         |                      |
| Storage temperature                                     | (-25 ~ +80) °C                         |                    |         |                      |
| Storage humidity                                        | (0 ~ 98) % RH, non-condensing          |                    |         |                      |
| Dimensions (h × w × d)                                  | (400 × 330 × 85) mm                    |                    |         |                      |
| Weight (excluding batteries)                            | 4.6 kg                                 |                    |         |                      |

<sup>a</sup> Requires 6001-06 loop expansion card.

Ordering Information

|           | 1-Loop | 1-Loop, Expandable | 2-Loops | 1-Loop Wired + 1 Loop wireless |
|-----------|--------|--------------------|---------|--------------------------------|
| 6004-01   | ✓      | —                  | —       | —                              |
| 6004-02/E | —      | ✓                  | —       | —                              |
| 6004-03   | —      | —                  | ✓       | —                              |
| 6004-03/W | —      | —                  | —       | ✓                              |

View the complete range of products at [www.numens.com](http://www.numens.com)

