

Accuracy-Aware ISCC Optimization for Aerial Edge Inference in SI-TNTNs

Thien Hieu Hoang, Tri Nhu Do, and Georges Kaddoum

Abstract—We study integrated sensing, communication, and computation (ISCC) for uplink–downlink coexistence edge inference over stochastic integrated terrestrial and non-terrestrial networks (SI-TNTNs). Ground user equipments sense their environment, compress the raw observation into a feature payload, and partially offload the resulting inference task to hovering unmanned aerial vehicles hosting inference servers in 3D space, while jammers impair both links. Node locations follow homogeneous Poisson point processes. Using matched-filter successive interference cancellation on the uplink and zero-forcing beam-forming on the downlink, we formulate a mixed-integer nonlinear program trading off delay, energy, downlink rate, and inference accuracy. Both sensing-induced variables admit closed forms (the three-point delay–energy offloading split and the utility-optimal feature-retention ratio), so the ISCC extension leaves the search complexity of the whale/particle-swarm solver unchanged.

Index Terms—ISCC, UAV edge inference, SI-TNTN, partial offloading, inference accuracy, resource allocation, whale optimization.

I. INTRODUCTION

Sixth-generation networks are expected to deliver sensing, communication, and computation as one service. Integrated sensing, communication, and computation (ISCC) changes the figure of merit accordingly: what matters is the accuracy of the inference the sensed data supports, not the rate at which its bits arrive. Stochastic integrated terrestrial and non-terrestrial networks (SI-TNTNs) [1] host such services naturally, unmanned aerial vehicles (UAVs) carrying servers beyond fixed terrestrial cells at positions neither planned nor static, so performance must hold in distribution over deployments.

Edge inference is the workload: a device senses, extracts features, and forwards part of them to a UAV-hosted server. How aggressively the observation is compressed before transmission is one knob fixing accuracy, airtime, and server cycles at once, so the three functions share a single budget. Coexisting uplink (UL) and downlink (DL) complicates it: half-duplex UAVs reusing sub-channels leak power between offloading UL and broadcasting DL, successive interference cancellation leaves residual intra-cell interference and decoding-margin constraints, zero-forcing (regularized when overloaded) nulls intra-cell DL interference, and jammers corrupt both directions. All enter the achievable rates, hence the delay and energy against which compression is priced.

The resulting mixed-integer nonlinear program couples association, powers, server frequencies, and the sensing-induced

variables through interference, and is NP-hard [2], so swarm heuristics [3], [4] are the usual recourse. Prior work is fragmented with respect to this setting. ISCC supplies the accuracy objective, through discriminant-gain task-oriented compression [5] and, more recently, energy-efficient split edge inference [6], but on single-cell terrestrial topologies with deterministic geometry and no jamming [7]. Non-terrestrial designs address integrated communication and computation under uncertainty [8], and sensing-offloading scheduling has been studied for multi-UAV edge inference [9], yet both assume a single link direction and benign spectra. None combines stochastic aerial geometry, UL–DL coexistence under jamming, and an inference-accuracy objective.

This letter recasts stochastic UL–DL edge inference on a SI-TNTN as an ISCC problem, contributing: (i) a planar-HPPP UAV edge-inference model with independent altitudes, jamming-aware MF-SIC and ZFBF, each UL UE sensing, compressing features at a tunable retention ratio, and partially offloading; (ii) an MINLP over delay, energy, DL rate, and accuracy; (iii) closed forms for both sensing-induced variables and a clipped water-filling compute rule, so ISCC adds no search cost; (iv) a hybrid WOA/IWOA/PSO–BWOA solver benchmarked against exhaustive search.

II. SYSTEM AND SIGNAL MODELS

Consider a square area with M hovering UAVs (each with L antennas and an onboard inference server), ground UEs, and ground jammers (Fig. 1). UAVs are half-duplex, $M = M^{\text{ul}} + M^{\text{dl}}$. Bandwidth B is reused over K sub-channels of width $B_k = B/K$. Horizontal locations of UAVs, UEs, and jammers are independent 2D HPPPs $\Phi_0, \Phi_{\text{UE}}, \Phi_{\text{Q}}$ of intensities $\lambda_0, \lambda_{\text{UE}}, \lambda_{\text{Q}}$. Ground nodes sit on $z = z_{\min}$; UAV altitudes are drawn independently and uniformly from $[z_{\text{uav}}^{\min}, z_{\text{uav}}^{\max}]$. UAV m , UE n , and jammer q thus sit at $\ell_m, \ell_n, \ell_q \in \mathbb{R}^3$. Nearest-UAV association $d_{n,m} = \|\ell_m - \ell_n\|_2$ induces Voronoi-like cells; the binary $\vec{A}^{\text{ul}}$ then assigns a sub-channel, or local execution, inside the serving cell.

Each slot splits into an orthogonal sensing sub-slot, in which UL UEs acquire and compress their observations, and a communication sub-slot carrying UL offloading and DL broadcasting. Sensing thus contends for time and energy but not spectrum, leaving Secs. II-B–II-C unaffected by the sensing waveform.

UL/DL UAV roles are an independent Bernoulli split with $\lambda_0^{\text{ul}} = \lambda_0^{\text{dl}}$.

For $\psi \in \{\text{G2A}, \text{A2G}\}$, $\vec{h}_{\text{AB}} = \sqrt{\beta_{\text{AB}}^{\psi}} \vec{g}_{\text{AB}} \in \mathbb{C}^{L \times 1}$, where $\beta_{\text{AB}}^{\psi} = 10^{-\text{PL}_{\text{AB}}^{\psi}/10} \zeta_{\text{AB}}$ is the linear large-scale gain, PL^{ψ} is

T. H. Hoang and G. Kaddoum are with the Department of Electrical Engineering, ÉTS, Montréal, Québec, Canada (e-mail: thien-hieu.hoang.1@ens.etsmtl.ca; Georges.Kaddoum@etsmtl.ca). T. N. Do is with the Department of Electrical Engineering, Polytechnique Montréal, Montréal, Québec, Canada (e-mail: tri-nhu.do@polymtl.ca).




Fig. 1. One HPPP realisation of the SI-TNTN drawn by the simulator: UAVs hover at their sampled altitudes over ground UEs and jammers, with G2A offloading, A2G broadcasting, and jamming on both directions.

path loss in dB, ζ_{AB} is inverse-Gamma shadowing, and $\bar{g}_{AB}$ is Nakagami- m fading with i.i.d. uniform phases. G2A path loss is $PL^{G2A} = 10\alpha \log_{10}(d/d_0) + PL_0$; A2G is $PL^{A2G} = FSPL(d) + \eta_0$ with $FSPL(d) = 20 \log_{10}(d) + 20 \log_{10}(f_c) - 27.55$ for distance d in metres and carrier f_c in MHz, and excess loss η_0 . Denote $\vec{h}_{n,k,m}$ the UE-UAV channel on sub-channel k .

A. Sensing, Feature Extraction, and Accuracy

Each UL UE $n \in \mathcal{N}^{ul}$ illuminates its field of view for T_n^{sen} at power p_n^{sen} , at cost $E_n^{sen} = p_n^{sen} T_n^{sen}$, and collects a raw observation of D_n^{raw} bits at sensing SNR γ_n^{sen} . The sensing configuration (T_n^{sen}, p_n^{sen}) is part of the task descriptor; joint sensing-power control is left to future work. The UE then extracts features at ϖ_n cycles/bit, costing $T_n^{ext} = \varpi_n D_n^{raw} / F_n^{loc}$ and $E_n^{ext} = \kappa_n \varpi_n D_n^{raw} (F_n^{loc})^2$ with switched-capacitance coefficient κ_n , and retains a fraction $\chi_n \in (0, 1]$ of the extracted features. The surviving inference task is

$$I_n(\chi_n) = \{\chi_n D_n^{raw}, \chi_n C_n^{raw}, \gamma_n^{sen}\}, \quad (1)$$

i.e. retention scales payload and workload alike. Following the discriminant-gain view of task-oriented compression, in which classification accuracy grows with, and saturates in, the discriminant information carried by the retained features, we adopt the saturating surrogate

$$\Lambda_n(\chi_n) = 1 - e^{-\vartheta_n \chi_n \Gamma_n}, \quad \Gamma_n \triangleq \log_2(1 + \gamma_n^{sen}), \quad (2)$$

with task sensitivity $\vartheta_n > 0$, so that accuracy is increasing and concave in the retained feature information $\chi_n \Gamma_n$ and bounded by one. Thus χ_n is the single ISCC knob: raising it improves accuracy but inflates airtime, transmit energy, and server cycles simultaneously. Imposing $\Lambda_n \geq \Lambda^{th}$ gives the retention floor

$$\chi_n^{\min} = -\ln(1 - \Lambda^{th}) / (\vartheta_n \Gamma_n), \quad (3)$$

and UE n is admissible only if $\chi_n^{\min} \leq 1$, i.e. only if its sensing quality satisfies $\vartheta_n \Gamma_n \geq -\ln(1 - \Lambda^{th})$. When $\chi_n^{\min} > 1$ the accuracy constraint is infeasible at any $\chi_n \leq 1$; such UEs leave the constraint set, execute locally, and are assigned zero utility.

B. UL Partial Offloading and MF-SIC

UE n splits its task: a fraction $\rho_n \in [0, 1]$ is offloaded and $1 - \rho_n$ is executed locally at F_n^{loc} . It has association $a_{n,k}^{ul} \in \{0, 1\}$ with $\sum_k a_{n,k}^{ul} \leq 1$, and power $p_n \in [0, p_n^{\max}]$. The all-local, full-retention reference costs are

$$T_n^{\text{ref}} = T_n^{\text{sen}} + T_n^{\text{ext}} + C_n^{\text{raw}} / F_n^{\text{loc}}, \quad (4)$$

$$E_n^{\text{ref}} = E_n^{\text{sen}} + E_n^{\text{ext}} + \kappa_n C_n^{\text{raw}} (F_n^{\text{loc}})^2.$$

For a given UE i , sub-channel k , and UAV m , denote $g_i \triangleq \|\vec{h}_{i,k,m}\|^2$ and $c_{n,i} \triangleq |\vec{h}_{n,k,m}^H \vec{h}_{i,k,m}|^2$. Let $m(n)$ be the UAV serving UE n , with $\mathcal{N}_m^{ul} = \{n : m(n) = m\}$. We denote the set of UEs using sub-channel k by $\mathcal{N}_k^{\text{sub}} = \{i : a_{i,k}^{ul} = 1\}$, and the set of weaker intra-cell co-channel users by $\mathcal{W}_{n,k,m} = \{i \in (\mathcal{N}_m^{ul} \cap \mathcal{N}_k^{\text{sub}}) \setminus \{n\} : g_i \leq g_n\}$. The received vector at UL UAV m on sub-channel k is

$$\vec{y}_{k,m} = \sum_{i \in \mathcal{N}_k^{\text{sub}}} \vec{h}_{i,k,m} \sqrt{p_i} s_i + \sum_{m' \in \mathcal{M}_k^{\text{sub}}} \vec{G}_{m',k,m} \vec{P}_{m',k}^{\text{UAV}} + \sum_{q \in \mathcal{Q}} a_{q,k} \vec{h}_{q,k,m} \sqrt{p_q} s_q + \vec{z}_{k,m}, \quad (5)$$

with $\mathcal{M}_k^{\text{sub}}$ the set of DL UAVs using sub-channel k with transmit matrices $\vec{P}_{m',k}^{\text{UAV}}$, the UAV-to-UAV channel $\vec{G}_{m',k,m} \in \mathbb{C}^{L \times L}$, jammer activity $a_{q,k} \sim \text{Bernoulli}(q_k)$ (q_k is a probability, distinct from the DL powers $q_{m',n'}$), and $\vec{z}_{k,m} \sim \mathcal{CN}(\vec{0}, N_0 \vec{I}_L)$. MF-SIC uses $\vec{v}_{m,n} = \vec{h}_{n,k,m}$ and cancels stronger users first. The Signal-to-Interference-plus-Jamming-and-Noise Ratio (SIJNR) is

$$\gamma_{n,k,m} = \frac{g_n^2 p_n}{\mathcal{I}_{n,k,m}^w + \mathcal{I}_{n,k,m}^o + \mathcal{J}_{n,k,m} + g_n (\Xi_{k,m}/L + B_k N_0)}, \quad (6)$$

where $\mathcal{I}_{n,k,m}^w = \sum_{i \in \mathcal{W}_{n,k,m}} c_{n,i} p_i$ is residual intra-cell interference after SIC, $\mathcal{I}_{n,k,m}^o = \sum_{i \in \mathcal{N}_k^{\text{sub}} \setminus (\mathcal{N}_m^{ul} \cup \{n\})} c_{n,i} p_i$ is inter-cell UL interference, $\Xi_{k,m} = \sum_{m' \in \mathcal{M}_k^{\text{sub}}} \|\vec{G}_{m',k,m} \vec{P}_{m',k}^{\text{UAV}}\|^2$, and $\mathcal{J}_{n,k,m} = \sum_{q \in \mathcal{Q}} a_{q,k} c_{n,q} p_q$ is jamming, $\mathcal{Q}$ being the jammer set. Because the MF combiner is unnormalized, the projected noise is $g_n B_k N_0$ and the isotropic DL leakage is $g_n \Xi_{k,m}/L$, so both scale with g_n as the numerator does. Reliable SIC requires a decoding margin $\epsilon_m^{\text{th}} \geq 1$,

$$p_n g_n / \sum_{i \in \mathcal{W}_{n,k,m}} p_i g_i \geq \epsilon_m^{\text{th}}. \quad (7)$$

If $\mathcal{W}_{n,k,m} = \emptyset$ (the last-decoded UE in a cell), the constraint is vacuous. The transmission rate is $R_{n,k,m} = B_k \log_2(1 + \gamma_{n,k,m})$, and $a_n^{ul} = \sum_k a_{n,k}^{ul}$ with $\rho_n \leq a_n^{ul}$ so that a UE without a sub-channel computes locally. The local branch and the offload branch run in parallel, so with $R_n \triangleq \sum_{m,k} a_{n,k}^{ul} R_{n,k,m}$ and ignoring result-feedback payload,

$$T_n = T_n^{\text{sen}} + T_n^{\text{ext}} + \chi_n \Delta_n, \quad \Delta_n = \max\{\Delta_n^{\text{loc}}, \Delta_n^{\text{of1}}\}, \quad (8)$$

$$\Delta_n^{\text{loc}} = \frac{(1 - \rho_n) C_n^{\text{raw}}}{F_n^{\text{loc}}}, \quad \Delta_n^{\text{of1}} = \rho_n \left(\frac{D_n^{\text{raw}}}{R_n} + \frac{C_n^{\text{raw}}}{F_{nm(n)}} \right), \quad (9)$$

$$E_n = E_n^{\text{sen}} + E_n^{\text{ext}} + \chi_n \Theta_n, \quad (10)$$

$$\Theta_n = (1 - \rho_n) \kappa_n C_n^{\text{raw}} (F_n^{\text{loc}})^2 + \frac{\rho_n p_n D_n^{\text{raw}}}{\xi_n R_n}, \quad (11)$$

where $\xi_n \in (0, 1]$ is the power-amplifier efficiency. $\Delta_n^{\text{loc}}, \Delta_n^{\text{ofl}}$ are the total delay needed for local and offloading branches for transmitting and computing the features, respectively. Θ_n is UE-side energy only (local compute and UL transmit); UAV server energy is omitted. Setting $\chi_n = 1$ and $\rho_n = a_n^{\text{ul}}$ recovers the conventional atomic-task model. Note that χ_n factors out of both branches in (9), which decouples retention from the split; this is exploited in Sec. III.

C. DL Broadcasting and ZFBF

DL UAV m' uses one sub-channel, $\sum_k a_{m',k}^{\text{dl}} = 1$, and ZFBF precoder $\tilde{W}_{m',k} = \tilde{H}_{m',k}^{\text{dl}} [(\tilde{H}_{m',k}^{\text{dl}})^H \tilde{H}_{m',k}^{\text{dl}}]^\dagger$, the Moore–Penrose inverse (where column $\tilde{w}_{m',n'}$ is the beam-forming vector for UE n'), which nulls intra-cell interference when $L \geq |\mathcal{N}_{m'}^{\text{dl}}|$ and is regularized otherwise. The SIJNR of UE n' is

$$\gamma_{m',k,n'}^{\text{dl}} = q_{m',n'} / (\mathcal{I}_{n'}^{\text{inter}} + \mathcal{I}_{n'}^{\text{CCI}} + \mathcal{J}_{n'}^{\text{dl}} + \sigma_{k,n'}^2), \quad (12)$$

where $q_{m',n'}$ is the DL transmit power allocated by UAV m' to UE n' , $\mathcal{I}_{n'}^{\text{inter}} = \sum_{j \neq m'} \sum_{i \in \mathcal{N}_j^{\text{dl}}} q_{j,i} |\tilde{h}_{n',k,j}^H \tilde{w}_{j,k,i}|^2$ is inter-cell DL interference, $\mathcal{I}_{n'}^{\text{CCI}} = \sum_{i \in \mathcal{N}_k^{\text{sub}}} p_i |\ell_{i,k,n'}|^2$ is UL-to-DL co-channel interference with G2G channel $\ell_{i,k,n'}$, $\mathcal{J}_{n'}^{\text{dl}} = \sum_q a_{q,k} |h_{q,k,n'}|^2 p_q$ is jamming, and $\sigma_{k,n'}^2 = B_k N_0$ is thermal noise. Then $R_{n'}^{\text{dl}} = \sum_{m',k} a_{m',k}^{\text{dl}} B_k \log_2(1 + \gamma_{m',k,n'}^{\text{dl}})$, with total DL power $\sum_{n'} q_{m',n'} \|\tilde{w}_{m',n'}\|^2 \leq P_{m'}^{\text{max}}$, $\gamma_{m',k,n'}^{\text{dl}} \geq \gamma_{\text{th}}$.

III. PROBLEM AND SOLUTION

The UL utility is defined as the weighted sum of normalized execution time, energy, and sensing accuracy improvement to the reference values as

$$\mathbb{U}_n^{\text{ul}} = \beta_n^{\text{t}} \frac{T_n^{\text{ref}} - T_n}{T_n^{\text{ref}}} + \beta_n^{\text{e}} \frac{E_n^{\text{ref}} - E_n}{E_n^{\text{ref}}} + \beta_n^{\text{a}} \frac{\Lambda_n - \Lambda^{\text{th}}}{1 - \Lambda^{\text{th}}}, \quad (13)$$

with $\beta_n^{\text{t}} + \beta_n^{\text{e}} + \beta_n^{\text{a}} = 1$, and T_n^{ref} and E_n^{ref} are got from Eq. (8), (10) with $\chi_n = 1$ and $\rho_n = 0$, $\Lambda^{\text{th}} \in (0, 1)$ is the minimum required inference accuracy threshold. The DL utility is $\mathbb{U}_{n'}^{\text{dl}} = R_{n'}^{\text{dl}} / R_{\text{const}}$ with R_{const} a reference rate that puts both utilities on one scale. The snapshot objective is $\mathbb{U} = \sum_{n \in \mathcal{N}^{\text{ul}}} \mathbb{U}_n^{\text{ul}} + \sum_{n' \in \mathcal{N}^{\text{dl}}} \mathbb{U}_{n'}^{\text{dl}}$. The HPPP-averaged utility is

$$\Upsilon_{\text{sys}} = \mathbb{E}[\mathbb{U}]. \quad (14)$$

Writing $\vec{\Pi} \triangleq (\vec{A}^{\text{ul}}, \vec{A}^{\text{dl}}, \vec{p}, \vec{F}, \vec{\rho}, \vec{\chi})$ for the decision tuple, each snapshot solves the MINLP

$$\max_{\vec{\Pi}} \quad (15a)$$

$$\text{s.t. } a_{n,k}^{\text{ul}}, a_{m',k}^{\text{dl}} \in \{0, 1\}, \sum_k a_{n,k}^{\text{ul}} \leq 1, F_{nm} \geq 0, \quad (15b)$$

$$0 \leq p_n \leq p_n^{\text{max}}, \sum_{n \in \mathcal{N}^{\text{ul}}} F_{nm} \leq F_m^{\text{max}}, \quad (15c)$$

$$0 \leq \rho_n \leq a_n^{\text{ul}}, \chi_n^{\text{min}} \leq \chi_n \leq 1, \quad (15d)$$

$$\sum_k a_{m',k}^{\text{dl}} = 1, \sum_{n'} q_{m',n'} \|\tilde{w}_{m',n'}\|^2 \leq P_{m'}^{\text{max}}, \quad (15e)$$

$$\gamma_{m',k,n'}^{\text{dl}} \geq \gamma_{\text{th}}, (7) \forall n \in \mathcal{N}_k^{\text{sub}}, \forall m, k. \quad (15f)$$

Constraint (15d) is the only structural addition over the atomic-task formulation, and it absorbs the accuracy constraint $\Lambda_n \geq \Lambda^{\text{th}}$ through (3). Problem (15) inherits NP-hardness from the atomic-task MINLP [2]. We prune associations by

Lemma 2, run penalty-augmented power control at the atomic split $(\rho_n, \chi_n) = (a_n^{\text{ul}}, 1)$, and then block-coordinate $\vec{F}$ with $(\vec{\rho}, \vec{\chi})$.

Proposition 1 (Compute allocation): For fixed $(\vec{A}^{\text{ul}}, \vec{p}, \vec{\rho}, \vec{\chi})$, $\mathbb{U}$ is concave in $\vec{F}$. The KKT point of (15c) is $F_{nm}^* = 0$ if $a_n^{\text{ul}} \rho_n = 0$, and otherwise the clipped water-filling rule

$$F_{nm}^* = \min \left\{ \mu_m^{-1/2} \sqrt{\beta_n^{\text{t}} \rho_n \chi_n C_n^{\text{raw}} / T_n^{\text{ref}}}, \bar{F}_{nm} \right\}, \quad (16)$$

where

$$\bar{F}_{nm} = \frac{\rho_n C_n^{\text{raw}}}{[(1 - \rho_n) C_n^{\text{raw}} / F_n^{\text{loc}} - \rho_n D_n^{\text{raw}} / R_n]_+} \quad (17)$$

is the computation rate beyond which the offload branch of (9) falls below the local branch (with $\bar{F}_{nm} = \infty$ when the bracket is nonpositive), and $\mu_m > 0$ is the unique water level giving $\sum_{n \in \mathcal{N}_m^{\text{ul}}} F_{nm}^* = F_m^{\text{max}}$, or $\mu_m \rightarrow 0$ if $\sum_n \bar{F}_{nm} \leq F_m^{\text{max}}$.

Proof: Δ_n^{ofl} is convex in F_{nm} and Δ_n^{loc} constant, so Δ_n is convex and $\mathbb{U}_n^{\text{ul}}$ concave by (8), (13); Θ_n, Λ_n are $\vec{F}$ -free. Where Δ_n^{ofl} is active, $\partial \mathbb{U}_n^{\text{ul}} / \partial F_{nm} = (\beta_n^{\text{t}} / T_n^{\text{ref}}) \chi_n \rho_n C_n^{\text{raw}} / F_{nm}^2 > 0$, so the budget binds; stationarity of $\sum_n \mathbb{U}_n^{\text{ul}} + \mu_m (F_m^{\text{max}} - \sum_n F_{nm})$ yields $F_{nm} \propto \sqrt{\beta_n^{\text{t}} \rho_n \chi_n C_n^{\text{raw}} / T_n^{\text{ref}}}$. Beyond $\bar{F}_{nm}$ the local branch is active and the derivative vanishes, giving the clip. Monotonicity of $\sum_n F_{nm}^*$ in μ_m^{-1} gives uniqueness. ■

Setting $\rho_n = \chi_n = 1$ makes $\bar{F}_{nm} = \infty$, and without sensing overhead $C_n^{\text{raw}} / T_n^{\text{ref}} = F_n^{\text{loc}}$, which recovers the conventional proportional allocation.

Proposition 2 (Offloading split): For fixed $(\vec{A}^{\text{ul}}, \vec{p}, \vec{F}, \vec{\chi})$ with $a_n^{\text{ul}} = 1$, $\mathbb{U}_n^{\text{ul}}$ is concave and piecewise linear in ρ_n with a single breakpoint at

$$\rho_n^* = \frac{C_n^{\text{raw}} / F_n^{\text{loc}}}{C_n^{\text{raw}} / F_n^{\text{loc}} + D_n^{\text{raw}} / R_n + C_n^{\text{raw}} / F_{nm(n)}}, \quad (18)$$

at which the two branches of (9) balance. An optimizer ρ_n^* lies in $\{0, \rho_n^*, 1\}$, and follows from three utility evaluations.

Proof: Δ_n^{loc} and Δ_n^{ofl} are affine in ρ_n , respectively decreasing and increasing, so Δ_n is convex piecewise linear and the branches cross once, at (18). As Θ_n is affine and Λ_n is ρ_n -free, (13) makes $\mathbb{U}_n^{\text{ul}}$ concave piecewise linear with a single kink, maximized there or at an endpoint. ■

Proposition 3 (Feature retention): For fixed $(\vec{A}^{\text{ul}}, \vec{p}, \vec{F}, \vec{\rho})$, $\mathbb{U}_n^{\text{ul}}$ is strictly concave in χ_n and

$$\chi_n^* = \min \left\{ 1, \max \left\{ \chi_n^{\text{min}}, -\frac{\ln \Psi_n}{\vartheta_n \Gamma_n} \right\} \right\}, \quad \Psi_n = \frac{(1 - \Lambda^{\text{th}}) \Omega_n}{\beta_n^{\text{a}} \vartheta_n \Gamma_n}, \quad (19)$$

where $\Omega_n = \beta_n^{\text{t}} \Delta_n / T_n^{\text{ref}} + \beta_n^{\text{e}} \Theta_n / E_n^{\text{ref}}$ is the marginal delay–energy price of one retained feature unit.

Proof: By (8) and (10), T_n and E_n are affine in χ_n , so the first two terms of (13) contribute $-\Omega_n \chi_n$ up to a constant, while (2) contributes the strictly concave $\beta_n^{\text{a}} (1 - e^{-\vartheta_n \chi_n \Gamma_n} - \Lambda^{\text{th}}) / (1 - \Lambda^{\text{th}})$. Setting $\partial \mathbb{U}_n^{\text{ul}} / \partial \chi_n = \beta_n^{\text{a}} \vartheta_n \Gamma_n e^{-\vartheta_n \chi_n \Gamma_n} / (1 - \Lambda^{\text{th}}) - \Omega_n = 0$ and projecting onto $[\chi_n^{\text{min}}, 1]$ gives (19). ■ Propositions 2–3 are in fact jointly optimal for fixed $(\vec{A}, \vec{p}, \vec{F})$: by (8)–(10), $\mathbb{U}_n^{\text{ul}} = \text{const} - \chi_n \Omega_n(\rho_n) + \beta_n^{\text{a}} (\Lambda_n - \Lambda^{\text{th}}) / (1 - \Lambda^{\text{th}})$, so for every $\chi_n > 0$ the maximizing split minimizes the convex piecewise-linear $\Omega_n(\rho_n)$ over $\{0, \rho_n^*, 1\}$ independently of χ_n , after which (19) is exact. Equation (19) is the ISCC

tradeoff in closed form: retention decays logarithmically in the marginal delay–energy price Ω_n and grows with sensing quality Γ_n and accuracy weight β_n^a . As Ω_n aggregates the radio state through R_n and the server state through F_{nm} , sensing fidelity is set jointly with communication and computation, not in advance.

For fixed $(\vec{A}^{\text{ul}}, \vec{F}, \vec{\rho}, \vec{\chi})$, the $\vec{p}$ -dependent part of $-\sum_n \mathbb{U}_n^{\text{ul}}$ is

$$\mathbb{W} = \sum_{n: a_n^{\text{ul}}=1} \frac{\eta_n + \theta_n p_n}{R_{n,k,m}}, \quad (20)$$

$$\eta_n = \frac{\beta_n^t \chi_n \rho_n D_n^{\text{raw}}}{\mathbb{T}_n^{\text{ref}}}, \quad \theta_n = \frac{\beta_n^e \chi_n \rho_n D_n^{\text{raw}}}{\xi_n \mathbb{E}_n^{\text{ref}}}.$$

The ISCC variables enter only as the scaling $\chi_n \rho_n$ of (η_n, θ_n) , so $\mathbb{W}$ retains its atomic-task structure and Lemma 1 applies at any fixed (ρ_n, χ_n) . Equation (20) assumes the offload branch active ($\rho_n \geq \rho_n^*$); on the local branch $\eta_n = 0$ and all statements below still hold. The map $\vec{p} \mapsto \mathbb{W}$ is nonconvex because $R_{n,k,m}$ couples all co-channel powers through (6). Dropping $\mathcal{I}^w, \mathcal{I}^o, \Xi$, and $\mathcal{J}$ yields the interference-free SIJNR $\tilde{\gamma}_n = \bar{h}_n p_n$ with $\bar{h}_n = g_n/(B_k N_0)$ and the separable lower bound

$$\widetilde{\mathbb{W}}(\vec{A}^{\text{ul}}, \vec{p}) = \sum_{n: a_n^{\text{ul}}=1} \frac{\eta_n + \theta_n p_n}{B_k \log_2(1 + \bar{h}_n p_n)} \leq \mathbb{W}(\vec{A}^{\text{ul}}, \vec{p}). \quad (21)$$

Lemma 1: For each offloading UE, $w_n(p) = (\eta_n + \theta_n p)/[B_k \log_2(1 + \bar{h}_n p)]$ is quasiconvex on $(0, p_n^{\max})$. A minimizer $p_n^\dagger$ is $p_n^{\max}$ if $\phi_n(p_n^{\max}) \leq 0$, and otherwise the unique root of

$$\phi_n(p) = \theta_n \log_2(1 + \bar{h}_n p) - \frac{\bar{h}_n}{\ln 2} \frac{\eta_n + \theta_n p}{1 + \bar{h}_n p} = 0, \quad (22)$$

which is found by bisection in $\mathcal{O}(\log(p_n^{\max}/\varepsilon))$ steps.

Proof: The sign of $w'_n(p)$ coincides with $\phi_n(p)$. Moreover $\phi'_n(p) > 0$ on $(0, \infty)$, so ϕ_n is strictly monotonically increasing, making w_n strictly quasiconvex. ■

Pruning must act before $(\vec{\rho}, \vec{\chi})$ are known, and both the compute and the power cost scale with $\chi_n \rho_n$, so the conventional atomic-task bound is no longer valid. Instead, for each offloading UE replace R_n by the interference-free rate $\bar{R}_n = B_k \log_2(1 + \bar{h}_n p_n^{\max})$, F_{nm} by $F_m^{\max}$, and the offload energy $p_n D_n^{\text{raw}}/(\xi_n R_n)$ by its floor $D_n^{\text{raw}} \ln 2/(\xi_n B_k \bar{h}_n)$, which follows from $\log_2(1+x) \leq x/\ln 2$. Each replacement lowers Δ_n and Θ_n pointwise, so $\bar{\Omega}_n(\rho_n)$ lower-bounds $\Omega_n(\rho_n)$ for every $(\vec{p}, \vec{F})$. With $\bar{u}_n$ the maximum of $\mathbb{U}_n^{\text{ul}}$ under $\bar{\Omega}_n$, obtained exactly by Propositions 2–3, leveraging the interference-free decoupling in (21) yields the upper-bound filter

$$\mathbb{F}(\vec{A}) = \sum_n \bar{u}_n(\vec{A}^{\text{ul}}) + \mathbb{U}_{\text{ub}}^{\text{dl}}(\vec{A}^{\text{dl}}), \quad (23)$$

with $\mathbb{U}_{\text{ub}}^{\text{dl}}$ an interference-free full-budget upper bound on $\mathbb{U}^{\text{dl}}$. Write $\mathbb{U}^*$ for the incumbent.

Lemma 2 (Pruning): Fix $\vec{A}$. If $\mathbb{F}(\vec{A}) \leq \mathbb{U}^*$, then no $(\vec{p}, \vec{F}, \vec{\rho}, \vec{\chi})$ can achieve a utility strictly greater than $\mathbb{U}^*$.

Proof: $\mathbb{U}_n^{\text{ul}} \leq \bar{u}_n$ for every $(\vec{p}, \vec{F}, \rho_n, \chi_n)$ since $\Omega_n \geq \bar{\Omega}_n$ enters with a negative sign, and $\mathbb{U}^{\text{dl}} \leq \mathbb{U}_{\text{ub}}^{\text{dl}}$, hence $\mathbb{U} \leq \mathbb{F}$. ■

Algorithm 1: Hybrid WOA/IWOA/PSO–BWOA for SI-TNTN UAV edge-inference ISCC.

Input: HPPP snapshot, channels $\vec{h}$, sensed tasks $\{D_n^{\text{raw}}, C_n^{\text{raw}}, \gamma_n^{\text{sen}}\}$, budgets, accuracy floor Λ^{th}
Output: $\vec{\Pi} = (\vec{A}^{\text{ul}}, \vec{A}^{\text{dl}}, \vec{p}, \vec{F}, \vec{\rho}, \vec{\chi})$

- 1 Force UEs with $\chi_n^{\min} > 1$ in (3) to local execution.
- 2 Generate a BWOA population of binary association matrices.
- 3 **for** each association candidate $\vec{A}$ **do**
- 4 **if** $\mathbb{F}(\vec{A}) \leq \mathbb{U}^*$ **then**
- 5 discard $\vec{A}$ by Lemma 2
- 6 **else**
- 7 Set $(\rho_n, \chi_n) \leftarrow (a_n^{\text{ul}}, 1)$.
- 8 Run WOA/IWOA/PSO on $\vec{p}$ with SIJNR/SIC penalties.
- 9 Alternate (16) with Propositions 2–3 until $(\vec{F}, \vec{\rho}, \vec{\chi})$ stabilises.
- 10 Evaluate $\mathbb{U}(\vec{\Pi})$ and update $\mathbb{U}^*$.
- 11 Update BWOA encircling/spiral search and retain the elite whale.
- 12 **return** the best $\vec{\Pi}$.

The remaining continuous problems use penalty-augmented search. For UL power,

$$\min_{\vec{p}} \mathbb{W}(\vec{A}^{\text{ul}}, \vec{p}) + \nu_p \sum_n (p_n - p_n^{\max})_+^2 + \nu_{\text{sic}} \sum_{n,k} g_{n,k}^{\text{sic}}(\vec{p})_+^2, \quad (24)$$

where $g_{n,k}^{\text{sic}}$ is the slack of (7). For the DL powers $\vec{q} = \{q_{m',n'}\}$, we maximize $\mathbb{U}^{\text{dl}}$ minus squared slacks of (15e). Both use WOA [10], IWOA (WOA with adaptive population resizing) [2], or PSO. Binary matching uses BWOA [11]: a whale position $x \in \mathbb{R}$ maps by $\sigma(x) = (1 + e^{-\tau x})^{-1}$ to $a = \mathbf{1}\{\text{rand} < \sigma(x)\}$.

The inner TPC costs $\mathcal{O}(I_1 S_1 N^{\text{ul}} K)$ per association that survives Lemma 2; BWOA over $\vec{A}$ costs $\mathcal{O}(I_3 S_3 K (N^{\text{ul}} + M^{\text{dl}}))$ plus the surviving inner solves. The ISCC variables add only $\mathcal{O}(N^{\text{ul}})$ per inner iteration (a few block-coordinate rounds of Propositions 1–3), which is dominated by the $\mathcal{O}(I_1 S_1 N^{\text{ul}} K)$ power search, so the overall order is unchanged from the atomic-task formulation. Exhaustive matching enumerates $(K+1)^{N^{\text{ul}}} K^{M^{\text{dl}}}$ associations.

IV. NUMERICAL RESULTS

Unless noted, $K = 5$, $B_k = 1$ MHz, $L = 4$, $N_0 = -174$ dBm/Hz, $f_c = 2.4$ GHz (FSPL uses 2400 MHz), $F_m^{\max} = 8$ GHz, $p_n^{\max} = 24$ dBm, $F_{m'}^{\max} = 46$ dBm, $C_n^{\text{raw}} = 10^9$ cycles, $D_n^{\text{raw}} = 420$ kbit, $F_n^{\text{loc}} \in \{0.5, 0.8, 1.0\}$ GHz, $\kappa_n = 5 \times 10^{-27}$, $\xi_n = 1$, $R_{\text{const}} = 10^8$ bit/s, and $\beta_n^t = \beta_n^e = \beta_n^a = 1/3$. Channels use Nakagami- m ($m = 2$), inverse-Gamma shadowing of shape 3, $\alpha = 2.5$, $\text{PL}_0 = 40$ dB, $d_0 = 1$ m, $\eta_0 = 20$ dB. In 1000×1000 m²: $\lambda_0^{\text{ul}} = \lambda_0^{\text{dl}} = 3$, $\lambda_{\text{UE}} = 10$, $\lambda_{\text{Q}} = 2$ nodes/km², UAV altitude [80, 120] m, $p_q = 20$ dBm, $q_k = 0.8$. The sensing/ISCC parameters are $\gamma_n^{\text{sen}} = 10$ dB (per-UE spread 3 dB), $\mathbb{T}_n^{\text{sen}} = 5$ ms,




Fig. 2. Proposed BWOA matching versus exhaustive search, $K = 3$, $M^{u1} = 2$, $M^{d1} = 1$: (a) attained utility, (b) runtime, versus active-UE density.

$p_n^{\text{sen}} = 0.1$ W, $\vartheta_n = 1$, $\Lambda^{\text{th}} = 0.9$, and $\varpi_n = 50$ cycles/bit, which by (3) gives a retention floor $\chi_n^{\min} \approx 0.67$. We benchmark the hybrids against exhaustive matching and against the atomic-task WOA/IWOA/PSO-BWOA framework of [2], with force-all-offload (every UL UE must offload), independent offloading (IOJOA: each UE freezes a coin-flip offload bit), orthogonal access (FDMA: at most one UL UE or DL UAV per sub-channel), and all-local computing (ALCA) as additional baselines. Each metaheuristic uses 30 search agents, and every curve averages 30 HPPP snapshots.

Fig. 2(a) shows BWOA tracking exhaustive sub-channel search, with a small gap that widens as the association space grows. Fig. 2(b) shows the corresponding runtime: exhaustive enumeration is cheaper at low density but grows steeply, whereas BWOA grows near-linearly and overtakes it as density increases. The closed-form ISCC updates leave this curve unchanged.

Fig. 3(a) shows aggregate utility rising with UE density, more terms entering $\mathbb{U}$ even as the co-channel and jamming terms of (6)–(12) grow. Fig. 3(b) shows added UAV inference servers changing utility through extra compute and extra G2A/A2G interference.

Fig. 4(a) sweeps β^a with $\beta^t = \beta^e = (1 - \beta^a)/2$. At low β^a retention sits on its floor and accuracy equals Λ^{th} , with lower delay than the atomic-task point; raising β^a drives χ_n^* to unity, trading latency for accuracy along (19), until ISCC coincides with the atomic task. In Fig. 4(b), at low sensing SNR the floor (3) exceeds one, UEs become inadmissible, and offloading collapses; above it, better sensing lowers both $\chi_n^{\min}$ and χ_n^* : higher-quality observations are compressed *more*, a coupling an atomic-task model cannot express.

V. CONCLUSION

We recast joint UL–DL edge-inference offloading and radio resource management on a SI-TNTN as an ISCC problem combining UAV-mounted servers, planar HPPP geometry with independent altitudes, and jamming-aware MF-SIC/ZFBF SI-JNR with sensing-derived tasks, partial offloading, and an inference-accuracy objective. The two sensing-induced variables admit closed forms (a three-point rule for the split and a logarithmic rule for retention), so the MINLP is still solved by the WOA/IWOA/PSO plus BWOA framework at unchanged complexity. Joint sensing-power control and sensing/communication antenna partitioning at the UAV are natural extensions.





Fig. 3. (a) Utility versus active-UE density for WOA/IWOA/PSO-BWOA (MF-SIC), force-all-offload, IOJOA, FDMA, and ALCA. (b) Utility versus UL UAV-server density.




Fig. 4. ISCC effects: (a) accuracy–delay frontier swept over β^a , versus the atomic-task baseline; (b) optimal retention χ_n^* , retention floor $\chi_n^{\min}$, and fraction of offloading UEs versus mean sensing SNR.

REFERENCES

- [1] A. Meftah, T. N. Do, G. Kaddoum, and C. Talhi, “Federated learning-empowered jamming detection for stochastic uplink and downlink integrated terrestrial and non-terrestrial networks,” *IEEE Trans. Netw. Service Manag.*, vol. 23, pp. 7097–7113, 2026.
- [2] T. H. Hoang, C. T. Nguyen, T. N. Do, and G. Kaddoum, “Joint task offloading and radio resource management in stochastic MEC systems,” *IEEE Trans. Commun.*, vol. 72, no. 5, pp. 2670–2686, May 2024.
- [3] A. Kordon, “Swarm intelligence: The benefits of swarms,” in *Applying Computational Intelligence: How to Create Value*. Berlin, Germany: Springer, 2010, pp. 145–174.
- [4] D. E. Goldberg, *Genetic Algorithms in Search, Optimization and Machine Learning*. Boston, MA, USA: Addison-Wesley Longman Publishing Co., Inc., 1989.
- [5] D. Wen, P. Liu, G. Zhu, Y. Shi, J. Xu, Y. C. Eldar, and S. Cui, “Task-oriented sensing, computation, and communication integration for multi-

- device edge AI,” *IEEE Trans. Wireless Commun.*, vol. 23, no. 3, pp. 2486–2502, 2024.
- [6] J. Yao, W. Xu, G. Zhu, K. Huang, and S. Cui, “Energy-efficient edge inference in integrated sensing, communication, and computation networks,” *IEEE J. Sel. Areas Commun.*, 2025, early access.
 - [7] D. Wen, Y. Zhou, X. Li, Y. Shi, K. Huang, and K. B. Letaief, “A survey on integrated sensing, communication, and computation,” *IEEE Commun. Surveys Tuts.*, 2025, early access.
 - [8] X. Tang, Y. Jiang, R. Zhang, Q. Du, J. Liu, and N. Liu, “Energy-efficient integrated communication and computation via non-terrestrial networks with uncertainty awareness,” *IEEE Internet Things J.*, 2025, early access.
 - [9] Y. Du, S. Xu, and Y. Yu, “Joint scheduling of sensing data offloading and edge inference for multi-UAV networks,” arXiv:2605.03898, 2026.
 - [10] S. Mirjalili and A. Lewis, “The whale optimization algorithm,” *Adv. Eng. Softw.*, vol. 95, pp. 51–67, 2016.
 - [11] V. Kumar and D. Kumar, “Binary whale optimization algorithm and its application to unit commitment problem,” *Neural Computing and Applications*, vol. 32, no. 7, pp. 2095–2123, 2020.