



NOMAD Toronto - Complete Lighting Power & DMX Schedule

Prepared by EMBLEM PROJECTS INC. | Rev 7.2 | 24 August 2026

Refactor: all inventory references are cropped to the actual fixture/device; full manual-page screenshots have been removed. DMX channel types use the legend below consistently throughout the report.

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

1. Complete Equipment Inventory

 LIGHT4ME Strobe Multi Bar Qty 7 200 W ea. 90-240 V DMX 4 / 16 / 168 CH	 BETOPPER LM70S Moving Wash Qty 10 100 W ea. 100-240 V DMX 9 / 14 CH
 YF Beam 230 Moving Head Qty 4 400 W planning 100-240 V DMX 16 / 20 CH	 Panda LS650 Six-Eye Laser Bar Qty 9 150 W ea. 100-240 V DMX 11 / 19 / 24 CH
 MICROH LEDBAR RGB Qty 1 50 W 120-220 V switchable DMX 13 CH	 CHAUVET Hurricane Haze 2D Qty 1 533 W fixed-voltage model DMX 2 CH
 Elation DP-415 Hybrid DMX Pack Qty 1 documented 120 V only 4 CH Dimmer / Switch	

Technical line-art is used only where the supplied manual does not contain a clean standalone product photograph.

2. 120 V / 240 V Power Comparison

Equipment	Qty	Input rating	W ea.	A ea. @120	A ea. @240	Total W	Total A @120	Total A @240
LIGHT4ME Strobe Multi Bar	7	90-240 V	200	1.67	0.83	1,400	11.67	5.83
BETOPPER LM70S	10	100-240 V	100	0.83	0.42	1,000	8.33	4.17
YF Beam 230	4	100-240 V	400*	3.33	1.67	1,600	13.33	6.67
Panda LS650	9	100-240 V	150	1.25	0.63	1,350	11.25	5.63
MICROH LEDBAR RGB	1	120-220 V switchable	50	0.42	N/A	50	0.42	N/A
Hurricane Haze 2D	1	fixed 120 / 230 V	533	4.40	N/A**	533	4.40	N/A**
LIGHTING + HAZE TOTAL	32	-	-	-	-	5,933	49.40	see note
Elation DP-415	1	120 V only	pass-through	-	N/A	-	-	-

* Beam 230 uses 400 W as the conservative planning figure. ** Hurricane Haze 2D is a fixed-voltage product family; do not treat the 120 V unit as universal input. MICROH is specified as 120-220 V switchable, so 240 V is N/A. DP-415 is 120 V only.

3. Recommended 120 V / 20 A Distribution

Circuit	Allocation	Load	Current	80% margin
LX-1	4 x YF Beam 230	1,600 W	13.33 A	320 W / 2.67 A
LX-2	7 x Strobe Multi Bar	1,400 W	11.67 A	520 W / 4.33 A
LX-3	9 x LS650 Laser Bar	1,350 W	11.25 A	570 W / 4.75 A
LX-4	10 x LM70S + MICROH + Haze 2D	1,583 W	13.19 A	337 W / 2.81 A
TOTAL	32 fixture/effect loads	5,933 W	49.40 A	1,747 W aggregate

4. DMX Personality Matrix - Every Documented Personality

Equipment	Personality	Footprint	Notes
LIGHT4ME Strobe Multi Bar	4 CH	4	Direct RGBW
	16 CH	16	Master, strobes, effects, RGBW/background
	168 CH	168	48 RGB sections + 24 white sections
BETOPPER LM70S	9 CH	9	Basic pan/tilt, RGBW, motor speed, reset
	14 CH	14	Adds 16-bit movement, macros, auto/sound
YF Beam 230	16 CH	16	Core beam functions
	20 CH	20	Adds extended wheel/effect speed channels
Panda LS650	11 CH	11	Linked Y movement + master/effects
	19 CH	19	Individual Y1-Y6 + individual laser enables
	24 CH	24	Adds X fine + extended effects
MICROH LEDBAR RGB	13 CH	13	Global RGB + three RGB segments
Hurricane Haze 2D	2 CH	2	Blower speed + haze volume
Elation DP-415	4 CH Dimmer	4	Proportional output
	4 CH Switch	4	Binary output

Showfile reconciliation: current June grandMA2 personalities still differ from several supplied manuals. Verify the physical fixture menu/mode before changing a working showfile.

5. LIGHT4ME Strobe Multi Bar

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

4 CH personality

CH	Type	Function
1	Intensity	Red dimmer
2	Intensity	Green dimmer
3	Intensity	Blue dimmer
4	Intensity	White dimmer

16 CH personality

CH	Type	Function
1	Intensity	Master dimmer
2	Shutter	RGB strobe
3	Color	Red
4	Color	Green
5	Color	Blue
6	Effect	RGB background effect
7	Effect	CH6 effect speed
8	Shutter	White strobe
9	Intensity	White dimmer
10	Effect	White main-source effect
11	Effect	CH10 effect speed
12	Shutter	RGBW strobe
13	Effect	RGBW main-source effect
14	Effect	CH13 effect speed
15	Color	Background color
16	Intensity	Background dimmer

168 CH personality

Range	Type	Assignment
CH1-CH144	Color	48 RGB sections, sequential R/G/B per section.
CH145-CH168	Color	24 white sections, one channel per section.

6. BETOPPER LM70S

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

9 CH personality

CH	Type	Function
1	Position	Pan / X axis
2	Position	Tilt / Y axis
3	Shutter	Master dimmer / strobe / on ranges
4	Color	Red
5	Color	Green
6	Color	Blue
7	Color	White
8	Position	Pan/Tilt motor speed
9	Control	Reset

14 CH personality

CH	Type	Function
1	Position	Pan
2	Position	Pan fine
3	Position	Tilt
4	Position	Tilt fine
5	Position	Movement speed
6	Shutter	Master dimmer / strobe / light on
7	Color	Red
8	Color	Green
9	Color	Blue
10	Color	White
11	Effect	Color macros / color jump
12	Effect	Color/effect speed
13	Effect	Auto programs / sound movement
14	Control	Reset

7. YF Beam 230

				Position	Color	Intensity	Shutter	Beam
				Effect	Laser	Atmos	Control	Power
CH	Type	16 CH			20 CH			
1	Color	Color wheel			Color wheel			
2	Shutter	Blackout / strobe			Blackout / strobe			
3	Intensity	Dimmer			Dimmer			
4	Beam	Gobo wheel			Gobo wheel			
5	Beam	Prism			Prism			
6	Beam	Prism rotation			Prism rotation			
7	Effect	Macro			Macro			
8	Beam	Frost			Frost			
9	Beam	Focus			Focus			
10	Position	Pan			Pan			
11	Position	Pan fine			Pan fine			
12	Position	Tilt			Tilt			
13	Position	Tilt fine			Tilt fine			
14	Position	Pan/Tilt speed			Pan/Tilt speed			
15	Control	Reset			Reset			
16	Intensity	Lamp control			Lamp control			
17	Control	-			Blank / reserved			
18	Effect	-			Color-wheel speed			
19	Beam	-			Dimming / prism / atomization speed			
20	Beam	-			Gobo-wheel speed			

8. Panda LS650 Six-Eye Laser Bar

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

11 CH personality

CH	Type	Function
1	Position	X-axis position
2	Position	X-axis motor speed
3	Position	Y1-Y6 linked position
4	Position	Y-axis motor speed
5	Laser	Main laser switch
6	Shutter	Strobe
7	Laser	Laser self-running effects
8	Laser	Laser self-running speed
9	Effect	Motor self-running / voice-control effects
10	Effect	Movement/self-walk speed
11	Control	Reset

19 CH personality

CH	Type	Function
1	Position	X-axis position
2	Position	X-axis motor speed
3	Position	Y1 position
4	Position	Y2 position
5	Position	Y3 position
6	Position	Y4 position
7	Position	Y5 position
8	Position	Y6 position
9	Position	Y-axis motor speed
10	Laser	Master laser switch
11	Shutter	Strobe
12	Laser	Laser 1 on/off
13	Laser	Laser 2 on/off
14	Laser	Laser 3 on/off
15	Laser	Laser 4 on/off
16	Laser	Laser 5 on/off
17	Laser	Laser 6 on/off

CH	Type	Function
18	Effect	Auto/reserved function per translated manual
19	Control	Reset

24 CH personality

CH	Type	Function
1	Position	X-axis position
2	Position	X-axis fine
3	Position	X-axis motor speed
4	Position	Y1 position
5	Position	Y2 position
6	Position	Y3 position
7	Position	Y4 position
8	Position	Y5 position
9	Position	Y6 position
10	Position	Y1-Y6 linked position
11	Position	Y-axis motor speed
12	Laser	Main laser switch
13	Shutter	Strobe
14	Laser	Laser 1 on/off
15	Laser	Laser 2 on/off
16	Laser	Laser 3 on/off
17	Laser	Laser 4 on/off
18	Laser	Laser 5 on/off
19	Laser	Laser 6 on/off
20	Laser	Laser self-running effects
21	Laser	Laser self-running speed
22	Effect	Motor self-running / voice-control effects
23	Effect	Movement/self-walk speed
24	Control	Reset

LS650 English wording is machine-translated; channel counts and principal assignments follow the supplied manual.

9. MICROH LEDBAR RGB

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

13 CH personality

CH	Type	Function
1	Control	Function / mode select
2	Intensity	All red intensity
3	Intensity	All green intensity
4	Intensity	All blue intensity
5	Color	Segment 1 red
6	Color	Segment 1 green
7	Color	Segment 1 blue
8	Color	Segment 2 red
9	Color	Segment 2 green
10	Color	Segment 2 blue
11	Color	Segment 3 red
12	Color	Segment 3 green
13	Color	Segment 3 blue

Current showfile uses an 11 CH LED Bar profile; field-verify before repatching.

10. CHAUVET Hurricane Haze 2D

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

2 CH personality

CH	Type	Function
1	Atmos	Blower speed 0-255 low-high
2	Atmos	Haze volume 0-255 low-high

11. Elation DP-415 Hybrid DMX Pack

Position	Color	Intensity	Shutter	Beam
Effect	Laser	Atmos	Control	Power

Personality	Type	DMX response
4 CH - Dimmer	Power	CH1-CH4 follow DMX 0-255 proportionally.
4 CH - Switch	Power	CH1-CH4 are OFF below 128 and ON at 128-255.

DP-415: 120 V, 15 A max input; 5 A / 600 W max per output channel.

12. Field Verification Note

Verify each physical fixture data plate and selected DMX mode before permanent repatching or electrical changes. Where manual and showfile disagree, preserve the working showfile until a channel-by-channel test confirms the correct personality.

Sources & Project Links

Prepared by EMBLEM PROJECTS INC. | Rev 7.2

Clickable references used to reconcile the supplied fixture manuals, current NØMAD lighting specification, manufacturer data, electrical ratings, and DMX personalities.

NØMAD Toronto AV repository

Project repository

<https://github.com/thisis-romar/nomad-toronto-av>

NØMAD lighting system specification v1

Fixture quantities and current grandMA2 showfile profiles

<https://github.com/thisis-romar/nomad-toronto-av/blob/main/08-lighting/nomad-lighting-spec-v1.md>

Panda Lighting LS650 / LS652 - 6 Heads Laser Bar XY Movement

Manufacturer product reference

<https://www.pandalightpro.com/product/6-heads-laser-bar-xy-movement/>

CHAUVET DJ Hurricane Haze 2D

Official manufacturer product page and downloads

<https://www.chauvetdj.com/products/hurricane-haze-2d/>

Elation / ADJ DP-415

Official discontinued product page and manual download

<https://www.elationlighting.com/products/dp-415>

BETOPPER LM70S manual reference

Public manual reference matching 9 CH / 14 CH personalities

<https://www.manualslib.com/guide/3267417/betopper-mini-moving-head-lm70s-7x8w-rgbw-mini-stage-lights-moving-head-manual.html>

YF BEAM 230 manual reference

Public manual reference matching 16 CH / 20 CH personalities

<https://www.manualslib.com/manual/908507/Yf-Beam-230.html>

Additional fixture information in this report is derived from the manuals supplied in the project archive. Where a reliable public manufacturer or manual URL was not available, no speculative external link was added.