
CS:5980
Foundations of Embedded Systems

Dynamical Systems

Part II

Copyright 2014-26, Rajeev Alur and Cesare Tinelli.
Created by Cesare Tinelli at the University of Iowa from notes originally developed by Rajeev Alur at the University of Pennsylvania. These notes are copyrighted materials and may not be used in other course settings outside of the University of Iowa in their current form or modified form without the express written permission of one of the copyright holders. During this course, students are prohibited from selling notes to or being paid for taking notes by any person or commercial firm without the express written permission of one of the copyright holders.

Control Design Problem



- We want to design a controller C so that C || H is stable
- Is there a mathematical way to check when a system is stable?
- Is there in fact a systematic way to design C so that C || H is stable?
  - Yes, if the plant model is linear

Linear Component

A *linear* expression over real variables x_1, x_2, …, x_n has the form

$$a_1 x_1 + a_2 x_2 + \ldots + a_n x_n$$

where a_1, a_2, … are rational constants

A continuous-time component H with state variables S, input variables I, and output variables O is *linear* if


1. for every state variable s, the dynamics is given by $ds = f_s(S, I)$, where f_s is a linear expression
2. every output variable o is defined by $o = h_o(S, I)$, where h_o is a linear expression

Examples

linear: heatflow, car, helicopter

nonlinear: pendulum


Continuous-time Component Car2



Problem: right-hand side of dv equation is not linear

Easy fix: replace disturbance θ by another variable $i_\theta = \sin \theta$

Continuous-time Component Car2



Rewriting to normal form:

$$dx = 0x + 1v + 0F + 0i_\theta$$
$$dv = 0x + (-k/m)v + (1/m)F + (-g)i_\theta$$
$$v = 0x + 1v + 0F + 0i_\theta$$

Matrix-based representation:

$$S = (x\ v)^T \quad I = (F\ i_\theta)^T \quad O = (v)$$

$$dS = A\,S + B\,I$$
$$O = C\,S + D\,I$$

$$A = \begin{pmatrix} 0 & 1 \\ 0 & -k/m \end{pmatrix} \quad B = \begin{pmatrix} 0 & 0 \\ 1/m & -g \end{pmatrix}$$

$$C = (0\ 1) \quad D = (0\ 0)$$

(A,B,C,D) Representation of Linear Components

Suppose a linear continuous-time component has

- n state variables $\mathbf{S} = \{ \mathbf{x}_1, \mathbf{x}_2, \ldots, \mathbf{x}_n \}$
- m input variables $\mathbf{I} = \{ \mathbf{u}_1, \mathbf{u}_2, \ldots, \mathbf{u}_m \}$
- k output variables $\mathbf{O} = \{ \mathbf{y}_1, \mathbf{y}_2, \ldots, \mathbf{y}_k \}$

Then the dynamics is given by

$$d\mathbf{S} = A\,\mathbf{S} + B\,\mathbf{I} \quad \text{and} \quad \mathbf{O} = C\,\mathbf{S} + D\,\mathbf{I}$$

where

A is an $n \times n$ matrix C is a $k \times n$ matrix


B is an $n \times m$ matrix D is a $k \times m$ matrix

The rate of change of i-th state variable and the value of j-th output are

$$d\mathbf{x}_i = A_{i,1}\,\mathbf{x}_1 + A_{i,2}\,\mathbf{x}_2 + \ldots + A_{i,n}\,\mathbf{x}_n + B_{i,1}\,\mathbf{u}_1 + B_{i,2}\,\mathbf{u}_2 + \ldots + B_{i,m}\,\mathbf{u}_m$$

$$\mathbf{y}_j = C_{j,1}\,\mathbf{x}_1 + C_{j,2}\,\mathbf{x}_2 + \ldots + C_{j,n}\,\mathbf{x}_n + D_{j,1}\,\mathbf{u}_1 + D_{j,2}\,\mathbf{u}_2 + \ldots + D_{j,m}\,\mathbf{u}_m$$

Input-Output Linearity



With a fixed initial state, a continuous-time component H maps input signals **I**(t) to output signals **O**(t)

Theorem: If H is linear, then both of the following hold.

1. *Scaling*: If the output response of H to signal **I**(t) is **O**(t), then for every constant α, the output response of H to signal α**I**(t) is α**O**(t)
2. *Additivity*: If the output responses of H to signals $\mathbf{I}_1(t)$ and $\mathbf{I}_2(t)$ are $\mathbf{O}_1(t)$ and $\mathbf{O}_2(t)$, then the output response of H to signal $(\mathbf{I}_1 + \mathbf{I}_2)(t)$ is $(\mathbf{O}_1 + \mathbf{O}_2)(t)$

Response of Linear Systems

Consider a one-dimensional linear system with no inputs:

$$d\mathbf{x} = a\mathbf{x} \;\; ; \;\; \text{initial state } x_0$$

Its execution is given by the signal

$$\mathbf{x}(t) = x_0 \, e^{at} \qquad (1)$$

- Recall that $e^a = 1 + \sum_{n>0} a^n/n!$
- Verify that solution $\mathbf{x}(t)$ satisfies the differential equation (1)
- See textbook on how solution is found

Response of Linear Systems

General Case with no inputs

State set **S**

Dynamics is given by

$$d\mathbf{S} = A\,\mathbf{S}$$

initial state s_0

Execution is described by the signal

$$\mathbf{S}(t) = e^{At}\, s_0$$

- $A\,t$ = scalar product of A and t
- $e^M = I + M + M^2/2 + M^3/3! + M^4/4! + \ldots = I + \sum_{n>0} M^n/n!$
- I = identity matrix ($I_{i,j}$ = if (i = j) then 1 else 0)

Response of Linear Systems

General Case with inputs input signal $\mathbf{I}(t)$

State set $\mathbf{S}$, input set $\mathbf{I}$

Dynamics is given by

$$d\mathbf{S} = A\,\mathbf{S} + B\,\mathbf{I}$$

initial state s_0

Execution is described by the signal

$$\mathbf{S}(t) = e^{At}\,s_0 + \int_0^t \left(e^{A(t-\tau)}\,B\,\mathbf{I}(\tau)\,d\tau\right)$$

Matrix Exponential

Matrix exponential $e^A = I + A + A^2/2 + A^3/3! + A^4/4! + \ldots$

Each term in the sum is an $n \times n$ matrix

How do we compute e^A?

- If $A^k = 0$ for some k, the sum is finite and can be computed directly
- If A is a diagonal matrix $\mathbf{D}(a_1, a_2, \ldots, a_n)$ (A_{ij} = if (i = j) then a_i else 0), then $e^A = \mathbf{D}(e^{a1}, e^{a2}, \ldots, e^{an})$
- In general, the sum of the first k terms will give an approximation with quality proportional to k
- Otherwise, we can use analytical methods based on eigenvalues and similarity transformations

Eigenvalues and Eigenvectors

Let A be an $n \times n$ matrix, λ a scalar value and x an n-dimensional non-zero vector

If $A\,x = \lambda\,x$, then x is an *eigenvector* of A and λ is the corresponding *eigenvalue*

How to compute eigenvalues and eigenvectors?

We solve the *characteristic equation* of A:

$$\det(A - \lambda I) = 0$$

Recall: the *determinant* $\det(M)$ of a 2×2 matrix M is

$$M_{1,1}M_{2,2} - M_{1,2}M_{2,1}$$

Eigenvalues and Eigenvectors

The eigenvalues of an $n \times n$ matrix A are the roots of the *characteristic polynomial* $p = \det(A - \lambda I)$

Note:

- The multiplicity of an eigenvalue (as a root of p) can be > 1
- An eigenvalue can be a complex number
- If A is a diagonal matrix, its eigenvalues are exactly its diagonal elements
- For a given eigenvalue λ, we can compute the corresponding eigenvector(s) by solving the linear system $A x = \lambda x$, with vector x of unknowns
- If all eigenvalues of are A distinct, then the set of corresponding eigenvectors is linearly independent

Similarity Transformation

Where P is an invertible $n \times n$ matrix of reals, consider the systems

H w/o inputs and with dynamics $\quad d\mathbf{S} = A\,\mathbf{S}$; s_0 (initial state)

H' w/o inputs and with dynamics $\quad d\mathbf{S}' = J\,\mathbf{S}'$; s'_0

where $\mathbf{S}' = P^{-1}\,\mathbf{S}$, $\quad J = P^{-1}\,A\,P$, $\quad s'_0 = P^{-1}\,s_0$

Then, $\quad \mathbf{S}'(t) = e^{Jt}\,s'_0$ $\quad$ and. $\quad \mathbf{S}(t) = P\,e^{Jt}\,P^{-1}\,s_0$

Note:

- H' is called the *transformed system* (since $S' = P^{-1}\,S$)
- Matrix $J = P^{-1}\,A\,P$ is said to be *similar* to A
- $d\mathbf{S}' = d(P^{-1}\,\mathbf{S}) = P^{-1}\,d\mathbf{S} = P^{-1}\,A\,\mathbf{S} = P^{-1}\,A\,P\,P^{-1}\,\mathbf{S} = P^{-1}\,A\,P\,\mathbf{S}' = J\,\mathbf{S}'$
- When is this useful? When can choose P so that J is diagonal

Similarity Transformation using Eigenvectors

Consider system H with dynamics given by:

$$d\mathbf{S} = A\,\mathbf{S} \;\; ; \;\; \text{initial state } s_0$$

1. Calculate eigenvalues $\lambda_1, \ldots, \lambda_n$ and suppose they are all distinct
2. Calculate corresponding eigenvectors $x_1, \ldots, x_n$
   (which must be linearly independent, vertical vectors of size n)
3. Consider the $n \times n$ matrix $P = (x_1 \;\; x_2 \;\; \ldots \;\; x_n)$
4. Find its inverse P^{-1} (which must exist in this case)

Claim: The matrix $J = P^{-1} A P$ is the diagonal matrix $\mathbf{D}(\lambda_1, \ldots, \lambda_n)$

Then, execution of H is given by:

$$\mathbf{S}(t) = P\,\mathbf{D}(e^{\lambda 1\, t}, \ldots, e^{\lambda n\, t})\,P^{-1}\,s_0$$

Example: Response of Linear Systems

Consider 2-dimensional system with dynamics given by

$ds_1 = 4\,s_1 + 6\,s_2$ initial state $(s_1, s_2) = (1, 1)^T$

$ds_2 = s_1 + 3\,s_2$

1. Compute eigenvalues λ_1 and λ_2 of $A = ((4\ \ 1)^T\ (6\ \ 3)^T)$
   - $\lambda_1 = 6$ and $\lambda_2 = 1$
2. Compute eigenvectors x_1 and x_2
   - $x_1 = (3\ \ 1)^T$ and $x_2 = (2\ \ -1)^T$
3. Choose the similarity transformation matrix $P = (x_1\ \ x_2) = ((3\ \ 1)^T\ \ (2\ \ -1)^T)$
4. Compute the inverse P^{-1} of P
   - $P^{-1} = ((-1\ \ -1)^T\ \ (-2\ \ 3)^T) / (-3-2) = ((1/5\ \ 1/5)^T\ \ (2/5\ \ -3/5)^T)$
5. Verify that $J = P^{-1} A P$ is diagonal matrix $\mathbf{D}(\lambda_1, \lambda_2) = ((6\ \ 0)^T\ \ (0\ \ 1)^T)$
   - $J = P^{-1} A P = ((6/5\ \ 1/5)^T\ \ (12/5\ \ -3/5)^T)\ ((3\ \ 1)^T\ \ (2\ \ -1)^T) = ((6\ \ 0)^T\ \ (0\ \ 1)^T)$
6. Desired solution is $\mathbf{S}(t) = P\ \mathbf{D}(e^{\lambda 1\, t}, e^{\lambda 2\, t})\ P^{-1}\ (1, 1)^T$
   - $\mathbf{S}(t) = ((3\ \ 1)^T\ \ (2\ \ -1)^T)\ ((e^{6t}\ \ 0)^T\ \ (0\ \ e^t)^T)\ ((1/5\ \ 1/5)^T\ \ (2/5\ \ -3/5)^T)\ (1, 1)^T = \ldots$

Back to Equilibria and Stability

Consider a closed linear system H with dynamics given by:

$$d\mathbf{S} = A\,\mathbf{S}$$

Recall: a state s is an equilibrium state of H if $A\,s = 0$

How to compute equilibria: solve system of linear equations

Prop. 1: State 0 is an equilibrium

Prop. 2: If A is invertible, then 0 is the sole equilibrium

If state s is a non-zero equilibrium of H, consider the transformed system H' with state $S' = S - s$

The equilibria 0 of H' and s of H have the same properties

Back to Equilibria and Stability

Henceforth, we will focus on closed linear systems H and their equilibrium state 0

Definition:

1. H is *stable* if state 0 is stable
2. H is *asymptotically stable* if state 0 is asymptotically stable

Stability: One-Dimensional System

Consider a 1-dimensional linear system H with dynamics given by:

$$dx = a\,x \;;\; s_0$$

Recall: H is asymptotically stable iff 0 is asymptotically stable iff

1. (Stable) For every $\varepsilon > 0$, there is a $\delta > 0$ such that for all initial states s with $||s|| < \delta$ and for all times t, $||e^{at}\,s|| < \varepsilon$
2. (Asymptotically) There is a $\delta > 0$ such that for all initial states s with $||s|| < \delta$, $||e^{at}\,s||$ goes to 0 as t goes to ∞

A. Case a < 0: $e^{at}\,s$ converges exponentially to 0 as t goes to ∞, regardless of s.
Asymptotically stable

B. Case a = 0: dynamics is $dx = 0$. The state stays equal to initial state s_0.
Stable but not asymptotically stable (unless $s_0 = 0$)

C. Case a > 0: $e^{at}\,s$ grows exponentially as t increases, and thus, state diverges away from 0.
Unstable!

Stability: Diagonal State Dynamics

Consider an n-dimensional linear system H with dynamics given by:

$$dS = A\,S;\ s \quad \text{with } A = \mathbf{D}(a_1, \ldots, a_n)$$

Each dimension evolves independently: the i-th component of $\mathbf{S}(t)$ is $e^{a_i t}\, s_i$

A. **All coefficients $a_i < 0$**: State converges to the equilibrium 0 regardless of s. Asymptotically stable

B. **All coefficients $a_i \leq 0$**: Stable but not asymptotically stable if some coefficient $a_j = 0$ (j-th state component stays unchanged)

C. **Some coefficient $a_i > 0$**: Some state component grows unboundedly away from equilibrium 0. Unstable!

Similarity Transformations and Stability

Consider system H with dynamics given by $dS = A\,S\,;\, s_0$

Let P be an invertible $n \times n$ matrix, and $J = P^{-1} A\, P$

Consider system H' with state $S' = P^{-1} S$ (and note that $S = P\, S'$)

Response signal of transformed system H': $\mathbf{S'}(t) = e^{Jt} P^{-1} s_0$

Response signal of original system H: $\mathbf{S}(t) = P\, e^{Jt} P^{-1} s_0$

Note: Response $\mathbf{S'}(t)$ is a linear transformation of $\mathbf{S}(t)$ and vice versa. Hence:

- If $\mathbf{S}(t)$ is bounded iff $\mathbf{S'}(t)$ is bounded
- If $\mathbf{S}(t)$ converges to 0 iff $\mathbf{S'}(t)$ converges to 0

Prop. 1: H is stable iff H' is stable

Prop. 2: H is asymptotically stable iff H' is asymptotically stable

Eigenvalues and Stability


Consider system H with dynamics given by $dS = A\,S$

Suppose all eigenvalues $\lambda_1, \ldots, \lambda_n$ of A are real and distinct

- Then the set of eigenvectors, $x_1, \ldots, x_n$ is guaranteed to be linearly independent
- Choose $n \times n$ matrix $P = (x_1\ x_2\ \ldots\ x_n)$ for similarity transformation
- The matrix $J = P^{-1} A P$ is the diagonal matrix $\mathbf{D}(\lambda_1, \ldots, \lambda_n)$
- If all eigenvalues are negative, then the transformed system H' is asymptotically stable, and so is H
- If all eigenvalues are non-positive, then H' is stable, and so is H

Theorem: A system H with dynamics $dS = A\,S$ is asymptotically stable iff each eigenvalue of A has a negative real part

Continuous-time Component Car



- Let $S = (x \;\; v)^T$
- The matrix A is $((0 \;\; 0)^T \;\; (1 \;\; -k/m)^T)$
- Eigenvalues: 0 and $-k/m$
- Stable but not asymptotically stable
- If we consider only the dimension v, then asymptotically stable

Exercise: Set $\mathbf{F}(t) = 0$ for all t, and analyze what happens if we perturb the system from the equilibrium $(0 \;\; 0)^T$

Lyapunov Stability vs BIBO Stability

Consider linear component H with dynamics given by

$$dS = A\,S + B\,I \qquad O = C\,S + D\,I$$

BIBO stability: Starting from initial state 0, if the input is a bounded signal, output must be a bounded signal

Theorem: For linear components, asymptotic stability implies BIBO stability

Proof of the theorem relies of analysis of dynamical systems using transfer functions

Note: Asymptotic stability depends only on the properties of matrix A

Credits

Notes based on Chapter 6 of

Principles of Cyber-Physical Systems
by Rajeev Alur
MIT Press, 2015