Implemented?	Frame	User? href	Description	extid	Device Type	Manufacturer	API Class	API Index	API	Mask	Device ID	Frame Type	Frame Length	RTR?	Data[0]	Data[1]	Data[2]	Data[3]			Data[6]	Data[7]	Enabled By Default	Default Rate?	Response
21.0.1	Status0	Y		8051800	powerDistribution	REV	6	0	0x60	0		Repeating Status	8	N			CH2_L4			CH4_L6	CH4_H4 CH5_L4	CH5_H6 Brownout 2-3	Y	20ms	
21.0.1	Status1	Y		8051840	powerDistribution	REV	6	1	0x61	0		Repeating Status	8	N	CH6_L8	CH6_H2 CH7_L6	CH7_H4 CH8_L4	CH8_H6 Brownout 4-5	CH9_L8	CH9_H2 CH10_L6	CH10_H4 CH11_L4	CH11_H6 Brownout 6-7	Y	20ms	
21.0.1	Status2	Υ		8051880	powerDistribution	REV	6	2	0x62	0		Repeating Status	8	N	CH12_L8	CH12_H2 CH13_L6	CH13_H4 CH14_L4	CH14_H6 Brownout 8-9	CH15_L8	CH15_H2 CH16_L6	CH16_H4 CH17_L4	CH17_H6 Brownout 10-11	Y	20ms	
21.0.1	Status3	Y			powerDistribution		6	3	0x63	0		Repeating Status	8	N	CH18 L8	CH18_H2 CH19_L6	CH19_H4 Brownout 12-15	CH20	CH21	CH22	CH23	Brownout 16-23	Υ	20ms	
																VBus_H4 System Enabled roboRIO Present	Faults and	Faults and							
21.0.1	Status4	Y		8051900	powerDistribution	REV	6	4	0x64	0		Repeating Status	8	N N					Total Current (2A Resolution)	<free></free>	<free></free>	<free></free>	Y	20ms	ĺ
21.0.1	SwitchChannelSet	Υ		8050840	powerDistribution	REV	2	1	0x21	0		Incoming Command	1	N	Enable/Disable									<i>i</i> '	
																								<i>i</i> '	ſ
21.0.1	Version	Y		8052600	powerDistribution	REV	9	8	0x98	0		Incoming Command	8				Firmware Major Version/Year		Hardware Major Version	Unique ID	Unique ID	Unique ID		ĺ	
21.1.0	Clear Faults	Υ		8051B80	powerDistribution	REV	6	14	0x6E	0		Incoming Command	0	N											ĺ