

M68000UM/AD
REV 8

M68000

MC68000
MC68008
MC68010
MC68HC000
MC68HC001
and the New
MC68EC000

8-/16-/32-Bit
Microprocessor User's Manual
Ninth Edition

Overview	1
Introduction	2
Signal Description	3
8-Bit Bus Operation	4
16-Bit Bus Operation	5
Exception Processing	6
8-Bit Instruction Execution Times	7
16-Bit Instruction Execution Times	8
MC68010 Instruction Execution Times	9
Electrical and Thermal Characteristics	10
Ordering Information and Mechanical Data	11
MC68010 Loop Mode Operation	A
M6800 Peripheral Interface	B
Index	I



M68000

8-/16-/32-Bit

Microprocessors User's Manual

Ninth Edition

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

68K FAX-IT

Documentation Comments

FAX 512-891-8593—Documentation Comments Only

The Motorola High-End Technical Publications Department provides a fax number for you to submit any questions or comments about this document or how to order other documents. We welcome your suggestions for improving our documentation. Please do not fax technical questions.

Please provide the part number and revision number (located in upper right-hand corner of the cover) and the title of the document. When referring to items in the manual, please reference by the page number, paragraph number, figure number, table number, and line number if needed.

When sending a fax, please provide your name, company, fax number, and phone number including area code.

Applications and Technical Information

For questions or comments pertaining to technical information, questions, and applications, please contact one of the following sales offices nearest you.

— Sales Offices —

UNITED STATES

ALABAMA, Huntsville	(205) 464-6800
ARIZONA, Tempe	(602) 897-5056
CALIFORNIA, Agoura Hills	(818) 706-1929
CALIFORNIA, Los Angeles	(310) 417-8848
CALIFORNIA, Irvine	(714) 753-7360
CALIFORNIA, Roseville	(916) 922-7152
CALIFORNIA, San Diego	(619) 541-2163
CALIFORNIA, Sunnyvale	(408) 749-0510
COLORADO, Colorado Springs	(719) 599-7497
COLORADO, Denver	(303) 337-3434
CONNECTICUT, Wallingford	(203) 949-4100
FLORIDA, Maitland	(407) 628-2636
FLORIDA, Pompano Beach/ Fort Lauderdale	(305) 486-9776
FLORIDA, Clearwater	(813) 538-7750
GEORGIA, Atlanta	(404) 729-7100
IDAHO, Boise	(208) 323-9413
ILLINOIS, Chicago/Hoffman Estates	(708) 490-9500
INDIANA, Fort Wayne	(219) 436-5818
INDIANA, Indianapolis	(317) 571-0400
INDIANA, Kokomo	(317) 457-6634
IOWA, Cedar Rapids	(319) 373-1328
KANSAS, Kansas City/Mission	(913) 451-8555
MARYLAND, Columbia	(410) 381-1570
MASSACHUSETTS, Marlborough	(508) 481-8100
MASSACHUSETTS, Woburn	(617) 932-9700
MICHIGAN, Detroit	(313) 347-6800
MINNESOTA, Minnetonka	(612) 932-1500
MISSOURI, St. Louis	(314) 275-7380
NEW JERSEY, Fairfield	(201) 808-2400
NEW YORK, Fairport	(716) 425-4000
NEW YORK, Hauppauge	(516) 361-7000
NEW YORK, Poughkeepsie/Fishkill	(914) 473-8102
NORTH CAROLINA, Raleigh	(919) 870-4355
OHIO, Cleveland	(216) 349-3100
OHIO, Columbus Worthington	(614) 431-8492
OHIO, Dayton	(513) 495-6800
OKLAHOMA, Tulsa	(800) 544-9496
OREGON, Portland	(503) 641-3681
PENNSYLVANIA, Colmar Philadelphia/Horsham	(215) 997-1020 (215) 957-4100
TENNESSEE, Knoxville	(615) 690-5593
TEXAS, Austin	(512) 873-2000
TEXAS, Houston	(800) 343-2692
TEXAS, Plano	(214) 516-5100
VIRGINIA, Richmond	(804) 285-2100
WASHINGTON, Bellevue Seattle Access	(206) 454-4160 (206) 622-9960
WISCONSIN, Milwaukee/Brookfield	(414) 792-0122

Field Applications Engineering Available
Through All Sales Offices

CANADA

BRITISH COLUMBIA, Vancouver	(604) 293-7605
ONTARIO, Toronto	(416) 497-8181
ONTARIO, Ottawa	(613) 226-3491
QUEBEC, Montreal	(514) 731-6881

INTERNATIONAL

AUSTRALIA, Melbourne	(61-3)887-0711
AUSTRALIA, Sydney	(61-2)906-3855
BRAZIL, Sao Paulo	55(11)815-4200
CHINA, Beijing	86 505-2180

FINLAND, Helsinki	358-0-35161191
Car Phone	358(49)211501
FRANCE, Paris/Vanves	33(1)40 955 900
GERMANY, Langenhagen/ Hanover	49(511)789911
GERMANY, Munich	49 89 92103-0
GERMANY, Nuremberg	49 911 64-3044
GERMANY, Sindelfingen	49 7031 69 910
GERMANY, Wiesbaden	49 611 761921
HONG KONG, Kwai Fong	852-4808333
Tai Po	852-6668333
INDIA, Bangalore	(91-812)627094
ISRAEL, Tel Aviv	972(3)753-8222
ITALY, Milan	39(2)82201
JAPAN, Aizu	81(241)272231
JAPAN, Atsugi	81(0462)23-0761
JAPAN, Kumagaya	81(0485)26-2600
JAPAN, Kyushu	81(092)771-4212
JAPAN, Mito	81(0292)26-2340
JAPAN, Nagoya	81(052)232-1621
JAPAN, Osaka	81(06)305-1801
JAPAN, Sendai	81(22)268-4333
JAPAN, Tachikawa	81(0425)23-6700
JAPAN, Tokyo	81(03)3440-3311
JAPAN, Yokohama	81(045)472-2751
KOREA, Pusan	82(51)4635-035
KOREA, Seoul	82(2)554-5188
MALAYSIA, Penang	60(4)374514
MEXICO, Mexico City	52(5)282-2864
MEXICO, Guadalajara	52(36)21-8977
Marketing	52(36)21-9023
Customer Service	52(36)669-9160
NETHERLANDS, Best	(31)49988 612 11
PUERTO RICO, San Juan	(809)793-2170
SINGAPORE	(65)2945438
SPAIN, Madrid	34(1)457-8204
or	34(1)457-8254
SWEDEN, Solna	46(8)734-8800
SWITZERLAND, Geneva	41(22)7991111
SWITZERLAND, Zurich	41(1)730 4074
TAIWAN, Taipei	886(2)717-7089
THAILAND, Bangkok	(66-2)254-4910
UNITED KINGDOM, Aylesbury	44(296)395-252

FULL LINE REPRESENTATIVES

COLORADO, Grand Junction	
Cheryl Lee Whitely	(303) 243-9658
KANSAS, Wichita	
Melinda Shores/Kelly Greiving	(316) 838 0190
NEVADA, Reno	
Galena Technology Group	(702) 746 0642
NEW MEXICO, Albuquerque	
S&S Technologies, Inc.	(505) 298-7177
UTAH, Salt Lake City	
Utah Component Sales, Inc.	(801) 561-5099
WASHINGTON, Spokane	
Doug Kenley	(509) 924-2322
ARGENTINA, Buenos Aires	
Argonics, S.A.	(541) 343-1787

HYBRID COMPONENTS RESELLERS

Elmo Semiconductor	(818) 768-7400
Minco Technology Labs Inc.	(512) 834-2022
Semi Dice Inc.	(310) 594-4631

TABLE OF CONTENTS

Paragraph Number	Title	Page Number
Section 1		
Overview		
1.1	MC68000	1-1
1.2	MC68008	1-2
1.3	MC68010	1-2
1.4	MC68HC000	1-2
1.5	MC68HC001	1-3
1.6	MC68EC000	1-3
Section 2		
Introduction		
2.1	Programmer's Model	2-1
2.1.1	User's Programmer's Model	2-1
2.1.2	Supervisor Programmer's Model	2-2
2.1.3	Status Register	2-3
2.2	Data Types and Addressing Modes	2-3
2.3	Data Organization In Registers	2-5
2.3.1	Data Registers	2-5
2.3.2	Address Registers	2-6
2.4	Data Organization In Memory	2-6
2.5	Instruction Set Summary	2-8
Section 3		
Signal Description		
3.1	Address Bus	3-3
3.2	Data Bus	3-4
3.3	Asynchronous Bus Control	3-4
3.4	Bus Arbitration Control	3-5
3.5	Interrupt Control	3-6
3.6	System Control	3-7
3.7	M6800 Peripheral Control	3-8
3.8	Processor Function Codes	3-8
3.9	Clock	3-9
3.10	Power Supply	3-9
3.11	Signal Summary	3-10

TABLE OF CONTENTS (Continued)

Paragraph Number	Title	Page Number
Section 4		
8-Bit Bus Operations		
4.1	Data Transfer Operations.....	4-1
4.1.1	Read Operations	4-1
4.1.2	Write Cycle	4-3
4.1.3	Read-Modify-Write Cycle.....	4-5
4.2	Other Bus Operations.....	4-8
Section 5		
16-Bit Bus Operations		
5.1	Data Transfer Operations.....	5-1
5.1.1	Read Operations	5-1
5.1.2	Write Cycle	5-4
5.1.3	Read-Modify-Write Cycle.....	5-7
5.1.4	CPU Space Cycle.....	5-9
5.2	Bus Arbitration	5-11
5.2.1	Requesting The Bus.....	5-14
5.2.2	Receiving The Bus Grant	5-15
5.2.3	Acknowledgment of Mastership (3-Wire Arbitration Only).....	5-15
5.3	Bus Arbitration Control	5-15
5.4	Bus Error and Halt Operation.....	5-23
5.4.1	Bus Error Operation	5-24
5.4.2	Retrying The Bus Cycle.....	5-26
5.4.3	Halt Operation	5-27
5.4.4	Double Bus Fault	5-28
5.5	Reset Operation.....	5-29
5.6	The Relationship of <u>DTACK</u> , <u>BERR</u> , and <u>HALT</u>	5-30
5.7	Asynchronous Operation	5-32
5.8	Synchronous Operation	5-35
Section 6		
Exception Processing		
6.1	Privilege Modes.....	6-1
6.1.1	Supervisor Mode	6-2
6.1.2	User Mode.....	6-2
6.1.3	Privilege Mode Changes	6-2
6.1.4	Reference Classification.....	6-3
6.2	Exception Processing.....	6-4
6.2.1	Exception Vectors	6-4
6.2.2	Kinds Of Exceptions	6-5
6.2.3	Multiple Exceptions.....	6-8

TABLE OF CONTENTS (Continued)

Paragraph Number	Title	Page Number
Section 10		
Electrical and Thermal Characteristics		
10.9	MC68008 AC Electrical Specifications—Clock Timing	10-9
10.10	AC Electrical Specifications—Read and Write Cycles	10-10
10.11	AC Electrical Specifications—MC68000 To M6800 Peripheral.....	10-15
10.12	AC Electrical Specifications—Bus Arbitration	10-17
10.13	MC68EC000 DC Electrical Specifications	10-23
10.14	MC68EC000 AC Electrical Specifications—Read and Write	10-24
10.15	MC68EC000 AC Electrical Specifications—Bus Arbitration	10-28
Section 11		
Ordering Information and Mechanical Data		
11.1	Pin Assignments	11-1
11.2	Package Dimensions	11-7
Appendix A		
MC68010 Loop Mode Operation		
Appendix B		
M6800 Peripheral Interface		
B.1	Data Transfer Operation.....	B-1
B.2	Interrupt Interface Operation	B-4

LIST OF ILLUSTRATIONS

Figure Number	Title	Page Number
2-1	User Programmer's Model	2-2
2-2	Supervisor Programmer's Model Supplement	2-2
2-3	Supervisor Programmer's Model Supplement (MC68010)	2-3
2-4	Status Register	2-3
2-5	Word Organization In Memory	2-6
2-6	Data Organization In Memory	2-7
2-7	Memory Data Organization (MC68008)	2-3
3-1	Input and Output Signals (MC68000, MC68HC000, MC68010)	3-1
3-2	Input and Output Signals (MC68HC001)	3-2
3-3	Input and Output Signals (MC68EC000)	3-2
3-4	Input and Output Signals (MC68008 48-Pin Version)	3-3
3-5	Input and Output Signals (MC68008 52-Pin Version)	3-3
4-1	Byte Read-Cycle Flowchart.....	4-2
4-2	Read and Write-Cycle Timing Diagram.....	4-2
4-3	Byte Write-Cycle Flowchart.....	4-4
4-4	Write-Cycle Timing Diagram	4-4
4-5	Read-Modify-Write Cycle Flowchart	4-6
4-6	Read-Modify-Write Cycle Timing Diagram.....	4-7
5-1	Word Read-Cycle Flowchart	5-2
5-2	Byte Read-Cycle Flowchart.....	5-2
5-3	Read and Write-Cycle Timing Diagram.....	5-3
5-4	Word and Byte Read-Cycle Timing Diagram	5-3
5-5	Word Write-Cycle Flowchart	5-5
5-6	Byte Write-Cycle Flowchart.....	5-5
5-7	Word and Byte Write-Cycle Timing Diagram	5-6
5-8	Read-Modify-Write Cycle Flowchart	5-7
5-9	Read-Modify-Write Cycle Timing Diagram.....	5-8
5-10	CPU Space Address Encoding	5-9
5-11	Interrupt Acknowledge Cycle Timing Diagram	5-10
5-12	Breakpoint Acknowledge Cycle Timing Diagram	5-11
5-13	3-Wire Bus Arbitration Flowchart (NA to 48-Pin MC68008 and MC68EC000)	5-12
5-14	2-Wire Bus Arbitration Cycle Flowchart	5-13

LIST OF ILLUSTRATIONS (Continued)

Figure Number	Title	Page Number
5-15	3-Wire Bus Arbitration Timing Diagram (NA to 48-Pin MC68008 and MC68EC000	5-13
5-16	2-Wire Bus Arbitration Timing Diagram	5-14
5-17	External Asynchronous Signal Synchronization	5-16
5-18	Bus Arbitration Unit State Diagrams	5-17
5-19	3-Wire Bus Arbitration Timing Diagram—Processor Active	5-18
5-20	3-Wire Bus Arbitration Timing Diagram—Bus Active	5-19
5-21	3-Wire Bus Arbitration Timing Diagram—Special Case	5-20
5-22	2-Wire Bus Arbitration Timing Diagram—Processor Active	5-21
5-23	2-Wire Bus Arbitration Timing Diagram—Bus Active	5-22
5-24	2-Wire Bus Arbitration Timing Diagram—Special Case	5-23
5-25	Bus Error Timing Diagram	5-24
5-26	Delayed Bus Error Timing Diagram (MC68010)	5-25
5-27	Retry Bus Cycle Timing Diagram	5-26
5-28	Delayed Retry Bus Cycle Timing Diagram	5-27
5-29	Halt Operation Timing Diagram	5-28
5-30	Reset Operation Timing Diagram	5-29
5-31	Fully Asynchronous Read Cycle	5-32
5-32	Fully Asynchronous Write Cycle	5-33
5-33	Pseudo-Asynchronous Read Cycle	5-34
5-34	Pseudo-Asynchronous Write Cycle	5-35
5-35	Synchronous Read Cycle	5-37
5-36	Synchronous Write Cycle	5-38
5-37	Input Synchronizers	5-38
6-1	Exception Vector Format	6-4
6-2	Peripheral Vector Number Format	6-5
6-3	Address Translated from 8-Bit Vector Number	6-5
6-4	Exception Vector Address Calculation (MC68010)	6-5
6-5	Group 1 and 2 Exception Stack Frame	6-10
6-6	MC68010 Stack Frame	6-10
6-7	Supervisor Stack Order for Bus or Address Error Exception	6-17
6-8	Exception Stack Order (Bus and Address Error)	6-18
6-9	Special Status Word Format	6-19
10-1	MC68000 Power Dissipation (P_D) vs Ambient Temperature (T_A)	10-3
10-2	Drive Levels and Test Points for AC Specifications	10-6
10-3	Clock Input Timing Diagram	10-9
10-4	Read Cycle Timing Diagram	10-13
10-5	Write Cycle Timing Diagram	10-14
10-6	MC68000 to M6800 Peripheral Timing Diagram (Best Case)	10-16

LIST OF ILLUSTRATIONS (Concluded)

Figure Number	Title	Page Number
10-7	Bus Arbitration Timing	10-18
10-8	Bus Arbitration Timing	10-19
10-9	Bus Arbitration Timing—Idle Bus Case	10-20
10-10	Bus Arbitration Timing—Active Bus Case	10-21
10-11	Bus Arbitration Timing—Multiple Bus Request	10-22
10-12	MC68EC000 Read Cycle Timing Diagram	10-26
10-13	MC68EC000 Write Cycle Timing Diagram	10-27
10-14	MC68EC000 Bus Arbitration Timing Diagram	10-29
11-1	64-Pin Dual In Line	11-2
11-2	68-Lead Pin Grid Array	11-3
11-3	68-Lead Quad Pack	11-4
11-4	52-Lead Quad Pack	11-5
11-5	48-Pin Dual In Line	11-6
11-6	64-Lead Quad Flat Pack	11-7
11-7	Case 740-03—L Suffix	11-8
11-8	Case 767-02—P Suffix	11-9
11-9	Case 746-01—LC Suffix	11-10
11-10	Case — Suffix	11-
11-11	Case 765A-05—RC Suffix	11-12
11-12	Case 778-02—FN Suffix	11-13
11-13	Case 779-02—FN Suffix	11-14
11-14	Case 847-01—FC Suffix	11-15
11-15	Case 840B-01—FU Suffix	11-16
A-1	DBcc Loop Mode Program Example	A-1
B-1	M6800 Data Transfer Flowchart	B-1
B-2	Example External VMA Circuit	B-2
B-3	External VMA Timing	B-2
B-4	M6800 Peripheral Timing—Best Case	B-3
B-5	M6800 Peripheral Timing—Worst Case	B-3
B-6	Autovector Operation Timing Diagram	B-5

LIST OF TABLES

Table Number	Title	Page Number
2-1	Data Addressing Modes	2-4
2-2	Instruction Set Summary	2-11
3-1	Data Strobe Control of Data Bus	3-5
3-2	Data Strobe Control of Data Bus (MC68008)	3-5
3-3	Function Code Output	3-9
3-4	Signal Summary	3-10
5-1	$\overline{DTACK}$, $\overline{BERR}$, and $\overline{HALT}$ Assertion Results	5-31
6-1	Reference Classification	6-3
6-2	Exception Vector Assignment	6-7
6-3	Exception Grouping and Priority	6-9
6-4	MC68010 Format Code	6-11
7-1	Effective Address Calculation Times	7-2
7-2	Move Byte Instruction Execution Times	7-2
7-3	Move Word Instruction Execution Times	7-3
7-4	Move Long Instruction Execution Times	7-3
7-5	Standard Instruction Execution Times	7-4
7-6	Immediate Instruction Execution Times	7-5
7-7	Single Operand Instruction Execution Times	7-6
7-8	Shift/Rotate Instruction Execution Times	7-6
7-9	Bit Manipulation Instruction Execution Times	7-7
7-10	Conditional Instruction Execution Times	7-7
7-11	JMP, JSR, LEA, PEA, and MOVEM Instruction Execution Times	7-8
7-12	Multiprecision Instruction Execution Times	7-9
7-13	Miscellaneous Instruction Execution Times	7-10
7-14	Move Peripheral Instruction Execution Times	7-10
7-15	Exception Processing Instruction Execution Times	7-11
8-1	Effective Address Calculation Times	8-2
8-2	Move Byte Instruction Execution Times	8-2
8-3	Move Word Instruction Execution Times	8-3
8-4	Move Long Instruction Execution Times	8-3

LIST OF TABLES (Concluded)

Table Number	Title	Page Number
8-5	Standard Instruction Execution Times	8-4
8-6	Immediate Instruction Execution Times	8-5
8-7	Single Operand Instruction Execution Times	8-6
8-8	Shift/Rotate Instruction Execution Times	8-6
8-9	Bit Manipulation Instruction Execution Times	8-7
8-10	Conditional Instruction Execution Times	8-7
8-11	JMP, JSR, LEA, PEA, and MOVEM Instruction Execution Times	8-8
8-12	Multiprecision Instruction Execution Times	8-9
8-13	Miscellaneous Instruction Execution Times	8-10
8-14	Move Peripheral Instruction Execution Times	8-10
8-15	Exception Processing Instruction Execution Times	8-11
9-1	Effective Address Calculation Times	9-2
9-2	Move Byte and Word Instruction Execution Times	9-3
9-3	Move Byte and Word Instruction Loop Mode Execution Times	9-3
9-4	Move Long Instruction Execution Times	9-4
9-5	Move Long Instruction Loop Mode Execution Times	9-4
9-6	Standard Instruction Execution Times	9-5
9-7	Standard Instruction Loop Mode Execution Times	9-5
9-8	Immediate Instruction Execution Times	9-6
9-9	Single Operand Instruction Execution Times	9-7
9-10	Clear Instruction Execution Times	9-7
9-11	Single Operand Instruction Loop Mode Execution Times	9-8
9-12	Shift/Rotate Instruction Execution Times	9-8
9-13	Shift/Rotate Instruction Loop Mode Execution Times	9-9
9-14	Bit Manipulation Instruction Execution Times	9-9
9-15	Conditional Instruction Execution Times	9-10
9-16	JMP, JSR, LEA, PEA, and MOVEM Instruction Execution Times	9-10
9-17	Multiprecision Instruction Execution Times	9-11
9-18	Miscellaneous Instruction Execution Times	9-12
9-19	Exception Processing Instruction Execution Times	9-13
10-1	Power Dissipation and Junction Temperature vs Temperature ($\theta_{JC} = \theta_{JA}$)	10-4
10-2	Power Dissipation and Junction Temperature vs Temperature ($\theta_{JC} = \theta_{JC}$)	10-4
A-1	MC68010 Loop Mode Instructions	A-3

SECTION 1 OVERVIEW

This manual includes hardware details and programming information for the MC68000, the MC68HC000, the MC68HC001, the MC68008, the MC68010, and the MC68EC000. For ease of reading, the name M68000 MPUs will be used when referring to all processors. Refer to M68000PM/AD, *M68000 Programmer's Reference Manual*, for detailed information on the MC68000 instruction set.

The six microprocessors are very similar. They all contain the following features

- 16 32-Bit Data and Address Registers
- 16-Mbyte Direct Addressing Range
- Program Counter
- 6 Powerful Instruction Types
- Operations on Five Main Data Types
- Memory-Mapped Input/Output (I/O)
- 14 Addressing Modes

The following processors contain additional features:

- MC68010
 - Virtual Memory/Machine Support
 - High-Performance Looping Instructions
- MC68HC001/MC68EC000
 - Statically Selectable 8- or 16-Bit Data Bus
- MC68HC000/MC68EC000/MC68HC001
 - Low-Power

All the processors are basically the same with the exception of the MC68008. The MC68008 differs from the others in that the data bus size is eight bits, and the address range is smaller. The MC68010 has a few additional instructions and instructions that operate differently than the corresponding instructions of the other devices.

1.1 MC68000

The MC68000 is the first implementation of the M68000 16-/32 bit microprocessor architecture. The MC68000 has a 16-bit data bus and 24-bit address bus while the full architecture provides for 32-bit address and data buses. It is completely code-compatible with the MC68008 8-bit data bus implementation of the M68000 and is upward code compatible with the MC68010 virtual extensions and the MC68020 32-bit implementation of the architecture. Any user-mode programs using the MC68000 instruction set will run unchanged on the MC68008, MC68010, MC68020, MC68030, and MC68040. This is possible because the user programming model is identical for all processors and the instruction sets are proper subsets of the complete architecture.

1.2 MC68008

The MC68008 is a member of the M68000 family of advanced microprocessors. This device allows the design of cost-effective systems using 8-bit data buses while providing the benefits of a 32-bit microprocessor architecture. The performance of the MC68008 is greater than any 8-bit microprocessor and superior to several 16-bit microprocessors.


The MC68008 is available as a 48-pin dual-in-line package (plastic or ceramic) and 52-pin plastic leaded chip carrier. The additional four pins of the 52-pin package allow for additional signals: A20, A21, $\overline{\text{BGACK}}$, and $\overline{\text{IPL2}}$. The 48-pin version supports a 20-bit address that provides a 1-Mbyte address space; the 52-pin version supports a 22-bit address that extends the address space to 4 Mbytes. The 48-pin MC68008 contains a simple two-wire arbitration circuit; the 52-pin MC68008 contains a full three-wire MC68000 bus arbitration control. Both versions are designed to work with daisy-chained networks, priority encoded networks, or a combination of these techniques.

A system implementation based on an 8-bit data bus reduces system cost in comparison to 16-bit systems due to a more effective use of components and byte-wide memories and peripherals. In addition, the nonmultiplexed address and data buses eliminate the need for external demultiplexers, further simplifying the system.

The large nonsegmented linear address space of the MC68008 allows large modular programs to be developed and executed efficiently. A large linear address space allows program segment sizes to be determined by the application rather than forcing the designer to adopt an arbitrary segment size without regard to the application's individual requirements.

1.3 MC68010

The MC68010 utilizes VLSI technology and is a fully implemented 16-bit microprocessor with 32-bit registers, a rich basic instruction set, and versatile addressing modes. The vector base register (VBR) allows the vector table to be dynamically relocated



**Figure 2-1. User Programmer's Model
(MC68000/MC68HC000/MC68008/MC68010)**

2.1.2 Supervisor Programmer's Model

The supervisor programmer's model consists of supplementary registers used in the supervisor mode. The M68000 MPUs contain identical supervisor mode register resources, which are shown in Figure 2-2, including the status register (high-order byte) and the supervisor stack pointer (SSP/A7').




Figure 2-2. Supervisor Programmer's Model Supplement

The supervisor programmer's model supplement of the MC68010 is shown in Figure 2-3. In addition to the supervisor stack pointer and status register, it includes the vector base register (VRB) and the alternate function code registers (AFC). The VBR is used to determine the location of the exception vector table in memory to support multiple vector

tables. The SFC and DFC registers allow the supervisor to access user data space or emulate CPU space cycles.




Figure 2-3. Supervisor Programmer's Model Supplement (MC68010)

2.1.3 Status Register

The status register (SR) contains the interrupt mask (eight levels available) and the following condition codes: overflow (V), zero (Z), negative (N), carry (C), and extend (X). Additional status bits indicate that the processor is in the trace (T) mode and/or in the supervisor (S) state (see Figure 2-4). Bits 5, 6, 7, 11, 12, and 14 are undefined and reserved for future expansion




Figure 2-4. Status Register

2.2 DATA TYPES AND ADDRESSING MODES

The five basic data types supported are as follows:

1. Bits
2. Binary-Coded-Decimal (BCD) Digits (4 Bits)
3. Bytes (8 Bits)
4. Words (16 Bits)
5. Long Words (32 Bits)

Table 2-1. Data Addressing Modes

Mode	Generation	Syntax
Register Direct Addressing Data Register Direct Address Register Direct	EA=Dn EA=An	Dn An
Absolute Data Addressing Absolute Short Absolute Long	EA = (Next Word) EA = (Next Two Words)	(xxx).W (xxx).L
Program Counter Relative Addressing Relative with Offset Relative with Index and Offset	EA = (PC)+d ₁₆ EA = (PC)+d ₈	(d ₁₆ ,PC) (d ₈ ,PC,Xn)
Register Indirect Addressing Register Indirect Postincrement Register Indirect Predecrement Register Indirect Register Indirect with Offset Indexed Register Indirect with Offset	EA = (An) EA = (An), An ← An+N An ← An-N, EA=(An) EA = (An)+d ₁₆ EA = (An)+(Xn)+d ₈	(An) (An)+ -(An) (d ₁₆ ,An) (d ₈ ,An,Xn)
Immediate Data Addressing Immediate Quick Immediate	DATA = Next Word(s) Inherent Data	#<data>
Implied Addressing¹ Implied Register	EA = SR, USP, SSP, PC, VBR, SFC, DFC	SR,USP,SSP,PC, VBR, SFC,DFC

NOTES: 1. The VBR, SFC, and DFC apply to the MC68010 only

EA = Effective Address
Dn = Data Register
An = Address Register
() = Contents of
PC = Program Counter
d₈ = 8-Bit Offset (Displacement)
d₁₆ = 16-Bit Offset (Displacement)
N = 1 for byte, 2 for word, and 4 for long word. If An is the stack pointer and the operand size is byte, N = 2 to keep the stack pointer on a word boundary.
◄ = Replaces
Xn = Address or Data Register used as Index Register
SR = Status Register
USP = User Stack Pointer
SSP = Supervisor Stack Pointer
CP = Program Counter
VBR = Vector Base Register

2.3 DATA ORGANIZATION IN REGISTERS

The eight data registers support data operands of 1, 8, 16, or 32 bits. The seven address registers and the active stack pointer support address operands of 32 bits.

2.3.1 Data Registers

Each data register is 32 bits wide. Byte operands occupy the low-order 8 bits, word operands the low-order 16 bits, and long-word operands, the entire 32 bits. The least significant bit is addressed as bit zero; the most significant bit is addressed as bit 31.

When a data register is used as either a source or a destination operand, only the appropriate low-order portion is changed; the remaining high-order portion is neither used nor changed.

2.3.2 Address Registers

Each address register (and the stack pointer) is 32 bits wide and holds a full, 32-bit address. Address registers do not support byte-sized operands. Therefore, when an address register is used as a source operand, either the low-order word or the entire long-word operand is used, depending upon the operation size. When an address register is used as the destination operand, the entire register is affected, regardless of the operation size. If the operation size is word, operands are sign-extended to 32 bits before the operation is performed.

2.4 DATA ORGANIZATION IN MEMORY

Bytes are individually addressable. As shown in Figure 2-5, the high-order byte of a word has the same address as the word. The low-order byte has an odd address, one count higher. Instructions and multibyte data are accessed only on word (even byte) boundaries. If a long-word operand is located at address n (n even), then the second word of that operand is located at address $n+2$.




Figure 2-5. Word Organization in Memory

The data types supported by the M68000 MPUs are bit data, integer data of 8, 16, and 32 bits, 32-bit addresses, and binary-coded-decimal data. Each data type is stored in memory as shown in Figure 2-6. The numbers indicate the order of accessing the data from the processor. For the MC68008 with its 8-bit bus, the appearance of data in memory is identical to the all the M68000 MPUs. The organization of data in the memory of the MC68008 is shown in Figure 2-7.



MOTOROLA




Figure 2-7. Memory Data Organization of the MC68008

2.5 INSTRUCTION SET SUMMARY

Table 2-2 provides an alphabetized listing of the M68000 instruction set listed by opcode, operation, and syntax. In the syntax descriptions, the left operand is the source operand, and the right operand is the destination operand. The following list contains the notations used in Table 2-2.

Table 2-2. Instruction Set Summary (Sheet 1 of 4)

Opcode	Operation	Syntax
ABCD	Source ₁₀ + Destination ₁₀ + X → Destination	ABCD Dy,Dx ABCD -(Ay), -(Ax)
ADD	Source + Destination → Destination	ADD <ea>,Dn ADD Dn,<ea>
ADDA	Source + Destination → Destination	ADDA <ea>,An
ADDI	Immediate Data + Destination → Destination	ADDI # <data>,<ea>
ADDQ	Immediate Data + Destination → Destination	ADDQ # <data>,<ea>
ADDX	Source + Destination + X → Destination	ADDX Dy, Dx ADDX -(Ay), -(Ax)
AND	Source $\wedge$ Destination → Destination	AND <ea>,Dn AND Dn,<ea>
ANDI	Immediate Data $\wedge$ Destination → Destination	ANDI # <data>,<ea>
ANDI to CCR	Source $\wedge$ CCR → CCR	ANDI # <data>, CCR
ANDI to SR	If supervisor state then Source $\wedge$ SR → SR else TRAP	ANDI # <data>, SR
ASL, ASR	Destination Shifted by <count> → Destination	ASd Dx,Dy ASd # <data>,Dy ASd <ea>
Bcc	If (condition true) then PC + d → PC	Bcc <label>
BCHG	$\sim$ (<number> of Destination) → Z; $\sim$ (<number> of Destination) → <bit number> of Destination	BCHG Dn,<ea> BCHG # <data>,<ea>
BCLR	$\sim$ (<bit number> of Destination) → Z; 0 → <bit number> of Destination	BCLR Dn,<ea> BCLR # <data>,<ea>
BKPT	Run breakpoint acknowledge cycle; TRAP as illegal instruction	BKPT # <data>
BRA	PC + d → PC	BRA <label>
BSET	$\sim$ (<bit number> of Destination) → Z; 1 → <bit number> of Destination	BSET Dn,<ea> BSET # <data>,<ea>
BSR	SP - 4 → SP; PC → (SP); PC + d → PC	BSR <label>
BTST	$\sim$ (<bit number> of Destination) → Z;	BTST Dn,<ea> BTST # <data>,<ea>
CHK	If Dn < 0 or Dn > Source then TRAP	CHK <ea>,Dn
CLR	0 → Destination	CLR <ea>
CMP	Destination—Source → cc	CMP <ea>,Dn
CMPA	Destination—Source	CMPA <ea>,An
CMPI	Destination—Immediate Data	CMPI # <data>,<ea>
CMPM	Destination—Source → cc	CMPM (Ay)+, (Ax)+
DBcc	If condition false then (Dn - 1 → Dn; If Dn $\neq$ -1 then PC + d → PC)	DBcc Dn,<label>

Table 2-2. Instruction Set Summary (Sheet 2 of 4)

Opcode	Operation	Syntax
DIVS	Destination/Source $\rightarrow$ Destination	DIVS.W <ea>,Dn 32/16 $\rightarrow$ 16r:16q
DIVU	Destination/Source $\rightarrow$ Destination	DIVU.W <ea>,Dn 32/16 $\rightarrow$ 16r:16q
EOR	Source $\oplus$ Destination $\rightarrow$ Destination	EOR Dn,<ea>
EORI	Immediate Data $\oplus$ Destination $\rightarrow$ Destination	EORI # <data>,<ea>
EORI to CCR	Source $\oplus$ CCR $\rightarrow$ CCR	EORI # <data>,CCR
EORI to SR	If supervisor state then Source $\oplus$ SR $\rightarrow$ SR else TRAP	EORI # <data>,SR
EXG	Rx $\leftrightarrow$ Ry	EXG Dx,Dy EXG Ax,Ay EXG Dx,Ay EXG Ay,Dx
EXT	Destination Sign-Extended $\rightarrow$ Destination	EXT.W Dn extend byte to word EXT.L Dn extend word to long word
ILLEGAL	SSP - 2 $\rightarrow$ SSP; Vector Offset $\rightarrow$ (SSP); SSP - 4 $\rightarrow$ SSP; PC $\rightarrow$ (SSP); SSP - 2 $\rightarrow$ SSP; SR $\rightarrow$ (SSP); Illegal Instruction Vector Address $\rightarrow$ PC	ILLEGAL
JMP	Destination Address $\rightarrow$ PC	JMP <ea>
JSR	SP - 4 $\rightarrow$ SP; PC $\rightarrow$ (SP) Destination Address $\rightarrow$ PC	JSR <ea>
LEA	<ea> $\rightarrow$ An	LEA <ea>,An
LINK	SP - 4 $\rightarrow$ SP; An $\rightarrow$ (SP) SP $\rightarrow$ An, SP + d $\rightarrow$ SP	LINK An, # <displacement>
LSL,LSR	Destination Shifted by <count> $\rightarrow$ Destination	LSd ¹ Dx,Dy LSd ¹ # <data>,Dy LSd ¹ <ea>
MOVE	Source $\rightarrow$ Destination	MOVE <ea>,<ea>
MOVEA	Source $\rightarrow$ Destination	MOVEA <ea>,An
MOVE from CCR	CCR $\rightarrow$ Destination	MOVE CCR,<ea>
MOVE to CCR	Source $\rightarrow$ CCR	MOVE <ea>,CCR
MOVE from SR	SR $\rightarrow$ Destination If supervisor state then SR $\rightarrow$ Destination else TRAP (MC68010 only)	MOVE SR,<ea>
MOVE to SR	If supervisor state then Source $\rightarrow$ SR else TRAP	MOVE <ea>,SR

Table 2-2. Instruction Set Summary (Sheet 4 of 4)

Opcode	Operation	Syntax
RTE	If supervisor state then (SP) → SR; SP + 2 → SP; (SP) → PC; SP + 4 → SP; restore state and deallocate stack according to (SP) else TRAP	RTE
RTR	(SP) → CCR; SP + 2 → SP; (SP) → PC; SP + 4 → SP	RTR
RTS	(SP) → PC; SP + 4 → SP	RTS
SBCD	Destination ₁₀ – Source ₁₀ – X → Destination	SBCD Dx,Dy SBCD –(Ax),–(Ay)
Scc	If condition true then 1s → Destination else 0s → Destination	Scc <ea>
STOP	If supervisor state then Immediate Data → SR; STOP else TRAP	STOP # <data>
SUB	Destination – Source → Destination	SUB <ea>,Dn SUB Dn,<ea>
SUBA	Destination – Source → Destination	SUBA <ea>,An
SUBI	Destination – Immediate Data → Destination	SUBI # <data>,<ea>
SUBQ	Destination – Immediate Data → Destination	SUBQ # <data>,<ea>
SUBX	Destination – Source – X → Destination	SUBX Dx,Dy SUBX –(Ax),–(Ay)
SWAP	Register [31:16] ↔ Register [15:0]	SWAP Dn
TAS	Destination Tested → Condition Codes; 1 → bit 7 of Destination	TAS <ea>
TRAP	SSP – 2 → SSP; Format/Offset → (SSP); SSP – 4 → SSP; PC → (SSP); SSP – 2 → SSP; SR → (SSP); Vector Address → PC	TRAP # <vector>
TRAPV	If V then TRAP	TRAPV
TST	Destination Tested → Condition Codes	TST <ea>
UNLK	An → SP; (SP) → An; SP + 4 → SP	UNLK An

NOTE: d is direction, L or R.


SECTION 3

SIGNAL DESCRIPTION

This section contains descriptions of the input and output signals. The input and output signals can be functionally organized into the groups shown in Figure 3-1 (for the MC68000, the MC68HC000 and the MC68010), Figure 3-2 (for the MC68HC001), Figure 3-3 (for the MC68EC000), Figure 3-4 (for the MC68008, 48-pin version), and Figure 3-5 (for the MC68008, 52-pin version). The following paragraphs provide brief descriptions of the signals and references (where applicable) to other paragraphs that contain more information about the signals.

NOTE

The terms **assertion** and **negation** are used extensively in this manual to avoid confusion when describing a mixture of "active-low" and "active-high" signals. The term assert or assertion is used to indicate that a signal is active or true, independently of whether that level is represented by a high or low voltage. The term negate or negation is used to indicate that a signal is inactive or false.



**Figure 3-1. Input and Output Signals
(MC68000, MC68HC000 and MC68010)**

Address Bus (A23–A0)

This 24-bit, unidirectional, three-state bus is capable of addressing 16 Mbytes of data. This bus provides the address for bus operation during all cycles except interrupt acknowledge cycles and breakpoint cycles. During interrupt acknowledge cycles, address lines A1, A2, and A3 provide the level number of the interrupt being acknowledged, and address lines A23–A4 and A0 are driven to logic high. In 16-Bit mode, A0 is always driven high.

MC68008 Address Bus

The unidirectional, three-state buses in the two versions of the **MC68008** differ from each other and from the other processor bus only in the number of address lines and the addressing range. The 20-bit address (A19–A0) of the 48-pin version provides a 1-Mbyte address space; the 52-pin version supports a 22-bit address (A21–A0), extending the address space to 4 Mbytes. During an interrupt acknowledge cycle, the interrupt level number is placed on lines A1, A2, and A3. Lines A0 and A4 through the most significant address line are driven to logic high.

3.2 DATA BUS (D15–D0; MC68008: D7–D0)

This bidirectional, three-state bus is the general-purpose data path. It is 16 bits wide in all the processors except the **MC68008** which is 8 bits wide. The bus can transfer and accept data of either word or byte length. During an interrupt acknowledge cycle, the external device supplies the vector number on data lines D7–D0. The MC68EC000 and MC68HC001 use D7–D0 in 8-bit mode, and D15–D8 are undefined.

3.3 ASYNCHRONOUS BUS CONTROL

Asynchronous data transfers are controlled by the following signals: address strobe, read/write, upper and lower data strobes, and data transfer acknowledge. These signals are described in the following paragraphs.

Address Strobe ($\overline{AS}$).

This three-state signal indicates that the information on the address bus is a valid address.

Read/Write ($R/\overline{W}$).

This three-state signal defines the data bus transfer as a read or write cycle. The $R/\overline{W}$ signal relates to the data strobe signals described in the following paragraphs.

Upper And Lower Data Strobes ($\overline{UDS}$, $\overline{LDS}$).

These three-state signals and $R/\overline{W}$ control the flow of data on the data bus. Table 3-1 lists the combinations of these signals and the corresponding data on the bus. When the $R/\overline{W}$ line is high, the processor reads from the data bus. When the $R/\overline{W}$ line is low, the processor drives the data bus. In 8-bit mode, $\overline{UDS}$ is always forced high and the $\overline{LDS}$ signal is used.

Bus Request ($\overline{BR}$).

This input can be wire-ORed with bus request signals from all other devices that could be bus masters. This signal indicates to the processor that some other device needs to become the bus master. Bus requests can be issued at any time during a cycle or between cycles.

Bus Grant ($\overline{BG}$).

This output signal indicates to all other potential bus master devices that the processor will relinquish bus control at the end of the current bus cycle.

Bus Grant Acknowledge ($\overline{BGACK}$).

This input indicates that some other device has become the bus master. This signal should not be asserted until the following conditions are met:

1. A bus grant has been received.
2. Address strobe is inactive, which indicates that the microprocessor is not using the bus.
3. Data transfer acknowledge is inactive, which indicates that neither memory nor peripherals are using the bus.
4. Bus grant acknowledge is inactive, which indicates that no other device is still claiming bus mastership.

The 48-pin version of the **MC68008** has no pin available for the bus grant acknowledge signal and uses a two-wire bus arbitration scheme instead. If another device in a system supplies a bus grant acknowledge signal, the bus request input signal to the processor should be asserted when either the bus request or the bus grant acknowledge from that device is asserted.

3.5 INTERRUPT CONTROL ($\overline{IPL0}$, $\overline{IPL1}$, $\overline{IPL2}$)

These input signals indicate the encoded priority level of the device requesting an interrupt. Level seven, which cannot be masked, has the highest priority; level zero indicates that no interrupts are requested. $\overline{IPL0}$ is the least significant bit of the encoded level, and $\overline{IPL2}$ is the most significant bit. For each interrupt request, these signals must remain asserted until the processor signals interrupt acknowledge (FC2–FC0 and A19–A16 high) for that request to ensure that the interrupt is recognized.

NOTE

The 48-pin version of the **MC68008** has only two interrupt control signals: $\overline{IPL0}/\overline{IPL2}$ and $\overline{IPL1}$. $\overline{IPL0}/\overline{IPL2}$ is internally connected to both $\overline{IPL0}$ and $\overline{IPL2}$, which provides four interrupt priority levels: levels 0, 2, 5, and 7. In all other respects, the interrupt priority levels in this version of the **MC68008** are identical to those levels in the other microprocessors described in this manual.

Table 3-3. Function Code Outputs

Function Code Output			Address Space Type
FC2	FC1	FC0	
Low	Low	Low	(Undefined, Reserved)
Low	Low	High	User Data
Low	High	Low	User Program
Low	High	High	(Undefined, Reserved)
High	Low	Low	(Undefined, Reserved)
High	Low	High	Supervisor Data
High	High	Low	Supervisor Program
High	High	High	CPU Space

3.9 CLOCK (CLK)

The clock input is a TTL-compatible signal that is internally buffered for development of the internal clocks needed by the processor. This clock signal is a constant frequency square wave that requires no stretching or shaping. The clock input should not be gated off at any time, and the clock signal must conform to minimum and maximum pulse-width times listed in **Section 10 Electrical Characteristics**.

3.10 POWER SUPPLY (V_{CC} and GND)

Power is supplied to the processor using these connections. The positive output of the power supply is connected to the V_{CC} pins and ground is connected to the GND pins.




Figure 4-1. Byte Read-Cycle Flowchart




Figure 4-2. Read and Write-Cycle Timing Diagram




Figure 5-7. Word and Byte Write-Cycle Timing Diagram

The descriptions of the eight states of a write cycle are as follows:

- STATE 0** The write cycle starts in S0. The processor places valid function codes on FC2-FC0 and drives R/W high (if a preceding write cycle has left R/W low).
- STATE 1** Entering S1, the processor drives a valid address on the address bus.
- STATE 2** On the rising edge of S2, the processor asserts $\overline{AS}$ and drives R/W low.
- STATE 3** During S3, the data bus is driven out of the high-impedance state as the data to be written is placed on the bus.
- STATE 4** At the rising edge of S4, the processor asserts $\overline{UDS}$, or $\overline{LDS}$. The processor waits for a cycle termination signal ($\overline{DTACK}$ or $\overline{BERR}$) or $\overline{VPA}$, an M6800 peripheral signal. When $\overline{VPA}$ is asserted during S4, the cycle becomes a peripheral cycle (refer to **Appendix B M6800 Peripheral Interface**). If neither termination signal is asserted before the falling edge at the end of S4, the processor inserts wait states (full clock cycles) until either $\overline{DTACK}$ or $\overline{BERR}$ is asserted.
- STATE 5** During S5, no bus signals are altered.
- STATE 6** During S6, no bus signals are altered.

- STATE 12 The write portion of the cycle starts in S12. The valid function codes on FC2–FC0, the address bus lines, $\overline{AS}$, and $R/\overline{W}$ remain unaltered.
- STATE 13 During S13, no bus signals are altered.
- STATE 14 On the rising edge of S14, the processor drives $R/\overline{W}$ low.
- STATE 15 During S15, the data bus is driven out of the high-impedance state as the data to be written are placed on the bus.
- STATE 16 At the rising edge of S16, the processor asserts $\overline{UDS}$ or $\overline{LDS}$. The processor waits for $\overline{DTACK}$ or $\overline{BERR}$ or $\overline{VPA}$, an M6800 peripheral signal. When $\overline{VPA}$ is asserted during S16, the cycle becomes a peripheral cycle (refer to **Appendix B M6800 Peripheral Interface**). If neither termination signal is asserted before the falling edge at the close of S16, the processor inserts wait states (full clock cycles) until either $\overline{DTACK}$ or $\overline{BERR}$ is asserted.
- STATE 17 During S17, no bus signals are altered.
- STATE 18 During S18, no bus signals are altered.
- STATE 19 On the falling edge of the clock entering S19, the processor negates $\overline{AS}$, $\overline{UDS}$, and $\overline{LDS}$. As the clock rises at the end of S19, the processor places the address and data buses in the high-impedance state, and drives $R/\overline{W}$ high. The device negates $\overline{DTACK}$ or $\overline{BERR}$ at this time.

5.1.4 CPU Space Cycle

A CPU space cycle, indicated when the function codes are all high, is a special processor cycle. Bits A16–A19 of the address bus identify eight types of CPU space cycles. Only the interrupt acknowledge cycle, in which A16–A19 are high, applies to all the microprocessors described in this manual. The MC68010 defines an additional type of CPU space cycle, the breakpoint acknowledge cycle, in which A16–A19 are all low. Other configurations of A16–A19 are reserved by Motorola to define other types of CPU cycles used in other M68000 Family microprocessors. Figure 5-10 shows the encoding of CPU space addresses.






Figure 5-10. CPU Space Address Encoding



(a) 3-Wire Bus Arbitration



(b) 2-Wire Bus Arbitration

R = Bus Request Internal
 A = Bus Grant Acknowledge Internal
 G = Bus Grant
 T = Three-state Control to Bus Control Logic
 X = Don't Care

Notes:

1. State machine will not change if the bus is S0 or S1. Refer to **BUS ARBITRATION CONTROL, 5.2.3.**
2. The address bus will be placed in the high-impedance state if T is asserted and $\overline{AS}$ is negated.

Figure 5-18. Bus Arbitration Unit State Diagrams

Figures 5-19, 5-20, and 5-21 applies to all processors using 3-wire bus arbitration. Figures 5-22, 5-23, and 5-24 applies to all processors using 2-wire bus arbitration.

supervisor mode. Therefore, when instruction execution resumes at the address specified to process the exception, the processor is in the supervisor privilege mode.

NOTE

The transition from supervisor to user mode can be accomplished by any of four instructions: return from exception (RTE) (MC68010 only), move to status register (MOVE to SR), AND immediate to status register (ANDI to SR), and exclusive OR immediate to status register (EORI to SR). The RTE instruction in the MC68010 fetches the new status register and program counter from the supervisor stack and loads each into its respective register. Next, it begins the instruction fetch at the new program counter address in the privilege mode determined by the S bit of the new contents of the status register.

The MOVE to SR, ANDI to SR, and EORI to SR instructions fetch all operands in the supervisor mode, perform the appropriate update to the status register, and then fetch the next instruction at the next sequential program counter address in the privilege mode determined by the new S bit.

6.1.4 Reference Classification

When the processor makes a reference, it classifies the reference according to the encoding of the three function code output lines. This classification allows external translation of addresses, control of access, and differentiation of special processor states, such as CPU space (used by interrupt acknowledge cycles). Table 6-1 lists the classification of references.

Table 6-1. Reference Classification

Function Code Output			Address Space
FC2	FC1	FC0	
0	0	0	(Undefined, Reserved)*
0	0	1	User Data
0	1	0	User Program
0	1	1	(Undefined, Reserved)*
1	0	0	(Undefined, Reserved)*
1	0	1	Supervisor Data
1	1	0	Supervisor Program
1	1	1	CPU Space

*Address space 3 is reserved for user definition, while 0 and 4 are reserved for future use by Motorola.

shown in Figure 6-9. If the bus cycle is a read, the data at the fault address should be written to the images of the data input buffer, instruction input buffer, or both according to the data fetch (DF) and instruction fetch (IF) bits.* In addition, for read-modify-write cycles, the status register image must be properly set to reflect the read data if the fault occurred during the read portion of the cycle and the write operation (i.e., setting the most significant bit of the memory location) must also be performed. These operations are required because the entire read-modify-write cycle is assumed to have been completed by software. Once the cycle has been completed by software, the rerun (RR) bit in the special status word is set to indicate to the processor that it should not rerun the cycle when the RTE instruction is executed. If the RR bit is set when an RTE instruction executes, the MC68010 reads all the information from the stack, as usual.




Figure 6-9. Special Status Word Format

6.3.10 Address Error

An address error exception occurs when the processor attempts to access a word or long-word operand or an instruction at an odd address. An address error is similar to an internally generated bus error. The bus cycle is aborted, and the processor ceases current processing and begins exception processing. The exception processing sequence is the same as that for a bus error, including the information to be stacked, except that the vector number refers to the address error vector. Likewise, if an address error occurs during the exception processing for a bus error, address error, or reset, the processor is halted.

On the MC68010, the address error exception stacks the same information stacked by a bus error exception. Therefore, the RTE instruction can be used to continue execution of the suspended instruction. However, if the RR flag is not set, the fault address is used when the cycle is retried, and another address error exception occurs. Therefore, the user must be certain that the proper corrections have been made to the stack image and user registers before attempting to continue the instruction. With proper software handling, the address error exception handler could emulate word or long-word accesses to odd addresses if desired.

*If the faulted access was a byte operation, the data should be moved from or to the least significant byte of the data output or input buffer images, unless the high-byte transfer (HB) bit is set. This condition occurs if a MOVEP instruction caused the fault during transfer of bits 8–15 of a word or long word or bits 24–31 of a long word.

Table 7-1. Effective Address Calculation Times

Addressing Mode		Byte	Word	Long
Register				
Dn	Data Register Direct	0(0/0)	0(0/0)	0(0/0)
An	Address Register Direct	0(0/0)	0(0/0)	0(0/0)
Memory				
(An)	Address Register Indirect	4(1/0)	8(2/0)	16(4/0)
(An)+	Address Register Indirect with Postincrement	4(1/0)	8(2/0)	16(4/0)
-(An)	Address Register Indirect with Predecrement	6(1/0)	10(2/0)	18(4/0)
(d16, An)	Address Register Indirect with Displacement	12(3/0)	16(4/0)	24(6/0)
(dg, An, Xn)*	Address Register Indirect with Index	14(3/0)	18(4/0)	26(6/0)
(xxx).W	Absolute Short	12(3/0)	16(4/0)	24(6/0)
(xxx).L	Absolute Long	20(5/0)	24(6/0)	32(8/0)
(d16, PC)	Program Counter Indirect with Displacement	12(3/0)	16(3/0)	24(6/0)
(dg, PC, Xn)*	Program Counter Indirect with Index	14(3/0)	18(4/0)	26(6/0)
#<data>	Immediate	8(2/0)	8(2/0)	16(4/0)

*The size of the index register (Xn) does not affect execution time.

7.2 MOVE INSTRUCTION EXECUTION TIMES

Tables 7-2, 7-3, and 7-4 list the numbers of clock periods for the move instructions. The totals include instruction fetch, operand reads, and operand writes. The total number of clock periods, the number of read cycles, and the number of write cycles are shown in the previously described format.

Table 7-2. Move Byte Instruction Execution Times

Source	Destination								
	Dn	An	(An)	(An)+	-(An)	(d16, An)	(dg, An, Xn)*	(xxx).W	(xxx).L
Dn	8(2/0)	8(2/0)	12(2/1)	12(2/1)	12(2/1)	20(4/1)	22(4/1)	20(4/1)	28(6/1)
An	8(2/0)	8(2/0)	12(2/1)	12(2/1)	12(2/1)	20(4/1)	22(4/1)	20(4/1)	28(6/1)
(An)	12(3/0)	12(3/0)	16(3/1)	16(3/1)	16(3/1)	24(5/1)	26(5/1)	24(5/1)	32(7/1)
(An)+	12(3/0)	12(3/0)	16(3/1)	16(3/1)	16(3/1)	24(5/1)	26(5/1)	24(5/1)	32(7/1)
-(An)	14(3/0)	14(3/0)	18(3/1)	18(3/1)	18(3/1)	26(5/1)	28(5/1)	26(5/1)	34(7/1)
(d16, An)	20(5/0)	20(5/0)	24(5/1)	24(5/1)	24(5/1)	32(7/1)	34(7/1)	32(7/1)	40(9/1)
(dg, An, Xn)*	22(5/0)	22(5/0)	26(5/1)	26(5/1)	26(5/1)	34(7/1)	36(7/1)	34(7/1)	42(9/1)
(xxx).W	20(5/0)	20(5/0)	24(5/1)	24(5/1)	24(5/1)	32(7/1)	34(7/1)	32(7/1)	40(9/1)
(xxx).L	28(7/0)	28(7/0)	32(7/1)	32(7/1)	32(7/1)	40(9/1)	42(9/1)	40(9/1)	48(11/1)
(d16, PC)	20(5/0)	20(5/0)	24(5/1)	24(5/1)	24(5/1)	32(7/1)	34(7/1)	32(7/1)	40(9/1)
(dg, PC, Xn)*	22(5/0)	22(5/0)	26(5/1)	26(5/1)	26(5/1)	34(7/1)	36(7/1)	34(7/1)	42(9/1)
#<data>	16(4/0)	16(4/0)	20(4/1)	20(4/1)	20(4/1)	28(6/1)	30(6/1)	28(6/1)	36(8/1)

*The size of the index register (Xn) does not affect execution time.

INDEX

—A—

A23–A0 3-3, 3-4
Acknowledgment Of Mastership 5-15
Address Bus 3-3
Address Error 6-8, 6-19
Address Register 2-5, 2-6
Address Space 6-2
Address Strobe ($\overline{AS}$) 3-4, 3-8, 4-3, 4-5, 4-7, 4-8, 5-4, 5-6, 5-7, 5-8, 5-9, 5-15, 5-16, 5-32, 5-34, 5-36, 5-37
Addressing Modes 2-4
Alternate Function Code Registers 2-2
ANDI to SR 6-3
 $\overline{AS}$ 3-4, 3-8, 4-3, 4-5, 4-7, 4-8, 5-4, 5-6, 5-7, 5-8, 5-9, 5-15, 5-16, 5-32, 5-34, 5-36, 5-37
Asynchronous Bus Arbitration 5-15
Asynchronous Operation 5-32, 5-33
Auto Vector (AVEC) 5-10, 5-32, 6-13
AVEC 5-10, 5-32, 6-13

—B—

$\overline{BERR}$ 3-7, 4-3, 4-5, 4-7, 4-8, 5-4, 5-6, 5-7, 5-8, 5-9, 5-11, 5-24, 5-26, 5-27, 5-30, 5-31, 5-32, 5-37, 5-35, 5-38, 5-39, 6-13
 $\overline{BG}$ 3-5, 3-6, 5-14, 5-15, 5-16
 $\overline{BGACK}$ 1-2, 3-5, 3-6, 5-15, 5-16
Bit Manipulation Instruction Execution Times 7-7, 8-7, 9-9
 $\overline{BR}$ 3-5, 3-6, 5-14, 5-16
Breakpoint Acknowledge Cycle 5-11
Breakpoint Acknowledge Cycle Timing Diagram 5-11
Bus Arbitration, 2-Wire 5-11
Bus Arbitration 2-Wire Cycle Flowchart 5-13
Bus Arbitration 2-Wire Timing Diagram 5-14, 5-23
Bus Arbitration, 3-5, 5-11
Bus Arbitration, 3-wire 5-11
Bus Arbitration 3-Wire Cycle Flowchart 5-12
Bus Arbitration 3-Wire Timing Diagram 15-3, 5-18
Bus Arbitration Control 5-15, 5-16
Bus Arbitration Unit State Diagrams 5-17
Bus Cycle 5-27, 6-11, 6-18, 6-19
Bus Cycle Retry 5-26

Bus Error ($\overline{BERR}$) 3-7, 4-3, 4-5, 4-7, 4-8, 5-4, 5-6, 5-7, 5-8, 5-9, 5-11, 5-24, 5-26, 5-27, 5-30, 5-31, 5-32, 5-37, 5-35, 5-38, 5-39, 6-13
Bus Error Operation 5-23, 5-26, 5-24, 6-8, 6-13, 6-16, 6-17
Bus Grant ($\overline{BG}$) 3-5, 3-6, 5-14, 5-15, 5-16
Bus Grant Acknowledge ($\overline{BGACK}$) 1-2, 3-5, 3-6, 5-15, 5-16

Bus Operations

16-Bit Mode 3-4, 3-7
2-wire Bus Arbitration 5-11
3-wire Bus Arbitration 5-11
8-bit Data Bus 1-2
8-bit Mode 3-4, 3-7
Bus Arbitration 3-5, 5-11
Bus Arbitration Control 5-15, 5-16
Bus Cycle Retry 5-26
Delayed Bus Error 5-25
Double Bus Fault 5-28
Halted Processing State 6-1
Interrupt Acknowledge Bus Cycle 6-4
Interrupt Request 6-12
STOP Instruction 6-2
Bus Request ($\overline{BR}$) 3-5, 3-6, 5-14, 5-16
Byte Read-Cycle Flowchart 5-2
Byte Write-Cycle Flowchart 5-5

—C—

CHK 6-6
Clear Instruction Execution Times 9-7
CLOCK (CLK) 3-9
Condition Codes 2-3
Conditional Instruction Execution Times 7-7, 8-7, 9-10
CPU Space 4-1, 6-3
CPU Space Address Encoding 5-9
CPU Space Cycle 5-9

—D—

Data Bus 3-4, 4-1, 3-4, 6-4
Data Bus 8-bit 1-2
Data Organization in Memory 2-6
Data Registers 2-5
Data Strobe ($\overline{DS}$) 3-5, 4-3, 4-5, 4-7, 4-8, 5-4, 5-32, 5-36, 5-37



1.1 INTEGER UNIT USER PROGRAMMING MODEL

Figure 1-1 illustrates the integer portion of the user programming model. It consists of the following registers:

- 16 General-Purpose 32-Bit Registers (D7 – D0, A7 – A0)
- 32-Bit Program Counter (PC)
- 8-Bit Condition Code Register (CCR)




Figure 1-1. M68000 Family User Programming Model

1.1.1 Data Registers (D7 – D0)

These registers are for bit and bit field (1 – 32 bits), byte (8 bits), word (16 bits), long-word (32 bits), and quad-word (64 bits) operations. They also can be used as index registers.

1.1.2 Address Registers (A7 – A0)

These registers can be used as software stack pointers, index registers, or base address registers. The base address registers can be used for word and long-word operations. Register A7 is used as a hardware stack pointer during stacking for subroutine calls and exception handling. In the user programming model, A7 refers to the user stack pointer (USP).

1.2.2 Floating-Point Control Register (FPCR)

The FPCR (see Figure 1-3) contains an exception enable (ENABLE) byte and a mode control (MODE) byte. The user can read or write to the FPCR. Motorola reserves bits 31 – 16 for future definition; these bits are always read as zero and are ignored during write operations. The reset function or a restore operation of the null state clears the FPCR. When cleared, this register provides the IEEE 754 Standard for Binary Floating-Point Arithmetic defaults.

1.2.2.1 EXCEPTION ENABLE BYTE. Each bit of the ENABLE byte (see Figure 1-3) corresponds to a floating-point exception class. The user can separately enable traps for each class of floating-point exceptions.

1.2.2.2 MODE CONTROL BYTE. MODE (see Figure 1-3) controls the user-selectable rounding modes and precisions. Zeros in this byte select the IEEE 754 standard defaults. The rounding mode (RND) field specifies how inexact results are rounded, and the rounding precision (PREC) field selects the boundary for rounding the mantissa. Refer to Table 3-21 for encoding information. .




Figure 1-3. Floating-Point Control Register

1.2.3 Floating-Point Status Register (FPSR)

The FPSR (see Figure 1-2) contains a floating-point condition code (FPCC) byte, a floating-point exception status (EXC) byte, a quotient byte, and a floating-point accrued exception (AEXC) byte. The user can read or write to all the bits in the FPSR. Execution of most floating-point instructions modifies this register. The reset function or a restore operation of the null state clears the FPSR.

1.2.3.1 FLOATING-POINT CONDITION CODE BYTE. The FPCC byte, illustrated in Figure 1-4, contains four condition code bits that set after completion of all arithmetic instructions involving the floating-point data registers. The move floating-point data register

supported, where T0 is always zero, and only one system stack where the M-bit is always zero. I2, I1, and I0 define the interrupt mask level.




Figure 1-8. Status Register

1.3.3 Vector Base Register (VBR)

The VBR contains the base address of the exception vector table in memory. The displacement of an exception vector adds to the value in this register, which accesses the vector table.

1.3.4 Alternate Function Code Registers (SFC and DFC)

The alternate function code registers contain 3-bit function codes. Function codes can be considered extensions of the 32-bit logical address that optionally provides as many as eight 4-Gbyte address spaces. The processor automatically generates function codes to select address spaces for data and programs at the user and supervisor modes. Certain instructions use SFC and DFC to specify the function codes for operations.

1.3.5 Acu Status Register (MC68EC030 only)

The access control unit status register (ACUSR) is a 16-bit register containing the status information returned by execution of the PTEST instruction. The PTEST instruction searches the access control (AC) registers to determine a match for a specified address. A match in either or both of the AC registers sets bit 6 in the ACUSR. All other bits in the ACUSR are undefined and must not be used.

1.3.6 Transparent Translation/access Control Registers

Transparent translation is actually a misnomer since the whole address space transparently translates in an embedded control environment with no on-chip MMU present as well as in processors that have built-in MMUs. For processors that have built-in MMUs, such as the MC68030, MC68040, and MC68LC040, the transparent translation (TT) registers define blocks of logical addresses that are transparently translated to corresponding physical addresses. These registers are independent of the on-chip MMU. For embedded controllers, such as the MC68EC030 and MC68EC040, the access control registers (AC) are similar in function to the TT registers but just named differently. The AC registers, main function are to define blocks of address space that control address space properties such as cachability. The following paragraphs describe these registers.

NOTE

For the paged MMU related supervisor registers, please refer to the appropriate user’s manual for specific programming detail.

1.3.6.1 TRANSPARENT TRANSLATION/ACCESS CONTROL REGISTER FIELDS FOR THE M68030. Figure 1-9 illustrates the MC68030 transparent translation/MC68EC030 access control register format.

31								24	23	16				
ADDRESS BASE								ADDRESS MASK						
E	0	0	0	0	CI	R/W	RWM	0	FC BASE		0	FC MASK		
15	14	13	12	11	10	9	8	7	6	4	3	2	0	

Figure 1-9. MC68030 Transparent Translation/MC68EC030 Access Control Register Format

Address Base

This 8-bit field is compared with address bits A31 – A24. Addresses that match in this comparison (and are otherwise eligible) are transparently translated/access controlled.

Address Mask

This 8-bit field contains a mask for the address base field. Setting a bit in this field causes the corresponding bit of the address base field to be ignored. Blocks of memory larger than 16 Mbytes can be transparently translated/accessed controlled by setting some logical address mask bits to ones. The low-order bits of this field normally are set to define contiguous blocks larger than 16 Mbytes, although this is not required.

1.6.1 Normalized Numbers

Normalized numbers encompass all numbers with exponents laying between the maximum and minimum values. Normalized numbers can be positive or negative. For normalized numbers in single and double precision the implied integer bit is one. In extended precision, the mantissa's MSB, the explicit integer bit, can only be a one (see Figure 1-13); and the exponent can be zero.




Figure 1-13. Normalized Number Format

1.6.2 Denormalized Numbers

Denormalized numbers represent real values near the underflow threshold. The detection of the underflow for a given data format and operation occurs when the result's exponent is less than or equal to the minimum exponent value. Denormalized numbers can be positive or negative. For denormalized numbers in single and double precision the implied integer bit is a zero. In extended precision, the mantissa's MSB, the explicit integer bit, can only be a zero (see Figure 1-14).



Figure 1-14. Denormalized Number Format

Traditionally, the detection of underflow causes floating-point number systems to perform a "flush-to-zero". This leaves a large gap in the number line between the smallest magnitude normalized number and zero. The IEEE 754 standard implements gradual underflows: the result mantissa is shifted right (denormalized) while the result exponent is incremented until reaching the minimum value. If all the mantissa bits of the result are shifted off to the right during this denormalization, the result becomes zero. Usually a gradual underflow limits the potential underflow damage to no more than a round-off error. This underflow and denormalization description ignores the effects of rounding and the user-selectable rounding modes. Thus, the large gap in the number line created by "flush-to-zero" number systems is filled with representable (denormalized) numbers in the IEEE "gradual underflow" floating-point number system.

Since the extended-precision data format has an explicit integer bit, a number can be formatted with a nonzero exponent, less than the maximum value, and a zero integer bit. The IEEE 754 standard does not define a zero integer bit. Such a number is an unnormalized number. Hardware does not directly support denormalized and unnormalized numbers, but implicitly supports them by trapping them as unimplemented data types, allowing efficient conversion in software.

Table 1-4. Single-Precision Real Format Summary Data Format

Data Format	
31 30 23 22 0 s e f	
Field Size In Bits	
Sign (s)	1
Biased Exponent (e)	8
Fraction (f)	23
Total	32
Interpretation of Sign	
Positive Fraction	$s = 0$
Negative Fraction	$s = 1$
Normalized Numbers	
Bias of Biased Exponent	+127 (\$7F)
Range of Biased Exponent	$0 < e < 255$ (\$FF)
Range of Fraction	Zero or Nonzero
Fraction	1.f
Relation to Representation of Real Numbers	$(-1)^s \times 2^{e-127} \times 1.f$
Denormalized Numbers	
Biased Exponent Format Minimum	0 (\$00)
Bias of Biased Exponent	+126 (\$7E)
Range of Fraction	Nonzero
Fraction	0.f
Relation to Representation of Real Numbers	$(-1)^s \times 2^{-126} \times 0.f$
Signed Zeros	
Biased Exponent Format Minimum	0 (\$00)
Fraction	$0.f = 0.0$
Signed Infinities	
Biased Exponent Format Maximum	255 (\$FF)
Fraction	$0.f = 0.0$
NaNs	
Sign	Don't Care
Biased Exponent Format Maximum	255 (\$FF)
Fraction	Nonzero
Representation of Fraction	Nonsignaling Signaling Nonzero Bit Pattern Created by User Fraction When Created by FPCP 0.1xxxx...xxxx 0.0xxxx...xxxx xxxxx...xxxx 11111...1111
Approximate Ranges	
Maximum Positive Normalized	3.4×10^{38}
Minimum Positive Normalized	1.2×10^{-38}
Minimum Positive Denormalized	1.4×10^{-45}

SECTION 2

ADDRESSING CAPABILITIES

Most operations take a source operand and destination operand, compute them, and store the result in the destination location. Single-operand operations take a destination operand, compute it, and store the result in the destination location. External microprocessor references to memory are either program references that refer to program space or data references that refer to data space. They access either instruction words or operands (data items) for an instruction. Program space is the section of memory that contains the program instructions and any immediate data operands residing in the instruction stream. Data space is the section of memory that contains the program data. Data items in the instruction stream can be accessed with the program counter relative addressing modes; these accesses classify as program references.

2.1 INSTRUCTION FORMAT

M68000 family instructions consist of at least one word; some have as many as 11 words. Figure 2-1 illustrates the general composition of an instruction. The first word of the instruction, called the simple effective address operation word, specifies the length of the instruction, the effective addressing mode, and the operation to be performed. The remaining words, called brief and full extension words, further specify the instruction and operands. These words can be floating-point command words, conditional predicates, immediate operands, extensions to the effective addressing mode specified in the simple effective address operation word, branch displacements, bit number or bit field specifications, special register specifications, trap operands, pack/unpack constants, or argument counts.





Figure 2-1. Instruction Word General Format


2.2.1 Data Register Direct Mode

In the data register direct mode, the effective address field specifies the data register containing the operand.




2.2.2 Address Register Direct Mode

In the address register direct mode, the effective address field specifies the address register containing the operand.



2.2.3 Address Register Indirect Mode

In the address register indirect mode, the operand is in memory. The effective address field specifies the address register containing the address of the operand in memory.



2.5.1 No Memory Indirect Action Mode

No memory indirect action mode uses BR, Xn with its modifiers, and bd to calculate the address of the required operand. Data register indirect (Dn) and absolute address with index (bd,Xn.SIZE*SCALE) are examples of the no memory indirect action mode. Figure 2-5 illustrates the no memory indirect action mode.

BR	Xn	bd	Addressing Mode
S	S	S	Not Applicable
S	S	A	Absolute Addressing Mode
S	A	S	Register Indirect
S	A	A	Register Indirect with Constant Index
An	S	S	Address Register Indirect
An	S	A	Address Register Indirect with Constant Index
An	A	S	Address Register Indirect with Variable Index
An	A	A	Address Register Indirect with Constant and Variable Index
PC	S	S	PC Relative
PC	S	A	PC Relative with Constant Index
PC	A	S	PC Relative with Variable Index
PC	A	A	PC Relative with Constant and Variable Index

NOTE: S indicates suppressed and A indicates active.




Figure 2-5. No Memory Indirect Action

Table 3-5. Shift and Rotate Operation Format

Instruction	Operand Syntax	Operand Size	Operation
ASL	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
ASR	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
LSL	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
LSR	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
ROL	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
ROR	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
ROXL	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
ROXR	Dn, Dn # <data>, Dn ea	8, 16, 32 8, 16, 32 16	
SWAP	Dn	32	

NOTE: X indicates the extend bit and C the carry bit in the CCR.




Figure 3-2. Rounding Algorithm Flowchart

The three additional bits beyond the extended-precision format, the difference between the intermediate result's 67-bit mantissa and the storing result's 64-bit mantissa, allow the FPU to perform all calculations as though it were performing calculations using a float engine with infinite bit prec. The result is always correct for the specified destination's data format before performing rounding (unless an overflow or underflow error occurs). The specified rounding operation then produces a number that is as close as possible to the infinitely precise




Figure 3-3. Instruction Description Format



SECTION 4

INTEGER INSTRUCTIONS

This section contains detailed information about the integer instructions for the M68000 family. A detailed discussion of each instruction description is arranged in alphabetical order by instruction mnemonic.

Each instruction description identifies the differences among the M68000 family for that instruction. Noted under the title of the instruction are all specific processors that apply to that instruction—for example:

Test Bit Field and Change (MC68030, MC68040)

The MC68HC000 is identical to the MC68000 except for power dissipation; therefore, all instructions that apply to the MC68000 also apply to the MC68HC000. All references to the MC68000, MC68020, and MC68030 include references to the corresponding embedded controllers, MC68EC000, MC68EC020, and MC68EC030. All references to the MC68040 include the MC68LC040 and MC68EC040. This referencing applies throughout this section unless otherwise specified.

Identified within the paragraphs are the specific processors that use different instruction fields, instruction formats, etc.—for example:

MC68020, MC68030, and MC68040 only

(bd,An,Xn)	110	reg. number:An	(bd,PC,Xn)**	111	011
------------	-----	----------------	--------------	-----	-----

**Can be used with CPU32 processor

Appendix A Processor Instruction Summary provides a listing of all processors and the instructions that apply to them for quick reference.

ABCD

Add Decimal with Extend (M68000 Family)

ABCD

Operation: Source10 + Destination10 + X → Destination

Assembler ABCD Dy,Dx

Syntax: ABCD – (Ay), – (Ax)

Attributes: Size = (Byte)

Description: Adds the source operand to the destination operand along with the extend bit, and stores the result in the destination location. The addition is performed using binary-coded decimal arithmetic. The operands, which are packed binary-coded decimal numbers, can be addressed in two different ways:

- 1. Data Register to Data Register: The operands are contained in the data registers specified in the instruction.
- 2. Memory to Memory: The operands are addressed with the predecrement addressing mode using the address registers specified in the instruction.

This operation is a byte operation only.

Condition Codes:

X	N	Z	V	C
*	U	*	U	*

- X — Set the same as the carry bit.
- N — Undefined.
- Z — Cleared if the result is nonzero; unchanged otherwise.
- V — Undefined.
- C — Set if a decimal carry was generated; cleared otherwise.

NOTE

Normally, the Z condition code bit is set via programming before the start of an operation. This allows successful tests for zero results upon completion of multiple-precision operations.

ABCD

Add Decimal with Extend (M68000 Family)

ABCD

Instruction Format:

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
1	1	0	0	REGISTER Rx			1	0	0	0	0	R/M	REGISTER Ry		

Instruction Fields:

- Register Rx field—Specifies the destination register.
If R/M = 0, specifies a data register.
If R/M = 1, specifies an address register for the predecrement addressing mode.
- R/M field—Specifies the operand addressing mode.
0 — The operation is data register to data register.
1 — The operation is memory to memory.
- Register Ry field—Specifies the source register.
If R/M = 0, specifies a data register.
If R/M = 1, specifies an address register for the predecrement addressing mode.

ADD

Add (M68000 Family)

ADD

Operation: Source + Destination → Destination

Assembler ADD < ea > ,Dn

Syntax: ADD Dn, < ea >

Attributes: Size = (Byte, Word, Long)

Description: Adds the source operand to the destination operand using binary addition and stores the result in the destination location. The size of the operation may be specified as byte, word, or long. The mode of the instruction indicates which operand is the source and which is the destination, as well as the operand size.

Condition Codes:

X	N	Z	V	C
*	*	*	*	*

- X — Set the same as the carry bit.
- N — Set if the result is negative; cleared otherwise.
- Z — Set if the result is zero; cleared otherwise.
- V — Set if an overflow is generated; cleared otherwise.
- C — Set if a carry is generated; cleared otherwise.

Instruction Format:

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
1	1	0	1	REGISTER			OPMODE			EFFECTIVE ADDRESS					
										MODE		REGISTER			

ADD

Add (M68000 Family)

ADD

Instruction Fields:

Register field—Specifies any of the eight data registers.

Opmode field

Byte	Word	Long	Operation
000	001	010	$\langle ea \rangle + Dn \rightarrow Dn$
100	101	110	$Dn + \langle ea \rangle \rightarrow \langle ea \rangle$

Effective Address field—Determines addressing mode.

- a. If the location specified is a source operand, all addressing modes can be used as listed in the following tables:

Addressing Mode	Mode	Register	Addressing Mode	Mode	Register
Dn	000	reg. number:Dn	(xxx).W	111	000
An*	001	reg. number:An	(xxx).L	111	001
(An)	010	reg. number:An	#<data>	111	100
(An) +	011	reg. number:An			
– (An)	100	reg. number:An			
(d ₁₆ ,An)	101	reg. number:An	(d ₁₆ ,PC)	111	010
(d ₈ ,An,Xn)	110	reg. number:An	(d ₈ ,PC,Xn)	111	011

MC68020, MC68030, and MC68040 only

(bd,An,Xn)**	110	reg. number:An	(bd,PC,Xn)†	111	011
([bd,An,Xn],od)	110	reg. number:An	([bd,PC,Xn],od)	111	011
([bd,An],Xn,od)	110	reg. number:An	([bd,PC],Xn,od)	111	011

*Word and long only

**Can be used with CPU32.



ADD

Add (M68000 Family)

ADD

- b. If the location specified is a destination operand, only memory alterable addressing modes can be used as listed in the following tables:

Addressing Mode	Mode	Register	Addressing Mode	Mode	Register
Dn	—	—	(xxx).W	111	000
An	—	—	(xxx).L	111	001
(An)	010	reg. number:An	#<data>	—	—
(An) +	011	reg. number:An			
– (An)	100	reg. number:An			
(d ₁₆ ,An)	101	reg. number:An	(d ₁₆ ,PC)	—	—
(d ₈ ,An,Xn)	110	reg. number:An	(d ₈ ,PC,Xn)	—	—

MC68020, MC68030, and MC68040 only

(bd,An,Xn)*	110	reg. number:An	(bd,PC,Xn)*	—	—
([bd,An,Xn],od)	110	reg. number:An	([bd,PC,Xn],od)	—	—
([bd,An],Xn,od)	110	reg. number:An	([bd,PC],Xn,od)	—	—

*Can be used with CPU32

NOTE

The Dn mode is used when the destination is a data register; the destination < ea > mode is invalid for a data register.

ADDA is used when the destination is an address register. ADDI and ADDQ are used when the source is immediate data. Most assemblers automatically make this distinction.

ADDA

Add Address (M68000 Family)

ADDA

Operation: Source + Destination → Destination

Assembler

Syntax: ADDA < ea > , An

Attributes: Size = (Word, Long)

Description: Adds the source operand to the destination address register and stores the result in the address register. The size of the operation may be specified as word or long. The entire destination address register is used regardless of the operation size.

Condition Codes:

Not affected.

Instruction Format:

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
1	1	0	1	REGISTER			OPMODE			EFFECTIVE ADDRESS					
										MODE			REGISTER		

Instruction Fields:

Register field—Specifies any of the eight address registers. This is always the destination.

Opmode field—Specifies the size of the operation.

011— Word operation; the source operand is sign-extended to a long operand and the operation is performed on the address register using all 32 bits.

111— Long operation.



ADDA

Add Address (M68000 Family)

ADDA

Effective Address field—Specifies the source operand. All addressing modes can be used as listed in the following tables:

Addressing Mode	Mode	Register
Dn	000	reg. number:Dn
An	001	reg. number:An
(An)	010	reg. number:An
(An) +	011	reg. number:An
– (An)	100	reg. number:An
(d ₁₆ ,An)	101	reg. number:An
(d ₈ ,An,Xn)	110	reg. number:An

Addressing Mode	Mode	Register
(xxx).W	111	000
(xxx).L	111	001
#<data>	111	100
(d ₁₆ ,PC)	111	010
(d ₈ ,PC,Xn)	111	011

MC68020, MC68030, and MC68040 only

(bd,An,Xn)*	110	reg. number:An
([bd,An,Xn],od)	110	reg. number:An
([bd,An],Xn,od)	110	reg. number:An

(bd,PC,Xn)*	111	011
([bd,PC,Xn],od)	111	011
([bd,PC],Xn,od)	111	011

*Can be used with CPU32

FDIV

Floating-Point Divide
(MC6888X, MC68040)

FDIV

Operation:

FPn ÷ Source → FPn

Assembler Syntax:

FDIV. < fmt > < ea > ,FPn
 FDIV.X FPM,FPn
 *FrDIV. < fmt > < ea > ,FPn
 *FrDIV.X FPM,FPn
 where r is rounding precision, S or D
 *Supported by MC68040 only

Attributes:

Format = (Byte, Word, Long, Single, Double, Extended, Packed)

Description:

Converts the source operand to extended precision (if necessary) and divides that number into the number in the destination floating-point data register. Stores the result in the destination floating-point data register.

FDIV will round the result to the precision selected in the floating-point control register. FSDIV and FDDIV will round the result to single or double precision, respectively, regardless of the rounding precision selected in the floating-point control register.

Operation Table:

DESTINATION	SOURCE ¹								
	+	In Range	–	+	Zero	–	+	Infinity	–
In Range	+	Divide		+	inf ²	– inf ²	+	0.0	– 0.0
	–			– inf ²	+ inf ²	–	0.0	+ 0.0	
Zero	+	+ 0.0	+ 0.0	NAN ³			+	0.0	– 0.0
	–	– 0.0	+ 0.0				–	0.0	+ 0.0
Infinity	+	+ inf	– inf	+	inf	– inf	NAN‡		
	–	– inf	+ inf	–	inf	+ inf			

- NOTES:
1. If the source operand is a NAN, refer to **1.6.5 Not-A-Numbers** for more information.
 2. Sets the DZ bit in the floating-point status register exception byte.
 3. Sets the OPERR bit in the floating-point status register exception byte.

APPENDIX A

PROCESSOR INSTRUCTION SUMMARY

This appendix provides a quick reference of the M68000 family instructions. The organization of this section is by processors and their addressing modes. All references to the MC68000, MC68020, and MC68030 include references to the corresponding embedded controllers, MC68EC000, MC68EC020, and MC68EC030. All references to the MC68040 include the MC68LC040 and MC68EC040. This referencing applies throughout this section unless otherwise specified. Table A-1 lists the M68000 family instructions by mnemonic and indicates which processors they apply to.

Table A-1. M68000 Family Instruction Set And Processor Cross-Reference

Mnemonic	68000	68008	68010	68020	68030	68040	68881/ 68882	68851	CPU32
ABCD	X	X	X	X	X	X			X
ADD	X	X	X	X	X	X			X
ADDA	X	X	X	X	X	X			X
ADDI	X	X	X	X	X	X			X
ADDQ	X	X	X	X	X	X			X
ADDX	X	X	X	X	X	X			X
AND	X	X	X	X	X	X			X
ANDI	X	X	X	X	X	X			X
ANDI to CCR	X	X	X	X	X	X			X
ANDI to SR ¹	X	X	X	X	X	X			X
ASL, ASR	X	X	X	X	X	X			X
Bcc	X	X	X	X	X	X			X
BCHG	X	X	X	X	X	X			X
BCLR	X	X	X	X	X	X			X
BFCHG				X	X	X			
BFCLR				X	X	X			
BFEXTS				X	X	X			
BFEXTU				X	X	X			
BFFFO				X	X	X			

Table A-1. M68000 Family Instruction Set And Processor Cross-Reference (Continued)

Mnemonic	68000	68008	68010	68020	68030	68040	68881/ 68882	68851	CPU32
BFINS				X	X	X			
BFSET				X	X	X			
BFTST				X	X	X			
BGND									X
BKPT			X	X	X	X			X
BRA	X	X	X	X	X	X			X
BSET	X	X	X	X	X	X			X
BSR	X	X	X	X	X	X			X
BTST	X	X	X	X	X	X			X
CALLM				X					
CAS, CAS2				X	X	X			
CHK	X	X	X	X	X	X			X
CHK2				X	X	X			X
CINV ¹						X			
CLR	X	X	X	X	X	X			X
CMP	X	X	X	X	X	X			X
CMPA	X	X	X	X	X	X			X
CMPI	X	X	X	X	X	X			X
CMPM	X	X	X	X	X	X			X
CMP2				X	X	X			X
cpBcc				X	X				
cpDBcc				X	X				
cpGEN				X	X				
cpRESTORE ¹				X	X				
cpSAVE ¹				X	X				
cpScc				X	X				
cpTRAPcc				X	X				
CPUSH ¹						X			
DBcc	X	X	X	X	X	X			X
DIVS	X	X	X	X	X	X			X
DIVSL				X	X	X			X
DIVU	X	X	X	X	X	X			X
DIVUL				X	X	X			X

**Table A-1. M68000 Family Instruction Set And
Processor Cross-Reference (Concluded)**

Mnemonic	68000	68008	68010	68020	68030	68040	68881/ 68882	68851	CPU32
SWAP	X	X	X	X	X	X			X
TAS	X	X	X	X	X	X			X
TBLS, TBLSN									X
TBLU, TBLUN									X
TRAP	X	X	X	X	X	X			X
TRAPcc				X	X	X			X
TRAPV	X	X	X	X	X	X			X
TST	X	X	X	X	X	X			X
UNLK	X	X	X	X	X	X			X
UNPK				X	X	X			

NOTES:

1. Privileged (Supervisor) Instruction.
2. Not applicable to MC68EC040 and MC68LC040
3. These instructions are software supported on the MC68040.
4. This instruction is not privileged for the MC68000 and MC68008.
5. Not applicable to MC68EC030.




Figure B-7. MC68EC040 and MC68LC040 Floating-Point Unimplemented Stack Frame, Format \$4




Figure B-8. MC68040 Access Error Stack Frame, Format \$7




Figure B-21. MC68040 Idle Stack Frame


 Reserved

Figure B-22. MC68040 Unimplimented Instruction Stack Frame

EXTRA KEYS ON THE KEYBOARD

Both the Amiga 2000 and 500 feature 94-key keyboards, as compared to the A1000's 89-key keyboard. (The European versions of the keyboards have 96 keys.) The new keys are all located on the numeric keypad, and include:

KEY		SCAN CODE
Left parentheses	(	\$5A
Right parentheses	)	\$5B
Slash	/	\$5C
Asterisk	*	\$5D
Plus	+	\$5E

In PC mode on the Amiga 2000 (using a Bridgeboard), these keys assume typical PC functions, including Number lock (left parenthesis), Print screen (asterisk) and Scroll lock (right parenthesis).

On some keyboards, the left Amiga key has been replaced by the Commodore key. This key performs identically in either case.

RAW KEY CODES ON THE KEYBOARD

Keyboard Layout Showing Raw Key Codes




Figure 1.1 Key Codes

Note: On the U.S. keyboard, the keys with codes 44 and 60 are extended to include the European keys with codes 2B and 30, respectively. Also note that England uses the U.S. rather than the European keyboard, but not the U.S. keypad.

See Table 1-1 at the end of this section for a table of the raw key codes.


As you will notice, the A500 and 2000 deletes clocks and interrupt lines from the A1000. The $\pm 5\text{Vdc}$ and reset lines are also deleted. The $\pm 12\text{Vdc}$ lines are identical to a PC10/20.

The following signals (formerly on the RS232 connector) can be found on other connectors:

ResB = parallel connector
C2 = video connector

Centronics Port

The Centronics port also has some non-standard signals. Below is a table comparing the A1000 Centronics port with the A500/A2000 Centronics port. Again, this is the opposite sex from the A1000 and the same sex connector as an IBM®-PC (i.e., a female DB25 connector).



PIN	A1000	A500/A2000	PC10
1	DRDY*	STROBE*	STROBE*
2	Data 0	Data 0	Data 0
3	Data 1	Data 1	Data 1
4	Data 2	Data 2	Data 2
5	Data 3	Data 3	Data 3
6	Data 4	Data 4	Data 4
7	Data 5	Data 5	Data 5
8	Data 6	Data 6	Data 6
9	Data 7	Data 7	Data 7
10	ACK*	ACK*	ACK*
11	BUSY(data)	BUSY	BUSY
12	POUT(clk)	POUT	POUT
13	SEL	SEL	SEL
14	GND	+5v pullup	AUTOFDXT*
15	GND	NC	ERROR*
16	GND	RESET*	INIT*
17	GND	GND	SLCT IN*
18-22	GND	GND	GND
23	+5v	GND	GND
24	NC	GND	GND
25	Reset*	GND	GND

Video Output

The A500 and A2000, like the A1000, use a DB23 video connector.

This 23 pin connector contains all the signals necessary to work with a Genlock, but the current Genlock will need to be redesigned in order to meet the physical requirements of the A500 and A2000, in-

Table 1-1 RAW KEY CODES

Raw Key Number	Keycap Legend	Unshifted Default Value	Shifted Default Value
00	` ~	` (Accent grave)	~ (tilde)
01	1 !	1	!
02	2 @	2	@
03	3 #	3	#
04	4 \$	4	\$
05	5 %	5	%
06	6 ^	6	^
07	7 &	7	&
08	8 *	8	*
09	9 (	9	(
0A	0)	0	)
0B	- _	- (Hyphen)	_ (Underscore)
0C	= +	=	+
0D	\	\	
0E		(undefined)	
0F	0	0	0 (Numeric pad)
10	Q	q	Q
11	W	w	W
12	E	e	E
13	R	r	R
14	T	t	T
15	Y	y	Y
16	U	u	U
17	I	i	I
18	O	o	O
19	P	p	P
1A	[{	[	{
1B	] }	]	}
1C		(undefined)	
1D	1	1	1 (Numeric pad)
1E	2	2	2 (Numeric pad)
1F	3	3	3 (Numeric pad)
20	A	a	A
21	S	s	S
22	D	d	D
23	F	f	F
24	G	g	G
25	H	h	H
26	J	j	J
27	K	k	K
28	L	l	L
29	::	:	::
2A	;"	' (single quote)	;"

Raw Key Number	Keycap Legend	Unshifted Default Value	Shifted Default Value
2B		(RESERVED)	(RESERVED)
2C		(undefined)	
2D	4	4	4 (Numeric pad)
2E	5	5	5 (Numeric pad)
2F	6	6	6 (Numeric pad)
30		(RESERVED)	(RESERVED)
31	Z	z	Z
32	X	x	X
33	C	c	C
34	V	v	V
35	B	b	B
36	N	n	N
37	M	m	M
38	, <	, (comma)	<
39	. >	. (period)	>
3A	/ ?	/	?
3B		(undefined)	
3C		.	. (Numeric pad)
3D	7	7	7 (Numeric pad)
3E	8	8	8 (Numeric pad)
3F	9	9	9 (Numeric pad)
40	(Space bar)	20	20
41	BACK SPACE	08	08
42	TAB	09	09
43	ENTER	0D	0D (Numeric pad)
44	RETURN	0D	0D
45	ESC	1B	1B
46	DEL	7F	7F
47		(undefined)	
48		(undefined)	
49		(undefined)	
4A	-	-	- (Numeric Pad)
4B		(undefined)	
4C	Up Arrow	<CSI>A	<CSI>T
4D	Down Arrow	<CSI>B	<CSI>S
4E	Forward Arrow	<CSI>C	<CSI> A ¹
4F	Backward Arrow	<CSI>D	<CSI> @

¹ In shifted Forward Arrow and Backward Arrow, note blank space after <CSI>.
<CSI> stands for Command Sequence Initiator.

Raw Key Number	Keycap Legend	Unshifted Default Value	Shifted Default Value
50	F1	<CSI>0~	<CSI>10~
51	F2	<CSI>1~	<CSI>11~
52	F3	<CSI>2~	<CSI>12~
53	F4	<CSI>3~	<CSI>13~
54	F5	<CSI>4~	<CSI>14~
55	F6	<CSI>5~	<CSI>15~
56	F7	<CSI>6~	<CSI>16~
57	F8	<CSI>7~	<CSI>17~
58	F9	<CSI>8~	<CSI>18~
59	F10	<CSI>9~	<CSI>19~
5A	(	(	(
5B	)	)	)
5C	/	/	/
5D	*	*	*
5E	+	+	+
5F	HELP	<CSI>?~	<CSI>?~

Designing Hardware for the Amiga Expansion Architecture

INTRODUCTION

This section gives guidelines for designing hardware to reside on the Amiga expansion bus. The Amiga expansion bus is a relatively straightforward extension of the 68000 bus.

Hardware for the bus can be viewed as two categories: backplanes and PICs. Backplanes interface to the 86 pin connector of either another backplane or the Amiga itself. Backplanes buffer the bus and provide 100 pin connectors for PICs to plug into.

PIC is an acronym for plug-in card. A PIC is usually a card that plugs into the standard 100 pin Amiga connectors.

A sub-type of PIC is a combination of backplane and PIC integrated into one package. These combination products should follow all of the applicable backplane and PIC rules, especially auto-configuration.

Software never sees backplanes; all expansion hardware appears to the software as PICs.

WARNING

These specifications represent "worst case" design targets. Products that do not comply with these specifications can be expected to fail on worst case production units.

Following conservative design practices and allowing the widest safety margins is your best assurance against problems in the field.

EXPANSION ARCHITECTURE OVERVIEW

As shown in Figure 3.1, "Expansion Architecture Overview," the expansion bus is implemented as backplane (an expansion box) which accept PICs (boards). The recommended number of PICs to a backplane is five.

Due to timing considerations, it is not possible to daisy-chain more than two buffered backplanes without inserting wait states.

NOTE

You should also take extreme care in controlling signal radiation from your product, in order to pass FCC class B regulations.




Figure 3.1. Expansion Architecture Overview

requirement is because the eight megabyte space reserved for expansion in the current machine begins at hex 200000 (See auto-config notes below).


Auto-Config Notes

- 1) There is currently no provision for 6MB PICs. Designers of 8 MB memory boards should consider auto-configs as two PICs to allow partial loading flexibility.
- 2) PIC size/alignment rules are subject to change. If so, bit(s) will be defined to allow a PIC to specify that it is more flexible than the old rules require.
- 3) The address map is subject to change. A PIC should assume that it may be placed anywhere in the address space.
- 4) All expansion devices are strongly encouraged to use the auto-config protocols. Assignment of fixed I/O addresses is subject to negotiation.




Address Specification Table

All nibbles except 00, 02, 40 and 42 should be inverted.

Descriptions:



(04/06)	7	6	5	4	3	2	1	0	Product number, this number is defined by the manufacturer of the board and is used by auto-config software to initialize drivers for the board.
(08/0A)	7	6	5	4	3	2	1	0	Reserved, must be as specified
									Bits are currently zero 0 means this board can be shut up 1 means this board cannot be shut up 0 means any space okay 1 means preference to be put in the 8 Meg space
(0C/0E)	7	6	5	4	3	2	1	0	Reserved, must be 0
(10/12)	7	6	5	4	3	2	1	0	Mfg # high byte
(14/16)	7	6	5	4	3	2	1	0	Mfg # low byte; These 2 bytes are assigned by CBM. They are used by the auto-config software to initialize drivers for boards.
(18/1A)	7	6	5	4	3	2	1	0	Optional serial number, byte 0 (msb)
(1C/1E)	7	6	5	4	3	2	1	0	Optional serial number, byte 1
(20/22)	7	6	5	4	3	2	1	0	Optional serial number, byte 2
(24/26)	7	6	5	4	3	2	1	0	Optional serial number, byte 3 (lsb)
(28/2A)	7	6	5	4	3	2	1	0	Optional ROM vector high byte
(2C/2E)	7	6	5	4	3	2	1	0	Optional ROM vector low byte. If the 'ROM addr valid' bit (4 of nibble 0) is set, then these 2 bytes are the offset from the board's base address at which the start of the ROM code information is located (e.g., the hard disk driver). If the bit is not set, then these 2 bytes have no meaning.
(30/32)	7	6	5	4	3	2	1	0	Reserved, read must be 0; write resets base address register
(34/36)	7	6	5	4	3	2	1	0	Reserved, must be 0
(38/3A)	7	6	5	4	3	2	1	0	Reserved, must be 0
(3C/3E)	7	6	5	4	3	2	1	0	Reserved, must be 0



(4C/4E) x x x x x x x x Optional "shut up" address, a write to this address will cause the board to pass its config out and then never again respond to any address. RESET will re-enable the board. The actual address that has this effect is 4C. A write to 4E is ignored. This is write only.

(50/52)	7	6	5	4	3	2	1	0	Reserved, must be 00
(54/56)	7	6	5	4	3	2	1	0	Reserved, must be 00
(58/5A)	7	6	5	4	3	2	1	0	Reserved, must be 00
(5C/5E)	7	6	5	4	3	2	1	0	Reserved, must be 00
(60/62)	7	6	5	4	3	2	1	0	Reserved, must be 00
(64/66)	7	6	5	4	3	2	1	0	Reserved, must be 00
(68/6A)	7	6	5	4	3	2	1	0	Reserved, must be 00
(6C/6E)	7	6	5	4	3	2	1	0	Reserved, must be 00
(70/72)	7	6	5	4	3	2	1	0	Reserved, must be 00
(74/76)	7	6	5	4	3	2	1	0	Reserved, must be 00
(78/7A)	7	6	5	4	3	2	1	0	Reserved, must be 00
(7C/7E)	7	6	5	4	3	2	1	0	Reserved, must be 00

Note: The actual reserved values will be FF rather than 00, because the system will invert them. See the section on reading I/O locations for more information.

2000 SYSTEM BUS LOADING

The following numbers and notations are used for standard load and drive values:

Type		From A2000 (IC input load)		To A2000 (IC output drive)
F-Driver TTL	FD	20 μ A @ 2.7V -1.6mA @ 0.5V	fd	2.0V @ -15mA 0.5V @ 64mA
F-Series TTL	F	20 μ A @ 2.7V -0.6mA @ 0.5V	f	2.7V @ -1mA 0.5V @ 20mA
LS-Driver TTL	LSD	20 μ A @ 2.7V -0.4mA @ 0.4V	lsd	2.0V @ -15mA 0.5V @ 24mA
LS-Series TTL	LS	20 μ A @ 2.7V -0.4mA @ 0.4V	ls	2.7V @ -400 μ A 0.5V @ 8mA
MOS	MOS	10 μ A @ 2.4V -10 μ A @ 0.4V	mos	2.4V @ -200 μ A 0.4V @ 3.2mA
Open Collector			oc	FROM RESISTOR 0.5V @ 8mA

Any lesser input load can be used on a signal in place of a greater load or equivalent load. Varying the number of load elements while still meeting the DC loading criteria can be done if necessary, but it is not a good idea, as it can still exceed the expected capacitive loading on the signal.

A final type of drive is the open collector (oc). Some PIC outputs must be open collector, as they are in a wired-or configuration with the same output from other PICs or motherboard signals.

Most of the system bus signals provide a standard drive to their respective connectors. If your drivers can meet the input specification, don't worry about what is actually required. However, even if your loading doesn't exceed the specified drive capacity of slot signal mentioned above, consult the following chart for specific signals that may provide less drive than a standard signal of that type. Signals that match the STANDARD loading are not separately listed.

Named Signals	DIR	Expansion Slots (each)	Coprocessor Slot	Video Slot
STANDARD	I	2F	1F	1F
STANDARD	O	10f	10f	10f
/DTACK	I	1F	1F	
	O	10f	10f	
/OVR	O	oc	oc	
XRDY	O	oc	oc	
/INT2	O	oc	oc	
/INT6	O	oc	oc	
/EINT1	O	oc		
/EINT4	O	oc		
/EINT5	O	oc		

Named Signals	DIR	Expansion Slots (each)	Coprocessor Slot	Video Slot
/EINT7	0	0c		
/SLAVEn	0	2f		
/CFGOUTn	0	2f		
/COPCFG	0		2f	
E Clock	1	1F	1F	
7MHz Clock	1	1F	1F	
/BERR	1	1F	1F	
	0	0c	0c	
/VPA	1	1F	1F	
	0	0c	0c	
/VMA	1	1F	1F	
	0	10f	10f	
/RST	1	1F	1F	
	0	0c	0c	
/HLT	1	1F	1F	
	0	0c	0c	
/OWN	0	0c		
/BRn	0	2f		
/CBR	1		2F	
	0		2f	
/CBG	1		2F	
	0		2f	
/BGACK	1	1F	1F	
	0	0c	0c	
/BOSS	0		2f	
XCLK	0			2f
/XCLKEN	0			2f

TABLE 3-2

PAL16L8
STEERING150R17 REV3
11-17-85
AMIGA

/SLVOUT RD /ASQ /ASQ90 COLLIS /BG /AS /BGACK /DMAIN GND
 /OWN /AOE /UDS /BERR /DMAOUT /LDS /DBOE /RES /D2P VCC

DBOE	= AS * /RD * /BERR + UDS * RD * ASQ * /BERR + LDS * RD * ASQ * /BERR	;DATA DRIVERS DURING WRITE CYCLE ;TURN ON DRIVERS LATE FOR RD ;UDS AND LDS PROTECT RD MOD WR ;TO AVOID TRI__STATE FIGHT
D2P	= /DMAOUT * SLVOUT * RD + DMAOUT * /SLVOUT * /RD + DMAOUT * SLVOUT	;DOWNSTREAM READS UPSTREAM SLAVE ;UPSTREAM WRITES DOWNSTREAM SLAVE ;MASTER AND SLAVE ARE UPSTREAM
AOE	= BGACK + /BG * /DMAOUT + AS + ASQ90	;AS KEEPS ADDR WHEN /BG DROPS ;ASQ90 MAINTAINS VALID ADDR ON ;LAST PROC CYCLE

DMAOUT = DMAIN + OWN

IF (/RES * COLLIS) BERR = VCC

DESCRIPTION

SLVOUT = SLAVEOUT, ASQ = AS DELAYED, ASQ90 = AS CLKD ON LOW EDGE OF 7M,
 BG = BUS GRANT, OWN = LOCAL OWN
 COLLIS = BUS COLLISION, AOE = ADDR OUTPUT EN, DOE = DATA OE
 RES = RESET, D2P = DATA TO PROCESSOR
 UDS LDS PROTECT AGAINST RDMODIFYWRITE 3STFIGHT & BERR = /DOE

TABLE 3-3

PAL16R6
ARBITRATE REV1
1-6-86
AMIGA

7M /BRIN /RES /BGIN /BR5 /BR4 /BR3 /BR2 /BR1 GND
 GROUND /BGOUT /BGOLD /BG5 /BG4 /BG3 /BG2 /BG1 /BR VCC

$\text{BG1} = \text{BGIN} * \text{/BGOLD} * \text{BR1} *$ $\text{BGIN} * \text{BG1} \quad *$	$\text{/RES} + \text{;GENERATE BG1}$ $\text{/RES} \quad \text{;HOLD UNTIL /BG}$
$\text{BG2} = \text{BGIN} * \text{/BGOLD} * \text{BR2} * \text{/BR1} *$ $\text{BGIN} * \text{BG2} \quad *$	$\text{/RES} +$ /RES
$\text{BG3} = \text{BGIN} * \text{/BGOLD} * \text{BR3} * \text{/BR1} * \text{/BR2} *$ $\text{BGIN} * \text{BG3} \quad *$	$\text{/RES} +$ /RES
$\text{BG4} = \text{BGIN} * \text{/BGOLD} * \text{BR4} * \text{/BR1} * \text{/BR2} * \text{/BR3} *$ $\text{BGIN} * \text{BG4} \quad *$	$\text{/RES} +$ /RES
$\text{BG5} = \text{BGIN} * \text{/BGOLD} * \text{BR5} * \text{/BR1} * \text{/BR2} * \text{/BR3} * \text{/BR4} *$ $\text{BGIN} * \text{BG5} \quad *$	$\text{/RES} +$ /RES
$\text{BGOLD} = \text{BGIN}$	$\text{;STORE OLD STATE OF BG}$
$\text{BR} = \text{BRIN} * \text{/RES} +$ $\text{BR1} \quad * \text{/RES} +$ $\text{BR2} \quad * \text{/RES} +$ $\text{BR3} \quad * \text{/RES} +$ $\text{BR4} \quad * \text{/RES} +$ $\text{BR5} \quad * \text{/RES}$	$\text{;BR IS RQST TO 68K}$
$\text{BGOUT} = \text{BGIN} * \text{BGOLD} * \text{/BG1} * \text{/BG2} * \text{/BG3} * \text{/BG4} * \text{/BG5}$	

DESCRIPTION

BG1 IS HIGHEST PRIORITY

Description of PC/XT Emulator for AMIGA 2000

AMIGA ACCESS: Amiga Interface Offset Address = Base Addr.

Base Addr. + (00000 – 1FFFF) : Byte Access
Base Addr. + (20000 – 3FFFF) : Word Access
Base Addr. + (40000 – 5FFFF) : Graphic Access
Base Addr. + (60000 – 7FFFF) : I/O Register Access

INTERFACE MEMORY MAP:

Interface Offset Address	Size	Usage
00000 ... 0FFFF	64K	DISK BUFFER RAM
10000 ... 17FFF	32K	COLOR VIDEO RAM
18000 ... 1BFFF	16K	PARAMETER RAM
1C000 ... 1DFFF	8K	MONO VIDEO RAM
1E000 ... 1FFFF	8K	IO-PAGE

Kinds of memory access on the following pages:

B = Byte access

G = Graphic access

W = Word access

(*) selectable by BIT 5 and 6 of the MODE REGISTER

BIT 5 = SEL1

BIT 6 = SEL2

PC MEMORY AND I/O MAP:

PC Address	Range	Size	Usage	kind of access	Amiga Interface Offset Address
0000 ...	03FF	1K	IO-PAGE	B W G	1E000 ... 1FFFF 3E000 ... 3FFFF 5E000 ... 5FFFF 7E000 ... 7FFFF
A0000 ...	AFFFF	64K	DISK BUFFER RAM (*) (*) (*)	B W G	00000 ... 0FFFF 20000 ... 2FFFF 40000 ... 4FFFF
B0000 ...	B1FFF	8K	MONO VIDEO RAM	B W G	1C000 ... 1DFFF 3C000 ... 3DFFF 5C000 ... 5DFFF
B8000 ...	BFFFF	32K	COLOR VIDEO RAM	B W G	10000 ... 17FFF 30000 ... 37FFF 50000 ... 57FFF
E0000 ...	EFFFF	64K	DISK BUFFER RAM (*) (*) (*)	B W G	00000 ... 0FFFF 20000 ... 2FFFF 40000 ... 4FFFF
D0000 ...	DFFFF	64K	DISK BUFFER RAM (*) (*) (*)	B W G	00000 ... 0FFFF 20000 ... 2FFFF 40000 ... 4FFFF
F0000 ...	F3FFF	16K	PARAMETER RAM	B W G	18000 ... 1BFFF 38000 ... 3BFFF 58000 ... 5BFFF

AMIGA MEMORY MAP:

Amiga Interface Offset Address	PC Address Range	Size	Usage	kind of access
00000 ... 0FFFF	A0000 ... AFFFF	64K	DISK BUFFER RAM (*)	B
00000 ... 0FFFF	D0000 ... DFFFF	64K	DISK BUFFER RAM (*)	B
00000 ... 0FFFF	E0000 ... EFFFF	64K	DISK BUFFER RAM (*)	B
10000 ... 17FFF	B8000 ... BFFFF	32K	COLOR VIDEO RAM	B
18000 ... 1BFFF	F0000 ... F3FFF	16K	PARAMETER RAM	B
1C000 ... 1DFFF	B0000 ... B1FFF	8K	MONO VIDEO RAM	B
1E000 ... 1FFFF	0000 ... 03FF	1K	IO-PAGE	B
20000 ... 2FFFF	A0000 ... AFFFF	64K	DISK BUFFER RAM (*)	W
20000 ... 2FFFF	D0000 ... DFFFF	64K	DISK BUFFER RAM (*)	W
20000 ... 2FFFF	E0000 ... EFFFF	64K	DISK BUFFER RAM (*)	W
30000 ... 37FFF	B8000 ... BFFFF	32K	COLOR VIDEO RAM	W
38000 ... 3BFFF	F0000 ... F3FFF	16K	PARAMETER RAM	W
3C000 ... 3DFFF	B0000 ... B1FFF	8K	MONO VIDEO RAM	W
3E000 ... 3FFFF	0000 ... 03FF	1K	IO-PAGE	W
40000 ... 4FFFF	A0000 ... AFFFF	64K	DISK BUFFER RAM (*)	G

PC/AT I/O

Address Usage

Offset Address
INTERFACE / Amiga

379	"	RESET IRQ7	(R)	1E1BF	7E1BF
379	"	INTERRUPT CONTROL BIT 6 = 0 : ON BIT 6 = 0 : OFF	(W)	1E19F	7E19F
37A	"	CONTROL	(W)	1E1DF	7E1DF
37A	"	CONTROL	(R)	1E19F	7E19F
380	MONO	CRT ADDRESS INDEX REGISTER	(W)	1E1FF	7E1FF
380	"	RESET IRQ3 _a	(R)	1E01F	7E01F
382	"	CRT ADDRESS INDEX REGISTER	(W)	1E1FF	7E1FF
382	"	DUMMY	(R)	1E01F	7E01F
384	"	CRT ADDRESS INDEX REGISTER	(W)	1E1FF	7E1FF
384	"	DUMMY	(R)	1E01F	7E01F
386	"	CRT ADDRESS INDEX REGISTER	(W)	1E1FF	7E1FF
386	"	DUMMY	(R)	1E01F	7E01F
381	"	CRT DATA REGISTER	(R/W)		s.b.
383	"	CRT DATA REGISTER	(R/W)		s.b.
385	"	CRT DATA REGISTER	(R/W)		s.b.
387	"	CRT DATA REGISTER	(R/W)		s.b.
		LAST WRITE ON INDEX = 00		1E2A1	7E2A1
		LAST WRITE ON INDEX = 01		1E2A3	7E2A3
		LAST WRITE ON INDEX = 02		1E2A5	7E2A5
		LAST WRITE ON INDEX = 03		1E2A7	7E2A7
		LAST WRITE ON INDEX = 04		1E2A9	7E2A9
		LAST WRITE ON INDEX = 05		1E2AB	7E2AB
		LAST WRITE ON INDEX = 06		1E2AD	7E2AD
		LAST WRITE ON INDEX = 07		1E2AF	7E2AF
		LAST WRITE ON INDEX = 08		1E2B1	7E2B1
		LAST WRITE ON INDEX = 09		1E2B3	7E2B3
		LAST WRITE ON INDEX = 0A		1E2B5	7E2B5
		LAST WRITE ON INDEX = 0B		1E2B7	7E2B7
		LAST WRITE ON INDEX = 0C		1E2B9	7E2B9
		LAST WRITE ON INDEX = 0D		1E2BB	7E2BB
		LAST WRITE ON INDEX = 0E		1E2BD	7E2BD
		LAST WRITE ON INDEX = 0F		1E2BF	7E2BF
388	MONO	CONTROL REGISTER	(W)	1E2FF	7E2FF
38A	MONO	STATUS REGISTER	(R)	—	—
		BIT 0 : H-SYNC (18KHz)			
		BIT 3 : V-SYNC (50 Hz)			
38A	DUMMY		(W)	1E01F	7E01F
38B	DUMMY		(R/W)	1E01F	7E01F
38C	DUMMY		(R/W)	1E01F	7E01F
38D	DUMMY		(R/W)	1E01F	7E01F
38E	DUMMY		(R/W)	1E01F	7E01F
38F	DUMMY		(R/W)	1E01F	7E01F

WRITE TELETYPE (AH = 0EH)

INPUT AL = CHARACTER TO BE WRITTEN
BL = FOREGROUND COLOR OF CHAR (USED ONLY IN GRAPHICS MODE)
BH = REQUESTED DISPLAY PAGE (REALLY IS IGNORED)

OUTPUT: None

READ CURRENT VIDEO STATE (AH = 0FH)


INPUT: DS = ROM data segment

OUTPUT: AH = NUMBER OF SCREEN COLUMNS
AL = CURRENT VIDEO MODE
BH = ACTIVE DISPLAY PAGE


EQUIPMENT CHECK VIA S/W INT 11H

OUTPUT: AX = Equipment Flags

Bits of AL:



Bits of AH:



MEMORY SIZE CHECK VIA S/W INT 12H

OUTPUT: AX = Total Memory size in Kilobytes


EIA DSR ENTRY POINT VIA S/W INT 14H

INITIALIZE COMM PORT (AH = 00H)

INPUT: DX = Modem Control Register port
AL = Baud Rate and UART control parameters
BH = 0, upper bits of baud rate index

OUTPUT: AH = Line Status
AL = Modem Status
Serial Port Control bits in AL Register

Bits of AL on Entry:



TRANSMIT A CHAR (AH = 01H)

INPUT: DX = Index into device table
AL = Character to transmit
CX = Timeout value
BX = 0, used as timeout counter

OUTPUT: AH = Line Status

RECEIVE A CHAR (AH = 02H)

INPUT: DX = Index into device table
CX = Timeout value
BX = 0, used as timeout counter

OUTPUT: AH = Line Status (error bits only, = 0 if OK)
AL = Received Character

Janus.Library

PREFACE

This is a brief description of the janus code. This code supports low level access to the "janus" system — the link between a PC and an Amiga.

THE PUBLIC ROUTINES

Contents

- AllocJanusMem
- CheckJanusInt
- CleanupJanusSig
- FreeJanusMem
- GetJanusStart
- GetParamOffset
- JBCopy
- JanusLock
- JanusMemBase
- JanusMemToOffset
- JanusMemType
- JanusUnLock
- SendJanusInt
- SetJanusEnable
- SetJanusHandler
- SetJanusRequest
- SetParamOffset
- SetupJanusSig

Descriptions

The code is packaged as a library (specifically "janus.library"), which is loaded during Autoconfig procedure.

All routines that return a value return it in D0. There is a link library for C routines, "jlib.lib".

oldHandler = SetJanusHandler(jintnum, intserver)
D0 A1

This routine sets up an interrupt handler for a particular janus interrupt. The old interrupt is returned. A null means that there is no interrupt handler. If there is no interrupt handler then interrupts not will be processed for that jintnum.

oldEnable = SetJanusEnable(jintnum, newvalue)
D0 D1

INCLUDE FILES

janus.[hi]:

gives interface to janus.library. All definitions in this file are amiga specific. The most useful thing in this file are the definitions for janus memory allocation types

janusreg.[hi]:

hardware constants. Most people should not need this. If you do, we need to hide more information.

janusvar.[hi]:

the shared data structure between the amiga and the pc. Once again, you should not need direct access to these routines. We have tried to provide interface routines to do all the normal things.

i86block.i:

command blocks for calling pc's interrupt's directly and for the hard disk.

services.[hi]:

hard coded constants for interrupt numbers. Eventually these numbers will be gotten at run time, but for now they are constants. These numbers correspond to the "jintnum" parameters below.

setupsig.[hi]:

data structure for SetupJanusSig() call.

LISTINGS

i86block.i — interface definitions between amiga and
commodore-pc
Copyright © 1986, Commodore-Amiga Inc., All rights reserved

IFND
JANUS.I86BLOCK.I

JANUS_I86BLOCK_I
SET 1

; All registers in this section are arranged to be read and written
; from the WordAccessOffset area of the shared memory. If you really
; need to use the ByteAccessArea, all the words will need to be byte
; swapped.

```

        UWORD   adr_BufferAddr           ; offset into MEMF-
                                           _BUFFER memory for
                                           buffer
        UWORD   adr_Err                   ; return code, 0 if all OK
        LABEL   AmigaDskReq_SIZEOF

```

; Function codes for AmigaDskReq adr_Funct word:

```

ADR_FNCTN_INIT      EQU    0 ; given nothings, sets adr_
                          Part to # partitions
ADR_FNCTN_READ      EQU    1 ; given partition, offset,
                          count, buffer
ADR_FNCTN_WRITE     EQU    2 ; given partition, offset,
                          count, buffer
ADR_FNCTN_SEEK      EQU    3 ; given partition, offset
ADR_FNCTN_INFO      EQU    4 ; given part, buff adr, cnt,
                          copys in a DskPartition
                          structure. cnt set to actual
                          number of bytes copied.

```

; Error codes for adr_Err, returned in low byte:

```

ADR_ERR_OK          EQU    0 ; no error
ADR_ERR_OFFSET      EQU    1 ; offset not on sector
                          boundary
ADR_ERR_COUNT       EQU    2 ; dsk_count not a multiple
                          of sector size
ADR_ERR_PART        EQU    3 ; partition does not exist
ADR_ERR_FNCT        EQU    4 ; illegal function code
ADR_ERR_EOF         EQU    5 ; offset past end of
                          partition
ADR_ERR_MULPL       EQU    6 ; multiple calls while
                          pending service

```

; Error condition from IBM-PC BIOS, returned in high byte:

```

ADR_ERR_SENSE_FAIL  EQU    $ff
ADR_ERR_UNDEF_ERR   EQU    $bb
ADR_ERR_TIME_OUT    EQU    $80
ADR_ERR_BAD_SEEK    EQU    $40
ADR_ERR_BAD_CNTRLR  EQU    $20
ADR_ERR_DATA_CORRECTED EQU    $11 ; data corrected
ADR_ERR_BAD_ECC     EQU    $10
ADR_ERR_BAD_TRACK   EQU    $0b
ADR_ERR_DMA_BOUNDARY EQU    $09
ADR_ERR_INIT_FAIL   EQU    $07
ADR_ERR_BAD_RESET   EQU    $05
ADR_ERR_RECRD_NOT_FOUND EQU    $04
ADR_ERR_BAD_ADDR_MARK EQU    $02
ADR_ERR_BAD_CMD     EQU    $01

```

```

ENDC      !JANUS.I86BLOCK.I

```

janus.i — software conventions for janus.i
 Copyright © 1986, Commodore-Amiga Inc., All rights reserved

```
IFND      EXEC_TYPES.I
INCLUDE   "exec/types.i"
ENDC      EXEC_TYPES.I
```

```
IFND      EXEC_LIBRARIES.I
INCLUDE   "exec/libraries.i"
ENDC      EXEC_LIBRARIES.I
```

```
IFND      EXEC_INTERRUPTS.I
INCLUDE   "exec/interrupts.i"
ENDC      EXEC_INTERRUPTS.I
```

; JanusResource — an entity which keeps track of the reset state of the 8088. If this resource does not exist, it is assumed the 8088 can be reset.

```
STRUCTURE JanusResource, LN_SIZE
    APTR    jr_BoardAddress      ; address of JANUS board
    UBYTE    jr_Reset            ; non_zero indicates 8088
                                ; is held reset
    LABEL    JanusResource_SIZEOF
```

*; As a coding convenience, we assume a maximum of 32 handlers.
 ; People should avoid using this in their code, because we want to
 ; be able to relax this constraint in the future. All the standard
 ; commands' syntactically support any number of interrupts, but
 ; the internals are limited to 32.*

```
MAXHANDLER    EQU    32
```

; JanusAmiga — amiga specific data structures for janus project:

```
STRUCTURE JanusAmiga, LIB_SIZE
ULONG    ja_IntReq      ; software copy of out-
                        ; standing requests
ULONG    ja_IntEna      ; software copy of enabled
                        ; interrupts
APTR     ja_ParamMem     ; ptr to (word arranged)
                        ; param mem
APTR     ja_IoBase       ; ptr to base of io register
                        ; region
APTR     ja_ExpanBase    ; ptr to start of shared
                        ; memory
APTR     ja_ExecBase     ; ptr to exec library
APTR     ja_DOSBase      ; ptr to DOS library
APTR     ja_SegList      ; holds a pointer to our
                        ; code segment
```

janus.h—the software data structures for the janus board
 Copyright © 1986, Commodore Amiga Inc., All rights reserved

```

/* all bytes described here are described in the byte order of the
 * 8088. Note that words and longwords in these structures will be
 * accessed from the word access space to preserve the byte order in
 * a word — the 8088 will access longwords by reversing the words:
 * like a 68000 access to the word access memory.
 */

```

```

/* JanusMemHead — a data structure roughly analogous to an exec
 mem chunk.
 * It is used to keep track of memory used between the 8088 and the
 68000.
 */

```

```

struct JanusMemHead [
    UBYTE   jmh_Lock;           /* lock byte between
                                processors */
    UBYTE   jmh_pad0;
    APTR    jmh_68000Base;     /* rpтр's are relative to this */
    UWORD    jmh_8088Segment; /* segment base for 8088 */
    RPTR     jmh_First;        /* offset to first free chunk */
    RPTR     jmh_Max;          /* max allowable index */
    UWORD    jmh_Free;         /* total number of free
                                bytes -1 */
];

```

```

/* JanusMemChunk — keep track of individually freed chunks of
 memory.
 * Memory Chunks are longword aligned in this memory.
 */

```

```

struct JanusMemChunk [
    RPTR     jmc_Next;         /* rpтр to next free chunk */
    UWORD    jmc_Size;         /* size of chunk -1 */
];

```

```

#ifdef undef
this stuff is saved for future use, but is not yet thought out
/* JanusList — an RPTR/Exec style list header.
 */

```

```

struct JanusList [
    RPTR     jl_Head;
    RPTR     jl_Tail;
    RPTR     jl_TailPred;
    UBYTE    jl_Lock;          /* lock byte between
                                processors

```

```

        */UBYTE jI—pad0;
    ];

    /* JanusNode — an RPTR/Exec style node.
    */
    struct JanusReqList
    {
        RPTR    jn—Succ;
        RPTR    jn—Pred;
        RPTR    jn—Name;
        UWORD   jn—ReqIndex;    /* this' index into jb—
                                CommRegs */
    };

    #endif undef

    /* JanusBase — the master data table for the janus project. It is
    located
    * at the bottom of parameter memory.*/

    struct JanusBase [
        UBYTE   jb—Lock;        /* lock byte between
                                processors */

        UBYTE   jb—8088Go;

        struct   JanusMemHead /* free mem pool for param
                                jb—ParamMem;      memory
        struct   JanusMemHead /* free mem pool for buffer
                                jb—BufferMem;      memory */
        RPTR    jb—Interrupts; /* (UBYTE *) of request
                                byte-pairs */
        RPTR    jb—Parameters; /* array of ptrs to parameter
                                areas */
        UWORD   jb—NumInterrupts; /* number of interrupts &
                                parameters */];

    /* constant to set to indicate a pending software interrupt
    */
    #define JSETINT    0x7f

```

memrw.i—parameter area definition for access to other
processors mem
Copyright © 1986, Commodore-Amiga Inc., All rights reserved

```

    #ifndef JANUS_MEMRW_H
    #define JANUS_MEMRW_H

    /*
    ** this is the parameter block for the JSERV_READPC and JSERV_
    ** READAMIGA services — read and/or write the other processors
    memory.
    */

```

PC JANUS SERVICE

This service is called via INT JANUS.
AH contains a function code

J_GET_SERVICE

Gets a new Service Number

Expects:

nothing

Returns:

AL : New Service Number to use
- 1 if no service available (J_NO_SERVICE)

J_GET_BASE

Gets Segments & offset of Janus Memory

Expects:

AL : Janus Service Number

Returns:

ES : Janus Parameter Segment
DI : Janus Parameter Offset (if defined),
else - 1
DX : Janus Buffer Segment
AL : Status (J_OK, J_NO_SERVICE)

J_ALLOC_MEM

Allocates Janus Memory

Expects:

AL : Type of memory to allocate
BX : Number of Bytes to allocate

Returns:

BX : Offset of registered memory if success,
AL : Status (J_OK, J_NO_MEMORY)

J_FREE_MEM

Releases Janus Memory

Expects:

AL : Type of memory to free
BX : Offset of Memory to free

Returns:

Crash if offset/type was wrong (J_GOODBYE, later)

J_SET_PARAM

Set the default parameter memory pointer

Expects:

AL : Janus Service Number to support
BX : Default Offset of Param Memory to install

Returns:

AL : Status (J_OK, J_NO_SERVICE)

COMMAND DESCRIPTION

All commands executed by the HDC are summarized in the table below. Fields of the command block not specified are don't cares. Following this summary is a generalized description of the commands.

Table 5-6. Command Summary

Command Description	Class	LUN	LADD (21)	Int/ BCNT	Control Options	Possible Error Codes
Read Drive Status	00	0-1				RDS
Restore to TKO	01	0-1				06, RDS
Request Status	03	0-1				Last Oper.
Check Trk Fmt	05	0-1	L		R	RDE, RDS, IDA
Format Track	06	0-1	L	B	S	IDA
Read Drive	08	0-1	L	B	R, S	RDE, RDS, IDA
Write Drive	0A	0-1	L	B	R, S	15, 19, RDS, IDA
Seek	0B	0-1	L			RDS, IDA
Set Drive Param.	0C	0-1				20, 32
Change Command Block Address/	0F					20, 32
Read Drive Long	E5	0-1	L	B	R, S	RDE, RDS, IDA
Write Drive Long	E6	0-1	L	B	R, S	15, 19, RDS, IDA
Init. Unit 1	CC	1				20, 32

R = 0 Retries/ECC enable
= 1 Retries/ECC disabled

S = 0 Set correction span to 5 bits
= 1 Set correction span to 11 bits

L = Logical Sector Address

B = Block or sector count required

Read Drive Status (RDS) = 02, 03, 04, 20, 32

Illegal Disk Access (IDA) = 20, 21, 22, 32

Read Sector Error (RDE) = 11, 12, 13, 14, 15

Read Drive Status (Class 0, Opcode 0)

Action

Read the drive's status and determine if drive is ready. For Hard disk drives supporting buffered seeks this command is useful for determining the first drive to reach its target track. The command will be aborted, if the drive status read is incorrect.

Possible Error Codes

No error, invalid command, seek in progress, drive not ready, write fault, DMA error.

Restore (Class 0, Opcode 1)

Action

This four bit field can be used to specify options as indicated below:

Bit 7 = 0 5 bit correction span (default value)
 = 1 11 bit correction span

Bit 6 = 0 Retries & ECC enabled (default value)
 = 1 Retries & ECC disabled

Bit 5 = 0 Not Used

Bit 4 = 0 Not Used

Step Rate

Step Rate 14 = 11.1 usec
 Step Rate 15 = 30 usec
 All Others = 3 msec

Possible Error Codes

No error, invalid command, DMA error.

Initialize Unit 1 (Opcode CC)

Action

This command with initialize or set drive parameters of unit 1 only. This allows for the HDC to support two different drive types at the same time. The action of this command is identical to the action of the 'Set Drive Parameter' command noted above except that it will effect only unit 1. For command details see section 6.2.9.

Change Command Block (Class 0, Opcode F)

Action

The Change Command Block is used to move the location of the command block from the default on power up to a new location. Bytes 6 and 7 of the command block are used as indirect address pointers for the beginning of a 7 byte block of memory organized as follows:

Table 5-10. Change Command Block Address

D7	D6	D5	D4	D3	D2	D1	D0
0							0
A23				High Order DMA Byte			A16
A15				Mid Order DMA Byte			A08
A07				Low Order DMA Byte			0

LINE DRAW: BLTADAT is used as an index register and must be preloaded with 8000. BLTBDAT is used for texture. It must be preloaded with FF if no texture (solid line) is desired.

BLTDDAT *Blitter destination data register*

This register holds the data resulting from each word of Blitter operation until it is sent to a RAM destination. This is a dummy address and cannot be read by the micro. The transfer is automatic during Blitter operation.

BLTCON0 *Blitter control register 0*

BLTCON1 *Blitter control register 1*

These two control registers are used together to control Blitter operations. There are 2 basic modes, area and line, which are selected by bit 0 of BLTCON1, as shown below.

AREA MODE ("normal")		
BIT#	BLTCON0	BLTCON1
15	ASH3	BSH3
14	ASH2	BSH2
13	ASH1	BSH1
12	ASAO	BSH0
11	USEA	X
10	USEB	X
09	USEC	X
08	USED	X
07	LF7	X
06	LF6	X
05	LF5	X
04	LF4	EFE
03	LF3	IFE
02	LF2	FCI
01	LF1	DESC
00	LF0	LINE(=0)
ASH3-0	Shift value of A source	
BSH3-0	Shift value of B source	
USEA	Mode control bit to use Source A	
USEB	Mode control bit to use Source B	
USEC	Mode control bit to use Source C	
USED	Mode control bit to use Destination D	
LF7-0	Logic function minterm select lines	
EFE	Exclusive fill enable	
IFE	Inclusive fill enable	
FCI	Fill carry input	
DESC	Descending (decreasing address) control bit	
LINE	Line mode control bit (set to 0)	

LINE DRAW:

LINE MODE (line draw)

BIT#	BLTCON0	BLTCON1
15	START3	0
14	START2	0
13	START1	0
12	START0	0
11	1	0
10	0	0
09	1	0
08	1	0
07	LF7	0
06	LF6	SIGN
05	LF5	OVF
04	LF4	SUD
03	LF3	SUL
02	LF2	AUL
01	LF1	SING
00	LF0	LINE(= 1)

START3-0 Starting point of line (0 thru 15 hex)
 LF7-0 Logic function minterm select lines
 should be preloaded with 4A in order
 to select the equation $D = (\bar{A}C + ABC)$.
 Since A contains a single bit true
 (8000), most bits will pass the C field
 unchanged (not A and C), but one bit
 will invert the C Field and combine it
 with texture (A and B and not C). The
 A bit is automatically moved across
 the word by the hardware.

LINE Line mode control bit (set to 1)
 SIGN Sign flag
 OVF Word overflow flag
 SING Single bit per horiz. line
 for use with subsequent Area Fill
 SUD Sometimes Up or Down (= AUD*)
 SUL Sometimes Up or Left
 AUL Always Up or Left

The 3 bits above select the Octant for line draw:

OCT	SUD	SUL	AUL
0	1	1	0
1	0	0	1
2	0	1	1
3	1	1	1
4	1	0	1
5	0	1	0
6	0	0	0
7	0	0	0

Blitter start and size (Window, width height)

COP1LCH	Copper first location register (high 3 bits)
COP1LCL	Copper first location register (low 15 bits)
COP2LCH	Copper second location register (high 3 bits)
COP2LCL	Copper second location register (low 15 bits)
COP1NS	<i>Copper instruction fetch identify</i>

This is a dummy address that is generated by the Copper whenever it is loading instructions into its own instruction register. This actually occurs every Copper cycle except for the second (IR2) cycle of the MOVE instruction. The three types of instructions are shown below:

MOVE	<i>Move immediate to dest.</i>
WAIT	<i>Wait until beam counter is equal to, or greater than (keeps Copper off of bus until beam position has been reached).</i>
SKIP	<i>Skip if beam counter is equal to, or greater than (skips following MOVE inst. unless beam position has been reached).</i>

BIT#	MOVE		WAIT UNTIL		SKIP IF	
	IR1	IR2	IR1	IR2	IR1	IR2
15	X	RD15	VP7	BFD *	VP7	BFD *
14	X	RD14	VP6	VE6	VP6	VE6
13	X	RD13	VP5	VE5	VP5	VE5
12	X	RD12	VP4	VE4	VP4	VE4
11	X	RD11	VP3	VE3	VP3	VE3
10	X	RD10	VP2	VE2	VP2	VE2
09	X	RD09	VP1	VE1	VP1	VE1
08	DA8	RD08	VP0	VE0	VP0	VE0
07	DA7	RD07	HP8	HE6	HP8	HE6
06	DA6	RD06	HP7	HE7	HP7	HE7
05	DA5	RD05	HP6	HE6	HP6	HE6
04	DA4	RD04	HP5	HE5	HP5	HE5
03	DA3	RD03	HP4	HE4	HP4	HE4
02	DA2	RD02	HP3	HE3	HP3	HE3
01	DA1	RD01	HP2	HE2	HP2	HE2
00	0	RD00	1	1	1	1

IR1 = First instruction register

IR2 = Second instruction register

DA = Destination Address for MOVE instruction. Fetched during IR1 time, used during IR2 time on RGA bus.

RD = RAM data moved by MOVE instruction at IR2 time directly from RAM to the address given by the DA field.

VP = Vertical Beam Position comparison bit

HP = Horizontal Beam Position comparison bit

VE = Enable comparison (mask bit)

HE = Enable comparison (mask bit)

These registers control the horizontal timing of the beginning and end of the Bit Plane DMA display data fetch. The vertical Bit Plane DMA timing is identical to the Display windows described above. The Bit Plane Modulos are dependent on the Bit Plane horizontal size, and on this data fetch window size.

Register bit assignment

BIT# 15,14,13,12,11,10,09,08,07,06,05,04,03,02,01,00
 USE X X X X X X X HB H7 H6 H5 H4 H3 X X

(X bits should always be driven with 0 to maintain upward compatibility)

The tables below show the start and stop timing for different register contents.

DDFSTRT (Left edge of display data fetch)

PURPOSE	H8,	H7,	H6,	H5,	H4
Extra wide (max) *	0	0	1	0	1
wide	0	0	1	1	0
normal	0	0	1	1	1
narrow	0	1	0	0	0

DDFSTOP (Right edge of display data fetch)

PURPOSE	H8,	H7,	H6,	H5,	H4,
narrow	1	1	0	0	1
normal	1	1	0	1	0
wide (max)	1	1	0	1	1


DMACON DMA control write (clear or set)
 DMACONR DMA control (and Blitter status) read

This register controls all of the DMA channels, and contains Blitter DMA status bits.

BIT#	FUNCTION	DESCRIPTION
15	SET/CLR	Set/Clear control bit. Determines if bits written with a 1 get set or cleared.
14	BBUSY	Blitter busy status bit (read only)
13	BZERO	Blitter logic zero status bit (read only)
12	X	
11	X	
10	BLTPRI	Blitter DMA priority (over CPU micro) —also called "Blitter Nasty" —disables /BLS pin, preventing micro from stealing any bus cycles while blitter DMA is running.

DMA Time Slot Allocation/Horizontal Line (Cont'd)

Hardware stop installed here. Data fetch cannot begin any sooner than cycle 18. This allows the user to wipe out most of the sprites if desired (by defining an extra-wide display) but leaves the audio and disk DMA untouched.



Some sprites are unusable if the display starts early due to an extra word(s) associated with a wide display and/or horizontal scrolling. In this case, the bit-plane DMA steals the cycles normally allocated to the sprites, as illustrated above.

A2000 PAL Equations

PAL20L8' PAL DESIGN SPECIFICATION
 PART NO.: 380 XXX-01 DESCRIPT.:PALEN REV.2 FRANK ULLMANN 03-09-86
 MEM- AND DTACK-DECODER FOR A2500 MAINBOARD (U26) ASSY 380...
 COMMODORE BSW !! PRELIMINARY !!

A23 A22 A21 A20 A19 A18 PRW AS DBR OVL OVR GND
 C1 C3 VPA MYAME CLKE RGAE RE DTACK BLS ROME XRDY VCC

```

IF (OVR) /VPA = /AS*A23*/A22*A21                ; PERIPHERAL ACCESS
                                                    ; $A00000-BFFFFF

/MYAME = /AS*DTACK*A23*A22*A21*OVR*/C1*C3        ; $E00000-FFFFFF
+ /AS*DTACK*/A23*/A22*/A21*OVR*OVL*/C1*C3        ; $000000-1FFFFFF IF
                                                    ; OVL=H, OVR=H !
+ /AS*DTACK*A23*A22*/A21*A20*A19*/A18*OVR*/C1*C3  ; $D80000-DBFFFF
+ /MYAME*/C1
+ /MYAME*/C3

/RE = DBR*/AS*DTACK*/A23*/A22*/A21*OVR*/OVL*      ; $000000-1FFFFFF IF
/C1*C3                                              ; OVL=L, OVR=H !
+ /RE*/C1
+ /RE*/C3


IF (OVR) /DTACK =
  /AS*/A23*/A22*A21*XRDY                          ; $200000-3FFFFFF EXP RAM
+ /AS*/A23*A22*XRDY                                ; $400000-7FFFFFF " "
+ /AS*A23*/A22*/A21*XRDY                            ; $800000-9FFFFFF " "
+ /MYAME*XRDY*/C3                                    ; $000000-1FFFFFF OVL=H
                                                    ; AND $E00000-FFFFFF
+ /RE*/C3                                            ; $000000-1FFFFFF OVL=L
+ /RGAE*/C3                                          ; $C00000-D7FFFF
                                                    ; AND $DC0000-DF0000
+ /DTACK*/AS*XRDY

/RGAE = DBR*/AS*DTACK*A23*A22*/A21*A20*/A19* OVR*/C1*C3;$000000-$D7FFFF
+ DBR*/AS*DTACK*A23*A22*/A21*A20*A19*A18*OVR*/C1*C3;$DC0000-$DFFFFFF
+ DBR*/AS*DTACK*A23*A22*/A21*/A20* OVR*/C1*C3;$C00000-$CFFFFFF
+ /RGAE*/C1
+ /RGAE*/C3


/BLS = /AS*DTACK*/A23*/A22*/A21*OVR*/OVL*/C1*C3 ; $000000-1FFFFFF OVL=L
+ /AS*DTACK*A23*A22*/A21*OVR*/C1*C3              ; $C00000-DFFFFFF
+ /BLS*/C1
+ /BLS*/C3

```


List of B2000 Motherboard Jumpers



This jumper determines the high-order address bit for Fat Agnus. In its normal position shown the high-order bit is A23; in its other position, this bit is A19. The current Fat Agnus chip requires the A23 signal for proper management of the memory at \$C00000. Future Fat Agnus chips may map things differently.



This jumper is used to set the light-pen port number. In the normal position shown, the light pen input will be the FIRE input of mouse/joystick port 1, as with the A500. With the jumper in the other position, the light pen input will be the FIRE input of mouse/joystick port 0, which is the scheme used on the A1000 machine.



This jumper determines the time base used for the 50/60Hz CIA timer chip. In the normal position, the 50/60Hz TICK clock, based on AC line frequency, is used as a time base. In the alternate position, the vertical sync pulse from the video section is used. The system will not operate properly without one of these clocks.

J301


This jumper is closed to add a second internal floppy drive, open to leave the second floppy out of the main unit box.


X X

J500

This jumper is used to enable the 512K of RAM at \$C00000. It is normally closed; opening it will disable this extra RAM.


X-X








A2000

Keyboard Connector



Pin	Name	Description
1	KCLK	Keyboard clock
2	KDAT	Keyboard data
3	NC	Not connected
4	GND	Ground
5	+5V	+ 5 Volts power (100 mA)
6	SHIELD	Shield





CONNECTION TABLE	
PIN NO.	FUNCTION
1	Y _B
2	X _A
3	Y _A
4	X _B
5	NC
6	BUTTON #1 (LEFT)
7	+B 5V
8	GND
9	BUTTON #2 (RIGHT)

Amiga 500/2000 Mouse

NOTE

The offset values of the registers are the addresses that the Copper must use to talk to the registers.

For example, in assembler:

```
INCLUDE "exec/types.i"
INCLUDE "hardware/custom.i"

XREF    _custom                ; External reference...

Start:  lea    _custom,a0        ; Use a0 as base register
        move.w #$7FFF,intena(a0) ; Disable all interrupts
```

In C, you would use the structure definitions in hardware/custom.h For example:

```
#include "exec/types.h"
#include "hardware/custom.h"

extern struct Custom custom;

/* You may need to define the above external as
** extern struct Custom far custom;
** Check you compiler manual.
*/

main()
{
    custom.intena = 0x7FFF;        /* Disable all interrupts */
}
```

The Amiga hardware include files are generally supplied with your compiler or assembler. Listings of the hardware include files may also be found in the Addison-Wesley Amiga ROM Kernel Manual “Includes and Autodocs”. Generally, the include file label names are very similar to the equivalent hardware register list names with the following typical differences.

- Address registers which have low word and high word components are generally listed as two word sized registers in the hardware register list, with each register name containing either a suffix or embedded “L” or “H” for low and high. The include file label for the same register will generally treat the whole register as a longword (32 bit) register, and therefore will not contain the “L” or “H” distinction.
- Related sequential registers which are given individual names with number suffixes in the hardware register list, are generally referenced from a single base register definition in the include files. For example, the color registers in the hardware list (COLOR00, COLOR01, etc.) would be referenced from the “color” label defined in “hardware/custom.i” (color+0, color+2, etc.).
- Examples of how to define the correct register offset can be found in the hw_examples.i file listed in Appendix J.

Do not read, write, or use any currently undefined address ranges. The current and future usage of such areas is reserved by Commodore and is definitely subject to change.

If you are using the system libraries, devices, and resources, you must follow the defined interface. Assembler programmers (and compiler writers) must enter functions through the library base jump tables, with arguments passed as longs and library base address in A6. Results returned in D0 must be tested, and the contents of D0-D1/A0-A1 must be assumed gone after a system call.

NOTE

The assembler TAS instruction should not be used in any Amiga program. The TAS instruction assumes an indivisible read-modify-write but this can be defeated by system DMA. Instead use BSET and BCLR. These instructions perform a test and set operation which cannot be interrupted.

TAS is only needed for a multiple CPU system. On a single CPU system, the BSET and BCLR instructions are identical to TAS, as the 68000 does not interrupt instructions in the middle. BSET and BCLR first test, then set bits.

Do not use assembler instructions which are privileged on any 68000 family processor, most notably MOVE SR,<ea> which is privileged on the 68010/20/30. Use the Exec function GetCC() instead of MOVE SR, or use the appropriate non-privileged instruction as shown below:

CPU	User Mode	Super Mode
68000	MOVE SR,<ea>	MOVE SR,<ea>
68010/20/30	MOVE CCR,<ea>	MOVE SR,<ea>

All addresses must be 32 bits. Do not use the upper 8 bits for other data, and do not use signed variables or signed math for addresses. Do not execute code on your stack or use self-modifying code since such code can be defeated by the caching capabilities of some 68xxx processors. And never use processor or clock speed dependent software loops for timing delays. See Appendix F for information on using an 8520 timer for delays.

NOTE

When strobing any register which responds to either a read or a write, (for example copjmp2) be sure to use a MOVE.W #\$00, not CLR.W. The CLR instruction causes a read and a clear (two accesses) on a 68000, but only a single access on 68020 and above. This will give different results on different processors.

If you are programming at the hardware level, you must follow hardware interfacing specifications. All hardware is NOT the same. Do not assume that low level hacks for speed or copy protection will work on all drives, or all keyboards, or all systems, or future systems. Test your software on many different systems, with different processors, OS, hardware, and RAM configurations.

The WAIT Instruction

The WAIT instruction causes the Copper to wait until the video beam counters are equal to (or greater than) the coordinates specified in the instruction. While waiting, the Copper is off the bus and not using memory cycles.

The first instruction word contains the vertical and horizontal coordinates of the beam position. The second word contains enable bits that are used to form a "mask" that tells the system which bits of the beam position to use in making the comparison.

FIRST INSTRUCTION WORD (IR1)

Bit 0	Always set to 1.
Bits 15 - 8	Vertical beam position (called VP).
Bits 7 - 1	Horizontal beam position (called HP).

SECOND INSTRUCTION WORD (IR2)

Bit 0	Always set to 0.
Bit 15	The blitter-finished-disable bit. Normally, this bit is a 1. (See the "Advanced Topics" section below.)
Bits 14 - 8	Vertical position compare enable bits (called VE).
Bits 7 - 1	Horizontal position compare enable bits (called HE).

The following example WAIT instruction waits for scan line 150 (\$96) with the horizontal position masked off.

```
DC.W    $9601,$FF00    ;Wait for line 150,  
                        ; ignore horizontal counters.
```

The following example WAIT instruction waits for scan line 255 and horizontal position 254. This event will never occur, so the Copper stops until the next vertical blanking interval begins.

```
DC.W    $FFFF,$FFFE    ;Wait for line 255,  
                        ; H = 254 (ends Copper list).
```

To understand why position VP=\$FF HP=\$FE will never occur, you must look at the comparison operation of the Copper and the size restrictions of the position information. Line number 255 is a valid line to wait for, in fact it is the maximum value that will fit into this field. Since 255 is the maximum number, the next line will wrap to zero (line 256 will appear as a zero in the

Instruction	Explanation
[... other instructions ...]	
WAIT for position (0,255)	<i>At this point, the vertical counter appears to wrap to 0 because the comparison works on the least significant bits of the vertical count.</i>
WAIT for any horizontal position with vertical position 0 through 5, covering the last 6 lines of the scan before vertical blanking occurs.	<i>Thus the total of $256 + 6 = 262$ lines of video beam travel during which Copper instructions can be executed.</i>

NOTE

The vertical is like the horizontal—as there are alternating long and short lines, there are also long and short fields (interlace only). In NTSC, the fields are 262, then 263 lines and in PAL, 312,313.

This alternation of lines & fields produces the standard NTSC 4 field repeating pattern:

short field ending on short line
long field ending on long line
short field ending on long line
long field ending on short line
& back to the beginning...

1 horiz count takes 1 cycle of the system clock. (Processor is twice this)

NTSC- 3,579,545 Hz

PAL- 3,546,895 Hz

genlocked- basic clock frequency plus or minus about 2%.

THE COMPARISON ENABLE BITS

Bits 14-1 are normally set to all 1s. The use of the comparison enable bits is described later in the “Advanced Topics” section.

COMPLETE SAMPLE COPPER LIST

The following example shows a complete Copper list. This list is for two bit-planes—one at \$21000 and one at \$25000. At the top of the screen, the color registers are loaded with the following values:

Register	Color
COLOR00	white
COLOR01	red
COLOR02	green
COLOR03	blue

At line 150 on the screen, the color registers are reloaded:

Register	Color
COLOR00	black
COLOR01	yellow
COLOR02	cyan
COLOR03	magenta

The complete Copper list follows.

```
;
; Notes:
; 1. Copper lists must be in CHIP ram.
; 2. Bitplane addresses used in the example are arbitrary.
; 3. Destination register addresses in copper move instructions
;    are offsets from the base address of the custom chips.
; 4. As always, hardware manual examples assume that your
;    application has taken full control of the hardware,
;    and is not conflicting with operating system use of
;    the same hardware.
; 5. Many of the examples just pick memory addresses to
;    be used. Normally you would need to allocate the
;    required type of memory from the system with AllocMem()
; 6. As stated earlier, the code examples are mainly to help
;    clarify the way the hardware works.
; 7. The following INCLUDEs are required by all example code
;    in this chapter.
;

INCLUDE "exec/types.i"
INCLUDE "hardware/custom.i"
INCLUDE "hardware/dmabits.i"
INCLUDE "hardware/hw_examples.i"
```

```

COPPERLIST:
;
; Set up pointers to two bit planes
;
    DC.W    BPL1PTH,$0002    ;Move $0002 into register $0E0 (BPL1PTH)
    DC.W    BPL1PTL,$1000    ;Move $1000 into register $0E2 (BPL1PTL)
    DC.W    BPL2PTH,$0002    ;Move $0002 into register $0E4 (BPL2PTH)
    DC.W    BPL2PTL,$5000    ;Move $5000 into register $0E6 (BPL2PTL)
;
; Load color registers
;
    DC.W    COLOR00,$0FFF    ;Move white into register $180 (COLOR00)
    DC.W    COLOR01,$0F00    ;Move red into register $182 (COLOR01)
    DC.W    COLOR02,$00F0    ;Move green into register $184 (COLOR02)
    DC.W    COLOR03,$000F    ;Move blue into register $186 (COLOR03)
;
; Specify 2 lo-res bitplanes
;
    DC.W    BPLCON0,$2200    ;2 lores planes, coloron
;
; Wait for line 150
;
    DC.W    $9601,$FF00      ;Wait for line 150, ignore horiz. position
;
; Change color registers mid-display
;
    DC.W    COLOR00,$0000    ;Move black into register $0180 (COLOR00)
    DC.W    COLOR01,$0FF0    ;Move yellow into register $0182 (COLOR01)
    DC.W    COLOR02,$00FF    ;Move cyan into register $0184 (COLOR02)
    DC.W    COLOR03,$0F0F    ;Move magenta into register $0186 (COLOR03)
;
; End Copper list by waiting for the impossible
;
    DC.W    $FFFF,$FFFE      ;Wait for line 255, H = 254 (never happens)

```

For more information about color registers, see Chapter 3, “Playfield Hardware.”

LOOPS AND BRANCHES

Loops and branches in Copper lists are covered in the “Advanced Topics” section below.

Starting and Stopping the Copper

STARTING THE COPPER AFTER RESET

At power-on or reset time, you must initialize one of the Copper location registers (COP1LC or COP2LC) and write to its strobe address before Copper DMA is turned on. This ensures a known start address and known state. Usually, COP1LC is used because this particular register is reused during each vertical blanking time. The following sequence of instructions shows how to

- Vertical resolution, or interlacing.
- Data fetch and modulo, which tell the system how much data to put on a horizontal line and how to fetch data from memory to the screen.

In addition, you need to allocate memory to store the playfield, set pointers to tell the system where to find the data in memory, and (optionally) write a Copper routine to handle redisplay of the playfield.

HEIGHT AND WIDTH OF THE PLAYFIELD

To create a playfield that is the same size as the screen, you can use a width of either 320 pixels or 640 pixels, depending upon the resolution you choose. The height is either 200 or 400 lines for NTSC, 256 or 512 lines for PAL, depending upon whether or not you choose interlaced mode.

BIT-PLANES AND COLOR

You define playfield color by:

1. Deciding how many colors you need and how you want to color each pixel.
2. Loading the colors into the color registers.
3. Allocating memory for the number of bit-planes you need and setting a pointer to each bit-plane.
4. Writing instructions to place a value in each bit in the bit-planes to give you the correct color.

Table 3-1 shows how many bit-planes to use for the color selection you need.

Table 3-1: Colors in a Single Playfield

Number of Colors	Number of Bit-Planes
1 - 2	1
3 - 4	2
5 - 8	3
9 - 16	4
17 - 32	5

The Color Table

The color table contains 32 registers, and you may load a different color into each of the registers. Here is a condensed view of the contents of the color table:

Table 3-2: Portion of the Color Table

Register Name	Contents	Meaning
COLOR00	12 bits	User-defined color for the background area and borders.
COLOR01	12 bits	User-defined color number 1 (For example, the alternate color selection for a two-color playfield).
COLOR02	12 bits	User-defined color number 2.
.		
.		
.		
COLOR31	12 bits	User-defined color number 31.

COLOR00 is always reserved for the background color. The background color shows in any area on the display where there is no other object present and is also displayed outside the defined display window, in the border area.

NOTE

If you are using the optional genlock board for video input from a camera, VCR, or laser disk, the background color will be replaced by the incoming video display.

Twelve bits of color selection allow you to define, for each of the 32 registers, one of 4,096 possible colors, as shown in Table 3-3.

The following example sets DIWSTOP for a basic playfield to \$F4 for the vertical position and \$C1 for the horizontal position.

```
LEA      CUSTOM,a0          ; Get base address of custom hardware...
MOVE.W  #$F4C1,DIWSTOP(a0) ; Display window stop register...
```

Table 3-9: DIWSTRT AND DIWSTOP Summary.

	---Nominal Values---		---Possible Values---	
	NTSC	PAL	MIN	MAX
DIWSTRT:				
VSTART	\$2C	\$2C	\$00	\$FF
HSTART	\$81	\$81	\$00	\$FF
DIWSTOP:				
VSTOP	\$F4	\$2C (= \$12C)	\$80	\$7F (= \$17F)
HSTOP	\$C1	\$C1	\$00 (= \$100)	\$FF (= \$1FF)

TELLING THE SYSTEM HOW TO FETCH AND DISPLAY DATA

After defining the size and position of the display window, you need to give the system the on-screen location for data fetched from memory. To do this, you describe the horizontal positions where each line starts and stops and write these positions to the data-fetch registers. The data-fetch registers have a four-pixel resolution (unlike the display window registers, which have a one-pixel resolution). Each position specified is four pixels from the last one. Pixel 0 is position 0; pixel 4 is position 1, and so on.

The data-fetch start and display window starting positions interact with each other. It is recommended that data-fetch start values be restricted to a programming resolution of 16 pixels (8 clocks in low-resolution mode, 4 clocks in high-resolution mode). The hardware requires some time after the first data fetch before it can actually display the data. As a result, there is a difference between the value of window start and data-fetch start of 4.5 color clocks.

The normal low-resolution DDFSTRT is (\$0038).
The normal high-resolution DDFSTRT is (\$003C).

Recall that the hardware resolution of display window start and stop is twice the hardware resolution of data fetch:

$$\frac{\$81}{2} - 8.5 = \$38$$

$$\frac{\$81}{2} - 4.5 = \$3C$$

Combination 000 selects transparent mode, to show the color of whatever object (the other playfield, a sprite, or the background color) may be “behind” the playfield.

Table 3-12 shows the color registers for high-resolution, dual-playfield mode.

Table 3-12: Playfields 1 and 2 Color Registers — High-resolution Mode

PLAYFIELD 1	
Bit Combination	Color Selected
00	Transparent mode
01	COLOR1
10	COLOR2
11	COLOR3

PLAYFIELD 2	
Bit Combination	Color Selected
00	Transparent mode
01	COLOR9
10	COLOR10
11	COLOR11

DUAL-PLAYFIELD PRIORITY AND CONTROL

Either playfield 1 or 2 may have priority; that is, either one may be displayed in front of the other. Playfield 1 normally has priority. The bit known as PF2PRI (bit 6) in register BPLCON2 is used to control priority. When PF2PRI = 1, playfield 2 has priority over playfield 1. When PF2PRI = 0, playfield 1 has priority.

You can also control the relative priority of playfields and sprites. Chapter 7, “System Control Hardware,” shows you how to control the priority of these objects.

You can control the two playfields separately as follows:

- They can have different-sized representations in memory, and different portions of each one can be selected for display.
- They can be scrolled separately.

Data for Line 2:				
Location:	START+80	START+82	START+84	START+118
	Leftmost	Next Word	Next Word	Last Display
	Display Word			Word

Figure 3-16: Data Fetch for the Second Line When Modulo = 40

To display the right half of the big picture, you set up a vertical blanking routine to start the bit-plane pointers at location START+40 rather than START with the modulo remaining at 40. The data layout is shown in Figures 3-17 and 3-18.

Data for Line 1:				
Location:	START+40	START+42	START+44	START+78
	Leftmost	Next Word	Next Word	Last Display
	Display Word			Word

Figure 3-17: Data Layout for First Line—Right Half of Big Picture

Now, the bit-plane pointers contain the value START+80. The modulo (40) is added to the pointers so that when they begin the data fetch for the second line, the correct data is fetched.

Data for Line 2:				
Location:	START+120	START+122	START+124	START+158
	Leftmost	Next Word	Next Word	Last Display
	Display Word			Word

Figure 3-18: Data Layout for Second Line—Right Half of Big Picture

Remember, in high-resolution mode, you need to fetch twice as many bytes as in low-resolution mode. For a normal-sized display, you fetch 80 bytes for each horizontal line instead of 40.




Figure 3-19: Display Window Horizontal Starting Position

The eight bits allocated to VSTART are assigned to the first 256 positions counting down from the top of the display.




Figure 3-20: Display Window Vertical Starting Position

Recall that you select the values for the starting position as if the display were in low-resolution, non-interlaced mode. Keep in mind, though, that for interlaced mode the display window should be an even number of lines in height to allow for equal-sized odd and even fields.

To set the display window starting position, write the value for HSTART into bits 0 through 7 and the value for VSTART into bits 8 through 15 of DIWSTRT.

Table 3-19: High-resolution Color Selection

Single Playfield Bit-planes 4,3,2,1	Dual Playfields	Color Register Number
Playfield 1		
<u>Bit-planes 3,1</u>		
0000	00 *	0 **
0001	01	1
0010	10	2
0011	11	3
0100		4
0101	NOT USED	5
0110	IN THIS MODE	6
0111		7
Playfield 2		
<u>Bit-planes 4,2</u>		
1000	00 *	8
1001	01	9
1010	10	10
1011	11	11
1100		12
1101	NOT USED	13
1110	IN THIS MODE	14
1111		15

* Selects “transparent” mode.

** Color register 0 always defines the background color.

hardware in the same manner as the original words that were first loaded into the control registers. If the VSTART value contained in these words is lower than the current beam position, this sprite will not be reused in this display field. For consistency, the value 0 should be used for both words when ending the usage of a sprite. Sprite reuse is discussed later.

The following data structure is for the spaceship sprite. It will be located at V = 65 and H = 128 on the normally visible part of the screen.

```
SPRITE:
DC.W      $6D60,$7200      ;VSTART, HSTART, VSTOP
DC.W      $0990,$07E0      ;First pair of descriptor words
DC.W      $13C8,$0FF0
DC.W      $23C4,$1FF8
DC.W      $13C8,$0FF0
DC.W      $0990,$07E0
DC.W      $0000,$0000      ;End of sprite data
```

Displaying a Sprite

After building the data structure, you need to tell the system to display it. This section describes the display of sprites in “automatic” mode. In this mode, once the sprite DMA channel begins to retrieve and display the data, the display continues until the VSTOP position is reached. Manual mode is described later on in this chapter.

The following steps are used in displaying the sprite:

1. Decide which of the eight sprite DMA channels to use (making certain that the chosen channel is available).
2. Set the sprite pointers to tell the system where to find the sprite data.
3. Turn on sprite direct memory access if it is not already on.
4. For each subsequent display field, during the vertical blanking interval, rewrite the sprite pointers.

CAUTION

If sprite DMA is turned off while a sprite is being displayed (that is, after VSTART but before VSTOP), the system will continue to display the line of sprite data that was most recently fetched. This causes a vertical bar to appear on the screen. It is recommended that sprite DMA be turned off only during vertical blanking or during some portion of the display where you are *sure* that no sprite is being displayed.

Sprites can be attached in the following combinations:

- Sprite 1 to sprite 0
- Sprite 3 to sprite 2
- Sprite 5 to sprite 4
- Sprite 7 to sprite 6

Any or all of these attachments can be active during the same display field. As an example, assume that you wish to have more colors in the spaceship sprite and you are using sprite DMA channels 0 and 1. There are five colors plus transparent in this sprite.

0000154444510000
0001564444651000
0015676446765100
0001564444651000
0000154444510000

The first line in this sprite requires the four data words shown in Table 4-4 to form the correct binary color selector numbers.

Table 4-4: Data Words for First Line of Spaceship Sprite

	Pixel Number															
	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Line 1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Line 2	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0
Line 3	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Line 4	0	0	0	0	1	1	0	0	0	0	1	1	0	0	0	0

The highest numbered sprite (number 1, in this example) contributes the highest order bits (left-most) in the binary number. The high-order data word in each sprite contributes the leftmost digit. Therefore, the lines above are written to the sprite data structures as follows:

- Line 1 Sprite 1 high-order word for sprite line 1
- Line 2 Sprite 1 low-order word for sprite line 1
- Line 3 Sprite 0 high-order word for sprite line 1
- Line 4 Sprite 0 low-order word for sprite line 1


See Figure 4-7 for the order these words are stored in memory. Remember that this data is contained in *two* sprite structures.

Table 4-6: Color Registers for Single Sprites

Single Sprites Sprite	Value	Color Register
0 or 1	00	Not used *
	01	17
	10	18
	11	19
2 or 3	00	Not used *
	01	21
	10	22
	11	23
4 or 5	00	Not used *
	01	25
	10	26
	11	27
6 or 7	00	Not used *
	01	29
	10	30
	11	31

* Selects transparent mode.

If the bit combinations from attached sprites are as shown in Table 4-7, then the colors will be taken from the registers shown.



—→
Samples taken over time —

TIME	SINE	SQUARE	TRIANGLE
0	0	100	0
1	39	100	20
2	75	100	40
3	103	100	60
4	121	100	80
5	127	100	100
6	121	100	80
7	103	100	60
8	75	100	40
9	39	100	20
10	0	-100	0
11	-39	-100	-20
12	-75	-100	-40
13	-103	-100	-60
14	-121	-100	-80
15	-127	-100	-100
16	-121	-100	-80
17	-103	-100	-60
18	-75	-100	-40
19	-39	-100	-20

Figure 5-2: Digitized Amplitude Values

THE AMIGA SOUND HARDWARE

The Amiga has four hardware sound channels. You can independently program each of the channels to produce complex sound effects. You can also attach channels so that one channel modulates the sound of another or combine two channels for stereo effects.

Sound data is organized as a set of eight-bit data items; each item is a sample from the waveform. Each data word retrieved for the audio channel consists of two samples. Sample values can range from -128 to +127.

As an example, the data set shown below produces a close approximation to a sine wave.

NOTE

The data is stored in byte address order with the first digitized amplitude value at the lowest byte address, the second at the next byte address, and so on. Also, note that the first byte of data must start at a word-address boundary. This is because the audio DMA retrieves one word (16 bits) at a time and uses the sample it reads as two bytes of data.

To use audio channel 0, write the address of “audiodata” into AUD0LC, where the audio data is organized as shown below. For simplicity, “AUDxLC” in the table below stands for the combination of the two actual location registers (AUDxLCH and AUDxLCL). For the audio DMA channels to be able to retrieve the data, the data address to which AUD0LC points must be somewhere in chip RAM.

Table 5-1: Sample Audio Data Set for Channel 0

audiodata --->	AUD0LC *	100	98
	AUD0LC + 2 **	92	83
	AUD0LC + 4	71	56
	AUD0LC + 6	38	20
	AUD0LC + 8	0	-20
	AUD0LC + 10	-38	-56
	AUD0LC + 12	-71	-83
	AUD0LC + 14	-92	-83
	AUD0LC + 16	-100	-98
	AUD0LC + 18	-92	-83
	AUD0LC + 20	-71	-56
	AUD0LC + 22	-38	-20
	AUD0LC + 24	0	20
	AUD0LC + 26	38	56
	AUD0LC + 28	71	83
	AUD0LC + 30	92	98

Notes

- * Audio data is located on a word-address boundary.
- ** AUD0LC stands for AUD0LCL and AUD0LCH.

For a typical output at volume 64, with maximum data values of -128 to 127, the voltage output is between +.4 volts and -.4 volts. Some volume levels and the corresponding decibel values are shown in Table 5-2.

Table 5-2: Volume Values

Volume	Decibel Value	
64	0	(maximum volume)
48	-2.5	
32	-6.0	
16	-12.0	(12 db down from the volume at maximum level)

For any volume setting from 64 to 0, you write the value into bits 5-0 of AUDOVOL. For example:

```
SETAUDOVOLUME:
    LEA     CUSTOM, a0
    MOVE.W #48, AUDOVOL(a0)
```

The decibels are shown as negative values from a maximum of 0 because this is the way a recording device, such as a tape recorder, shows the recording level. Usually, the recorder has a dial showing 0 as the optimum recording level. Anything less than the optimum value is shown as a minus quantity.

SELECTING THE DATA OUTPUT RATE

The pitch of the sound produced by the waveform depends upon its frequency. To tell the system what frequency to use, you need to specify the sampling period. The sampling period specifies the number of system clock ticks, or timing intervals, that should elapse between each sample (byte of audio data) fed to the digital-to-analog converter in the audio channel. There is a period register for each audio channel. The value of the period register is used for count-down purposes; each time the register counts down to 0, another sample is retrieved from the waveform data set for output. In units, the period value represents clock ticks per sample. The minimum period value you should use is 124 ticks per sample NTSC (123 PAL) and the maximum is 65535. These limits apply to both PAL and NTSC machines. For high-quality sound, there are other constraints on the sampling period (see the section called “Producing High-quality Sound”).

NOTE

A low period value corresponds to a higher frequency sound and a high period value corresponds to a lower frequency sound.

Limitations on Selection of Sampling Period

The sampling period is limited by the number of DMA cycles allocated to an audio channel. Each audio channel is allocated one DMA slot per horizontal scan line of the screen display. An audio channel can retrieve two data samples during each horizontal scan line. The following calculation gives the maximum sampling rate in samples per second.

$$2 \text{ samples/line} * 262.5 \text{ lines/frame} * 59.94 \text{ frames/second} = 31,469 \text{ samples/second}$$

The figure of 31,469 is a theoretical maximum. In order to save buffers, the hardware is designed to handle 28,867 samples/second. The system timing interval is 279.365 nanoseconds, or .279365 microseconds. The maximum sampling rate of 28,867 samples per second is 34.642 microseconds per sample ($1/28,867 = .000034642$). The formula for calculating the sampling period is:

$$\text{Period value} = \frac{\text{sample interval}}{\text{clock interval}} = \frac{\text{clock constant}}{\text{samples per second}}$$

Thus, the minimum period value is derived by dividing 34.642 microseconds per sample by the number of microseconds per interval:

$$\text{Minimum period} = \frac{34.642 \text{ microseconds/sample}}{0.279365 \text{ microseconds/interval}} = 124 \text{ timing intervals/sample}$$

or:

$$\text{Minimum period} = \frac{3,579,545 \text{ ticks/second}}{28,867 \text{ samples/second}} = 124 \text{ ticks/sample}$$

Therefore, a value of at least 124 must be written into the period register to assure that the audio system DMA will be able to retrieve the next data sample. If the period value is below 124, by the time the cycle count has reached 0, the audio DMA will not have had enough time to retrieve the next data sample and the previous sample will be reused.

28,867 samples/second is also the maximum sampling rate for PAL systems. Thus, for PAL systems, a value of at least 123 ticks/sample must be written into the period register.

Clock Values			
	NTSC	PAL	units
Clock Constant	3579545	3546895	ticks per second
Clock Interval	0.279365	0.281937	microseconds per interval

Table 5-3: DMA and Audio Channel Enable Bits

DMACON Register

Bit	Name	Function
15	SET/CLR	When this bit is written as a 1, it sets any bit in DMACONW for which the corresponding bit position is also a 1, leaving all other bits alone.
9	DMAEN	Only while this bit is a 1 can <i>any</i> direct memory access occur.
3	AUD3EN	Audio channel 3 enable.
2	AUD2EN	Audio channel 2 enable.
1	AUD1EN	Audio channel 1 enable.
0	AUD0EN	Audio channel 0 enable.

For example, if you are using channel 0, then you write a 1 into bit 9 to enable DMA and a 1 into bit 0 to enable the audio channel, as shown below.

```
BEGINCHAN0:
    LEA        CUSTOM, a0
    MOVE.W    #(DMAF_SETCLR!DMAF_AUD0!DMAF_MASTER), DMACON(a0)
```

STOPPING THE AUDIO DMA

You can stop the channel by writing a 0 into the AUDxEN bit at any time. However, you cannot resume the output at the same point in the waveform by just writing a 1 in the bit again. Enabling an audio channel almost always starts the data output again from the top of the list of data pointed to by the location registers for that channel. If the channel is disabled for a very short time (less than two sampling periods) it may stay on and thus continue from where it left off.

The following example shows how to stop audio DMA for one channel.

```
STOPAUDCHAN0:
    LEA        CUSTOM, a0
    MOVE.W    #(DMAF_AUD0), DMACON(a0)
```

Table 5-6: Sampling Rate and Frequency Relationship

	Sampling Period	Sampling Rate (KHz)	Maximum Output Frequency (KHz)
Maximum sampling rate	124	29	7
Minimum sampling rate for 7 KHz output	256	14	7
Sampling rate too low for 7 KHz output	320	11	4

In A2000s with 2 layer motherboards and later A500 models there is a control bit that allows the audio output to bypass the low pass filter. This control bit is the same output bit of the 8520 CIA that controls the brightness of the red “power” LED. Bypassing the filter allows for improved sound in some applications, but an external filter with an appropriate cutoff frequency may be required.

Using Direct (Non-DMA) Audio Output

It is possible to create sound by writing audio data one word at a time to the audio output addresses, instead of setting up a list of audio data in memory. This method of controlling the output is more processor-intensive and is therefore not recommended.

To use direct audio output, do not enable the DMA for the audio channel you wish to use; this changes the timing of the interrupts. The normal interrupt occurs after a data address has been read; in direct audio output, the interrupt occurs after one data word has been output.

Unlike in the DMA-controlled automatic data output, in direct audio output, if you do not write a new set of data to the output addresses before two sampling intervals have elapsed, the audio output will cease changing. The last value remains as an output of the digital-to-analog converter.

The volume and period registers are set as usual.

256 Byte Sample

0	2	4	6	8	10	12	14	16	18	20	22	24	26	28	30
32	34	36	38	40	42	44	46	48	50	52	54	56	58	60	62
64	66	68	70	72	74	76	78	80	82	84	86	88	90	92	94
96	98	100	102	104	106	108	110	112	114	116	118	120	122	124	126
128	126	124	122	120	118	116	114	112	110	108	106	104	102	100	98
96	94	92	90	88	86	84	82	80	78	76	74	72	70	68	66
64	62	60	58	56	54	52	50	48	46	44	42	40	38	36	34
32	30	28	26	24	22	20	18	16	14	12	10	8	6	4	2
0	-2	-4	-6	-8	-10	-12	-14	-16	-18	-20	-22	-24	-26	-28	-30
-32	-34	-36	-38	-40	-42	-44	-46	-48	-50	-52	-54	-56	-58	-60	-62
-64	-66	-68	-70	-72	-74	-76	-78	-80	-82	-84	-86	-88	-90	-92	-94
-96	-98	-100	-102	-104	-106	-108	-110	-112	-114	-116	-118	-120	-122	-124	-126
-127	-126	-124	-122	-120	-118	-116	-114	-112	-110	-108	-106	-104	-102	-100	-98
-96	-94	-92	-90	-88	-86	-84	-82	-80	-78	-76	-74	-72	-70	-68	-66
-64	-62	-60	-58	-56	-54	-52	-50	-48	-46	-44	-42	-40	-38	-36	-34
-32	-30	-28	-26	-24	-22	-20	-18	-16	-14	-12	-10	-8	-6	-4	-2

128 Byte Sample

0	4	8	12	16	20	24	28	32	36	40	44	48	52	56	60
64	68	72	76	80	84	88	92	96	100	104	108	112	116	120	124
128	124	120	116	112	108	104	100	96	92	88	84	80	76	72	68
64	60	56	52	48	44	40	36	32	28	24	20	16	12	8	4
0	4	8	12	16	20	24	28	32	36	40	44	48	52	56	60
64	68	72	76	80	84	88	92	96	100	104	108	112	116	120	124
-127	-124	-120	-116	-112	-108	-104	-100	-96	-92	-88	-84	-80	-76	-72	-68
-64	-60	-56	-52	-48	-44	-40	-36	-32	-28	-24	-20	-16	-12	-8	-4

64 Byte Sample

0	8	16	24	32	40	48	56	64	72	80	88	96	104	112	120
128	120	112	104	96	88	80	72	64	56	48	40	32	24	16	8
0	-8	-16	-24	-32	-40	-48	-56	-64	-72	-80	-88	-96	-104	-112	-120
-127	-120	-112	-104	-96	-88	-80	-72	-64	-56	-48	-40	-32	-24	-16	-8

32 Byte Sample

0	16	32	48	64	80	96	112	128	112	96	80	64	48	32	16
0	-16	-32	-48	-64	-80	-96	-112	-127	-112	-96	-80	-64	-48	-32	-16

16 Byte Sample

0	32	64	96	128	96	64	32	0	-32	-64	-96	-127	-96	-64	-32
---	----	----	----	-----	----	----	----	---	-----	-----	-----	------	-----	-----	-----

Each of the DMA channels can be independently enabled or disabled. The enable bits are bits SRCA, SRCB, SRCC, and DEST in control register zero (BLTCON0).

When disabled, no memory cycles will be executed for that channel and, for a source channel, the constant value stored in the data register of that channel will be used for each blitter cycle. For this purpose, each of the three source channels have preloadable data registers, called BLTxDAT.

Images in memory are usually stored in a linear fashion; each word of data on a line is located at an address that is one greater than the word on its left. i.e. Each line is a “plus one” continuation of the previous line. (See Figure 6-1.)

20	21	22	23	24	24	26
27	28	29	30	31	32	33
34	35	36	37	38	39	40
41	42	43	44	45	46	47
48	49	50	51	52	53	54
55	56	57	58	59	60	61

Figure 6-1: How Images are Stored in Memory

The map in Figure 6-1 represents a single bit-plane (one bit of color) of an image at word addresses 20 through 61. Each of these addresses accesses one word (16 pixels) of a single bit-plane. If this image required sixteen colors, four bit-planes like this would be required in memory, and four copy (move) operations would be required to completely move the image.

The blitter is very efficient at copying such blocks because it needs to be told only the starting address (20), the destination address, and the size of the block (height = 6, width = 7). It will then automatically move the data, one word at a time, whenever the data bus is available. When the transfer is complete, the blitter will signal the processor with a flag and an interrupt.

NOTE

This copy (move) operation operates on memory and may or may not change the memory currently being used for display.

All data copy blits are performed as rectangles of words, with a given width and height. All four DMA channels use a single blit size register, called BLTSIZE, used for both the width and height. The width can take a value of from 1 to 64 words (16 to 1024 bits). The height can run from 1 to 1024 rows. The width is stored in the least significant six bits of the BLTSIZE register. If a value of zero is stored, a width count of 64 words is used. This is the only parameter in the blitter

Function Generator

The blitter can combine the data from the three source DMA channels in up to 256 different ways to generate the values stored by the destination DMA channel. These sources might be one bit-plane from each of three separate graphics images. While each of these sources is a rectangular region composed of many points, the same logic operation will be performed on each point throughout the rectangular region. Thus, for purposes of defining the blitter logic operation it is only necessary to consider what happens for all of the possible combinations of one bit from each of the three sources.

There are eight possible combinations of values of the three bits, for each of which we need to specify the corresponding destination bit as a zero or one. This can be visualized with a standard truth table, as shown below. We have listed the three source channels, and the possible values for a single bit from each one.

A	B	C	D	BLTCON0 position	Minterm
0	0	0	?	0	$\overline{ABC}$
0	0	1	?	1	$\overline{AB}C$
0	1	0	?	2	$A\overline{B}C$
0	1	1	?	3	$AB\overline{C}$
1	0	0	?	4	$A\overline{B}\overline{C}$
1	0	1	?	5	$AB\overline{C}$
1	1	0	?	6	ABC
1	1	1	?	7	ABC

This information is collected in a standard format, the LF control byte in the BLTCON0 register. This byte programs the blitter to perform one of the 256 possible logic operations on three sources for a given blit.

To calculate the LF control byte in BLTCON0, fill in the truth table with desired values for D, and read the function value from the bottom of the table up.

For example, if we wanted to set all bits in the destination where the corresponding A source bit is 1 or the corresponding B source bit is 1, we would fill in the last four entries of the truth table with 1 (because the A bit is set) and the third, fourth, seven, and eight entries with 1 (because the B bit is set), and all others (the first and second) with 0, because neither A nor B is set. Then, we read the truth table from the bottom up, reading 11111100, or \$FC.¹

¹ “\$” indicates hex notation.

For another example, an LF control byte of \$80 (= 1000 0000 binary) turns on bits only for those points of the D destination rectangle where the corresponding bits of A, B, and C sources were all on ($ABC = 1$, bit 7 of LF on). All other points in the rectangle, which correspond to other combinations for A, B, and C, will be 0. This is because bits 6 through 0 of the LF control byte, which specify the D output for these situations, are set to 0.

DESIGNING THE LF CONTROL BYTE WITH MINTERMS

One approach to designing the LF control byte uses logic equations. Each of the rows in the truth table corresponds to a “minterm”, which is a particular assignment of values to the A, B, and C bits. For instance, the first minterm is usually written $\overline{A}\overline{B}\overline{C}$, or “not A and not B and not C”. The last is written as ABC .

NOTE

Two terms that are adjacent are and’ed, and two terms that are separated by “+” are or’ed. “And” has a higher precedence, so $AB + BC$ is equal to $(AB) + (BC)$.

Any function can be written as a sum of minterms. If we wanted to calculate the function where D is one when the A bit is set and the C bit is clear, or when the B bit is set, we can write that as $A\overline{C} + B$, or “A and not C or B”. Since “1 and A” is “A”:

$$D = A\overline{C} + B$$

$$D = A(1)\overline{C} + (1)B(1)$$

Since either A or $\overline{A}$ is true ($1 = A + \overline{A}$), and similarly for B, and C; we can expand the above equation further:

$$D = A(1)\overline{C} + (1)B(1)$$

$$D = A(B + \overline{B})\overline{C} + (A + \overline{A})B(C + \overline{C})$$

$$D = A\overline{B}\overline{C} + A\overline{B}C + A\overline{B}\overline{C} + A\overline{B}C + \overline{A}B(C + \overline{C}) + \overline{A}B(C + \overline{C})$$

$$D = A\overline{B}\overline{C} + A\overline{B}C + A\overline{B}\overline{C} + A\overline{B}C + \overline{A}B\overline{C} + \overline{A}B\overline{C} + \overline{A}BC + \overline{A}B\overline{C}$$

After eliminating duplicates, we end up with the five minterms:

$$A\overline{C} + B = A\overline{B}\overline{C} + A\overline{B}C + A\overline{B}\overline{C} + A\overline{B}C + \overline{A}B\overline{C}$$

These correspond to BLTCON0 bit positions of 6, 4, 7, 3, and 2, according to our truth table, which we would then set, and clear the rest.

The wide range of logic operations allow some sophisticated graphics techniques. For instance, you can move the image of a car across some pre-existing building images with a few blits. Producing this effect requires predrawn images of the car, the buildings (or background), and a car

3. To use a function that is the inverse, or “not”, of one of the sources, such as $\overline{A}$, take all of the minterms not enclosed by the circle represented by A on the above Figure. In this case, we have minterms 0, 1, 2, and 3.

Minterm Numbers	7 6 5 4 3 2 1 0
Selected Minterms	0 0 0 0 1 1 1 1
	0 F

equals \$0F

4. To combine minterms, or “or” them, “or” the values together. For example, the equation $AB+BC$ becomes

Minterm Numbers	7 6 5 4 3 2 1 0
AB	1 1 0 0 0 0 0 0
BC	1 0 0 0 1 0 0 0
AB+BC	1 1 0 0 1 0 0 0
	C 8

equals \$C8

Shifts and Masks

Up to now we have dealt with the blitter only in moving words of memory around and combining them with logic operations. This is sufficient for moving graphic images around, so long as the images stay in the same position relative to the beginning of a word. If our car image has its leftmost pixel on the second pixel from the left, we can easily draw it on the screen in any position where the leftmost pixel also starts two pixels from the beginning of some word. But often we want to draw that car shifted left or right by a few pixels. To this end, both the A and B DMA channels have a barrel shifter that can shift an image between 0 and 15 bits.

This shifting operation is completely free; it requires no more time to execute a blit with shifts than a blit without shifts, as opposed to shifting with the 68000. The shift is normally towards the right. This shifter allows movement of images on pixel boundaries, even though the pixels are addressed 16 at a time by each word address of the bit-plane image.

So if the incoming data is shifted to the right, what is shifted in from the left? For the first word of the blit, zeros are shifted in; for each subsequent word of the same blit, the data shifted out from the previous word is shifted in.

The shift value for the A channel is set with bits 15 through 12 of BLTCON0; the B shift value is set with bits 15 through 12 of BLTCON1. For most operations, the same value will be used for both shifts. For shifts of greater than fifteen bits, load the address register pointer of the destination with a higher address; a shift of 100 bits would require the destination pointer to be advanced 100/16 or 6 words (12 bytes), and a right shift of the remaining 4 bits to be used.

As an example, let us say we are doing a blit that is three words wide, two words high, and we are using a shift of 4 bits. For simplicity, let us assume we are doing a straight copy from A to D. The first word that will be written to D is the first word fetched from A, shifted right four bits

Table 6-2: Typical Blitter Cycle Sequence

USE Code in BLTCON0	Active Channels				Cycle Sequence													
F	A	B	C	D	A0	B0	C0	-	A1	B1	C1	D0	A2	B2	C2	D1	D2	
E	A	B	C		A0	B0	C0	A1	B1	C1	A2	B2	C2					
D	A	B		D	A0	B0	-	A1	B1	D0	A2	B2	D1	-	D2			
C	A	B			A0	B0	-	A1	B1	-	A2	B2						
B	A		C	D	A0	C0	-	A1	C1	D0	A2	C2	D1	-	D2			
A	A		C		A0	C0	A1	C1	A2	C2								
9	A			D	A0	-	A1	D0	A2	D1	-	D2						
8	A				A0	-	A1	-	A2									
7		B	C	D	B0	C0	-	-	B1	C1	D0	-	B2	C2	D1	-	D2	
6		B	C		B0	C0	-	B1	C1	-	B2	C2						
5		B		D	B0	-	-	B1	D0	-	B2	D1	-	D2				
4		B			B0	-	-	B1	-	-	B2							
3			C	D	C0	-	-	C1	D0	-	C2	D1	-	D2				
2			C		C0	-	C1	-	C2									
1				D	D0	-	D1	-	D2									
0		none			-	-	-	-										

Notes for the above Table:

- No fill.
- No competing bus activity.
- Three-word blit.
- Typical operation involves fetching all sources twice before the first destination becomes available. This is due to internal pipelining. Care must be taken with overlapping source and destination regions.

NOTE

This Table is only meant to be an illustration of the typical order of blitter cycles on the bus. Bus cycles are dynamically allocated based on blitter operating mode; competing bus activity from processor, bit-planes, and other DMA channels; and other factors. Commodore Amiga does not guarantee the accuracy of or future adherence to this chart. We reserve the right to make product improvements or design changes in this area without notice.

Table 6-3: BLTCON1 Code Bits for Octant Line Drawing

BLTCON1 Code Bits	Octant #
4 3 2	
1 1 0	0
0 0 1	1
0 1 1	2
1 1 1	3
1 0 1	4
0 1 0	5
0 0 0	6
1 0 0	7

We initialize BLTCON1 bits 4 through 2 according to the above Table. Now, we introduce the variables dx and dy , and set them to the absolute values of the difference between the x coordinates and the y coordinates of the endpoints of the line, respectively.

```
dx = abs(x2 - x1) ;
dy = abs(y2 - y1) ;
```

Now, we rearrange them if necessary so dx is greater than dy .

```
if (dx < dy)
{
    temp = dx ;
    dx = dy ;
    dy = temp ;
}
```

Alternately, set dx and dy as follows:

```
dx = max(abs(x2 - x1), abs(y2 - y1)) ;
dy = min(abs(x2 - x1), abs(y2 - y1)) ;
```

These calculations have the effect of “normalizing” our line into octant 0; since we have already informed the blitter of the real octant to use, it has no difficulty drawing the line.

We initialize the A pointer register to $4 * dy - 2 * dx$. If this value is negative, we set the sign bit (SIGNFLAG in BLTCON1), otherwise we clear it. We set the A modulo register to $4 * (dy - dx)$ and the B modulo register to $4 * dy$.

The A data register should be preloaded with \$8000. Both word masks should be set to \$FFFF. The A shift value should be set to the x coordinate of the first point ($x1$) modulo 15.

The B data register should be initialized with the line texture pattern, if any, or \$FFFF for a solid line. The B shift value should be set to the bit number at which to start the line texture (zero means the last significant bit.)

The C and D pointer registers should be initialized to the word containing the first pixel of the line; the C and D modulo registers should be set to the width of the bitplane in bytes.

The SRCA, SRCC, and DEST bits of BLTCON0 should be set to one, and the SRCB flag should be set to zero. The OVFLAG should be cleared. If only a single bit per horizontal row is desired, the ONEDOT bit of BLTCON1 should be set; otherwise it should be cleared.

The logic function remains. The C DMA channel represents the original source, the A channel the bit to set in the line, and the B channel the pattern to draw. Thus, to draw a line, the function $AB+AC$ is the most common. To draw the line using exclusive-or mode, so it can be easily erased by drawing it again, the function $ABC+AC$ can be used.

We set the blit height to the length of the line, which is $dx + 1$. The width must be set to two for all line drawing. (Of course, the BLTSIZE register should not be written until the very end, when all other registers have been filled.)

REGISTER SUMMARY FOR LINE MODE

Preliminary setup:

The line goes from $(x1,y1)$ to $(x2,y2)$.

```
dx = max(abs(x2 - x1), abs(y2 - y1)) ;  
dy = min(abs(x2 - x1), abs(y2 - y1)) ;
```

Register setup:

BLTADAT = \$8000

BLTBDAT = line texture pattern (\$FFFF for a solid line)

BLTAFWM = \$FFFF

BLTALWM = \$FFFF

BLTAMOD = $4 * (dy - dx)$

BLTBMOD = $4 * dy$

BLTCMOD = width of the bitplane in bytes

BLTDMOD = width of the bitplane in bytes

BLTAPT = $(4 * dy) - (2 * dx)$

BLTBPT = unused

BLTCPT = word containing the first pixel of the line

BLTDPT = word containing the first pixel of the line

Blitter Speed

The speed of the blitter depends entirely on which DMA channels are enabled. You might be using a DMA channel as a constant, but unless it is enabled, it does not count against you. The minimum blitter cycle is four ticks; the maximum is eight ticks. Use of the A register is always free. Use of the B register always adds two ticks to the blitter cycle. Use of either C or D is free, but use of both adds another two ticks. Thus, a copy cycle, using A and D, takes four clock ticks per cycle; a copy cycle using B and D takes six ticks per cycle, and a generalized bit copy using B, C, and D takes eight ticks per cycle. When in line mode, each pixel takes eight ticks.

The system clock speed for NTSC Amigas is 7.16 megahertz (PAL Amigas 7.09 megahertz). The clock for the blitter is the system clock. To calculate the total time for the blit in microseconds, excluding setup and DMA contention, you use the equation (for NTSC):

$$t = \frac{n * H * W}{7.16}$$

For PAL:

$$t = \frac{n * H * W}{7.09}$$

where t is the time in microseconds, n is the number of clocks per cycle, and H and W are the height and width (in words) of the blit, respectively.

For instance, to copy one bitplane of a 320 by 200 screen to another bitplane, we might choose to use the A and D channels. This would require four ticks per blitter cycle, for a total of

$$\frac{4 * 200 * 20}{7.16} = 2235 \text{ microseconds.}$$

These timings do not take into account blitter setup time, which is the time required to calculate and load the blitter registers and start the blit. They also ignore DMA contention.

DMA Time Slot Allocation/Horizontal line




Figure 6-9: DMA Time Slot Allocation




Figure 6-11: Time Slots Used by a Six Bit Plane Display

If you specify four high-resolution bit-planes (640 pixels wide), bit-plane DMA needs all of the available memory time slots during the display time just to fetch the 40 data words for each line of the four bit-planes ($40 * 4 = 160$ time slots). This effectively locks out the 68000 (as well as the blitter or Copper) from any memory access during the display, except during horizontal and vertical blanking.




Figure 6-12: Time Slots Used by a High Resolution Display

Each horizontal line in a normal, full-sized display contains 320 pixels in low-resolution mode or 640 pixels in high-resolution mode. Thus, either 20 or 40 words will be fetched during the horizontal line display time. If you want to scroll a playfield, one extra data word per line must be fetched from the memory.

Display size is adjustable (see Chapter 3, “Playfield Hardware”), and bit-plane DMA takes precedence over sprite DMA. As shown in Figure 6-9, larger displays may block out one or more of the highest-numbered sprites, especially with scrolling.

Table 7-5: Contents of the Beam Position Counter

VPOSR	<i>Read-only</i>	Read the high bit of the vertical position (V8) and the frame-type bit.
Bit 15		LOF (Long-frame bit). Used to initialize interlaced displays.
Bits 14-1		Unused
Bit 0		High bit of the vertical position (V8). Allows PAL line counts (313) to appear in PAL versions of the Amiga.
VHPOSR	<i>Read-only</i>	Read vertical and horizontal position of the counter that is producing the beam on the screen (also reads the light pen).
Bits 15-8		Low bits of the vertical position, bits V7-V0
Bits 7-0		The horizontal position, bits H8-H1. Horizontal resolution is 1/160th of the screen width.
VPOSW	<i>Write only</i>	Bits same as VPOSR above.
VHPOSW	<i>Write only</i>	Bits same as VHPOSR above. Used for counter synchronization with chip test patterns.

As usual, the address pairs VPOSR,VHPOSR and VPOSW,VHPOSW can be read from and written to as long words, with the most significant addresses being VPOSR and VPOSW.

Interrupts

This system supports the full range of 68000 processor interrupts. The various kinds of interrupts generated by the hardware are brought into the peripherals chip and are translated into six of the seven available interrupts of the 68000.

Bit 1, DSKBLK, indicates “disk block finished.” It is used to indicate that the specified disk DMA task that you have requested has been completed. This bit generates a level 1 interrupt.

More information about disk data transfer and interrupts may be found in Chapter 8, “Interface Hardware.”

Serial Port Interrupts

The following serial interrupts are associated with the specified bits of the interrupt registers.

Bit 11, RBF (for receive buffer full), specifies that the input buffer of the UART has data that is ready to read. This bit generates a level 5 interrupt.

Bit 0, TBE (for “transmit buffer empty”), specifies that the output buffer of the UART needs more data and data can now be written into this buffer. This bit generates a level 1 interrupt.

Hardware priority	Exec Software priority		Label
		Description	
1	1	software interrupt	SOFTINT
	2	disk block complete	DSKBLK
	3	transmitter buffer empty	TBE
2	4	external INT2 & CIAA	PORTS
3	5	graphics coprocessor	COPER
	6	vertical blank interval	VERTB
	7	blitter finished	BLIT
4	8	audio channel 2	AUD2
	9	audio channel 0	AUD0
	10	audio channel 3	AUD3
	11	audio channel 1	AUD1
5	12	receiver buffer full	RBF
	13	disk sync pattern found	DSKSYNC
6	14	external INT6 & CIAB	EXTER
	15	special (master enable)	INTEN
7	--	non-maskable interrupt	NMI

Figure 7-4: Interrupt Priorities

Table 8-1: Typical Controller Connections

Pin	Joystick	Mouse, Trackball, Driving Controller	Proportional Controller (Pair)	X-Y Proportional Joystick	Light Pen
1	Forward	V-pulse	---	Button 3 ‡	---
2	Back	H-pulse	---	---	---
3	Left	VQ-pulse	Left button	Button 1	---
4	Right	HQ-pulse	Right button	Button 2	---
5 †	---	Middle button ‡	Right POT	POT X	Pen pressed to screen
6 †	Button 1	Left button	---	---	Beam trigger
7	---	+5V	+5V	+5V	+5V
8	GND	GND	GND	GND	GND
9 †	Button 2 ‡	Right button	Left POT	POT Y	Button 2 ‡
† These pins may also be configured as outputs					
‡ These buttons are optional					

REGISTERS USED WITH THE CONTROLLER PORT

JOY0DAT	(\$DFF00A)	Counter for digital (mouse) input (port 1)
JOY1DAT	(\$DFF00C)	Counter for digital (mouse) input (port 2)
CIAAPRA	(\$BFE001)	Input and output for pin 6 (port 1 and 2 fire buttons)
POT0DAT	(\$DFF012)	Counter for proportional input (port 1)
POT1DAT	(\$DFF014)	Counter for proportional input (port 2)
POTGO	(\$DFF034)	Write proportional pin values and start counters
POTGOR	(\$DFF016)	Read proportional pin values
BPLCON0	(\$DFF100)	Bit 3 enables the light pen latch
VPOSR	(\$DFF004)	Read light pen position (high order bits)
VHPOSR	(\$DFF006)	Read light pen position (low order bits)

CIAAPRA/CIABPRB - Disk selection, control and sensing

The following table lists how 8520 chip bits used by the disk subsystem. Bits labeled "PA" are input bits in CIAAPRA (\$BFE001). Bits labeled "PB" are output bits located in CIAAPRB (\$BFD100). More information on how the 8520 chips operate can be found in Appendix F.

Table 8-5: Disk Subsystem

Bit	Name	Function
PA5	DSKRDY*	Disk ready (active low). The drive will pull this line low when the motor is known to be rotating at full speed. This signal is only valid when the motor is ON, at other times configuration information may obscure the meaning of this input.
PA4	DSKTRACK0*	Track zero detect. The drive will pull this line low when the disk heads are positioned over track zero. Software must not attempt to step outwards when this signal is active. Some drives will refuse to step, others will attempt the step, possibly causing alignment damage. All new drives must refuse to step outward in this condition.
PA3	DSKPROT*	Disk is write protected (active low).
PA2	DSKCHANGE*	Disk has been removed from the drive. The signal goes low whenever a disk is removed. It remains low until a disk is inserted AND a step pulse is received.

PB7	DSKMOTOR*	Disk motor control (active low). This signal is nonstandard on the Amiga system. Each drive will latch the motor signal at the time its select signal turns on. The disk drive motor will stay in this state until the next time select turns on. DSKMOTOR* also controls the activity light on the front of the disk drive. All software that selects drives must set up the motor signal <i>before</i> selecting any drives. The drive will "remember" the state of its motor when it is not selected. All drive motors turn off after system reset.

After turning on the motor, software must further wait for one half second (500ms), or for the DSKRDY* line to go low.

PB6	DSKSEL3*	Select drive 3 (active low).
PB5	DSKSEL2*	Select drive 2 (active low).
PB4	DSKSEL1*	Select drive 1 (active low).
PB3	DSKSEL0*	Select drive 0 (internal drive) (active low).
PB2	DSKSIDE	Specify which disk head to use. Zero indicates the upper head. DSKSIDE must be stable for 100 microseconds before writing. After writing, at least 1.3 milliseconds must pass before switching DSKSIDE.
PB1	DSKDIREC	Specify the direction to seek the heads. Zero implies seek towards the center spindle. Track zero is at the outside of the disk. This line must be set up <i>before</i> the actual step pulse, with a separate write to the register.
PB0	DSKSTEP*	Step the heads of the disk. This signal must always be used as a quick pulse (high, momentarily low, then high).

The drives used for the Amiga are guaranteed to get to the next track within 3 milliseconds. Some drives will support a much faster rate, others will fail. Loops that decrement a counter to provide delay are **not acceptable**. See Appendix F for a better solution.

When reversing directions, a minimum of 18 milliseconds delay is required from the last step pulse. Settle time for Amiga drives is specified at 15 milliseconds.

FLAG	DSKINDEX*	Disk index pulse (\$BFDD00, bit 4). Can be used to create a level 6 interrupt. See Appendix F for details.
------	-----------	--

ESC 45	F1 50	F2 51	F3 52	F4 53	F5 54	F6 55	F7 56	F8 57	F9 58	F10 59	DEL 46						
00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	41	7 3D	8 3E	9 3F
TAB 42	Q 10	W 11	E 12	R 13	T 14	Y 15	U 16	I 17	O 18	P 19	1A	1B	44	5F	4 2D	5 2E	6 2F
CTRL 63	CAPS LOCK 62	A 20	S 21	D 22	F 23	G 24	H 25	J 26	K 27	L 28	29	2A	RETURN 4C	4C	1 1D	2 1E	3 1F
SHIFT 60		Z 31	X 32	C 33	V 34	B 35	N 36	M 37	< 38	> 39	3A	SHIFT 61	4F	4E	0 0F	3C	
ALT 64	A 66	40										67	65	4D	ENTER 4A	43	

Figure 8-9: The Amiga 1000 Keyboard, Showing Keycodes in Hexadecimal

ESC 45	F1 50	F2 51	F3 52	F4 53	F5 54	F6 55	F7 56	F8 57	F9 58	F10 59										
00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	41	DEL 46	HELP 5F	(5A	) 5B	/ 5C	. 5D
[<->] 42	Q 10	W 11	E 12	R 13	T 14	Y 15	U 16	I 17	O 18	P 19	{ 1A	} 1B	RETURN 44				7 3D	8 3E	9 3F	- 4A
CTRL 63	CAPS 62	A 20	S 21	D 22	F 23	G 24	H 25	J 26	K 27	L 28	29	2A	2B				4 2D	5 2E	6 2F	+ 5E
SHIFT 60		Z 30	X 31	C 32	V 33	B 34	N 35	M 36	< 37	> 38	? 39	3A	61	SHIFT			< 4F	V 4D	> 4E	
ALT 64	A 66	40										A 67	ALT 65							

4C		
----	--	--

1D	2E	3F	ENTER 43
0F	3C		

Figure 8-10: The Amiga 500/2000 Keyboard, Showing Keycodes in Hexadecimal

Table 8-10 shows the definitions of the various bit positions within SERDATR.

Table 8-9: SERDATR / ADKCON Registers

SERDATR		
Bit Number	Name	Function
15	OVRUN	OVERRUN bit (Mirror—also appears in the interrupt request register.) Indicates that another byte of data was received before the previous byte was picked up by the processor. To prevent this condition, it is necessary to reset INTF_RBF (bit 11, receive-buffer-full) in INTREQ.
14	RBF	READ BUFFER FULL (Mirror—also appears in the interrupt request register.) When this bit is 1, there is data ready to be picked up by the processor. After reading the contents of this data register, you must reset the INTF_RBF bit in INTREQ to prevent an overrun.
13	TBE	TRANSMIT BUFFER EMPTY (Not a mirror—interrupt occurs when the buffer <i>becomes</i> empty.) When bit 14 is a 1, the data in the output data register (SERDAT) has been transferred to the serial output shift register, so SERDAT is ready to accept another output word. This is also true when the buffer <i>is</i> empty. This bit is normally used for full-duplex operation.
12	TSRE	TRANSMIT SHIFT REGISTER EMPTY When this bit is a 1, the output shift register has completed its task, all data has been transmitted, and the register is now idle. If you stop writing data into the output register (SERDAT), then this bit will become a 1 after both the word currently in the shift register <i>and</i> the word placed into SERDAT have been transmitted. This bit is normally used for half-duplex operation.
11	RXD	Direct read of RXD pin on Paula chip.
10		Not used at this time.
9	STP	Stop bit if 9 data bits are specified for receive.

8	STP	Stop bit if 8 data bits are specified for receive.
	OR	
	DB8	9th data bit if 9 bits are specified for receive.
7-0	DB7-DB0	Low 8 data bits of received data. Data is TRUE (data you read is the same polarity as the data expected).

ADKCON

15	SET/CLR	Allows setting or clearing individual bits. If bit 15 is a 1 specified bits are set. If bit 15 is a 0 specified bits are cleared.
11	UARTBRK	Force the transmit pin to zero.

HOW OUTPUT DATA IS TRANSMITTED

You send data out on the transmit lines by writing into the serial data output register (SERDAT). This register is write-only.

Data will be sent out at the same rate as you have established for the read. Immediately after you write the data into this register, the system will begin the transmission at the baud rate you selected.

At the start of the operation, this data is transferred from SERDAT into an internal serial shift register. When the transfer to the serial shift register has been completed, SERDAT can accept new data; the TBE interrupt signals this fact.

Data will be moved out of the shift register, one bit during each time interval, starting with the least significant bit. The shifting continues until all 1 bits have been shifted out. Any number or combination of data and stop bits may be specified this way.

SERDAT is a 16-bit register that allows you to control the format (appearance) of the transmitted data. To form a typical data sequence, such as one start bit, eight data bits, and one stop bit, you write into SERDAT the contents shown in Figures 8-11 and 8-12.

Register	Address	Read/ Write	Agnus/ Denise/ Paula	Function
ADKCON	09E	W	P	Audio, disk, control write
ADKCONR	010	R	P	Audio, disk, control read

BIT#	USE
15	SET/CLR Set/clear control bit. Determines if bits written with a 1 get set or cleared. Bits written with a zero are always unchanged.
14-13	PRECOMP 1-0

CODE	PRECOMP VALUE
00	none
01	140 ns
10	280 ns
11	560 ns

12	MFMPREC	(1=MFM precomp 0=GCR precomp)
11	UARTBRK	Forces a UART break (clears TXD) if true.
10	WORDSYNC	Enables disk read synchronizing on a word equal to DISK SYNC CODE, located in address (3F)*2.
09	MSBSYNC	Enables disk read synchronizing on the MSB (most signif bit). Appl type GCR.
08	FAST	Disk data clock rate control 1=fast(2us) 0=slow(4us). (fast for MFM, slow for MFM or GCR)
07	USE3PN	Use audio channel 3 to modulate nothing.
06	USE2P3	Use audio channel 2 to modulate period of channel 3.
05	USE1P2	Use audio channel 1 to modulate period of channel 2.
04	USE0P1	Use audio channel 0 to modulate period of channel 1.
03	USE3VN	Use audio channel 3 to modulate nothing.
02	USE2V3	Use audio channel 2 to modulate volume of channel 3.
01	USE1V2	Use audio channel 1 to modulate volume of channel 2.
00	USE0V1	Use audio channel 0 to modulate volume of channel 1.

NOTE: If both period and volume are modulated on the same channel, the period and volume will be alternated. First word xxxxxxxx V6-V0 , Second word P15-P0 (etc)

AUDxDAT	0AA	W	P	Audio channel x data
---------	-----	---	---	----------------------

This register is the audio channel x (x=0,1,2,3) DMA data buffer. It contains 2 bytes of data that are each 2's complement and are outputted sequentially (with digital-to-analog conversion) to the audio output pins. (LSB = 3 MV) The DMA controller automatically transfers data to this register from RAM. The processor can also write directly to this register. When the DMA data is finished (words outputted=length) and the data in this register has been used, an audio channel interrupt request is set.

```

BLTCON0  040  W   A       Blitter control register 0
BLTCON1  042  W   A       Blitter control register 1

```

These two control registers are used together to control blitter operations. There are two basic modes, area and line, which are selected by bit 0 of BLTCON1, as shown below.

AREA MODE ("normal")

BIT#	BLTCON0	BLTCON1
15	ASH3	BSH3
14	ASH2	BSH2
13	ASH1	BSH1
12	ASA0	BSH0
11	USEA	X
10	USEB	X
09	USEC	X
08	USED	X
07	LF7	X
06	LF6	X
05	LF5	X
04	LF4	EFE
03	LF3	IFE
02	LF2	FCI
01	LF1	DESC
00	LF0	LINE (=0)

```

ASH3-0  Shift value of A source
BSH3-0  Shift value of B source
USEA    Mode control bit to use source A
USEB    Mode control bit to use source B
USEC    Mode control bit to use source C
USED    Mode control bit to use destination D
LF7-0   Logic function minterm select lines
EFE     Exclusive fill enable
IFE     Inclusive fill enable
FCI     Fill carry input
DESC    Descending (decreasing address) control bit
LINE    Line mode control bit (set to 0)

```

JOY0DAT	00A	R	D	Joystick-mouse 0 data (left vertical, horizontal)
JOY1DAT	00C	R	D	Joystick-mouse 1 data (right vertical, horizontal)

These addresses each read a pair of 8-bit mouse counters. 0=left controller pair, 1=right controller pair (four counters total). The bit usage for both left and right addresses is shown below. Each counter is clocked by signals from two controller pins. Bits 1 and 0 of each counter may be read to determine the state of these two clock pins. This allows these pins to double as joystick switch inputs.

Mouse counter usage:
(pins 1,3=Yclock, pins 2,4=Xclock)

BIT#	15,14,13,12,11,10,09,08	07,06,05,04,03,02,01,00
ODAT	Y7 Y6 Y5 Y4 Y3 Y2 Y1 Y0	X7 X6 X5 X4 X3 X2 X1 X0
1DAT	Y7 Y6 Y5 Y4 Y3 Y2 Y1 Y0	X7 X6 X5 X4 X3 X2 X1 X0

The following table shows the mouse/joystick connector pin usage. The pins (and their functions) are sampled (multiplexed) into the DENISE chip during the clock times shown in the table. This table is for reference only and should not be needed by the programmer. (Note that the joystick functions are all "active low" at the connector pins.)

Conn Pin	Joystick Function	Mouse Function	Sampled by DENISE		
			Pin	Name	Clock
L1	FORW*	Y	38	MOV at CCK	
L3	LEFT*	YQ	38	MOV at CCK*	
L2	BACK*	X	9	M0H at CCK	
L4	RIGH*	XQ	9	M0H at CCK*	
R1	FORW*	Y	39	M1V at CCK	
R3	LEFT*	YQ	39	M1V at CCK*	
R2	BACK*	X	8	M1H at CCK	
R4	RIGH*	XQ	8	M1H at CCK*	

After being sampled, these connector pin signals are used in quadrature to clock the mouse counters. The LEFT and RIGHT joystick functions (active high) are directly available on the Y1 and X1 bits of each counter. In order to recreate the FORWARD and BACK joystick functions, however, it is necessary to logically combine (exclusive OR) the lower two bits of each counter. This is illustrated in the following table.

To detect	Read these counter bits
Forward	Y1 xor Y0 (BIT#09 xor BIT#08)
Left	Y1
Back	X1 xor X0 (BIT#01 xor BIT#00)
Right	X1

NAME	ADD	R/W	CHIP	FUNCTION
BLTDDAT	& *000	ER	A	Blitter destination early read (dummy address)
DMACONR	*002	R	A P	DMA control (and blitter status) read
VPOSR	*004	R	A	Read vert most signif. bit (and frame flop)
VHPOSR	*006	R	A	Read vert and horiz. position of beam
DSKDATR	& *008	ER	P	Disk data early read (dummy address)
JOYODAT	*00A	R	D	Joystick-mouse 0 data (vert,horiz)
JOY1DAT	*00C	R	D	Joystick-mouse 1 data (vert,horiz)
CLXDAT	*00E	R	D	Collision data register (read and clear)
ADKCONR	*010	R	P	Audio, disk control register read
POTODAT	*012	R	P	Pot counter pair 0 data (vert,horiz)
POT1DAT	*014	R	P	Pot counter pair 1 data (vert,horiz)
POTGOR	*016	R	P	Pot port data read (formerly POTINP)
SERDATR	*018	R	P	Serial port data and status read
DSKBYTR	*01A	R	P	Disk data byte and status read
INTENAR	*01C	R	P	Interrupt enable bits read
INTREQR	*01E	R	P	Interrupt request bits read
DSKPTH	+ *020	W	A	Disk pointer (high 3 bits)
DSKPTL	+ *022	W	A	Disk pointer (low 15 bits)
DSKLEN	*024	W	P	Disk length
DSKDAT	& *026	W	P	Disk DMA data write
REFPTR	& *028	W	A	Refresh pointer
VPOSW	*02A	W	A	Write vert most signif. bit (and frame flop)
VHPOSW	*02C	W	A	Write vert and horiz position of beam
COPCON	*02E	W	A	Coprocessor control register (CDANG)
SERDAT	*030	W	P	Serial port data and stop bits write
SERPER	*032	W	P	Serial port period and control
POTGO	*034	W	P	Pot port data write and start
JOYTEST	*036	W	D	Write to all four joystick-mouse counters at once
STREQU	& *038	S	D	Strobe for horiz sync with VB and EQU
STRVBL	& *03A	S	D	Strobe for horiz sync with VB (vert. blank)
STRHOR	& *03C	S	D P	Strobe for horiz sync
STRLONG	& *03E	S	D	Strobe for identification of long horiz. line.
BLTCON0	~040	W	A	Blitter control register 0
BLTCON1	~042	W	A	Blitter control register 1
BLTAFWM	~044	W	A	Blitter first word mask for source A
BLTALWM	~046	W	A	Blitter last word mask for source A
BLTCPTH	+ ~048	W	A	Blitter pointer to source C (high 3 bits)
BLTCPTL	+ ~04A	W	A	Blitter pointer to source C (low 15 bits)
BLTBPTH	+ ~04C	W	A	Blitter pointer to source B (high 3 bits)
BLTBPTL	+ ~04E	W	A	Blitter pointer to source B (low 15 bits)
BLTAPTH	+ ~050	W	A	Blitter pointer to source A (high 3 bits)
BLTAPTL	+ ~052	W	A	Blitter pointer to source A (low 15 bits)
BLTDPPTH	+ ~054	W	A	Blitter pointer to destination D (high 3 bits)
BLTDPTL	+ ~056	W	A	Blitter pointer to destination D (low 15 bits)
BLTSIZE	~058	W	A	Blitter start and size (window width, height)
	~05A			
	~05C			
	~05E			
BLTCMOD	~060	W	A	Blitter modulo for source C
BLTBMOD	~062	W	A	Blitter modulo for source B
BLTAMOD	~064	W	A	Blitter modulo for source A
BLTDMOD	~066	W	A	Blitter modulo for destination D
	~068			
	~06A			
	~06C			
	~06E			
BLTCDAT	% ~070	W	A	Blitter source C data register
BLTBDAT	% ~072	W	A	Blitter source B data register
BLTADAT	% ~074	W	A	Blitter source A data register

			~076						
			~078						
			~07A						
			~07C						
DSKSYNC			~07E	W		P		Disk sync pattern register for disk read	
COP1LCH	+	080	W	A				Coprocessor first location register (high 3 bits)	
COP1LCL	+	082	W	A				Coprocessor first location register (low 15 bits)	
COP2LCH	+	084	W	A				Coprocessor second location register (high 3 bits)	
COP2LCL	+	086	W	A				Coprocessor second location register (low 15 bits)	
COPJMP1		088	S	A				Coprocessor restart at first location	
COPJMP2		08A	S	A				Coprocessor restart at second location	
COPINS		08C	W	A				Coprocessor instruction fetch identify	
DIWSTRT		08E	W	A				Display window start (upper left vert.-horiz position)	
DIWSTOP		090	W	A				Display window stop (lower right vert.-horiz. position)	
DDFSTRT		092	W	A				Display bit plane data fetch start (horiz. position)	
DDFSTOP		094	W	A				Display bit plane data fetch stop (horiz. position)	
DMACON		096	W	A	D	P		DMA control write (clear or set)	
CLXCON		098	W		D			Collision control	
INTENA		09A	W			P		Interrupt enable bits (clear or set bits)	
INTREQ		09C	W			P		Interrupt request bits (clear or set bits)	
ADKCON		09E	W			P		Audio, disk, UART control	
AUD0LCH	+	0A0	W	A				Audio channel 0 location (high 3 bits)	
AUD0LCL	+	0A2	W	A				Audio channel 0 location (low 15 bits)	
AUD0LEN		0A4	W			P		Audio channel 0 length	
AUD0PER		0A6	W			P		Audio channel 0 period	
AUD0VOL		0A8	W			P		Audio channel 0 volume	
AUD0DAT	&	0AA	W			P		Audio channel 0 data	
		0AC							
		0AE							
AUD1LCH	+	0B0	W	A				Audio channel 1 location (high 3 bits)	
AUD1LCL	+	0B2	W	A				Audio channel 1 location (low 15 bits)	
AUD1LEN		0B4	W			P		Audio channel 1 length	
AUD1PER		0B6	W			P		Audio channel 1 period	
AUD1VOL		0B8	W			P		Audio channel 1 volume	
AUD1DAT	&	0BA	W			P		Audio channel 1 data	
		0BC							
		0BE							
AUD2LCH	+	0C0	W	A				Audio channel 2 location (high 3 bits)	
AUD2LCL	+	0C2	W	A				Audio channel 2 location (low 15 bits)	
AUD2LEN		0C4	W			P		Audio channel 2 length	
AUD2PER		0C6	W			P		Audio channel 2 period	
AUD2VOL		0C8	W			P		Audio channel 2 volume	
AUD2DAT	&	0CA	W			P		Audio channel 2 data	
		0CC							
		0CE							
AUD3LCH	+	0D0	W	A				Audio channel 3 location (high 3 bits)	
AUD3LCL	+	0D2	W	A				Audio channel 3 location (low 15 bits)	
AUD3LEN		0D4	W			P		Audio channel 3 length	
AUD3PER		0D6	W			P		Audio channel 3 period	
AUD3VOL		0D8	W			P		Audio channel 3 volume	
AUD3DAT	&	0DA	W			P		Audio channel 3 data	

				ODC	
				ODE	
BPL1PTH	+	OE0	W	A	Bit plane 1 pointer (high 3 bits)
BPL1PTL	+	OE2	W	A	Bit plane 1 pointer (low 15 bits)
BPL2PTH	+	OE4	W	A	Bit plane 2 pointer (high 3 bits)
BPL2PTL	+	OE6	W	A	Bit plane 2 pointer (low 15 bits)
BPL3PTH	+	OE8	W	A	Bit plane 3 pointer (high 3 bits)
BPL3PTL	+	OEA	W	A	Bit plane 3 pointer (low 15 bits)
BPL4PTH	+	OEC	W	A	Bit plane 4 pointer (high 3 bits)
BPL4PTL	+	OEE	W	A	Bit plane 4 pointer (low 15 bits)
BPL5PTH	+	OF0	W	A	Bit plane 5 pointer (high 3 bits)
BPL5PTL	+	OF2	W	A	Bit plane 5 pointer (low 15 bits)
BPL6PTH	+	OF4	W	A	Bit plane 6 pointer (high 3 bits)
BPL6PTL	+	OF6	W	A	Bit plane 6 pointer (low 15 bits)
				OF8	
				OFA	
				OFC	
				OFE	
BPLCON0		100	W	A D	Bit plane control register (misc. control bits)
BPLCON1		102	W	D	Bit plane control reg. (scroll value PF1, PF2)
BPLCON2		104	W	D	Bit plane control reg. (priority control)
		106			
BPL1MOD		108	W	A	Bit plane modulo (odd planes)
BPL2MOD		10A	W	A	Bit Plane modulo (even planes)
		10C			
		10E			
BPL1DAT	&	110	W	D	Bit plane 1 data (parallel-to-serial convert)
BPL2DAT	&	112	W	D	Bit plane 2 data (parallel-to-serial convert)
BPL3DAT	&	114	W	D	Bit plane 3 data (parallel-to-serial convert)
BPL4DAT	&	116	W	D	Bit plane 4 data (parallel-to-serial convert)
BPL5DAT	&	118	W	D	Bit plane 5 data (parallel-to-serial convert)
BPL6DAT	&	11A	W	D	Bit plane 6 data (parallel-to-serial convert)
		11C			
		11E			

AGNUS PIN ASSIGNMENT

PIN #	DESIGNATION	FUNCTION	DEFINITION
01-09	D8-D0	Data bus lines 8 to 0	I/O
10	VCC	+5 Volt	I
11	RES*	System reset	I
12	INT3*	Interrupt level 3	O
13	DMAL	DMA request line	I
14	BLS*	Blitter slowdown	I
15	DBR*	Data bus request	O
16	ARW*	Agnus RAM write	O
17-24	RGA8-RGA1	Register address bus 8-1	I/O
25	CCK	Color clock	I
26	CCKQ	Color clock delay	I
27	VSS	Ground	I
28-36	DRA0-DRA8	DRAM address bus 0 to 8	O
37	LP*	Light pen input	I
38	VSX*	Vertical sync	I/O
39	CSX*	Composite sync	O
40	HSX*	Horizontal sync	I/O
41	VSS	Ground	I
42-48	D15-D9	Data bus lines 15 to 9	I/O

DENISE PIN ASSIGNMENT

PIN #	DESIGNATION	FUNCTION	DEFINITION
01-07	D6-D0	Data bus lines 6 to 0	I/O
08	M1H	Mouse 1 horizontal	I
09	M0H	Mouse 0 horizontal	I
10-17	RGA8-RGA1	Register address bus 8-1	I
18	BURST*	Color burst	O
19	VCC	+5 Volt	I
20-23	R0-R3	Video red bits 0-3	O
24-27	B0-B3	Video blue bits 0-3	O
28-31	G0-G3	Video green bits 0-3	O
32	N/C	Not connected	N/C
33	ZD*	Background indicator	O
34	N/C	Not connected	N/C
35	7M	7.15909 MHZ	I
36	CCK	Color clock	I
37	VSS	Ground	I
38	M0V	Mouse 0 vertical	I
39	M1V	Mouse 1 vertical	I
40-48	D15-D7	Data bus lines 15 to 7	I/O

A true software memory map, showing system utilization of the various sections of RAM and free space is not provided, or possible with the Amiga. All memory is dynamically allocated by the memory manager, and the actual locations may change from release-to-release, machine-to-machine or boot-to-boot (see the `exec/AllocMem` function for details). To find the locations of system structures software must use the defined access procedures, starting by fetching the address of the `exec.library` from location 4; the only absolute memory location in the system. All software is written so that it can be loaded and relocated anywhere in memory by the loader. What follows is the general layout of memory areas withing the current generation of Amiga computers.

ADDRESS RANGE	NOTES
000000-03FFFF	256K Bytes of chip RAM
040000-07FFFF	256K bytes of chip RAM (option card)
080000-0FFFFFFF	512K Extended chip RAM (to 1 MB).
100000-1FFFFFFF	Reserved. Do not use.
200000-9FFFFFFF	Primary 8 MB Auto-config space.
A00000-BFFFFFFF	Reserved. Do not use.
BFD000-BFDF00	8520-B (access at even-byte addresses only)
-	
BFE001-BFEF01	8520-A (access at odd-byte addresses only)
-	
	The underlined digit chooses which of the 16 internal registers of the 8520 is to be accessed. See Appendix F.
C00000-DFFFFFFF	Reserved. Do not use.
C00000-D7FFFF	Internal expansion memory.
D80000-DBFFFF	Reserved. Do not use.
DC0000-DCFFFF	Real time clock.
DFF000-DFFFFFFF	Chip registers. See Appendix A and Appendix B.
+--	
E00000-E7FFFF	Reserved. Do not use.
E80000-E8FFFF	Auto-config space. Boards appear here before the system relocates them to their final address.
E90000-EFFFFFFF	Secondary auto-config space (usually 64K I/O boards).
F00000-FBFFFF	Reserved. Do not use.
FC0000-FFFFFFF	256K System ROM.


PARALLEL INTERFACE CONNECTOR SPECIFICATION

The 25-pin D-type connector with pins (DB25P=male for the A1000, female for A500/A2000 and IBM compatibles) at the rear of the Amiga is nominally used to interface to parallel printers. In this capacity, data flows from the Amiga to the printer. This interface may also be used for input or bidirectional data transfers. The implementation is similar to Centronics, but the pin assignment and drive characteristics vary significantly from that specification (see Pin Assignment). Signal names correspond to those used in the other places in this appendix, when possible.

PARALLEL CONNECTOR PIN ASSIGNMENT (J8)


NAME	DIR	NOTES
DRDY*	O	Output-data-ready signal to parallel device in output mode, used in conjunction with ACK* (pin 10) for a two-line asynchronous handshake. Functions as input data accepted from Amiga in input mode (similar to ACK* in output mode). See timing diagrams in the following section.
D0	I/O	+
D1	I/O	
D2	I/O	
D3	I/O	D0-D7 comprise an eight-bit bidirectional bus
D4	I/O	for communication with parallel devices,
D5	I/O	nominally, a printer.
D6	I/O	
D7	I/O	+
ACK*	I	Output-data-acknowledge from parallel device in output mode, used in conjunction with DRDY* (pin 1) for a two-line asynchronous handshake. Functions as input-data-ready from parallel device in input mode (similar to DRDY* in output mode). See timing diagrams. The 8520 can be programmed to conditionally generate a level 2 interrupt to the 68000 whenever the ACK* input goes active.
BUSY	I/O	This is a general purpose I/O pin also connected to a serial data I/O pin (serial clock on pin 12). Note: Nominally used to indicate printer buffer full.
POUT	I/O	This is a general purpose I/O pin to a serial clock I/O pin (serial data on pin 11). Note: Nominally used to indicate printer paper out.
SEL	I/O	This is a general purpose I/O pin. Note: nominally a select output from the parallel device to the Amiga. On the A500/A2000 also shared with RS232 "ring indicator" signal.
RESET*	O	Amiga system reset

PARALLEL CONNECTOR INTERFACE TIMING, OUTPUT CYCLE



nsp = not specified
upc = under program control

PARALLEL CONNECTOR INTERFACE TIMING, INPUT CYCLE



nsp = not specified
upc = under program control

CIAA Address Map

Byte Address	Register Name	7	6	5	4	3	2	1	0
BFE001	pra	/FIR1 /FIR0 /RDY /TK0 /WPRO /CHNG /LED OVL							
BFE101	prb	Parallel port							
BFE201	ddra	Direction for port A (BFE001);1=output (set to 0x03)							
BFE301	ddrb	Direction for port B (BFE101);1=output (can be in or out)							
BFE401	talo	CIAA timer A low byte (.715909 Mhz NTSC; .709379 Mhz PAL)							
BFE501	tahi	CIAA timer A high byte							
BFE601	tblo	CIAA timer B low byte (.715909 Mhz NTSC; .709379 Mhz PAL)							
BFE701	tbhi	CIAA timer B high byte							
BFE801	todlo	50/60 Hz event counter bits 7-0 (VSync or line tick)							
BFE901	todmid	50/60 Hz event counter bits 15-8							
BFEA01	todhi	50/60 Hz event counter bits 23-16							
BFEB01		not used							
BFEC01	sdr	CIAA serial data register (connected to keyboard)							
BFED01	icr	CIAA interrupt control register							
BFEE01	cra	CIAA control register A							
BFEF01	crb	CIAA control register B							

Note: CIAA can generate interrupt INT2.

CIAB Address Map

Byte Address	Register Name	7	6	5	4	3	2	1	0
BFD000	pra	/DTR /RTS /CD /CTS /DSR SEL POUT BUSY							
BFD100	prb	/MTR /SEL3 /SEL2 /SEL1 /SELO /SIDE DIR /STEP							
BFD200	ddra	Direction for Port A (BFD000);1 = output (set to 0xFF)							
BFD300	ddrb	Direction for Port B (BFD100);1 = output (set to 0xFF)							
BFD400	talo	CIAB timer A low byte (.715909 Mhz NTSC; .709379 Mhz PAL)							
BFD500	tahi	CIAB timer A high byte							
BFD600	tblo	CIAB timer B low byte (.715909 Mhz NTSC; .709379 Mhz PAL)							
BFD700	tbhi	CIAB timer B high byte							
BFD800	todlo	Horizontal sync event counter bits 7-0							
BFD900	todmid	Horizontal sync event counter bits 15-8							
BFDA00	todhi	Horizontal sync event counter bits 23-16							
BFDB00		not used							
BFDC00	sdr	CIAB serial data register (unused)							
BFDD00	icr	CIAB interrupt control register							
BFDE00	cra	CIAB Control register A							
BFD00	crb	CIAB Control register B							

Note: CIAB can generate INT6.

BIT MAP OF REGISTER CRA

REG#	NAME	UNUSED	SPMODE	INMODE	LOAD	RUNMODE	OUTMODE	PBON	START
E	CRA	unused unused	0=input 1=output	0=02 1=CNT	1=force load (strobe)	0=cont. 1=one- shot	0=pulse 1=toggle	0=PB6OFF 1=PB6ON	0=stop 1=start

|<----- Timer A Variables ----->|

All unused register bits are unaffected by a write and forced to 0 on a read.

CONTROL REGISTER B:

BIT	NAME	FUNCTION
-----	------	----------

0	START	1 = start Timer B, 0 = stop Timer B. This bit is automatically reset (= 0) when underflow occurs during one-shot mode.															
1	PBON	1 = Timer B output on PB7, 0 = PB7 is normal operation.															
2	OUTMODE	1 = toggle, 0 = pulse.															
3	RUNMODE	1 = one-shot mode, 0 = continuous mode.															
4	LOAD	1 = force load (this is a strobe input, there is no data storage; bit 4 will always read back a zero and writing a 0 has no effect.)															
6,5	INMODE	Bits CRB6 and CRB5 select one of four possible input modes for Timer B, as follows:															
		<table border="1"> <thead> <tr> <th>CRB6</th> <th>CRB5</th> <th>Mode Selected</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>Timer B counts 02 pulses</td> </tr> <tr> <td>0</td> <td>1</td> <td>Timer B counts positive CNT transitions</td> </tr> <tr> <td>1</td> <td>0</td> <td>Timer B counts Timer A underflow pulses</td> </tr> <tr> <td>1</td> <td>1</td> <td>Timer B counts Timer A underflow pulses while CNT pin is held high.</td> </tr> </tbody> </table>	CRB6	CRB5	Mode Selected	0	0	Timer B counts 02 pulses	0	1	Timer B counts positive CNT transitions	1	0	Timer B counts Timer A underflow pulses	1	1	Timer B counts Timer A underflow pulses while CNT pin is held high.
CRB6	CRB5	Mode Selected															
0	0	Timer B counts 02 pulses															
0	1	Timer B counts positive CNT transitions															
1	0	Timer B counts Timer A underflow pulses															
1	1	Timer B counts Timer A underflow pulses while CNT pin is held high.															
7	ALARM	1 = writing to TOD registers sets Alarm 0 = writing to TOD registers sets TOD clock. Reading TOD registers always reads TOD clock, regardless of the state of the Alarm bit.															




Figure G-1: How to read the Address Specification Table

NOTE

The bit numbering (7 6 5 4 3 2 1 0) is for use when two nibbles are to be interpreted together as a byte. Physically, each nibble is the high nibble of the word at its address (ie. bits 15 14 13 12).

Table G-1: Address Specification Table

OFFSET:	Address 1	Address 2	Description
(\$00/02) Read Not Inverted	7 6 5 4 3 2 1 0	7 6 5 4 3 2 1 0	Board size 000=8meg 100=512k 001=64k 101=1meg 010=128k 110=2meg 011=256k 111=4meg 1 = Next card is also on this board 1 = Optional ROM vector valid 1 = Link into memory free list (RAM) Board type 00 = Reserved 01 = Reserved 10 = Reserved 11 = Current type
(\$04/06) Read Inverted	7 6 5 4 3 2 1 0 Hi nibble Lo nibble	7 6 5 4 3 2 1 0	Manufacturer chosen product number
(\$08/0A) Read Inverted	7 6 5 4 3 2 1 0	7 6 5 4 3 2 1 0	(Remember - these read inverted) Reserved - Should be 0 currently 0 = this board can be shut-up 1 = this board ignores shut-up 0 = any space OK 1 = 8 Meg area preferred


Keyboard Communications

The keyboard transmits 8-bit data words serially to the main unit. Before the transmission starts, both KCLK and KDAT are high. The keyboard starts the transmission by putting out the first data bit (on KDAT), followed by a pulse on KCLK (low then high); then it puts out the second data bit and pulses KCLK until all eight data bits have been sent. After the end of the last KCLK pulse, the keyboard pulls KDAT high again.

When the computer has received the eighth bit, it must pulse KDAT low for at least 1 (one) microsecond, as a handshake signal to the keyboard. The handshake detection on the keyboard end will typically use a hardware latch. *The keyboard must be able to detect pulses greater than or equal to 1 microsecond. Software MUST pulse the line low for 85 microseconds to ensure compatibility with all keyboard models.*

All codes transmitted to the computer are rotated one bit before transmission. The transmitted order is therefore 6-5-4-3-2-1-0-7. The reason for this is to transmit the up/down flag last, in order to cause a key-up code to be transmitted in case the keyboard is forced to restore lost sync (explained in more detail below).

The KDAT line is active low; that is, a high level (+5V) is interpreted as 0, and a low level (0V) is interpreted as 1.



The keyboard processor sets the KDAT line about 20 microseconds before it pulls KCLK low. KCLK stays low for about 20 microseconds, then goes high again. The processor waits another 20 microseconds before changing KDAT.

Therefore, the bit rate during transmission is about 60 microseconds per bit, or 17 kbits/sec.

Matrix Table

Column	Row 5 (Bit 7)	Row 4 (Bit 6)	Row 3 (Bit 5)	Row 2 (Bit 4)	Row 1 (Bit 3)	Row 0 (Bit 2)
15 (PD.7)	(spare) (0E)	(spare) (1C)	(spare) (2C)	(spare) (47)	(spare) (48)	(spare) (49)
14 (PD.6)	* note 1 (5D)	<SHIFT> note 2 (30)	CAPS LOCK (62)	TAB (42)	~ (00)	ESC (45)
13 (PD.5)	+ note 1 (5E)	Z (31)	A (20)	Q (10)	! (01)	(note 1 (5A)
12 (PD.4)	9 note 3 (3F)	X (32)	S (21)	W (11)	@ 2 (02)	F1 (50)
11 (PD.3)	6 note 3 (2F)	C (33)	D (22)	E (12)	# 3 (03)	F2 (51)
10 (PD.2)	3 note 3 (1F)	V (34)	F (23)	R (13)	\$ 4 (04)	F3 (52)
9 (PD.1)	. note 3 (3C)	B (35)	G (24)	T (14)	% 5 (05)	F4 (53)
8 (PD.0)	8 note 3 (3E)	N (36)	H (25)	Y (15)	^ 6 (06)	F5 (54)
7 (PC.7)	5 note 3 (2E)	M (37)	J (26)	U (16)	& 7 (07)	) note 1 (5B)
6 (PC.6)	2 note 3 (1E)	< (38)	K (27)	I (17)	* 8 (08)	F6 (55)
5 (PC.5)	ENTER note 3 (43)	> (39)	L (28)	O (18)	(9 (09)	/ note 1 (5C)

Column	Row 5 (Bit 7)	Row 4 (Bit 6)	Row 3 (Bit 5)	Row 2 (Bit 4)	Row 1 (Bit 3)	Row 0 (Bit 2)
4 (PC.4)	7 note 3 (3D)	? / (3A)	: ; (29)	P (19)	) 0 (0A)	F7 (56)
3 (PC.3)	4 note 3 (2D)	(spare) (3B)	" ' (2A)	{ [(1A)	- (0B)	F8 (57)
2 (PC.2)	1 note 3 (1D)	SPACE BAR (40)	<RET> note 2 (2B)	}] (1B)	+ = (0C)	F9 (58)
1 (PC.1)	0 note 3 (0F)	BACK SPACE (41)	DEL (46)	RETURN (44)	 \ (0D)	F10 (59)
0 (PC.0)	- note 3 (4A)	CURS DOWN (4D)	CURS RIGHT (4E)	CURS LEFT (4F)	CURS UP (4C)	HELP (5F)

note 1: A500 and A2000 keyboards only (numeric pad)

note 2: International keyboards only (these keys are cutouts of the larger key on the US ASCII version.) The key that generates \$30 is cut out of the left shift key. Key \$2B is cut out of return. These keys are labeled with country-specific markings.

note 3: Numeric pad.

The following table shows which keys are independently readable. These keys never generate ghosts or phantoms.

(Bit 6)	(Bit 5)	(Bit 4)	(Bit 3)	(Bit 2)	(Bit 1)	(Bit 0)
LEFT	LEFT	LEFT	CTRL	RIGHT	RIGHT	RIGHT
AMIGA	ALT	SHIFT		AMIGA	ALT	SHIFT
(66)	(64)	(60)	(63)	(67)	(65)	(61)

INDEX

- 60 Pin Edge Connector, 299
- 68000, 2, 4, 10, 13-14, 20, 31, 181, 189, 217
 - instead of Copper, 31
 - interrupting, 31, 211
 - normal cycle, 191
 - Share Memory, 4
 - synchronizing with the video beam, 210
 - test-and-set instruction, 191
- 68010, 2
- 68010/20/30, 10
- 68020, 2, 181
- 68030, 2
- 8520, 10, 153, 219, 236, 238, 245, 317
 - alarm, 323
 - handshaking, 320
 - input modes, 322
 - interval timers, 320
 - continuous, 321
 - force load, 322
 - one-shot, 321
 - PB on/off, 321
 - start/stop, 321
 - Toggle/pulse, 321
 - I/O ports, 320
 - read bit names, 322
 - register map, 319
 - signal assignments, 313
 - time-of-day clock, 323
 - write bit names, 322
- 86 Pin Edge Connector, 300
- A0, 10
- A1, 10
- A1000, 1, 4, 6, 56, 59, 232, 255
 - expansion port, 299
- A2000, 1-2, 4, 6, 56, 153, 232, 255
- A500, 1-2, 4, 6, 56, 153, 232, 255
- A6, 10
- Address Registers, 8
- Addresses, 10
- ADKCON, 236, 244, 252
 - disk control bits, 242
 - in audio, 145, 147
- Agnus, 3-4, 160-161, 163
 - fat agnus, 4, 181
- Alarm, 323
- Aliasing
 - audio, 150
- AllocMem(), 46
- Amiga OS, 7
- Amplitude Modulation, 4
- Animated Objects, 5
- Animation, 170
- Apple II, 235
- Area Fill, 4, 178
- ATTACH, 117
- Attachment
 - audio, 146
 - sprites, 117
- Audio, 4, 7, 14
 - aliasing distortion, 150
 - amplitude modulation, 4
 - channels
 - attaching, 145, 160
 - choosing, 134
 - data, 134
 - data length registers, 136
 - data location registers, 135-136
 - data output rate, 137
 - decibel values, 137, 159
 - DMA, 135, 140, 143, 160
 - equal-tempered scale, 154
 - frequency modulation, 4