

FMUSER FUQ-4412B QAM Modulator 1ch ASI Input - RF Output DVB-C ITU-T J.83A-B-C QAM Modulation TS Processing RS Encoding Broadcast Satellite Applications Product overview



The FMUSER FUQ-4412B QAM Modulator performs QAM modulation with TS and ASI inputs and RF output. It processes transport streams, applies RS encoding and convolution interlacing, and modulates signals to RF. This device supports local control via LCD/keyboard and remote NMS control. Ideal for broadcasting, interactive services, and news gathering applications.

Key feature

Enables PSI/SI processing with PID filtering, re-mapping, PCR adjustment, and NIT insertion.

Specifications

Input	1channle ASI input, BNC interface, 75Ω	1channle ASI input, BNC interface, 75Ω
Modulation	QAM Channel	1
Modulation	Standard	EN300 429/ITU-T J.83A/B/C
Modulation	Symbol Rate	5.0~9.0Msps■1ksps stepping
Modulation	Constellation	16■32■64■128■256QAM
Modulation	FEC	RS(204, 188)
RF Output	Connector	F Type, 75Ω impedance
RF Output	RF Range	30~1000MHz■1kHzStepping
RF Output	Output Attenuation	-16dBm~+12dBm■0.5dB Stepping
System	LCD/keyboard operating and NMS support	LCD/keyboard operating and NMS support

System	English and Chinese interface conversion	English and Chinese interface conversion
System	Ethernet software upgrading	Ethernet software upgrading
General	Dimension(W*D*H)	482mm×300mm×44mm
General	Weight	2.3kg
General	Temperature	0~45■(Operation) ; -20~80■(Storage)
General	Power	AC 110V±10%■50/60Hz■ or AC 220V±10%■50/60Hz
General	Consumption	22W

About Us

FMUSER is a company specializing in broadcasting and television transmission systems and integrating hotel IPTV systems. The company was established in 2009 and has served over 180 countries worldwide. More than 20,000 television stations, radio stations, and hotel clients from different.

Contact:Tomleequan Email■sales@fmuser.com whatsapp: [+8613922702227](https://wa.me/8613922702227)