

rfidlib_nfc Function Instruction

V1.1

Contents

1.Instruction	3
2.Application Integration	3
3. API Function Interface	4
3.1. nfc_CreateUriNdef	4
3.2. nfc_WriteNdef	5
3.3. nfc_ReadNdef	6
3.4. nfc_ParseNdefByUri	7

1.Instruction

The development kit supports ANSI-C, ANSI-C++ and other languages to call the C function interface, such as delphi, VB, C# and MFC ,etc. All API call conventions are using the "__stdcall".

2.Application Integration

This package consists of the following files :

Files	Description
rfidlib_nfc.dll	Dynamic link library, contains all API interface
rfidlib_nfc.lib	VC++ project, static link library
rfidlib_nfc.h	Header file of C/C++ project, the function definition
rfidlib_nfc.cs	C# class file

Programming Language	Description
VC++	Copy rfidlib_nfc.lib and rfidlib_nfc.h to the project directory and add to the project . Copy rfidlib_nfc.dll to exe file output directory.
C#	Copy rfidlib_nfc.cs to the project directory and add to the project . Copy rfidlib_nfc.dll to exe file output directory.

3. API Function Interface

3.1. nfc_CreateUriNdef

Function Definition	nfc_CreateUriNdef(LPTSTR sNetAddr, Byte UriType)			
Description	Create NDEF message for the URI			
Parameter	Name	Type	Direction	Remarks
	sNetAddr	LPTSTR	[in]	URI Address
	UriType	DWORD	[in]	URI Type . Refer to“URI type contrast table”
Return (RFID_NFC_HANDLE)	Return handle of NDEF message			
Reference				

3.2. nfc_WriteNdef

Function Definition	err_t RFIDLIB_API nfc_WriteNdef(RFID_READER_HANDLE hReader,RFID_TAG_HANDLE hTag,RFID_NFC_HANDLE hNdef,BOOLEAN IsLock)			
Description	Written NDEF message			
Parameter	Name	Type	Direction	Remarks
	hReader	RFID_READER_HANDLE	[in]	Handle of reader
	hTag	RFID_TAG_HANDLE	[in]	Handle of tag connection
	hNdef	RFID_NFC_HANDLE	[in]	Handle of NDEF message, Created by CreateUriNdef interface
	IsLock	BOOLEAN	[in]	Whether to lock the tag
Return (err_t)	0: Success Not 0: Failure, please check API error list .			
Reference				

3.3. nfc_ReadNdef

Function Definition	err_t RFIDLIB_API nfc_ReadNdef(RFID_READER_HANDLE hReader,RFID_TAG_HANDLE hTag,RFID_NFC_HANDLE *hNdef,BYTE *NdefType)			
Description	Read NDEF message			
Parameter	Name	Type	Direction	Remarks
	hReader	RFID_READER_HANDLE	[in]	Handle of reader operation
	hTag	RFID_TAG_HANDLE	[in]	Handle of tag connection
	hNdef	RFID_NFC_HANDLE *	[out]	Use to save NDEF message have read
	NdefType	BYTE *	[out]	NDEF message type . URI:0X01
Return (err_t)	0: Success Not 0: Failure ,please check API error list .			
Reference				

3.4. nfc_ParseNdefByUri

Function Definition	err_t RFIDLIB_API nfc_ParseNdefByUri(RFID_NFC_HANDLE hNdef,LPTSTR sNetAddr,DWORD NetAddrSize,BYTE *netType)			
Description	Explain NDRF message by URI way			
Parameter	Name	Type	Direction	Remarks
	hNdef	RFID_NFC_HANDLE	[in]	Handle of NDEF message
	sNetAddr	LPTSTR	[out]	URI Address
	NetAddrSize	DWORD	[in]	Save the maximum length of the IP address memory
	netType	,BYTE *	[out]	URI type . Please check“URI type table ”
Return (err_t)	0: Success Not 0: Failure,please check API error list .			
Reference				

URI type contrast table

Value	Protocol
0	No
1	http://www.
2	https://www.
3	http://
4	https://
5	tel:
6	mailto:
7	ftp://anonymous:anonymous@
8	ftp://ftp.
9	ftps://
10	sftp://
11	smb://
12	nfs://
13	ftp://
14	dav://
15	news:
16	telnet://
17	imap:
18	rtsp://
19	urn:
20	pop
21	sip:
22	sips:
23	tftp:
24	btsp://
25	btl2cap://
26	btgoep://
27	tcpobex://
28	irdaobex://
29	file://
30	urn:epc:id:
31	urn:epc:tag:
32	urn:epc:pat:
33	urn:epc:raw:
34	urn:epc:
35	urn:nfc:
36	RFU

