# FI-WP2HL

## Dual Channel UHF Wireless bodypack transmitter with headset or Lapel Microphone, with True Diversity Receiver



The FI-WP2HL system allows for 10 frequency groups, each with up to 16 channels, adding up to a total of 160 usable channels that won't interfere with each other. The onboard Digital Volume Control system removes the need for a volume control knob and allows for seamless use between different microphone users. Up to 16 transmitter/receiver systems can be used at the same time.

### Wireless bodypack transmitter with Headset and Lapel Microphone

The Wireless headset and Lapel Microphone is a vocal microphone suitable for both speaking and live vocal performance. The frequency response replicates that of popular dynamic vocal mics giving crisp, clear mid-range sound that rejects feedback. The Wireless bodypack transmitter 's gain control allows for tweaking of mic's sensitivity to suit the vocal performer.
A back-lit LCD display shows the operational status of the microphone, including current group, channel, battery charge, and lock status. This microphone is perfect for performing bands, weddings and other functions with multiple or animated/ mobile speakers or vocalist.

### Dual Channel Wireless Receiver

The Dual Channel Wireless Receiver, easy to use high quality receiver with an impressive pick-up range. The receiver uses automatic frequency testing to detect vacant frequencies in the area. Combine this with infrared synchronization that automatically pairs the transmitter and receiver to the same frequency, and this system is as simple to set up as 1-2-3! To make life even easier, an onboard digital volume control system automates the volume level outputted ensuring maximum signal strength without distortion / clipping. The result is a clear, even sound between different speakers / singers.

### True Diversity Receiver

The unit incorporates two receiving antennas and monitors the signal strength on each antenna, switching automatically to the strongest receiving antenna. This prevents dropouts that can occur due to self-destructive interference patterns of the radio waves, or when a performer moves around stage with the transmitter. This is known as True Diversity reception technology, as opposed to quasi-diversity reception, which uses two antennas but only monitors one at a time, switching when that antenna drops below a certain signal strength, regardless of the strength on the other antenna. 2 Rack ears come with the unit for installing into a rack system.

### Other Useful Features

A mute level control on the rear of the unit acts like a noise gate and is useful if there are interference noises when the mic is not being used. The back-lit LCD shows the status of each receiving channel, including the current group and frequency, and active antenna. The 6 segment LED meter indicates RF signal strength and audio input levels.

UNIT 2 Intelligent manufacturing Industrial Park,YinZhou District, NingBo, China
Tel: 0574 8757 6644 Phone: 186 0661 6969 E-mail: Sales@frog-is.com

## Product Features

- LCD shows clear working status
- Digital volume control system light touch button with simple setup
- True diversity receiver technology, tone key squelch circuit to avoid interference
- Automatic frequency selection
- Transmitter battery volume indication
- Infrared data synchronisation
- 2 x rack ears included
- Metal body and rubber end structure for increased drop resistance
- LCD screen shows group, channel, battery volume, power, gain, mute status
- RF power adjustment and gain control adjustments
- Infrared data synchronisation.

## Application

- This is the ideal mic for most lead vocalists. It's also great for stage drama performance.

## Product Specification

| WP2BP UHF Wireless Bodypack Transmitter | |
|---|---|
| Frequency Range | 470 - 490 Mhz, 514 - 542 Mhz, 655 - 679 Mhz |
| Modulation | UHF |
| Optional Frequency Channel | 160 |
| Frequency Response | 60Hz - 16Khz |
| Form Factor | Bodypack Transmitter with Lapel Mic or Headset Mic |
| Gain Adjustment Range audio input level | 0/3/6dB |
| Input Impedance | 5KΩ |
| Output Power | 5mW / 10mW / 30mW |
| Harmonic Rejection | > 50dB |
| Pilot Tone | 32.768KHz |
| Display | LCD |
| Power Requirements | 1.5V x 2(AA) |
| Battery Life | >8H/1300mAH |
| Dimensions | 64 x 25 x 96 mm |
| Weight | 130g |
| **WP2R UHF Dual Channel Rack Mount Receiver** | |
| Frequency range | 470 - 490 Mhz, 514 - 542 Mhz, 655 - 679 Mhz |
| Modulation | UHF |
| Working Range | 60-80 Meters |
| Optional Frequency Channel | 160 |
| Frequency Response | 50Hz - 15Khz(+-3dB) |
| Dynamic Range | >105dB |
| THD | < 0.5% |
| S/N Ratio | >102dB(A) |
| RF Sensitivity | < -95dBm |
| Image Rejection | >60dB |
| Output Connectors | XLRx2 (individual), XLRx1 (2 in1 mix) , 1/4"x1 (2 in 1 mix) |
| Audio Output Level | XLR +10dBV , 1/4" + 8dBV |
| Impedance | XLR 3KΩ, 1/4" 3KΩ |
| Pilot Tone | 32.768Khz |
| Display | LCD |
| Power Requirements | 12V/0.5A DC |
| Working Temperature Range | 0°C - 50°C |
| Dimensions | 16 x 41 x 4.4 cm |
| Weight | 1800g |

FROGIS

UNIT 2 Intelligent manufacturing Industrial Park,YinZhou District, NingBo, China
Tel: 0574 8757 6644 Phone: 186 0661 6969 E-mail: Sales@frog-is.com