

The signal equation of MRI is given by

$$S_c(t) = \int_V s_c(\mathbf{r}) \rho(\mathbf{r}, t) e^{-i\gamma \int_0^t \Delta B(\mathbf{r}, \tau) d\tau} d\mathbf{r} \quad (1)$$

The difference  $\Delta B$  from the main magnetic field  $B_0$  can be expressed like

$$\Delta B(\mathbf{r}, t) = \Delta B_0(\mathbf{r}) + \sum_{\beta \in \{x, y, z\}} G_\beta^0(t) r_\beta + \sum_{\substack{|l|, |m| \geq 0 \\ \beta \in \{x, y, z\}}} G_\beta^{lm}(t) N_l^m(\mathbf{r}) \quad (2)$$

Where  $N_l^m(\mathbf{r})$  are scalar fields describing the non-linear spatial variations of the magnetic field, typically described either by the solid harmonics

$$R_l^m(\mathbf{r}) = \|\mathbf{r}\|^l Y_l^m(\mathbf{r}), \text{ for spherical harmonics } Y_l^m(\mathbf{r}) \quad (3)$$

In the ideal case, the higher order terms from the harmonics are zero, and only the linear terms  $G_\beta^0(t) r_\beta$  remain. However, in practice there are always some higher order terms present, and the ideal gradient fields prescribed are the actual gradient fields realized. The actual gradient waveforms can be modelled well by a convolution of the ideal gradient waveforms with an impulse response function  $\alpha(t)$ . This can be expressed for all orders of the gradient fields as

$$G_\beta^{lm}(t) = (\alpha_\beta^{lm} * G_\beta^{\text{ideal}})(t) \quad (4)$$

Or if gradient heating is to be taken into account, the impulse response function can be made time-varying as

$$G_\beta^{lm}(t) = (\alpha_\beta^{lm}(t) * G_\beta^{\text{ideal}})(t). \quad (5)$$

While the magnetization  $\rho(\mathbf{r}, t)$  is time dependent, we consider readout to be short enough that the only time dependence is due to  $T_2$  decay. Thus, we can express the magnetization as

$$S_c(t) = \int_V s_C(\mathbf{r}) \rho(\mathbf{r}) e^{-t/T_2(\mathbf{r})} e^{-i\gamma \int_0^t \Delta B(\mathbf{r}, \tau) d\tau} d\mathbf{r} \quad (6)$$

With this we can gather all terms that makes the signal equation deviate from a Fourier transform of the static magnetization in the linear gradient fields and form

$$S_c(t) = \int_V s_C(\mathbf{r}) \rho(\mathbf{r}) e^{\Phi(\mathbf{r}, t)} e^{-i\mathbf{k}(t) \cdot \mathbf{r}} d\mathbf{r} \quad (7)$$

where

$$\Phi(\mathbf{r}, t) = -t/T_2(\mathbf{r}) - i\gamma \int_0^t \Delta B_0(\mathbf{r}) d\tau + \sum_{\substack{|l|, |m| > 0 \\ \beta \in \{x, y, z\}}} N_l^m(\mathbf{r}) \int_0^t G_\beta^{lm}(\tau) d\tau \quad (8)$$

$$\mathbf{k}(t) = \gamma \int_0^t (G_x^0(\tau), G_y^0(\tau), G_z^0(\tau)) d\tau \quad (9)$$

Considering a voxel discretization, we can express the operators as matrices by

$$\begin{aligned} (\mathbf{A}_c)_{kj} &= s_C(\mathbf{r}_j) e^{\Phi(\mathbf{r}_j, t_k)} e^{-i\mathbf{k}(t_k) \cdot \mathbf{r}_j} \\ (\mathbf{A}_c^H)_{ik} &= s_C^*(\mathbf{r}_i) e^{\Phi^*(\mathbf{r}_i, t_k)} e^{i\mathbf{k}(t_k) \cdot \mathbf{r}_i} \\ (\mathbf{A}_c^H \mathbf{A}_c)_{ij} &= \sum_k s_C(\mathbf{r}_j) s_C^*(\mathbf{r}_i) e^{\Phi(\mathbf{r}_j, t_k) + \Phi^*(\mathbf{r}_i, t_k)} e^{-i\mathbf{k}(t_k) \cdot (\mathbf{r}_j - \mathbf{r}_i)} \end{aligned}$$

Now, to get back a Fourier transform, and to enable the Toeplitz property in  $\mathbf{A}_c^H \mathbf{A}_c$ . We introduce approximations

$$\exp(\Phi(\mathbf{r}_j, t_k)) \approx \sum_{l=0}^L \Omega_{kl} \Upsilon_{jl} \quad (10)$$

This enables us to approximate the forward and backward operators by evaluating  $L$  fourier transforms. We wish to get a similar decomposition for the normal operator. However, a naive application of the above approximation would give us a decomposition with  $L^2$  Fourier transforms, which is infeasible. We thus try to get a decomposition into fewer Fourier terms. We begin with the naive multiplication

$$\exp(\Phi(\mathbf{r}_j, t_k) + \Phi^*(\mathbf{r}_i, t_k)) \approx \sum_{l_1=0}^L \sum_{l_2=0}^L (\Omega_{kl_1} \Omega_{kl_2}^*) (\Upsilon_{jl_1} \Upsilon_{il_2}^*) \quad (11)$$

For each  $k$  we have a  $L \times L$  hermitian matrix, thus we can extract the  $L(L+1)/2$  unique elements to form a  $(L(L+1)/2) \times K$  matrix on which we can perform a SVD truncated to the  $P$ 'th largest singular values and reform the  $L \times L$  matrix to get

$$\Omega_{kl_1} \Omega_{kl_2}^* \approx \sum_{p=0}^P C_{l_1 l_2, p} \Lambda_{kp}. \quad (12)$$

For each  $p$  we have a  $L \times L$  matrix, for which we can perform a decomposition into the rank  $R$  approximation as

$$C_{l_1 l_2, p} \approx \sum_{r=0}^R \hat{C}_{l_1 r p} \hat{C}_{l_2 r p}^*. \quad (13)$$

With  $R = 1$  in (12) this would correspond to a Canonical Polyadic Decomposition.

Inserting these approximations into the normal operator (11) we get

$$\exp(\Phi(\mathbf{r}_j, t_k) + \Phi^*(\mathbf{r}_i, t_k)) \approx \sum_{l_1=0}^L \sum_{l_2=0}^L \sum_{p=0}^P \sum_{r=0}^R \Lambda_{kp} \hat{C}_{l_1 r p} \hat{C}_{l_2 r p}^* \Upsilon_{jl_1} \Upsilon_{il_2}^* \quad (14)$$

$$= \sum_{p=0}^P \sum_{r=0}^R \Lambda_{kp} \left( \sum_{l_1=0}^L \hat{C}_{l_1 r p} \Upsilon_{jl_1} \right) \left( \sum_{l_2=0}^L \hat{C}_{l_2 r p} \Upsilon_{il_2} \right)^* \quad (15)$$

$$= \sum_{p=0}^P \sum_{r=0}^R \Lambda_{kp} \Theta_{jrp} \Theta_{irp}^* \quad (16)$$

Now, to find the approximations, performing the randomized SVD and SVD in these steps is computationally expensive, therefore, one can approach this with a histogram based method. First of all, the off-resonance and off-linear gradient terms only have effects on the signal on the support of the image. Thus, we do these approximations first only on voxels that are within the support. Next we can consider the feature vector

$$\bar{\Psi}(\mathbf{r}) = \begin{bmatrix} \mathbf{z}(\mathbf{r}) = \Delta B_0(\mathbf{r}) + 1/T_2(\mathbf{r}) \\ R_0^0(\mathbf{r}) \\ R_1^0(\mathbf{r}) \\ R_1^{-1}(\mathbf{r}) \\ \vdots \end{bmatrix} \quad (17)$$

Now, we can make a histogram of the feature vectors for all voxels in the support, and perform the approximations on the histogram bins instead of on the individual voxels.