



UVLO SIZED FOR 36V TO ACCOMMODATE BATTERY VOLTAGE CHANGES, 2V HYSTERESIS ON BOOT
 VIN HAS LPF WITH R4 AND C13, CUTOFF ~87kHz TO ELIMINATE SWITCHING FREQ
 VCCDIS HAS INTERNAL PULLDOWN TO ENABLE INTERNAL LDO/EXTERNAL 12V ONCE STABLE
 COMP-FB CIRCUIT IS USED TO ENSURE BUCK RESPONDS TO DC CHANGES IN OUTPUT, DOESN'T OVERCORRECT TO TRANSIENTS
 CM (CURRENT MONITOR) HAS LPF TO CUTOFF SWITCHING NOISE
 RES & SS DETERMINE HICCUP PERIOD & RISE TIME

DEMB- WHEN LOW, EFFICIENCY BETTER, BUT WORSE TRANSIENT RESPONSE (SWITCHING FREQ. VARIES)
 VCC DRIVES FET GATES, DIODE SO NO CURRENT FLOWS INTO VOUT
 HO/LO HAS DAMPING RESISTORS TO CREATE RLC DUE TO HIGH SWITCHING
 CS (CURRENT SENSE) MEASURES WHEN LO SIDE IS ON, TRIPS AT 16.4A (7.3mOhms Req)
 RAMP PIN USED TO EMULATE L CURRENT USING VOLTAGE ON EITHER SIDE OF L

FB = 0.8V @12V

