

# Electrical BUS Literature Review

## Overview of the Electrical BUS Subsystem

The Electrical BUS subsystem's goal is to provide the CubeSat with a centralized point of control, which at a high level will involve observing indicators and driving actuators. More specifically, Electrical BUS will interact with the PAYload, RF, and EPS subsystems to manage the state of affairs on the CubeSat. Operations of the electrical subsystem may include directing the PAYload subsystem to send data to the RF subsystem for down-linking, and acquiring uplink data from RF to perform a reboot.

## Document Revisions

| Version | Date      | Author | Description               |
|---------|-----------|--------|---------------------------|
| 0.1     | July 2026 | Boris  | Initial                   |
| 0.2     | July 2026 | Boris  | Protection considerations |

## Literature Review Methodology

Hello

As it pertains to the design, the main components that make up the electrical subsystem essentially boil down to three categories: control unit (that is, device(s) responsible for carrying out generic operations of the electrical subsystem, for example an MCU), protocol (that is, an interface for connecting two or more devices and allowing them to share data in one way or another, for example I2C), and peripherals (that is, device(s) responsible for a particular function within the Electrical BUS subsystem, for example a watchdog). This classification is not a recognized one, but has been found to be useful when conducting this literature review since the overwhelming majority of the designs can be deconstructed into components each of which would fit into one of these categories [subjective].

In terms of sources, two major categories are surveyed:

- Commercial OBCs discussed in NASA's Small-Sat State of the Art reports from 2022 to 2026 ([1, pp. 215–226], [2, pp. 225–237], [3, pp. 227–239], [4, pp. 241–253]), with trends also observed.
- OBCs built by academic design teams around Canada and beyond (considered designs listed in Appendix A)

## Design Space

This section outlines the resulting design space for the Electrical BUS Subsystem based on the corresponding literature review. We establish a space of common control units, protocols and peripherals for our internal design process.

## Control Units

The control-unit design space ranges from low-power microcontrollers to heterogeneous processor-FPGA systems. NASA's State of the Art reports show that most conventional CubeSat OBCs use microcontrollers or embedded microprocessors because command execution, telemetry collection, timekeeping, fault management, and subsystem coordination do not require high computational performance [1, 2, 3, 4]. Higher-performance FPGAs, application processors, and system-on-chip devices are generally introduced when the OBC must also support image processing, autonomy, high-rate payload data, or machine-learning workloads.

**Table 1: Candidate OBC control-unit architectures**

| Architecture                | Characteristics                                                                                                                                                                                                                   | NASA SOA Examples                                                                                                                                                                                                                              | Academic Examples                                                                               |
|-----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------|
| Single MCU or processor     | One device performs command execution, telemetry, timekeeping, fault management, and subsystem control. Lowest complexity and generally lowest power.                                                                             | EnduroSat OBC, ARM Cortex-M7 [2, p. 229]; AAC Clyde Space Kryten-M3, Cortex-M3 [2, p. 228].                                                                                                                                                    | STM32L4 PC/104 OBC; Athena TMS570; ORCASat TMS570 [5, 6, 7].                                    |
| Multicore SoC               | Multiple cores share one device and memory system. Provides additional performance or lockstep capability, but does not remove the SoC as a single point of failure.                                                              | Argotec FERMI, dual-core LEON3FT [2, p. 229]; SPiN MA61C, dual-core GR712RC [3, p. 236]; Xiphos Q7S, dual-core Cortex-A9 [3, p. 238].                                                                                                          | Athena and ORCASat use lockstep-capable ARM safety microcontrollers [8, 9].                     |
| Dual redundant processors   | Two processor devices provide cold, warm, or active redundancy. One processor may take control following a fault in the primary device.                                                                                           | Andes OBC, two Cortex-M7 processors with full cold redundancy [4, p. 230]; Bradford Binary OBC, dual Cortex-R5 with internal cold redundancy [2, p. 229]; Bradford Stellar OBC, dual PolarFire SoCs with internal cold redundancy [4, p. 230]. | No directly equivalent two-device redundant architecture was identified in the academic survey. |
| Controller plus FPGA or DPU | A low-power controller performs critical spacecraft control while an FPGA or higher-performance processor handles payload data or acceleration. The secondary unit may be powered down when unused.                               | KP Labs Antelope, RM57 OBC plus Zynq UltraScale+ DPU [2, p. 230]; NOVI Gen 2, Vorago MCU plus Versal AI Edge SoC [4, p. 232].                                                                                                                  | NEUDOSE, primary AVR32 plus secondary Xilinx Zynq-7000 [10].                                    |
| FPGA-centric                | Control or processing is implemented using programmable logic and, optionally, a soft processor. Suitable for deterministic parallel interfaces and high-rate data paths, but more difficult to develop as a general-purpose OBC. | LASP Generic SmallSat FPGA Board, Kintex-7 [2, p. 230]; KP Labs Lion, Kintex UltraScale [2, p. 230].                                                                                                                                           | No FPGA-only primary OBC was identified in the academic survey.                                 |

**Table 1: Candidate OBC control-unit architectures (Continued)**

| Architecture            | Characteristics                                                                                                                                                                                        | NASA SOA Examples                                                                                                                                   | Academic Examples                                                         |
|-------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------|
| Distributed controllers | Subsystem-local processors control the EPS, ADCS, communications, or payload and exchange data with a coordinating OBC. This improves fault containment but increases network and software complexity. | NASA identifies federated, distributed, heterogeneous, and mixed-criticality avionics as viable SmallSat architectures [2, p. 225] [4, p. 221–222]. | Individual subsystem controllers used alongside the primary academic OBC. |

All architectures will be considered during preliminary design; however, the current baseline is a centralized microcontroller-based OBC with independent watchdog and reset circuitry. This approach is the most common among the academic systems surveyed and provides the lowest-risk balance of power, determinism, software complexity, and flight heritage. An FPGA or secondary processor may be added later if payload-processing requirements cannot be met by the primary MCU.

## Protocols and Interconnect

This section will summarize the survey of protocols across the NASA's SOAs as well as Canadian design teams' CubeSats in Table 2, as well as provide an overview of interconnect architectures in Table 3.

**Table 2: Protocol and electrical-interface design space**

| Protocol               | Representative Rate                                               | Survey Examples                                                                                                                        | Primary Considerations                                                                                                                                                              |
|------------------------|-------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| I <sup>2</sup> C       | 100 kbit/s–3.4 Mbit/s                                             | LORIS OBC [11]; identified as a common synchronous interface in all four NASA surveys [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 224]. | Low pin count and broad peripheral support; limited distance and bandwidth; shared-bus faults may block all devices.                                                                |
| SPI                    | Application-dependent; commonly 1–50+ Mbit/s                      | LORIS OBC [11]; NASA interface surveys [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 224].                                                | Deterministic and comparatively fast; requires separate chip-select signals and provides no standardized addressing or error handling.                                              |
| UART / RS-422 / RS-485 | Typically kbit/s to approximately 10 Mbit/s                       | LORIS uses UART [11]; differential serial interfaces are listed by NASA [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 224].               | Simple implementation. RS-422/485 provides greater noise immunity and cable length than logic-level UART; termination and driver control are required.                              |
| CAN / CAN FD           | 1 Mbit/s Classical CAN; commonly up to 8 Mbit/s CAN-FD data phase | STM32L4 PC/104 OBC [5]; CAN is listed as a common spacecraft fieldbus [1, p. 219] [2, p. 235] [3, p. 240] [4, pp. 224–225].            | Differential multidrop operation, arbitration, acknowledgements, and error confinement make it suitable for EPS, ADCS, RF, and housekeeping traffic. Payload throughput is limited. |
| USB 2.0                | Up to 480 Mbit/s                                                  | LORIS OBC [11].                                                                                                                        | High COTS compatibility and throughput, but host/device roles, connector retention, software complexity, and limited spacecraft-bus heritage must be considered.                    |

**Table 2: Protocol and electrical-interface design space (Continued)**

| Protocol               | Representative Rate                                          | Survey Examples                                                                                                                                       | Primary Considerations                                                                                                                                                      |
|------------------------|--------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Ethernet               | 100 Mbit/s–1 Gbit/s commonly                                 | Listed as a network interface in each NASA survey [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 224].                                                    | High throughput and broad software support; requires switching or routing and may require additional measures for deterministic real-time operation.                        |
| SpaceWire / SpaceFibre | SpaceWire: typically 10–400 Mbit/s; SpaceFibre: multi-Gbit/s | SpaceWire is listed in the 2022–2024 surveys [1, p. 219] [2, p. 235] [3, p. 240]; SpaceWire and SpaceFibre are included together in 2026 [4, p. 225]. | Space-qualified point-to-point networking with routing and fault-management support. Requires more specialized hardware and software than CAN or UART.                      |
| SerDes / MGT           | Gigabit-per-second class; XAUI provides 10 Gbit/s aggregate  | Identified by NASA as high-rate mission-data interfaces [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 225].                                              | Suitable for FPGA, payload, mass-memory, and radio data paths. Requires controlled-impedance routing, suitable connectors, reference clocks, and signal-integrity analysis. |
| GPIO / PWM / ADC / DAC | Application-dependent                                        | LORIS provides GPIO, PWM, and ADC [11]; discrete and analog interfaces are listed by NASA [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 225].            | Appropriate for enables, inhibits, deployment signals, and analog telemetry; creates dedicated wiring and provides little inherent fault detection.                         |
| JTAG / ISP / ICSP      | Not a mission-data interface                                 | Debug and programming interfaces are listed in the NASA surveys [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 225].                                      | Required for programming and board-level debugging; access should be isolated or protected during flight.                                                                   |

**Table 3: Candidate interconnect architectures**

| Architecture               | Connection Pattern                                                                                                                                                                                                                                                               | Advantages                                                             | Limitations                                                                                   |
|----------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------|
| Unified stack              | OBC, EPS, RF, ADCS, and payload share a PC/104-style stack-through connector carrying power and common buses. The STM32L4 academic OBC uses this format [5]. NASA discusses PC/104 and stackable mezzanines in [1, p. 210], [2, pp. 226–227], [3, pp. 229–230], and [4, p. 222]. | Compact, modular, and requires little harnessing.                      | Shared pinout constrains all boards; board order and connector bandwidth may become limiting. |
| Backplane                  | Subsystem cards plug into a shared CompactPCI or SpaceVPX backplane [1, p. 210] [2, p. 226] [3, p. 229] [4, p. 222].                                                                                                                                                             | Rigid mechanical support, modular replacement, and high-speed routing. | Higher mass, volume, connector cost, and chassis complexity.                                  |
| Centralized point-to-point | Each subsystem has a dedicated connection to the OBC; all commands and data pass through the OBC. NASA identifies direct point-to-point and centralized architectures in [1, p. 207] and [3, p. 226].                                                                            | Simple command authority and strong link-level isolation.              | High connector count; OBC becomes a bandwidth bottleneck and single point of failure.         |

**Table 3: Candidate interconnect architectures (Continued)**

| Architecture         | Connection Pattern                                                                                                                                                                                    | Advantages                                                                                   | Limitations                                                                                                                |
|----------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------|
| Shared peer network  | OBC, EPS, RF, ADCS, and payload controllers communicate as peers over CAN, Ethernet, or SpaceWire.                                                                                                    | Reduces wiring, allows direct subsystem communication, and supports distributed control.     | Requires addressing, arbitration, synchronization, and network-level fault management.                                     |
| Payload pass-through | The OBC controls the payload, while high-rate data travels directly between the payload, mass memory, FPGA, and RF subsystem.                                                                         | Avoids loading the housekeeping bus or copying all payload data through the primary MCU.     | Requires separate control and data paths, flow control, buffering, and an OBC mechanism to isolate or reset the data path. |
| Hybrid dual-plane    | A low-speed CAN or stack bus carries commands and housekeeping data, while dedicated Ethernet, SpaceWire, or SerDes links carry payload data. NASA describes this mixed topology in [4, pp. 222–223]. | Combines a robust housekeeping network with scalable payload throughput and fault isolation. | Requires two interface classes and clear ownership of commands, telemetry, and high-rate data.                             |

For the mission, the interconnect as well as the protocol bouquet selection will want to target higher throughput interfaces for RF and PAY subsystems, and thus will generally be dictated by them. In the spirit of a generic design, selecting a highest-speed interface is favoured, yet this might collide with the interconnect architecture selection since certain interfaces require specific connections that may not for example be routed through PC104 due to signal integrity requirements (e.g. SpaceFibre). The stack-up requirements and/or constraints might also be driven by Mechanical subsystem.

## Peripherals

This section reviews the common peripherals that are found OBCs surveyed by NASA's SOAs, as well as on OBCs designed by Canadian academic design teams, as summarized in Table 4. General considerations related to peripherals revolve around external vs internal peripherals since modern day SoCs contain many of the necessary peripherals on the same chip.

**Table 4: Common OBC peripheral classes**

| Peripheral Class                     | Examples                                                                                                                                                                                                                                                                                    | Primary Considerations                                                                                                                                                                                         |
|--------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Volatile working memory              | SRAM and DRAM are surveyed by NASA [1, p. 218] [2, p. 234] [3, p. 239] [4, p. 223]. LORIS uses 256 MB DDR3, RADSAT-SK uses external SDRAM, and ORCASat uses ECC-protected RAM [11, 12, 9].                                                                                                  | Internal memory reduces component count and PCB complexity; external memory provides greater capacity but introduces additional power, routing, timing, and radiation-mitigation requirements.                 |
| Non-volatile program and mass memory | NASA surveys Flash, MRAM, FRAM, NAND, and eMMC technologies. The C3S OBC uses MRAM with eMMC mass storage [2, p. 229] [3, p. 232] [4, p. 230]; the Andes OBC provides redundant MRAM and NAND [3, p. 232] [4, p. 230]. LORIS uses 4 GB eMMC, while Athena and ORCASat use Flash [11, 6, 7]. | Selection depends on capacity, write endurance, retention, access speed, boot reliability, and susceptibility to radiation-induced corruption. Redundant boot images and error detection should be considered. |

**Table 4: Common OBC peripheral classes (Continued)**

| Peripheral Class                           | Examples                                                                                                                                                                                                                                                                                                             | Primary Considerations                                                                                                                                                                                                        |
|--------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Watchdog, reset, and supervisor circuitry  | The C3S OBC uses a multi-level watchdog [2, p. 229] [3, p. 232] [4, p. 230]; the Aerospacelab OBC includes a radiation-hardened supervisor MCU and watchdog [3, p. 232] [4, p. 229]. NASA discusses watchdogs and power cycling as fault-mitigation mechanisms [1, p. 220] [2, p. 236] [3, p. 241] [4, pp. 220–222]. | An external watchdog is preferable for recovery from processor lock-up. Consider independent clocks, reset coverage, timeout configuration, communications watchdogs, and selective power cycling.                            |
| Timers and time-keeping                    | NASA identifies PLLs, capture/compare units, and time-processing units as common OBC peripherals [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 224]. Timers are integrated within the STM32L4, TMS570, and i.MX6DL devices used by the surveyed academic OBCs [5, 8, 9, 13].                                            | Used for scheduling, timestamping, watchdog servicing, and waveform generation. Clock drift, oscillator redundancy, synchronization, and operation during processor resets must be considered.                                |
| Analog and discrete I/O                    | NASA lists GPIO, ADC, and DAC peripherals in each avionics survey [1, p. 219] [2, p. 235] [3, p. 240] [4, pp. 224–225]. LORIS exposes GPIO, PWM, and ADC interfaces [11, 13].                                                                                                                                        | Used for analog telemetry, enables, inhibits, deployment signals, and simple sensors. Consider voltage compatibility, input protection, ADC accuracy, safe reset states, and whether signals require isolation or redundancy. |
| Debug and programming interfaces           | NASA lists JTAG, ISP, ICSP, BDM, BITP, and DB9 interfaces [1, p. 219] [2, p. 235] [3, p. 240] [4, p. 225].                                                                                                                                                                                                           | Required for programming, boundary scan, manufacturing tests, and debugging. Flight hardware should provide controlled physical access and prevent unintended entry into debug or programming modes.                          |
| Optional integrated navigation peripherals | The EnduroSat OBC is available with integrated GNSS [2, p. 229] [4, p. 230].                                                                                                                                                                                                                                         | Integration can reduce board count and harnessing, but may couple the OBC lifecycle to a specific receiver and complicate antenna placement, RF isolation, replacement, and independent fault recovery.                       |

[TODO: survey each class of peripherals in more detail]

## COTS (Commercial Off the Shelf) Design Alternatives

*Description: Determine what COTS solutions exist if we cannot produce a certain part of the subsystem in house. Find a COTS option for each in house design.*

*Will inform trades later on for COTS versus in house risks.*

This section outlines alternative off-the-shelf components that would in part or in full fulfil the operating requirements of the subsystem.

**TODO**

## System Architecture and Budgets

In this section we concern ourselves with the following considerations: power draw, physical dimensions, radiation tolerance, and weight for the purposes of the overall design and integration with other teams.

## Power draw

Based on the commercial onboard-computing systems surveyed in NASA's State of the Art reports [1, 2, 3, 4], OBC power consumption can be divided into three broad categories according to platform complexity and computational capability. The reports do not use a consistent average-power metric; reported values are variously identified as idle, static, typical, active-mode, full-load, or peak consumption. Consequently, Table 5 preserves the operating-state terminology used by the manufacturers.

The 2022 edition identifies representative onboard-computing products but does not tabulate their power consumption [1, Table 8-1, pp. 214–217]. Quantitative power values are therefore drawn primarily from the 2023, 2024, and 2026 editions [2, Table 8-1, pp. 228–233] [3, Table 8-1, pp. 230–236] [4, Table 8-4, pp. 229–234].

**Table 5: OBC power-consumption trends and reported operating states**

| Platform Complexity        | Reported Power Profile                                                                                                                                                                                 | Design Characteristics                                                                                                                                                                                                                                                                                                 | Example Designs                                                                                                                                                                                                                                                                                                                                                                                                 |
|----------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Low (Bare-Metal / Control) | <b>Minimum listed:</b> 0.05 W<br><b>Idle/steady:</b> approximately 0.2–0.5 W<br><b>Peak:</b> generally below 1 W                                                                                       | Simple command and data handling, housekeeping, telemetry, and fault management. These systems are normally based on low-power microcontrollers and execute bare-metal software or a small real-time operating system. Their power consumption is relatively insensitive to computational load.                        | Pumpkin PPM family: 0.05 W, operating state not specified [2, p. 231] [3, p. 235] [4, p. 233].<br>AAC Clyde Space Kryten-M3: 0.4 W [2, p. 228] [3, p. 230] [4, Table 8-4].<br>C3S Electronics OBC: 0.46 W in test mode [2, p. 229] [3, p. 232] [4, p. 230].<br>SkyLabs NANOobc-2: < 0.9 W idle and < 1 W peak [2, p. 232] [3, p. 236].                                                                          |
| Medium (Integrated OBC)    | <b>Idle:</b> approximately 0.2–1 W<br><b>Nominal/steady:</b> approximately 1–3 W<br><b>Peak:</b> approximately 1.5–5 W                                                                                 | Typical integrated CubeSat OBCs combining command and data handling, mass-memory management, communication interfaces, fault protection, and basic payload management. Power may vary with processor utilization, interface activity, and memory access.                                                               | SPiN MA61C CubeSat: 1–1.2 W [2, p. 232] [3, p. 236] [4, Table 8-4].<br>AAC Clyde Space Sirius OBC & TCM: 1.3 W [2, p. 228] [3, p. 230] [4, Table 8-4].<br>EnduroSat OBC I: 0.2 W idle and 1.5 W peak [2, p. 229] [3, Table 8-1] [4, p. 230].<br>Resilient Computing RadPC: 1.5 W [2, p. 232] [3, p. 236] [4, p. 233].<br>SatRev OBC: 2.8 W typical and 5 W peak [4, p. 233].                                    |
| High (Edge / AI / SoM)     | <b>Idle/static:</b> approximately 5–15 W<br><b>Typical/active:</b> approximately 6–10 W<br><b>Peak/full load:</b> commonly 10–20 W, with larger payload computers reaching substantially higher values | Heterogeneous systems-on-module and payload-processing computers supporting image processing, software-defined radio, autonomous navigation, data compression, and machine-learning inference. Power is strongly dependent on processor utilization, FPGA configuration, accelerator activity, and payload duty cycle. | Novo Space GPU002AF: 6–11 W in active mode [2, p. 231] [3, p. 235] [4, p. 233].<br>KP Labs Leopard DPU: 7 W static and up to 10 W during deep-learning inference [2, p. 230] [3, p. 234] [4, p. 231].<br>Aitech S-A1760: $\leq 5$ W idle, 8–10 W under a typical CUDA load, and < 20 W at full utilization [2, p. 228] [3, Table 8-1] [4, Table 8-4].<br>EnduroSat GPC: < 15 W idle and 130 W peak [4, p. 231]. |

Based on these results, a nominal power-design envelope of 1–10 W is adopted for the proposed OBC. This range encompasses conventional integrated CubeSat OBCs and moderate edge-processing workloads, while transient loads above 10 W are treated separately as peak operating conditions. The selected range is a project design boundary rather than the full commercial-hardware envelope, which extends from approximately 0.05 W for low-power microcontroller boards to 130 W peak for high-performance payload computers.

[TODO: peak loads and durations]

## Dimentions

## Weight

## Protections

Protecting the electrical compenets of the BUS electronics from the harsh space environment is of paramount concern to the design. This section details the consideraitons with respect to the design and how to achieve them

**Table 6: Protection considerations**

| Consideration                  | Description                                                                                                                                                                                                                                                                                                                                        | Example solutions                                                                                                                                                                                                                                                                            |
|--------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Mission radiation environment  | Radiation exposure depends on orbit, inclination, mission duration, shielding, and solar activity. Parts should be selected against a mission-specific radiation analysis with an appropriate design margin [1, pp. 219–220] [2, pp. 235–236] [3, pp. 240–241] [4, pp. 221–222].                                                                   | Model the expected environment using tools such as SPENVIS [14] or CREME-MC [15] and select components whose test conditions exceed the predicted exposure. Athena uses a TMS570 device characterized to approximately 30 krad, while ORCASat selected a device tested to 6 krad [16, 8, 9]. |
| Total ionizing dose (TID)      | TID represents cumulative ionizing-radiation exposure and can gradually alter device parameters or cause permanent failure. NASA notes that many COTS parts may tolerate only approximately 2–10 krad, although tolerance varies strongly with device and fabrication process [1, pp. 177–178] [2, pp. 191–193] [3, pp. 194–196] [4, pp. 191–192]. | Use components with tested TID ratings, such as the VORAGO VA41630 MCU or GR712RC processor, or apply shielding where COTS components cannot meet the required dose [17, 18].                                                                                                                |
| Displacement damage dose (DDD) | Displacement damage results from non-ionizing particle interactions and must be considered separately from TID, particularly for sensors, optoelectronics, and some semiconductor technologies [1, p. 219] [2, p. 235] [3, pp. 240–241] [4, p. 221].                                                                                               | Require component-specific proton or neutron characterization rather than assuming that a TID rating also covers displacement damage. Microchip publishes separate proton, TID, and SEE characterization for its radiation-tolerant FPGA families [19].                                      |
| Single-event upset (SEU)       | An SEU changes a memory or logic state without necessarily causing permanent damage. Protection is required for processor state, working memory, non-volatile memory, and FPGA configuration [1, pp. 219–220] [2, pp. 235–236] [3, pp. 240–241] [4, pp. 221–222].                                                                                  | Use ECC or EDAC, memory scrubbing, redundant boot images, software consistency checks, and configuration-immune programmable logic. The GR712RC provides memory EDAC, while the RTG4 FPGA uses SEU-immune flash configuration [18, 20].                                                      |
| Single-event latch-up (SEL)    | SEL may place a semiconductor device into a destructive high-current state. The affected circuit must be detected and disconnected before permanent damage occurs [1, pp. 219–220] [2, pp. 235–236] [3, pp. 240–241] [4, pp. 221–222].                                                                                                             | Select SEL-immune components where practical and place vulnerable loads behind current-limited, resettable power switches. The 3D PLUS 3DPM0168 LCL provides overcurrent detection, load disconnection, and controlled repowering [17, 21].                                                  |

**Table 6: Protection considerations (Continued)**

| Consideration                                | Description                                                                                                                                                                                                                                                                                                                            | Example solutions                                                                                                                                                                                                                                                                        |
|----------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| COTS versus radiation-hardened components    | COTS components generally provide higher performance, lower cost, and better availability, while radiation-hardened parts provide greater environmental assurance. Small spacecraft frequently use a hybrid approach [1, p. 219] [2, p. 235] [3, p. 240] [4, pp. 221–222].                                                             | Combine a COTS processor with radiation-tolerant supervisors, memories, programmable logic, or power-control circuitry. NEUDOSE uses a COTS AVR32 primary processor with a secondary Zynq-7000 system designed using both radiation-hardened and non-radiation-hardened components [10]. |
| Watchdog and fault recovery                  | Radiation-induced faults may leave the processor or communication interface unresponsive. Recovery mechanisms should remain operational even when the primary processor has failed [1, p. 220] [2, p. 236] [3, p. 241] [4, pp. 219–220,222].                                                                                           | Use an independent watchdog, reset supervisor, communication timeout, and individually switchable power domains. The GR712RC includes watchdog support, while external protection switches can independently cycle affected loads [18, 21].                                              |
| Memory protection                            | Processor memory, mass storage, boot images, and FPGA configuration can have different radiation responses and should be assessed independently. NASA identifies ECC, EDAC, scrubbing, and redundant storage as common mitigation methods [1, pp. 218–220] [2, pp. 234–236] [3, pp. 239–241] [4, pp. 221–224].                         | Use ECC-protected working memory, radiation-tolerant MRAM, redundant boot images, and TMR-protected non-volatile storage. Example devices include GR712RC EDAC-protected memory and radiation-tolerant MRAM and SPI NOR modules [18, 22, 23].                                            |
| Redundancy and voting                        | Redundancy may be applied at the logic, processor, memory, board, or subsystem level. It improves fault tolerance but increases power, mass, synchronization, and verification requirements [1, p. 220] [2, p. 236] [3, p. 241] [4, pp. 219–222].                                                                                      | Use lockstep processors, cold-redundant OBCs, triple-modular redundancy, or distributed backup controllers. Athena and ORCASat use lockstep-capable safety MCUs, while 3D PLUS offers TMR-protected SPI NOR memory [8, 9, 23].                                                           |
| Radiation-hardened-by-design (RHBD)          | RHBD improves radiation tolerance through hardened circuit cells, radiation-aware layout, specialized device structures, and selective hardening of vulnerable functions [4, p. 222].                                                                                                                                                  | Use RHBD devices such as VORAGO HARDSIL-based Cortex-M MCUs or Microchip RTG4 FPGAs with radiation-hardened registers and flash-based configuration [17, 20].                                                                                                                            |
| Structural and localized shielding           | The spacecraft structure provides some inherent shielding, but protection depends on material, thickness, component placement, and shielding in every direction. Local shielding may be more mass-efficient than increasing the thickness of the entire structure [1, pp. 176–179] [2, pp. 190–194] [3, pp. 193–196] [4, pp. 190–193]. | Place sensitive processors or memories within aluminium, titanium, graded-Z, or composite shields. Commercial localized shielding products, such as Plasteel, target high-performance COTS processors, cameras, and memories [24, 25].                                                   |
| Secondary-radiation effects                  | Increasing shield thickness does not always proportionally reduce dose. High-energy particles interacting with shielding may generate secondary particles, making material choice and layer ordering important [1, pp. 176–179] [3, pp. 193–196] [4, pp. 190–193].                                                                     | Evaluate shielding using particle-transport simulation rather than aluminium thickness alone. Graded-Z shielding combines materials with different atomic numbers to reduce secondary radiation [25].                                                                                    |
| Surface charging and electrostatic discharge | Surface charging and electrostatic discharge can damage or disrupt electrical systems. This is separate from TID and single-event-effect protection [1, p. 179] [2, p. 194] [3, pp. 196–197] [4, p. 193].                                                                                                                              | Use conductive bonding, controlled grounding paths, charge-dissipative coatings, and appropriate PCB surface treatments. The Shields-1 experiment included a charge-dissipation film together with radiation-shielding technologies [25].                                                |

## Conclusion

This report outlined the state-of-the-art OBC review from both internal design standpoint through the Design Space section as well as system integration standpoint through System Architecture section. Internal design is broken into selection of control unit, protocol set and interconnect topology, as well as peripheral array. Each of these components have a wide selection of components and designs which will need to be researched further and used as part of trades once requirements are established. Further research and collaboration with other subsystems is also required to guide the internal design decisions for this subsystem.

## Appendix A: Academic OBCs

| Name                        | Team                               | MCU                                             | Protocols                               | Standard | Notes                                                                                                                                                                                                                                                                | Ref      |
|-----------------------------|------------------------------------|-------------------------------------------------|-----------------------------------------|----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
| STM32L4 PC/104 academic OBC | VST104 thesis design               | STM32L4—ARM-based                               | CAN                                     | PC104    | pc 104 cubesat design.                                                                                                                                                                                                                                               | [5]      |
| Athena OBC                  | University of Alberta (Albertasat) | TI TMS570LC4357 (ARM Cortex R5F)                |                                         |          | Embedded memory type: Flash. Features ideal for satellite OBC application, including radiation & space reliability (rad-hard, SEL immune 48 MeV at 125°C, LAT 30krad), high computational performance (lockstep dual-core compare, 300MHz CPU clock, 1.66DMIPS/MHz). | [6, 8]   |
| Orcasat OBC                 | University of Victoria             | TI TMS570LS0714 (Dual ARM Cortex-R4F)           |                                         |          | Embedded memory type: Flash. Operates in lockstep, ECC integrated flash & RAM banks, radiation-tested up to 6 krad, 80MHz core clock.                                                                                                                                | [7, 9]   |
| LORIS OBC                   | Dalhousie University               | NXP i.MX6DL (Single-core ARM Cortex-A9)         | USB 2.0; SPI; I2C; PWM; UART; GPIO; ADC |          | Embedded memory type: Flash. Low profile, power efficient SoC SBC. 4GB eMMC flash storage, 256MB DDR3 RAM, 800MHz operational frequency, -40°C to 85°C temperature range.                                                                                            | [11, 13] |
| NEUDOSE OBC                 | McMaster University                | Primary: AVR32. Secondary: Xilinx Zynq-7000 SoC |                                         |          | Primary is COTS chosen for high TRL to reduce mission risk; secondary is designed for radiation tolerance using rad-hard and non-rad-hard components.                                                                                                                | [10]     |
| RADSAT-SK OBC               | University of Saskatchewan         | ARM926EJ-S                                      |                                         |          | Embedded memory type: SDRAM. Uses ISISpace satellite-subsystems libraries, contains MMU, designed to interface with external SDRAM.                                                                                                                                  | [12]     |

## References

- [1] NASA, “State of the Art of Small Spacecraft Technology (2022 Edition),” Tech. Rep. NASA/TP-20220014871, NASA Ames Research Center, Moffett Field, CA, May 2023. Available: <https://www.nasa.gov/wp-content/uploads/2023/05/2022-soa-full.pdf>.
- [2] NASA, “State of the Art of Small Spacecraft Technology (2023 Edition),” Tech. Rep. NASA/TP-20230014324, NASA Ames Research Center, Moffett Field, CA, March 2024. Available: <https://www.nasa.gov/wp-content/uploads/2024/03/soa-2023.pdf>.
- [3] NASA, “State of the Art of Small Spacecraft Technology (2024/25 Edition),” Tech. Rep. NASA/TP-20240014902, NASA Ames Research Center, Moffett Field, CA, February 2025. Available: <https://www.nasa.gov/wp-content/uploads/2025/02/soa-2024.pdf>.
- [4] NASA, “State of the Art of Small Spacecraft Technology (2026 Edition),” tech. rep., NASA Ames Research Center, Moffett Field, CA, May 2026. Available: <https://www.nasa.gov/wp-content/uploads/2026/05/soa-2026.pdf?emrc=12c9ca>.
- [5] F. Geib, “On-board computer for PC/104 format CubeSats.” Available: [https://www.researchgate.net/profile/Filip-Geib/publication/353125383\\_On-board\\_computer\\_for\\_PC104\\_format\\_CubeSats/links/60e85a70b8c0d5588ce61355/On-board-computer-for-PC104-format-CubeSats.pdf](https://www.researchgate.net/profile/Filip-Geib/publication/353125383_On-board_computer_for_PC104_format_CubeSats/links/60e85a70b8c0d5588ce61355/On-board-computer-for-PC104-format-CubeSats.pdf), 2021.
- [6] Albertasat (University of Alberta), “Athena OBC Team Site.” Available: <https://albertasat.ca/open-source-designs/athena/>, 2025.
- [7] University of Victoria, “Orcasat OBC Team Site.” Available: <https://www.orcasat.ca/design>, 2022.
- [8] Texas Instruments, “Hercules TMS570LC4357-SEP Space-Enhanced Plastic Microcontroller Datasheet.” Available: <https://www.ti.com/lit/ds/symlink/tms570lc4357-sep.pdf>, 2023.
- [9] Texas Instruments, “Hercules TMS570LS0714 Microcontroller Datasheet.” Available: <https://www.ti.com/lit/ds/symlink/tms570ls0714.pdf>, 2014.
- [10] McMaster University, “NEUDOSE OBC SmallSat Conference Publication.” Available: <https://digitalcommons.usu.edu/cgi/viewcontent.cgi?article=4664&context=smallsat>, SmallSat Conference, 2021.
- [11] Dalhousie University, “LORIS OBC Capstone Conference Publication.” Available: [https://cdn.dal.ca/content/dam/dalhousie/images/engineering/CapstoneConference/2020-projects/2020\\_ECED01\\_03.pdf](https://cdn.dal.ca/content/dam/dalhousie/images/engineering/CapstoneConference/2020-projects/2020_ECED01_03.pdf), Dalhousie Capstone Conference, 2020.
- [12] University of Saskatchewan, “RADSAT-SK OBC Software and Command Repository.” Available: <https://github.com/USST-RADSAT-SK/software-and-command/blob/alpha/radsat-sk/.cproject>, 2023.
- [13] NXP Semiconductors, “LORIS OBC i.MX6DL Product Page.” Available: <https://www.nxp.com/products/i.MX6DL>, 2025.
- [14] ESA / Royal Belgian Institute for Space Aeronomy, “SPENVIS – Space Environment Information System.” Available: <https://www.spENVIS.oma.be/intro.php>, 2024.
- [15] Vanderbilt University, Institute for Space and Defense Electronics, “CREME-MC – Cosmic Ray Effects on Micro-Electronics Monte Carlo.” Available: <https://creme.isde.vanderbilt.edu>, 2024.
- [16] Texas Instruments, “TMS570LC4357-SEP Space-Enhanced Plastic Microcontroller Product Page.” Available: <https://www.ti.com/product/TMS570LC4357-SEP>, 2023.
- [17] VORAGO Technologies, “VA41630 Radiation Hardened ARM Cortex-M4 MCU Datasheet.” Available: <https://www.voragotech.com/products/va41630>, 2022.
- [18] Cobham Gaisler, “GR712RC Dual-Core LEON3FT SPARC V8 Processor Datasheet.” Available: <https://www.gaisler.com/products/gr712rc>, 2021.
- [19] Microchip Technology, “Radiation-Tolerant FPGA and Memory Radiation Reports.” Available: <https://www.microchip.com/en-us/products/fpgas-and-plds/radiation-tolerant-fpgas>, 2023.
- [20] Microchip Technology, “RTG4 Radiation-Tolerant FPGAs Datasheet.” Available: <https://www.microchip.com/en-us/product/RTG4>, 2022.

- [21] 3D PLUS, "3DPM0168 Latch-Up Current Limiter (LCL)." Available: <https://www.3d-plus.com/products/space-radiation-tolerant-latch-up-current-limiter-lcl-protection/>, 2024.
- [22] 3D PLUS, "Radiation Tolerant Magnetoresistive RAM (MRAM) Modules." Available: <https://www.3d-plus.com/products/space-radiation-tolerant-mram/>, 2023.
- [23] 3D PLUS, "Radiation Tolerant SPI NOR Flash Memory Modules." Available: <https://www.3d-plus.com/products/space-radiation-tolerant-nor-flash/>, 2023.
- [24] Cosmic Shielding Corporation, "Plasteel Radiation Shielding Solutions for Spacecraft Components." Available: <https://cosmicshielding.com/>, 2024.
- [25] NASA Langley Research Center, "Shields-1 SmallSat Radiation Shielding Technology Demonstration." Available: <https://ntrs.nasa.gov/api/citations/20160006374/downloads/20160006374.pdf>, 2021.