[1]This command mimmics the button in the Cuety interface. It can be short-pressed for Go+ and long-pressed for Release. It expects a 1 first, and then 0. The time between these commands determine wheter it is a long-press or a short-press.

A.2.1 OSC Feedback

The following commands are used for feedback. For more information about feedback send by the LPU-2, see A.5 "Receiving API Feedback"

Description	URI	Parameter Type	Parameter Range
Playback intensity	/pb<playback index>/in	float	0.0 → 1.0
Playback speed	/pb<playback index>/sp	float	0.0 → 1.0
Playback button	/pb<playback index>/bu	bool	false / true
Playback active	/pb<playback index>/ac	bool	false / true
Hello API	/hello	-	-
Blackout	/blackout	bool	false / true

A.3 TCP & UDP

TCP (Transmission Control Protocol) is a protocol for sending messages across an Ethernet network. TCP provides reliable, ordered and error-checked delivery of messages between programs running on computers connected to a local area network, intranet or the public Internet.

UDP (User Datagram Protocol) is a simple protocol for sending message across the network. It does not provide any error checking. Although UDP is a bit faster than TCP, it is less secure.

Typically either TCP or UDP is supported by various media devices like video projectors and show controllers. The LPU-2 uses port 7000 for receiving the TCP and UDP messages.

The functionality within the LPU-2 can controlled by using the following ASCII strings (human readable text) messages:

Description	String	Parameter	Range	Example
Set playback intensity	pb<playback index>/in	int	0 → 100	pb01/in=55
Get playback intensity	pb<playback index>/in	-	-	pb00/in
Increment playback intensity	pb<playback index>/in=++	int	-100 → 100	pb01/in=++10
Decrement playback intensity	pb<playback index>/in=- -	int	-100 → 100	pb01/in=–10
Set playback speed	pb<playback index>/sp	int	-100 → 100	pb33/sp=-20
Get playback speed	pb<playback index>/sp	-	-	pb00/sp
Increment playback speed	pb<playback index>/sp=++	int	-100 → 100	pb33/sp=++10
Decrement playback speed	pb<playback index>/sp=- -	int	-100 → 100	pb33/sp=–10
Control playback button[1]	pb<playback index>/bu	int	0 / 1	pb59/bu=1
Control playback flash	pb<playback index>/fl	int	0 / 1	pb64/fl
Get active cue	pb<playback index>/cue	-	-	pb01/cue
Release playback	pb<playback index>/re	-	-	pb10/re
Playback go forward	pb<playback index>/go+	-	-	pb21/go+
Playback go back	pb<playback index>/go-	-	-	pb21/go-
Playback jump	pb<playback index>/ju	int	1 → 48	pb45/ju=17
Set all intensity	pbxx/int	float	0.0 → 1.0	pbxx/int=0.5
Get all intensity	pbxx/int	-	-	pbxx/int
Set all speed	pbxx/spd	float	-1.0 → 1.0	pbxx/spd=0.5
Get all speed	pbxx/spd	-	-	pbxx/spd
Get all active Cues	pbxx/cue	-	-	pbxx/cue
Get all playback status	pbxx/ac	-	-	pbxx/ac
Release all playbacks	release	-	-	release
Hello API	hello	-	-	hello
Set blackout	blackout	int	0 / 1	blackout=1

[1]This command mimmics the button in the Cuety interface. It can be short-pressed for Go+ and long-pressed for Release. It expects a =1 first, and then =0. The time between these commands determine wheter it is a long-press or a short-press.

A.3.1 UDP & TCP Feedback

The following commands are used for feedback. For more information about feedback send by the LPU-2, see A.5 "Receiving API Feedback"

Description	String	Parameter	Range	Example
Playback intensity	pb<playback index>/in	int	0 → 100	pb01/in=100
Playback speed	pb<playback index>/sp	int	0 → 100	pb01/sp=10
Playback button	pb<playback index>/bu	int	0 → 1	pb01/bu=1
Playback active	pb<playback index>/ac	int	0 → 1	pb01/ac=1
Playback cue	pb<playback index>/cue	int	0 → 48	pb01/cue=32
All intensity	pbxx/all/intensity	float Array	0.0 → 1.0	pbxx/all/intensity=[0.25,0.75,0...
All playback speed	pbxx/all/speed	float Array	0.0 → 1.0	pbxx/all/speed=[0.00,0.80,0.40...
All playback active	pbxx/all/ac	int Array	0 / 1	pbxx/all/ac=[1,1,0,1,0,0,0,0...
All active Cues	pbxx/all/cue	int Array	0 → 48	pbxx/all/cue=[1,-,4,-,-,-,1,1...
Hello API	hello	-	-	hello
Blackout	blackout	int	0 / 1	blackout=0

A.4 HTTP

HTTP (Hyper Text Transfer Protocol) is the standard protocol to access web pages. It can also be used to control the LPU-2, using the URLs listed below. You can send your HTTP GET requests to port 80.

Description	URL	Range	Example
Set playback intensity	/ajax/pb<playback index>/int=	0.0 → 1.0	http://192.168.1.10/ajax/pb01/int=0.55
Get playback intensity	/ajax/pb<playback index>/int	-	http://192.168.1.10/ajax/pb01/int
Increment playback intensity	/ajax/pb<playback index>/int=++	0.0 → 1.0	http://192.168.1.10/ajax/pb01/int=++0.05
Decrement playback intensity	/ajax/pb<playback index>/int=- -	0.0 → 1.0	http://192.168.1.10/ajax/pb01/int=–0.05
Set playback speed	/ajax/pb<playback index>/spd=	-1.0 → 1.0	http://192.168.1.10/ajax/pb33/sp=-0.20
Get playback speed	/ajax/pb<playback index>/spd	-	http://192.168.1.10/ajax/pb33/sp
Increment playback speed	/ajax/pb<playback index>/spd=++	0.0 → 1.0	http://192.168.1.10/ajax/pb33/spd=++0.1
Decrement playback speed	/ajax/pb<playback index>/spd=- -	0.0 → 1.0	http://192.168.1.10/ajax/pb33/spd=–0.1
Control playback button[1]	/ajax/pb<playback index>/btn=	-	http://192.168.1.10/ajax/pb59/btn=0
Control playback flash	/ajax/pb<playback index>/fla=	-	http://192.168.1.10/ajax/pb64/fla=1
Release playback	/ajax/pb<playback index>/rel	-	http://192.168.1.10/ajax/pb10/rel
Playback go forward	/ajax/pb<playback index>/go+	-	http://192.168.1.10/ajax/pb21/go+
Playback go back	/ajax/pb<playback index>/go-	-	http://192.168.1.10/ajax/pb21/go-
Playback jump	/ajax/pb<playback index>/jmp=	1 → 48	http://192.168.1.10/ajax/pb45/jmp=17
Set all playback intensity	/ajax/pbxx/int=	0.0 → 1.0	http://192.168.1.10/ajax/pbxx/int=0.6
Get all playback intensity	/ajax/pbxx/int	-	http://192.168.1.10/ajax/pbxx/int
Set all playback speed	/ajax/pbxx/spd=	0.0 → 1.0	http://192.168.1.10/ajax/pbxx/spd=0.2
Get all playback speed	/ajax/pbxx/spd	-	http://192.168.1.10/ajax/pbxx/spd
Get all active cues	/ajax/pbxx/cue	-	http://192.168.1.10/ajax/pbxx/cue
Get all active playback status	/ajax/pbxx/ac	-	http://192.168.1.10/ajax/pbxx/ac
Release all playbacks	/ajax/pbxx/rel	-	http://192.168.1.10/ajax/pbxx/rel
Hello API	/ajax/hello	-	http://192.168.1.10/ajax/hello
Blackout	/ajax/blackout=	0 / 1	http://192.168.1.10/ajax/blackout=1

[1]This command mimmics the button in the Cuety interface. It can be short-pressed for Go+ and long-pressed for Release. It expects a =1 first, and then =0. The time between these commands determine wheter it is a long-press or a short-press.

A.5 Receiving API Feedback

The LPU-2 is capable of sending messages back to the external control system when communicating via OSC or UDP. As soon as the LPU-2 receives a command via OSC or UDP it will store the IP and port of the external system in a list. When a status changes inside the LPU-2 (e.g. a playback gets released) then all 'clients' in this list will receive a message indicating the new status. The LPU-2 can store a maximum of four OSC clients plus four UDP clients. This internal client list will be cleared by a power-cycle.

The 'hello' command can be used to poll the LPU-2. The LPU-2 will respond to a incoming Hello by sending a Hello message back to the client.

Clients can also get the current levels of certain properties. Some properties (e.g. playback intensity) can be polled by sending the command message without a parameter. For example, the following UDP command will get the speed level of playback 9: `pb09/spd` The LPU-2 will now reply with `pb09/spd=-0.5` indicating the speed level is at -50%.