

```
// RF Receiver Code

// For this project, use RadioHead (RH) library

// Link for RadioHead zip: https://www.airspayce.com/mikem/arduino/RadioHead/

// Used a video to help for this tutorial by DroneBot Workshop

// Video link: https://www.youtube.com/watch?v=b5C9SPVlU4U&t=780s
```

```
/*
```

```
    PLUG RECEIVER INTO PIN 11 ON BOARD
```

```
*/
```

```
// Have RH Amplitude Shift Keying (ASK)
```

```
#include <RH_ASK.h>
```

```
// Include dependent Serial Peripheral Interface (SPI) Library
```

```
#include <SPI.h>
```

```
// Create RH ASK Object
```

```
RH_ASK receiver;
```

```
void setup()
```

```
{
```

```
    // Setup Serial Monitor
```

```
    Serial.begin(9600);
```

```
    // Initialize ASK Object
```

```
    receiver.init();
```

```

/*
// DEBUGGING
if (!receiver.init())
    Serial.println("Initialization Failed!");

if (receiver.init())
    Serial.println("Initialization Successful!");
*/
}

void loop()
{
    // Tell board how many characters it will receive
    uint8_t coords[12];
    uint8_t length = sizeof(coords);

    // Check to see if received packet is correct size
    if (receiver.recv(coords, &length))
    {
        // Print the reception of coords
        Serial.print("Coords Received: ");

        // Print received characters
        for (int i = 0; i < 12; i++)
        {

```

```
Serial.print((char)coords[i]);
```

```
}
```

```
Serial.println("");
```

```
}
```

```
}
```