

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2011_h (Multi-segment position function parameters)	31 _h	2CC _h	Paragraph 11 displacement acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	32 _h	2CD _h	Waiting time after completion of paragraph 11 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	33 _h	2CE _h	Paragraph 12 mobile displacement	int32	-2147483648~2147483647	RW	NO	-1073741824	user unit	Suspension in effect
	34 _h	2D0 _h	Segment 12 Displacement Maximum Run tempo	uint16	0~3000	RW	NO	1	rpm	Suspension in effect
	35 _h	2D1 _h	Paragraph 12 displacement acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	36 _h	2D2 _h	Waiting time after completion of paragraph 12 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	37 _h	2D3 _h	Paragraph 13 mobile displacement	int32	-2147483648~2147483647	RW	NO	-1073741824	user unit	Suspension in effect
	38 _h	2D5 _h	Maximum operating speed for paragraph 13 displacements	uint16	0~3000	RW	NO	1	rpm	Suspension in effect
	39 _h	2D6 _h	Paragraph 13	uint16	0~65535	RW	NO	0	ms	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2011_h (Multi-segment position function parameters)			displacement acceleration and deceleration times							in effect
	3A _h	2D7 _h	Waiting time after completion of paragraph 13 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	3B _h	2D8 _h	Paragraph 14 mobile displacements	int32	-2147483648~2147483647	RW	NO	-1073741824	user unit	Suspension in effect
	3C _h	2DA _h	Maximum operating speed for paragraph 14 displacements	uint16	0~3000	RW	NO	1	rpm	Suspension in effect
	3D _h	2DB _h	Paragraph 14 displacement acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	3E _h	2DC _h	Waiting time after completion of paragraph 14 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	3F _h	2DD _h	Paragraph 15 movement displacement	int32	-2147483648~2147483647	RW	NO	-1073741824	user unit	Suspension in effect
	40 _h	2DF _h	Maximum operating speed for paragraph 15 displacements	uint16	0~3000	RW	NO	1	rpm	Suspension in effect
	41 _h	2E0 _h	Paragraph 15 displacement plus deceleration time	uint16	0~65535	RW	NO	0	ms	Suspension in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
	42 _h	2E1 _h	Waiting time after completion of paragraph 15 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	43 _h	2E2 _h	Paragraph 16 mobile displacements	int32	-2147483648~2147483647	RW	NO	-1073741824	user unit	Suspension in effect
	44 _h	2E4 _h	Maximum operating speed for paragraph 16 displacements	uint16	0~3000	RW	NO	1	rpm	Suspension in effect
	45 _h	2E5 _h	Paragraph 16 displacement acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	46 _h	2E6 _h	Waiting time after completion of paragraph 16 displacement	uint16	0~65535	RW	NO	0	ms	Suspension in effect
2012_h (Multi-Speed Function Parameters)	01 _h	2E9 _h	Multi-speed command operation mode	uint16	0~2	RW	NO	0	1	Suspension in effect
		Specific description: see section 5.17.4 for details								
	02 _h	2EA _h	Speed command end segment selection	uint16	0~16	RW	NO	1	1	Suspension in effect
	03 _h	2EB _h	Number of multispeed cycles	uint16	0~65535	RW	NO	0	1	Suspension in effect
	0C _h	2F4 _h	1st speed command	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	0D _h	2F5 _h	Running time of the 1st instruction	uint16	0~65535	RW	NO	0	ms	Suspension in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2012_h (Multi-Speed Function Parameters)	0E _h	2F6 _h	Acceleration and deceleration time for paragraph 1	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	0F _h	2F7 _h	Paragraph 2 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	10 _h	2F8 _h	Running time of the 2nd instruction	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	11 _h	2F9 _h	Paragraph 2 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	12 _h	2FA _h	Paragraph 3 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	13 _h	2FB _h	Running time of paragraph 3 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	14 _h	2FC _h	Paragraph 3 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	15 _h	2FD _h	Paragraph 4 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	16 _h	2FE _h	Running time of paragraph 4 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	17 _h	2FF _h	Paragraph 4 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	18 _h	300 _h	Paragraph 5 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2012_h (Multi-Speed Function Parameters)	19 _h	301 _h	Running time of paragraph 5 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	1A _h	302 _h	Paragraph 5 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	1B _h	303 _h	Paragraph 6 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	1C _h	304 _h	Running time of paragraph 6 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	1D _h	305 _h	Paragraph 6 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	1E _h	306 _h	Paragraph 7 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	1F _h	307 _h	Running time of paragraph 7 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	20 _h	308 _h	Paragraph 7 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	21 _h	309 _h	Paragraph 8 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	22 _h	30A _h	Running time of paragraph 8 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	23 _h	30B _h	Paragraph 8 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2012_h (Multi-Speed Function Parameters)	24 _h	30C _h	Paragraph 9 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	25 _h	30D _h	Running time of paragraph 9 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	26 _h	30E _h	Paragraph 9 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	27 _h	30F _h	Paragraph 10 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	28 _h	310 _h	Running time of paragraph 10 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	29 _h	311 _h	Paragraph 10 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	2A _h	312 _h	Paragraph 11 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	2B _h	313 _h	Running time of paragraph 11 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	2C _h	314 _h	Paragraph 11 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	2D _h	315 _h	Paragraph 12 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	2E _h	316 _h	Running time of	uint16	0~65535	RW	NO	0	ms	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2012_h (Multi-Speed Function Parameters)			paragraph 12 instructions							in effect
	2F _h	317 _h	Paragraph 12 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	30 _h	318 _h	Paragraph 13 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	31 _h	319 _h	Running time of paragraph 13 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	32 _h	31A _h	Paragraph 13 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	33 _h	31B _h	Paragraph 14 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	34 _h	31C _h	Running time of paragraph 14 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	35 _h	31D _h	Paragraph 14 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	36 _h	31E _h	Paragraph 15 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	37 _h	31F _h	Running time of paragraph 15 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2012_h (Multi-Speed Function Parameters)	38 _h	320 _h	Paragraph 15 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	39 _h	321 _h	Paragraph 16 instructions	int16	0~3000	RW	NO	-6000	rpm	Suspension in effect
	3A _h	322 _h	Running time of paragraph 16 instructions	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	3B _h	323 _h	Paragraph 16 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
	3B _h	323 _h	Paragraph 16 acceleration and deceleration times	uint16	0~65535	RW	NO	0	ms	Suspension in effect
2017_h (virtual input terminal parameters)	01 _h	326 _h	VDI1 terminal function selection	uint16	0~44	RW	NO	0	1	Suspension in effect
			Specific description: see section 6.1 for details							
	02 _h	327 _h	VDI1 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
			Specific description: see section 6.1 for details							
	03 _h	328 _h	VDI2 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	04 _h	329 _h	VDI2 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	05 _h	32A _h	VDI3 terminal function	uint16	0~39	RW	NO	0	1	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2017_h (virtual input terminal parameters)			selection							in effect
	06 _h	32B _h	VDI3 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	07 _h	32C _h	VDI4 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	08 _h	32D _h	VDI4 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	09 _h	32E _h	VDI5 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	0A _h	32F _h	VDI5 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	0B _h	330 _h	VDI6 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	0C _h	331 _h	VDI6 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	0D _h	332 _h	VDI7 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	0E _h	333 _h	VDI7 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	0F _h	334 _h	VDI8 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	10 _h	335 _h	VDI8 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	11 _h	336 _h	VDI9 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	12 _h	337 _h	VDI9 terminal logic	uint16	0~1	RW	NO	0	1	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
2017_h (virtual input terminal parameters)			selection							in effect
	13 _h	338 _h	VDI10 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	14 _h	339 _h	VDI10 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	15 _h	33A _h	VDI11 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	16 _h	33B _h	VDI11 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	17 _h	33C _h	VDI12 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	18 _h	33D _h	VDI12 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	19 _h	33E _h	VDI13 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	1A _h	33F _h	VDI13 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	1B _h	340 _h	VDI14 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	1C _h	341 _h	VDI14 Terminal Logic Selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	1D _h	342 _h	VDI15 terminal function selection	uint16	0~39	RW	NO	0	1	Suspension in effect
	1E _h	343 _h	VDI15 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
	1F _h	344 _h	VDI16 terminal function	uint16	0~39	RW	NO	0	1	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
			selection							in effect
	20 _h	345 _h	VDI16 terminal logic selection	uint16	0~1	RW	NO	0	1	Suspension in effect
2031_h (communication given relevant variables)	01 _h	373 _h	Communication Given VDI Virtual Levels	uint16	0~65535	RW	NO	0	1	Suspension in effect
			Specific description: 2031 _h : 01 _h bit(n)=1 means VDI(n+1) is high; bit(n)=0 means VDI(n+1) is low							
	02 _h	374 _h	Communication given Do output state	uint16	0~65535	RW	NO	0	1	Suspension in effect
			2004 _h When the logic selection of is negative, 2031 _h : 02 _h =1,Do outputs low level; 2031 _h : 02 _h =0,Do outputs high level							

10.3 Sub-Protocol Definition Parameter 6000h Group Description

Table 10- 7

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
603F_h	00 _h	37F _h	Error code, see section 8.1 for details	uint16	0~65535	RO	TPDO	0	-	-
6040_h	00 _h	380 _h	control letter	uint16	0~65535	RW	RPDO	0	1	Suspensi on in effect
6041_h	00 _h	381 _h	status word	uint16	0~65535	RO	TPDO	0	1	-
6042_h	00 _h	382 _h	Target speed for VM mode	int16	-3000~3000	RW	RPDO	0	1rpm	Suspensi on in effect
6043_h	00 _h	383 _h	Target speed for VM mode to take effect	int16	-3000~3000	RO	TPDO	0	1rpm	-
6044_h	00 _h	384 _h	Actual speed in VM mode	int16	-2147483648~2147483647	RO	TPDO	0	1rpm	-
6046_h	01 _h	385 _h	Minimum speed for VM mode	uint32	0~6000	RW	RPDO	10	1rpm	Suspensi on in effect
	02 _h	387 _h	Maximum speed for VM mode	uint32	0~6000	RW	RPDO	3000	1rpm	Suspensi on in effect
6048_h	01 _h	389 _h	Acceleration in VM	uint32	0~4294967295	RW	RPDO	500	1rpm	Suspensi

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
			mode = delta speed/delta time							on in effect
	02 _h	38B _h		uint16	1~65535	RW	RPDO	1	1s	Suspensi on in effect
6049 _h	01 _h	38C _h	Deceleration of VM mode = delta speed/delta time	uint32	0~4294967295	RW	RPDO	500	1rpm	Suspensi on in effect
	02 _h	38E _h		uint16	1~65535	RW	RPDO	1	1s	Suspensi on in effect
604A _h	01 _h	38F _h	Emergency stop speed in VM mode = delta speed/delta time	uint32	0~4294967295	RW	RPDO	800	1rpm	Suspensi on in effect
	02 _h	391 _h		uint16	1~65535	RW	RPDO	1	1s	Suspensi on in effect
604C _h	01 _h	394 _h	Scaling factor for VM mode	int32	-2147483648~2147 483647	RW	RPDO	0	1	Suspensi on in effect
	02 _h	396 _h		int32	-2147483648~2147 483647	RW	RPDO	0	1	Suspensi on in effect
605A _h	00 _h	3BF _h	Quick stop mode selection, see	int16	0~2	RW	NO	2	1	Suspensi on in

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
			section 3.1.4 for details							effect
605Bh	00	3BDh	Shutdown mode selection, see section 3.1.4 for details	int16	0~1	RW	NO	0	1	Suspensi on in effect
605Ch	00	3BEh	Disablement operation shutdown mode selection, see section 3.1.4 for details	int16	0~1	RW	NO	0	1	Suspensi on in effect
605Dh	00 _h	3C0 _h	Pause mode selection, see section 3.1.4 for details	int16	1~2	RW	NO	1	1	Suspensi on in effect
605Eh	00 _h	3C1 _h	Failure shutdown mode selection, see section 3.1.4 for details	int16	0~2	RW	NO	0	1	Suspensi on in effect
6060_h	00 _h	3C2 _h	Mode selection, see section 5.1 for details	int8	0~10	RW	RPDO	1	1	Suspensi on in effect
6061_h	00 _h	3C3 _h	Operating mode display, see section 5.2 for details	int8	0~10	RO	TPDO	1	1	-

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
6062 _h	00 _h	3C4 _h	Target position command value currently in effect within the drive	int32	-2147483648~2147483647	RO	TPDO	0	user unit	-
6063 _h	00 _h	3C6 _h	Feedback on the current absolute position of the motor	int32	-2147483648~2147483647	RO	TPDO	0	Encoder Unit	-
6064 _h	00 _h	3C8 _h	Feedback on the current absolute user position of the motor	int32	-2147483648~2147483647	RO	TPDO	0	user unit	-
Specific description: Position feedback 6064 _h × Gear ratio (6091 _h) = Position feedback 6063 _h										
6065 _h	00 _h	3CA _h	Positional deviation oversize threshold	uint32	0~4294967295	RW	RPDO	50	user unit	Suspension in effect
Specific description: When the position deviation exceeds ±6065 _h and the time reaches 6066 _h , a tracking error is reported.										
6066 _h	00 _h	3CC _h	Excessive position deviation timeout	uint16	0~65535	RW	RPDO	30000	1ms	Suspension in effect
Specific description: When the position deviation exceeds ±6065 _h and the time reaches 6066 _h , a tracking error is reported.										
6067 _h	00 _h	3CD _h	Position reaches threshold	uint32	0~4294967295	RW	RPDO	10	user unit	Suspension in effect
Specific description: Position deviation within ±6067 _h and time up to 6068 _h is considered as position arrival, bit10=1 of										

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
			status word 6041 _h in position class mode							
6068 _h	00 _h	3CF _h	position arrival time window	uint16	0~65535	RW	RPDO	5	1ms	Suspensi on in effect
			Specific description: the position is considered to be reached when the position deviation is within $\pm 6067_h$ and the time reaches 6068 _h . In position class mode, bit10=1 in status word 6041 _h							
6069 _h	00 _h	3D0 _h	Feedback value of the speed sensor	int32	-2147483648~2147483647	RO	TPDO	0	User unit/s	-
606B _h	00 _h	3D3 _h	Speed command value validated within the controller	int32	-2147483648~2147483647	RO	RPDO	0	User unit/s	-
606C _h	00 _h	3D5 _h	Current actual speed feedback value	int32	-2147483648~2147483647	RO	TPDO	0	rpm	-
606D _h	00 _h	3D7 _h	Velocity reaches threshold	uint16	0~65535	RW	RPDO	500	rpm	Suspensi on in effect
			Specific description: the difference between the target speed 60FF _h (converted to motor speed rpm) and the actual motor speed is within $\pm 606D$, and when the time reaches 606E _h , it is considered that the speed is reached, and bit10=1 of the status word 6041 _h							
606E _h	00 _h	3D8 _h	Velocity Arrival Time Window	uint16	0~65535	RW	RPDO	5	ms	Suspensi on in effect
			Specific description: the difference between the target speed 60FF _h (converted to motor speed rpm) and the actual motor speed is within $\pm 606D$, and when the time reaches 606E _h , it is considered that the speed is reached, and bit10=1 of the status word 6041 _h							

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
606F _h	00 _h	3D9 _h	Zero reaches threshold	uint16	0~65535	RW	RPDO	5	User unit/s	Suspensi on in effect
			Specific description: the current speed 6069 _h is within $\pm 606F$, and the time reaches 6070 _h , it is considered that the zero speed arrives, the status word 6041 _h bit12=1							
6070 _h	00 _h	3DA _h	zero degree arrival time window	uint16	0~65535	RW	RPDO	5	ms	Suspensi on in effect
			Specific description: the current speed 6069 _h is within $\pm 606F$, and the time reaches 6070 _h , it is considered that the zero speed arrives, the status word 6041 _h bit12=1							
6071 _h	00 _h	3DB _h	Target torque	int16	-1000~1000	RW	RPDO	0	0.10%	Suspensi on in effect
			Specific description: 100.0% corresponds to 1 times the rated torque of the motor.							
6072 _h	00 _h	3DC _h	Maximum torque	uint16	0~2000	RW	RPDO	1000	0.10%	Suspensi on in effect
6073 _h	00 _h	3DD _h	Maximum current	uint16	0~2000	RW	NO	1500	0.10%	Suspensi on in effect
6074 _h	00 _h	3DE _h	Torque command, reflecting the torque command entered in the enable state.	int16	-32768~32767	RO	TPDO	0	0.10%	-
6075 _h	00 _h	3DF _h	rated current	uint32	0~11700	RW	RPDO	11700	0.001A	Suspensi

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
										on in effect
6076 _h	00 _h	3E1 _h	Rated torque	uint32	0~1270	RW	RPDO	1270	0.01N.m	Suspensi on in effect
6077 _h	00 _h	3E3 _h	Torque feedback value	int16	-32768~32767	RO	TPDO	-	0.10%	-
6078 _h	00 _h	3E4 _h	Current feedback value (percentage corresponding to rated current)	int16	-32768~32767	RO	TPDO	-	0.10%	-
607A _h	00 _h	3E7 _h	target location	int32	-2147483648~2147483647	RW	RPDO	0	user unit	Suspensi on in effect
607C _h	00 _h	3ED _h	origin offset value	int32	-2147483648~2147483647	RW	RPDO	0	user unit	Suspensi on in effect
			Specific description: Set the physical position of the mechanical zero point deviation from the motor home position in the home return mode; effective when bit15=1 of status word 6041 _h when home return operation is completed							
607D _h	01 _h	3EF _h	Software absolute position minimum limit	int32	-2147483648~2147483647	RW	RPDO	-65535	user unit	Suspensi on in effect
	02 _h	3F1 _h	Maximum software absolute position limit	int32	-2147483648~2147483647	RW	RPDO	65535	user unit	Suspensi on in effect

Index	Sub-index	Name	Description	Data type	Data range	Access-ability	Mapp-ability	Factory setting	Unit	Activate method
607E _h	00 _h	3F3 _h	Command polarity, see section 4.3 for details	uint8	0~255	RW	NO	0	1	Suspension in effect
607F _h	00 _h	3F4 _h	Maximum profile speed	uint32	0~1000000	RW	RPDO	500000	User unit/s	Suspension in effect
6080 _h	00 _h	3F6	Maximum motor speed	uint32	0~6000	RW	RPDO	4000	rpm	Suspension in effect
6081 _h	00 _h	3F8 _h	Profile speed	uint32	0~1000000	RW	RPDO	500000	User unit/s	Suspension in effect
			Specific description: Set the uniform running speed of the segment displacement command in contour position mode, which is calculated as follows: motor speed (rpm) = $\frac{6081h \times \text{齿轮比} \times 6091h}{\text{编码器分辨率}} \times 60$							
6082 _h	00 _h	3FA _h	Contour End Velocity	uint32	0~1000000	RW	RPDO	0	User unit/s	Suspension in effect
6083 _h	00 _h	3FC _h	contour acceleration	uint32	0~4294967295	RW	RPDO	409600	User unit/s ²	Suspension in effect
6084 _h	00 _h	3FE _h	contour deceleration	uint32	0~4294967295	RW	RPDO	409600	User unit/s ²	Suspension in effect
6085 _h	00 _h	400 _h	Quick stop	uint32	0~4294967295	RW	RPDO	500000	User	Suspension

Index	Sub-index	Name	Description	Data type	Data range	Access- ibility	Mapp- ability	Factory setting	Unit	Activate method
			deceleration						unit/s ²	on in effect
6086 _h	00 _h	402 _h	Contour Slope Type	int16	0~3	RW	RPDO	3	1	Suspensi on in effect
			Specific description: Sets the type of curve for motor position commands or speed commands. 0~ Linear, 3~ S-curve							
6087 _h	00 _h	403 _h	Torque Ramp	uint32	0~4294967295	RW	RPDO	10	0.10%	Suspensi on in effect
			Specific description: Setting the torque command acceleration in profile torque mode, the meaning of which is: torque command increment per second							
6088 _h	00 _h	405 _h	Torque Ramp Type	int16	0~2	RW	RPDO	0	1	Suspensi on in effect
			Specific descriptions: 0~ slopes, 2~ no slopes							
608F _h	01 _h	406 _h	Encoder increment	uint32	0~4294967295	RW	NO	10000	1	Suspensi on in effect
	02 _h	408 _h	Motor RPM	uint32	0~4294967295	RW	NO	1	1	Suspensi on in effect
6091 _h	01 _h	40E _h	gear ratio	uint32	0~4294967295	RW	NO	1	1	Suspensi on in effect
	02 _h	410 _h		uint32	0~4294967295	RW	NO	1	1	Suspensi