(180)

Coding & Decoding:

Vector India Pvt. Ltd.

↳ By Sunil Gupta Yarramalla

↳ Purpose of coding & decoding is to convey the information securely.

↳ Mainly it's used in defence system.

↳ Generally 'while sending the conveyed information it is coded & send to the receiver, there it's decoded' Means both sender & receiver must know the logic behind the coding.

↳ To Use coding & decoding while conveying the information, we must know different types of codings with Alphabet & their positions in all the ways.

↳ Actual Positions of Alphabet:-

→ First to remember all alphabet positions you must remember the 'EJOTY', here all the letters in this word are multiples of 5 positions in alphabet.

'E	J	O	T	Y'
↓	↓	↓	↓	↓
5	10	15	20	25
5X1	5X2	5X3	5X4	5X5

→ We know first 4 alphabet positions 1000 & last 3 alphabets positions too...

A	B	C	D	----	X	Y	Z
1	2	3	4		24	25	26

(18)

↳ Till now we got 11 alphabet positions
[ETOTY(5) + ABCD(4) + X43(3) − Y(1) = 12−1 = 11]

↳ Still we need to know all positions b/w 'F−W'.
Total (26) − known (11) = 15 we have to know.

↳ F → Fix → Six.

G → 7 (or) 7/G Brindavan colony

H → H → 8

I → looks 9

K → K → 2 st lines = '11'.

	1	2	3		12	13
1st half	A	B	C	.....	L	M
2nd half	N	O	P	.....	Y	Z
	14	15	16		25	26

L → (el) → Pronouncing like '12'
↳ Last but one letter in 1st half (13−1 = 12)

M → Last letter in first half = 13
↳ 1st 3 (M looks like 3)

N → Nov 14 / 1st (N) / 1st letter in 2nd half = 14

P → పడవరేఖ్ వరుసు (16)
↳ Water image of 'p' is 6 & with '6' we have total 3 possibilities. 6(F), 26(Z) the remaining one is 16 → which is P.

Q → 7 → with 7 we have 2 possibilities 7−G,
17 → which is 'Q'.

R → B → 8 → with 8 we have 2 possibilities 8−H,
18 → which is 'R'.

S → S → 9 → with 9 we have 2 possibilities 9−I.
So, 19 is 'S'. [ends with 9].

(182)

U → 2nd half 'Unique (1)' → 21.

→ 2|1 → 21.

U for unique means '1' & Ps in 2nd half 2nd 1.

V → 2nd half V (2 st lines) → 22.

W → 2nd half looks like 3 = 23.

E → 5×1, J → 5×2, O → 5×3, T → 5×4, Y → 5×5.

→ T-20

↳ Reverse Positions of alphabet:-

1	2	3	- - - - - - - - -	24	25	26	→ Actual Posns
A	B	C		X	Y	Z	
26	25	24		3	2	1	→ Reverse Posns.

From the above mapping diagram, we can consider a logic to all alphabet as.

[Actual Posn + Reverse Posn] of any alphabet = 27.

then, Reverse Posn of alphabet = 27 - Actual posn of alphabet.

Ex- Reverse posn of Q?

A.P of Q = 17 ⇒ R.P = 27 - A.P = 27 - 17 = 10th

↳ Pairing letters :- Pairing letters nothing but 1st half of letters are coded as second half of letters.

1	2	3	- - - - - - - - - - - - - -	11	12
A	B	C		L	M.
↓	↓	↓		↓	↓
N	O	P	- - - - - - - - - - - - - -	Y	Z
14	15	16.		25	26

Pairing letters of C → P.