

Vibe-IC — ALL Steps, by Stage, in Order (v2.2.0)

Plugin 0.2.6. ONE list. Every step of the flow, grouped by stage, in execution order, with a single continuous number (1 → 38). Two parallel tracks (Analog, Mixed-signal) are listed after the main flow. Source of truth = the runners.

The runner's internal implementation markers (Phase 1 [1/15] ... [15/15] + 19 sub-steps; Phase 2/3 `def step_*`) are a finer-grained code view, auto-generated in **FLOW_STEPS_GENERATED.md** by `flow_doc_emit.py`. They map onto the stages below; this doc is the single human-facing ordered list.

Stage map: **0** Spec/Docs (Phase 1) • **1** RTL+Verify • **2** Synthesis+DFT • **3** Physical+Sign-off (Phase 3) • **4** Output+Tapeout. (Phases: Phase 1 = Stage 0; Phase 2 ≈ Stage 1-2; Phase 3 ≈ Stage 3-4.)

Stage 0 — Spec & Documents (Phase 1)

#	Step	Tool / How
1	Ingest & text extraction (prompt or vendor docs → <code>input_doc/</code>)	<code>phase1_doc_one_shot_runner</code> ([1/15])
2	Generate L1–L13 core design-layer docs	deterministic extractors ([2/15] – [14/15])
3	Generate L14–L23 protocol / timing / skeleton docs	[14b/15] – [14d/15] overlays
4	Protocol-class synthesis dispatch (81 classes)	[14e/15] – [14e3/15] (<code>is_<proto> + <proto>_synth</code>)
5	Coverage / parity report	[15/15]

Stage 1 — RTL Generation & Verification (Phase 2, front)

#	Step	Tool / How
6	Spec-to-RTL (author RTL from L-docs)	<code>spec-to-rtl</code> skill (runner WAIVES <code>step_rtl_gen</code> for <code>rtl_gen=null</code> classes)
7	Lint	<code>eda_lint</code> + hygiene gates
8	CDC / RDC check	<code>cdc-check</code>
9	Simulation	<code>testbench-gen</code> + <code>eda_simulate</code> + coverage
10	Formal verification	<code>formal-verify</code> + <code>assertion-gen</code> (informational waiver if no model)
11	FPGA early prototype	<code>eda_fpga_compile</code> / <code>eda_fpga_program</code> + on-board BIST → <code>.sof</code>

Stage 2 — Synthesis & DFT (Phase 2, back)

#	Step	Tool / How
12	Constraint setup	<code>constraint-gen</code> → <code>*.sdc</code> + 3-corner PVT
13	SDC validation	SDC lint
14	Synthesis (Yosys)	<code>eda_synth</code> + <code>synth-doctor</code> (+ tie-cell pass)
15	Pre-layout STA	<code>eda_sta_mcorner</code> (SS/TT/FF)
16	DFT insertion (scan + ATPG)	<code>dft-insert</code> + <code>atpg</code> + <code>eda_dft</code>
17	Post-DFT optimization	<code>resynth</code> / buffering

#	Step	Tool / How
18	Equivalence check (LEC)	equivalence-check + Yosys equiv

Stage 3 — Physical Design & Sign-off (Phase 3)

#	Step	Tool / How	Open-source status
19	Floorplan + PDN	eda_pnr (init)	✓
20	Clock planning	clock-planning skill	✓
21	Placement (global + detailed)	eda_pnr	✓
22	CTS	eda_pnr enable_cts=true	✓
23	Post-CTS hold fixing	repair_timing -hold	✓
24	Routing (global + detailed)	eda_pnr enable_detailed_route=true	✓
25	Parasitic extraction → SPEF	OpenRCX extract_parasitics - ext_model_file rules.openrcx.sky130A.nom.ma gic	✓ FIXED v0.2.5 (real 268 KB SPEF)
26	Post-route STA (MMMC)	eda_sta_mcorner	✓
27	IR drop	OpenROAD PSM analyze_power_grid	✓ FIXED v0.2.4
28	EM check	PSM -enable_em	✓ FIXED v0.2.4
29	Antenna check	OpenROAD check_antennas	✓ FIXED v0.2.4
30	Signal integrity (crosstalk)	SPEF coupling-cap screen (Cc/ (Cc+Cg))	✓ WIRED v0.2.6 (advisory)
31	Post-layout gate-level sim (+SDF)	eda_simulate	✓
32	Physical verification (DRC / LVS / ERC + PERC-equiv)	KLayout DRC + LVS sign-off chain (below) + Magic ERC + perc_equivalent aggregate	✓ DRC/LVS/ERC ; PERC-equiv (~70% auto)
33	ECO repair loop	eco-plan	✓

Step 32 — LVS sign-off chain (under `step_lvs`): (1) structural LEC `eda_lvs yosys_equiv` → (2) device-level `eda_extraction` + `netgen` → (3) powered-netlist `write_verilog -include_pwr_gnd` → (4) port labels `magic_port_extract_emit` (Route A) / `lvs_def_port_seed` (Route B) → (5) **mandatory** `lvs_signoff_guard` (RAISES on a portless/vacuous match).

Step 32 — PERC-equivalent coverage (`perc_equivalent.{rpt,json}` + `PERC_SIGNOFF_MEMO.md`, v0.2.7-2.8): open-source stand-in for commercial Calibre PERC. AUTOMATED: antenna / IR / EM / floating-nets (verdicts read from steps 27-30/ERC). GUARDBAND: EM current-density ($<0.5 \text{ mA}/\mu\text{m}$) + $\geq 2 \times 2$ vias. MANUAL_REVIEW (never auto-PASS, pending checklist): latch-up spacing/device-physics, cross-voltage-domain — auto-N/A for core-only macros / single-supply designs. **Latch-up well-tap presence** (v0.2.10) is now AUTOMATED: a routed DEF with 0 valid well/substrate-tap cells is a conclusive `WELLTAP_GAP FAIL` → `PERC_EQUIV_FAIL` (catches the real v0.1.45-class tapcell-skip silicon bug; the real spm/subservient/neorv32 routed DEFs all ship 0 taps). Only tap presence is automated — tap spacing + the device-physics latch-up criterion ($V_{\text{hold}} > V_{\text{dd}}$, SCR β -product, guard-ring efficacy) stay MANUAL (an adversarial panel showed DEF-only spatial density/max-distance over-claims). The **ESD presence** check (v0.2.8) recognises sky130 IO integral-clamp pads (`gpiov2/hvc/lvc/clamped/esd`) — validated on the real Caravel `chip_io.def` (flips a 612-filler ring from a false `ESD_MISSING` to `PRESENT`, structural fillers excluded) with negation guards (`unc_lamped ≠ ESD`) + `esd-before-structural` ordering (`gpiov2_corner_pad=ESD`), and reports `esd_presence: PRESENT | MISSING | N/A`. The **ESD discharge-path topology** check (v0.2.9, a NEW AUTOMATED category) automates the connectivity half of ESD sign-off from DEF COMPONENTS + NETS: domain-loop completeness (a supply clamp with no matching ground-return clamp = open loop), clamp stitching (each clamp tied to BOTH a power and a ground net), and rated-cell membership. A `TOPOLOGY_GAP` is a conclusive automated `FAIL` → `PERC_EQUIV_FAIL`; `TOPOLOGY_OK` is necessary-but-not-sufficient. **This shrinks the ESD MANUAL_REVIEW residual to**

exactly the device-physics half — clamp HBM/CDM sizing (TLP/It2), inherited from the rated library-cell datasheet (an adversarial panel confirmed connectivity can never prove sizing, so the presence category stays MANUAL). Validated on the real Caravel `chip_io.def`: 63 ESD-pad instances, all 3 domain loops closed, 0 dangling, 0 unrated → TOPOLOGY_OK.

Stage 4 — Output & Tapeout (Phase 3, close)

#	Step	Tool / How	Open-source status
34	Power analysis	pre + post layout	✓
35	Metal fill (density fill)	OpenROAD <code>filler_placement</code> → <code>filled.def</code>	✓ FIXED v0.2.4
36	Tapeout checklist	<code>tapeout-checklist</code> + <code>signoff_audit</code> (4/4 strict)	✓
37	GDSII output	<code>eda_gds</code> + <code>def2gds</code> (only if step 32 clean)	✓
38	FPGA final sign-off	recompile + on-board test + attestation	✓

Parallel track — Analog A1–A8 (`analog_one_shot_runner.py`, runs alongside Stages 1-3)

#	Step	Output
A1	<code>spec_extract</code>	<code>analog/<block>/A1_spec.json</code>
A2	<code>topology_select</code>	<code>A2_topology.json</code>
A3	<code>netlist_gen</code>	<code><block>.sp</code>
A4	<code>corner_sweep</code>	<code>A4_corners.json</code>
A5	layout (Magic)	<code>A5_layout.json</code> (DRC-clean + LVS-match)
A6	<code>post_layout_resim</code>	<code>A6_postsim.json</code>
A7	<code>hardmacro_gen</code>	<code>{.lef,.lib,.gds,.v}</code> → feeds Stage 3
A8	<code>hw_verify</code> (HIL)	<code>A8_hw_verify.json</code>

Parallel track — Mixed-signal M1–M4 (`skill mixed-signal-cosim`, no dedicated runner)

#	Step
M1	top merge (<code>mixed_signal_m1_top_merge_check.py</code>)
M2	co-sim setup
M3	co-sim run
M4	integration verify

Totals

38 sequential steps (Stage 0: 1-5 • Stage 1: 6-11 • Stage 2: 12-18 • Stage 3: 19-33 • Stage 4: 34-38) + **8 Analog (A1-A8)** + **4 Mixed-signal (M1-M4)**, both parallel.

Pre-flight: P0 (`mcp_server_health_check`, `eda_doctor`). Orchestrator: `vibe_ic_one_shot_runner.py` runs Phase 1 → Phase 2 → Analog → Phase 3.

This is a **derived** list. The runner's live implementation markers are auto-generated in `FLOW_STEPS_GENERATED.md` (`flow_doc_emit.py --check` fails CI on drift). 繁体版見 `ALL_STEPS_v2.2.0.zh-TW.md`.