SONY

C-38B

Condenser Microphone



Overview

Condenser Microphone

The Sony C-38B is an all-purpose, large diaphragm microphone with a proven track record of reliability in broadcast production, music recording studios, or wherever circumstances demand a combination of powerful performance, versatile operation and simplicity of microphone set up. Ideal for vocal and instrument recording, this microphone is particularly adept at handling loud instruments such as percussion and wind instruments. The condenser element of the C-38B microphone provides dual switchable, omni-directional and uni-directional polar patterns, providing control over the pick up angle for flexibility in any recording senario. A low cut filter switch helps eliminate low frequency noise, and an 8 dB pad switch maximizes gain and reduces distortion noise. With its established performance record, the C-38B microphone continues to be the reliable, affordable choice of recording engineers around the world.

Highlights

- Switchable Polar Pattern (Omni and Uni Directional)
- Broad Dynamic Range
- Low Cut Filter and Pad Switch
- FET Output Stage

Features

Switchable Polar Patterns
The C-38B microphone features switchable omni-directional and uni-directional polar patterns for maximum flexibility and control over pick up angle

Function Select Switch
Just below the directivity switch, a function select switch allows quick adjustment of the C-38B microphone through 5 positions: OFF, M (full range response); M1 (slight low frequency attenuation); V1 (low frequency attenuation); V2 (severe low frequency attenuation)

Broad Dynamic Range
An improved amplifier gives the C-38B a dynamic range of greater than 116 dB, with flat frequency response and sharp directional characteristics in both uni-directional and omni-directional modes

Phantom Power System
In addition to internal battery power, the C-38B microphone is compatible for use with standardized 48V phantom powering

Low-Cut Filter
The C-38B microphone's low-cut filter switch helps eliminate low-frequency noise and proximity effect

Pad Switch
An -8dB pad switch on the C-38B microphone provides added headroom and minimizes distortion caused by transient peaks

FET Output Stage
The FET output stage of the C-38B microphone delivers high signal gain and low noise floor for superb sound quality

Vibration Resistant Construction
Designed for peak performance, the C-38B microphone's classic, vibration resistant construction provides excellent shielding against external magnetic fields and helps prevent distortion

Specifications

General Specifications

Capsule Type	Condenser
Frequency Response	30 Hz - 18 kHz
Directivity	Uni-directional/Omni-directional
Sensitivity	-48.0dB ±2.0dB
Dynamic Range	116dB or more
S/N Ratio	70dB or more
Inherent Noise (0dB=20µPa)	24 dB SPL or less
Induction Noise from External Magnetic Field	5dB SPL or less
Wind Noise	44dB SPL or less
Max SPL (dB SPL)(0dB=20µP)	140dB SPL
Connector	XLR-3 12C type
Cable Length	19.7 feet
Power Requirements	Battery: 9V External Power:DC 24 to 48V
Dimensions	3 1/8 dia. x 8 1/2 x 1 13/16 inches (78 dia. x 214 x 46 mm)
Weight	1 lb 7 oz (without battery)

Supplied Accessories

Supplied Accessories	Carrying case (1) Stand adaptor (NS5/8) (1) Stand adaptor (W3/8) (1) Screwdriver (1) Operation manual (1)

Related products



C800GPAC

Studio Tube Condenser Microphone PAC



C-80

Uni-directional Condenser Microphone



C-800GPAC1

Studio Tube Condenser Microphone PAC

Gallery



© 2004 - 2026 Sony Corporation. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Features and specifications are subject to change without notice. The values for mass and dimension are approximate. All trademarks are the property of their respective owners.

Export PDF : October 15 2026