Full tree ›

SmartHome OS menu tree

13 optional apps, Settings, desktop controls, alerts and shared dialogs.

17 branches / 581 menu entries / 25 screensavers

SmartHome OS
Menu branches

01 / OS
Desktop & windows ›
Launcher, taskbar, title-bar controls and window placement.

02 / OS
Settings ›
Appearance, system diagnostics, client names and saved app data.

03 / OS
Alert inbox ›
Recent alert history and the separate acknowledgment popup.

04 / OS
Shared dialogs ›
Reusable picker and editor flows linked from their calling menus.

05 / AUTOMATION
Clock ›
World-time alarms, timers, a stopwatch and optional redstone signals.

06 / AUTOMATION
Coffee ›
Harvest countdown, player input, output routing and counters.

07 / AUTOMATION
Logic Sandbox ›
Build rules by choosing an IF condition and arranging the THEN actions.

08 / AUTOMATION
Switchboard ›
IO side presets, timed buttons, custom switch grids and scenes.

09 / ME & MACHINES
ME monitors ›
Saved grid and list views for live ME item counts.

10 / ME & MACHINES
ME storage ›
Storage dashboards, exact counters and optional drive surveys.

11 / ME & MACHINES
Reactors ›
Reactor sensor readings and separate redstone control per reactor.

12 / ME & MACHINES
Solar farm ›
Finished HV arrivals, panel equivalents and production-sorted farm stock.

13 / UTILITIES
IO Scope ›
Browse IO history and save traces for selected wires.

14 / UTILITIES
Net Scope ›
Live list of SmartHome radio packets seen and sent by the central OS.

15 / UTILITIES
Notes ›
Notes, interactive checklists and Markdown export.

16 / UTILITIES
Screensaver ›
Fullscreen animations with invisible corner controls and a saved rotation.

17 / UTILITIES
Window Presets ›
Capture, reassign and restore monitor window layouts.

Menus, submenus & paths

Select a heading for its branch or an entry for the corresponding detail.

SmartHome OS

01 / OS
Desktop & windows
- **Taskbar**
  - Start [+]
    - Settings
    - [App]
    - Alert inbox
  - [Window tab]
  - ‹ / ›
  - [Clock / alert badge]
- **Window title bar**
  - Minimize [-]
  - X Close
  - [Title area]
  - Layout [#]
    - 1×1
    - 2×1 / 1×2 / 2×2
      - [Position]
    - 3×1 / 1×3 / 3×2 / 2×3 / 3×3
      - [Position]
    - Restore
    - Fullscreen
      - [Top-right cell]
    - Resize
      - First corner
        - Other corner
    - **Move**
      - Pick position
    - Cancel
- **[Monitor-client calibration]**
  - [Measure nine points]
  - [Test preview]
    - Save / Reset / Cancel
    - Remeasure
  - [Retry screen]

02 / OS
Settings
- **Appearance**
  - Background
  - Window border / Borders
  - Taskbar
- **System overview**
  - Central computer
  - Clients
    - **[Client] / Client details**
      - Targets
        - [Sensor target]
    - Filter
  - Sensors
    - [Sensor client]
    - Filter
  - Outputs
    - [Mapped output]
  - Apps
  - Windows
  - Uptime history
  - Relay map
    - [Client route] / Observed path
      - Details
  - Overview options
    - Client filter
    - About
- **Client names**
  - [Client] / Client name
    - Rename
    - Reset
- **Screensavers**
  - [Design names in cycle order]
- **App data**
  - Backup & restore
    - Create backup
      - [Entire OS / OS settings / app]
        - Replace backup?
    - Restore backup
      - [Existing backup]
        - Restore data?
  - Reset data
    - Entire OS
      - Are you sure?
        - Are you really sure?
    - OS settings
      - Are you sure?
    - [App]
      - Are you sure?
  - Delete apps
    - [Installed app]
      - Delete app?
- **Close**

03 / OS
Alert inbox
- **Alert list**
  - [Alert] / Details
  - Back
- **[Active popup]**
  - OK

04 / OS
Shared dialogs
- **Redstone picker**
  - Select IO
    - Select side
      - Select wire
        - Use this input?
          - Use
        - Use this output?
          - Test
          - Use
- **Sensor picker**
  - Sensor client
    - Sensor side
      - Select target
        - Use sensor?
          - Use
- **OS color palette**
  - [Color swatch]
  - Back
- **Touch keyboard**
  - [QWERTY keys]
  - ABC / 123 / abc
  - Space / Sp and Del
  - Set / Save / Find
  - Clr / Back
- **Number pad**
  - [Digits / Clr / Del]
  - Set / Back
- **Decimal number pad**
  - [Digits / . / Del]
  - Set / Back

05 / AUTOMATION
Clock
- **Alarms**
  - + Add alarm
  - [Alarm] / Details
    - Enabled / Disabled
    - Dismiss / OK
    - Output / signal details
    - **Edit / Alarm settings**
      - Name
      - Time
      - Repeat
      - Enabled
      - Select output
      - Disconnect output
      - Select dismiss input
      - Clear dismiss input
      - Signal
      - Length
      - ON / OFF / Total
      - Save / Cancel
    - Delete
      - Delete alarm?
- **Timers**
  - + Add timer
  - [Timer] / Details
    - Pause / Resume / Restart
    - Cancel timer
    - Dismiss / OK
    - Output / signal details
    - **Edit / Timer settings**
      - Name
      - Time
      - Clock
      - Select output
      - Disconnect output
      - Select dismiss input
      - Clear dismiss input
      - Signal
      - Length
      - ON / OFF / Total
      - Start / Save / Cancel
    - Delete
      - Delete timer?
- **Stopwatch**
  - Start / Stop
  - Lap
  - Reset
  - Real / Game
- **Settings**
  - UI color
  - Timer history
  - **Clock status**
  - About / restart rules
- **Status**
- **[Alarm / timer popup]**

06 / AUTOMATION
Coffee
- **Pause / Resume**
- **Harvest now**
- **Menu**
  - Settings
    - Player input / Player IO
    - Harvest output / Harvest IO
    - Countdown
      - Step / - / +
      - Save (next) / Cancel
    - Harvest time
      - Step / - / +
      - Save (next) / Cancel
    - UI color
  - Stats / Harvest counts
    - Reset trip
  - Maintenance
    - Reset timer
      - Reset timer?
    - Import save
      - Import save?

07 / AUTOMATION
Logic Sandbox
- **+ New rule**
- **[Saved rule]**
  - IF / Choose condition
    - Redstone
    - Item count
    - Combine / Combine IF
      - All true / Any true / Exactly one
      - Invert
      - Hold true
    - Change / Change IF
  - THEN
    - + Add / Add action
      - Alarm
        - Name
      - Set redstone
      - Wait
    - [Action]
      - Order
  - Set up IF / Set up THEN
  - Turn on / Turn off
  - More
    - Rename
    - Wiring
    - Delete / Delete?
- **More**
  - New output
    - THEN
  - Wiring
- **Wiring**
  - + New circuit
  - [Circuit]
    - OFF - Enable / ON - Disable
    - **Setup tips**
      - [Tip]
        - Edit / Back
    - + Add / Add logic node
      - Redstone input / Input
      - Item amount
      - AND / OR / NOT / XOR
      - Delay
      - If / Then
      - Redstone output / Output
      - Wait / Set output / Alarm
      - Output target
    - **Flow / Circuit flow**
    - Menu
      - View flow
      - Enable circuit / Disable circuit
      - Check setup
      - Rename circuit
      - Delete circuit
        - Delete?
    - [Node]
      - **Select redstone**
      - Clear routing
      - **Set item count / Edit count**
        - ME / Select ME
        - Select item
          - Find / Find item
            - Search
            - Refresh
            - Manual item
              - Name / RawName
              - Damage
            - Use / Back
        - Compare / Compare count
          - Under (<) / Over (>) / Exactly (=)
        - Level
        - Save / Cancel
      - **A / B**
      - **From**
      - **Delay editor**
        - When
        - Wait
        - + Link output
      - **If / Then editor**
        - When
        - Then blocks
          - + Block / Then add block
            - + Wait / + Set output / + Alarm
            - [Existing block]
          - [Step]
            - Edit block
            - Move earlier / Move later
            - Remove step / Remove from rule?
      - **Action block editors**
        - Wait
        - Set output
          - Choose target / Target
            - + New target
          - Set ON / Set OFF
          - Select redstone / saved route
        - Alarm
          - Name
      - **Output target editor**
      - Popup ON / OFF
      - Rename node
      - Setup tip
      - Delete node
        - Delete?
- **[Node / Alarm block popup]**
- **Close**

08 / AUTOMATION
Switchboard
- **+ Add view / New view**
  - + Empty view
    - Empty view
      - Create / Cancel
  - [IO client]
    - Select side
      - [Available side]
        - 16 switches
          - Create
- **[View] / Switch grid**
  - [Routed tile]
  - [Unwired / invalid tile]
  - Edit / View settings
    - Rename view
    - Edit switches
      - **[Switch]**
        - Rename / Name
        - Color / Button color
          - [Swatch] / IO default / By state
          - Apply / Cancel
        - State colors / States
          - Active / Inactive / Pending
        - Routing / Route
          - Behavior / Mode
            - Switch
            - Button
              - Time
        - Disconnect
          - Disconnect?
    - State colors / View state colors
      - Active / Inactive / Pending
    - Grid size
      - Cols / Rows
      - Save grid
        - Remove cells?
    - All OFF
      - All OFF?
    - Move earlier / Move later
    - Delete view
      - Delete view?
- **Scenes**
  - [Scene]
  - + New scene / Capture scene
    - All views
    - [One view]
  - Edit
    - [Scene]
      - Rename
      - Delete
        - Delete scene?
- **Settings / App settings**
  - UI color
  - Background
  - Button borders
  - Unwired tiles
  - Active color
  - Inactive color
  - Pending color
  - Density
  - All switches OFF
    - All OFF?

09 / ME & MACHINES
ME monitors
- **+ Add view**
  - [AE sensor picker]
    - New view layout
      - List / Grid
      - Items / Cols / Rows
      - Create / Cancel
- **[View]**
  - [+ Item / Empty tile]
  - [Assigned tile] / Item monitor
    - **Item / Select item**
      - Name / Amount
      - A-Z / Z-A / Low-Hi / Hi-Low
      - Search / Find
      - Refresh / Sync
      - [Item]
    - Color
      - [Color swatch]
      - Apply / Auto / Back
    - Clear
  - Edit / View settings
    - Change rates / Rates
    - Rename view
    - Edit items / Choose a tile
      - [Tile]
    - Layout / size
      - List / Grid
      - Items / Cols / Rows
      - Save grid
        - Remove last tiles?
    - AE source
    - Source information
    - Delete view
      - Delete view?
- **Settings / Monitor settings**
  - UI color
  - Density
  - About

10 / ME & MACHINES
ME storage
- **+ Add system**
- **[ME system] / Dashboard**
  - **Cells / Cell / Drive inventories**
    - Cell / drive totals
    - + Add drive
    - [Drive] / Drive slots
      - [Cell slot]
      - Source
      - Remove
        - Remove drive?
  - Edit / System settings
    - Rename
    - Change AE sensor
    - Source / exact figures
    - Drive inventories
    - Remove system
      - Remove system?
- **Settings / ME settings**
  - UI color
  - About / setup

11 / ME & MACHINES
Reactors
- **+ Add reactor**
- **[Reactor card]**
  - Set IO
  - ON / OFF
  - [Card body] / Reactor details
    - Set IO / ON / OFF
    - Edit / Reactor settings
      - Rename
      - Sensor target
      - Control output
      - Raw readings / Sensor fields
      - Delete reactor
        - Delete reactor?
- **Settings / App settings**
  - UI color
  - Panel color
  - About readings

12 / ME & MACHINES
Solar farm
- **HV output**
- **[Item / Amount header]**
- **[Item row] / Item overview**
  - Pin item / Edit pin
    - Name
    - Stick
    - Item color
    - Drop minimum / Drop percent
    - Use default filter
    - Select HV item
    - Unpin item
- **Pin item / Pin overview item**
  - [Farm ME item]
  - [HV solar / main ME]
  - Find
- **Menu / Solar farm menu**
  - ME sources
    - Select farm ME
    - Select main ME (HV)
  - **HV panel type / detection**
    - [HV item]
    - Auto
    - **Find / Find item**
      - Search
      - Sort / Order
      - Refresh list
      - Register absent item / Absent item identity
        - Name / RawName
        - Damage
        - Use item
  - Graph/change
  - Rate unit
  - List sorting / Overview order
    - Production order
    - Item A-Z / Item Z-A
    - Amount high-low / Amount low-high
  - Reset rate learning / Restart learned rates
    - Main / HV only
      - Reset rate learning?
    - Farm only
      - Reset rate learning?
    - Both ME sources
      - Reset rate learning?
  - Withdrawal filter / Ignore big withdrawals
    - Minimum
    - Percent
  - UI color
  - Source status
  - About rates

13 / UTILITIES
IO Scope
- **Used by apps**
- **Client side**
  - [IO client]
    - [Side] / Wires
      - Outputs
      - Inputs
- **+ New view**
- **[Saved view] / Trace**
  - [Wire lane] / Wire details
    - Remove
  - ‹ Earlier / Later ›
  - Hold / Live
  - Menu / ...
    - Range
    - All views
    - Add output
    - Add input
    - Rename view
    - Delete view
      - Delete view?
    - Save as view
- **Close**

14 / UTILITIES
Net Scope
- **[Packet row]**
- **[Packet details]**
  - Type
  - Client
- **Hold / Live**
- **Menu / Net Scope menu**
  - Direction
  - Type
    - [Packet type]
  - Client
    - [Client]
  - Ignored/foreign
  - Render packets
  - Statistics
  - Clear capture
  - UI color
- **Close**

15 / UTILITIES
Notes
- **+ New note**
- **[Note]**
  - [Text line]
  - [Checkbox]
  - **[Line details]**
    - Edit
      - Delete?
  - + Add / Add to note
    - Text line
    - Checkbox
  - Menu / Note menu
    - Edit lines / Done editing
    - Rename note
    - Export Markdown
    - Delete note
      - Delete?
- **Close**

16 / UTILITIES
Screensaver
- **[Top-left 2×2 area]**
- **[Top-right 2×2 area]**
- **[Any other touch]**
- **Design rotation**
  - 01 Matrix Rain
  - 02 Matrix Wall
  - 03 Plasma
  - 04 Ripple Pools
  - 05 Rainbow Tiles
  - 06 Silk Waves
  - 07 Kaleidoscope
  - 08 Life Garden
  - 09 Nyan Cat
  - 10 Starflight
  - 11 Northern Lights
  - 12 Lava Lamp
  - 13 Neon Tunnel
  - 14 Fireworks
  - 15 Spiral Ribbons
  - 16 Prism Tide
  - 17 Candy Confetti
  - 18 Sunset Surf
  - 19 Pixel Quilt
  - 20 Orbit Parade
  - 21 DVD Bounce
  - 22 Pac-Man Chase
  - 23 Tetris Rain
  - 24 Rainbow Road
  - 25 Among Us Drift

17 / UTILITIES
Window Presets
- **+ Save layout**
  - This monitor
  - All online monitors
- **[Preset] / Preview**
  - [Monitor slot] / Monitor preview
    - Assign / Assign monitor
      - Original
      - Skip this slot
      - [Online monitor]
  - Rename preset
  - Delete preset
    - Delete preset?
  - Apply
    - Replace layouts?
      - Apply / Cancel
- **Close**

Desktop & windows

Launcher, taskbar, title-bar controls and window placement.

Monitor desktop 33 ENTRIES

- **Taskbar**
  - Start [+]
    Lists Settings and compatible enabled apps alphabetically. A star marks a running app. Roomy menus use taller entries.
    - Settings · Opens the built-in Settings window.
    - [App] · Opens the app or focuses its existing window on this monitor.
    - Alert inbox · Launcher entry on monitors without the clock shortcut.
  - [Window tab] · Focus, minimize the focused window, or restore a minimized one.
  - ‹ / › · Scroll through the window tabs when they overflow.
  - [Clock / alert badge] · Opens or closes the Alert inbox where the clock fits.
- **Window title bar**
  - Minimize [-] · Restore from the taskbar.
  - X Close · Closes the window on this monitor.
  - [Title area] · Starts the Move workflow.
  - Layout [#] · Grid previews, panes, and actions grow with the available space.
    - 1×1 · Applies immediately. Uses the desktop area and keeps the taskbar.
    - 2×1 / 1×2 / 2×2 · Pick a numbered pane on the next screen.
      - [Position] · Positions that cannot fit the app are disabled.
    - 3×1 / 1×3 / 3×2 / 2×3 / 3×3 · More numbered panes.
      - [Position] · Positions that cannot fit the app are disabled.
    - Restore · Returns to the normal layout when a preset is active.
    - Fullscreen · Uses all monitor cells.
      - [Top-right cell] · Restores ordinary windows. Screensaver handles the corner itself.
    - Resize
      - First corner · Touch to select. Arrows nudge, Place repicks and OK accepts the corner.
        - Other corner · Touch, nudge or repick. OK applies if the window fits.
    - **Move**
      - Pick position · Touch, nudge or use Place to repick. OK applies and Cancel exits.
    - Cancel · Closes the layout menu.
- **[Monitor-client calibration]** · Run clients_monitor_client.lua calibrate [side].
  - [Measure nine points] · Touch the centers from the usual viewing position.
  - [Test preview] · The --test flag starts here. Arrows adjust the offset.
    - Save / Reset / Cancel · Save the offset, preview the stock offset or exit.
    - Remeasure · R on the client keyboard repeats the measurement.
  - [Retry screen] · Appears when samples disagree. Retry, Reset or Cancel.

SOURCE lib_desktop.lua lib_server.lua lib_monitor.lua documentation_desktop.md

Settings

Appearance, system diagnostics, client names and saved app data.

Desktop › Start › Settings — 51 ENTRIES

- **Appearance**
  - Background · Choose a desktop background color.
  - Window border / Borders · Choose a frame color.
  - Taskbar · Choose a taskbar color.
- **System overview**
  - Central computer · IDs, channels, uptime, last checkpoint, world clock and player status.
  - Clients · Announced clients and online/offline status.
    - **[Client] / Client details** · Role-specific monitor, IO, sensor or relay data.
      - Targets · Sensor clients only.
        - [Sensor target] · Catalog metadata and cached readings.
    - Filter · Cycles all, IO, monitor, sensor and relay.
  - Sensors · Opens the Sensor clients list.
    - [Sensor client] · Open details, then Targets.
    - Filter · Same control as on the Clients page.
  - Outputs · Mapped outputs with their requested ON/OFF states.
    - [Mapped output] · Route, desired value, online status and acknowledgment.
  - Apps · Enabled apps and running/background status.
  - Windows · Saved windows by monitor with geometry and state.
  - Uptime history · Observed OS and client online/offline events.
  - Relay map
    - [Client route] / Observed path · OS, relay hops and endpoint. Relay details also list downstream devices.
      - Details · Opens the selected client's details.
  - Overview options
    - Client filter · Cycles all, IO, monitor, sensor and relay.
    - About · Explains the live registry and last-observed paths.
- **Client names**
  - [Client] / Client name · Friendly label and stable ID.
    - Rename · Set saves the label. Back returns to the selected client.
    - Reset · Clears the friendly label and restores the ID.
- **Screensavers** · Read-only numbered list from the installed Screensaver app.
  - [Design names in cycle order] · To run or cycle them, open Screensaver from Start.
- **App data**
  - Backup & restore
    - Create backup
      - [Entire OS / OS settings / app] · Creates a backup immediately when none exists.
        - Replace backup? · Replace or Cancel if a backup already exists.
    - Restore backup
      - [Existing backup]
        - Restore data? · Restore or Cancel.
  - Reset data
    - Entire OS
      - Are you sure? · Continue or Cancel.
        - Are you really sure? · Erase all or Cancel.
    - OS settings
      - Are you sure? · Delete data or Cancel. Clears desktop layout, appearance and OS routes.
    - [App]
      - Are you sure? · Delete data or Cancel. Clears app data, routes and layouts.
  - Delete apps
    - [Installed app]
      - Delete app? · Uninstall or Cancel. Saved settings are kept.
- **Close** · Closes this monitor's Settings window.

SOURCE **lib_settings.lua** **lib_system.lua** **lib_server.lua**

Alert inbox

Recent alert history and the separate acknowledgment popup.

Desktop › Clock / alert badge or Start › Alert inbox 5 ENTRIES

- **Alert list** · Newest first. Active alerts are marked with an asterisk.
  - [Alert] / Details · Time, message and Active or Closed status. Back returns to the list.
  - Back · Closes the inbox.
- **[Active popup]** · Separate modal shown above the desktop and fullscreen apps.
  - OK · Acknowledges through the originating app. Clock can also use a configured dismiss input.

SOURCE lib_alert_inbox.lua lib_server.lua

Shared dialogs

Reusable picker and editor flows linked from their calling menus.

Opened by an app action — 30 ENTRIES

- **Redstone picker**
  - Select IO
    - Select side · Uses the selected IO client.
      - Select wire · Digital or one of 16 bundled colors. Roomy screens show the selected client and side.
        - Use this input? · Shows ON, OFF or Unknown when the input can be read.
          - Use · Passes the selected input to the app.
        - Use this output?
          - Test · Briefly tests the output from the confirmation screen.
          - Use · Passes the selected output to the app.
- **Sensor picker**
  - Sensor client
    - Sensor side · Filtered pickers require a compatible card.
      - Select target · The selected card supplies the catalog. Roomy screens show the path so far.
        - Use sensor?
          - Use · Passes the selected sensor address to the app.
- **OS color palette**
  - [Color swatch] · Standard OS palette applies on selection. Some apps have their own Apply preview.
  - Back · Returns to the calling screen.
- **Touch keyboard**
  - [QWERTY keys] · Three letter rows. Compact keyboards page the rows when needed.
  - ABC / 123 / abc · The mode key shows the next bank. Uppercase resets after one letter.
  - Space / Sp and Del · Insert a space or delete the last character.
  - Set / Save / Find · Apply the draft using the calling screen's action.
  - Clr / Back · Clear the draft or return.
- **Number pad**
  - [Digits / Clr / Del] · Full-size tiles fill the space below the draft. Clock uses HHMM for world time.
  - Set / Back · Apply the draft or return. The caller validates the value.
- **Decimal number pad**
  - [Digits / . / Del] · Full-size tiles enter decimal seconds for a Switchboard button or Logic Sandbox Wait.
  - Set / Back · Apply the draft or return. The caller checks precision and range.

SOURCE **lib_io_picker.lua** **lib_sensor_picker.lua** **lib_gui.lua** **lib_server.lua**

Clock

World-time alarms, timers, a stopwatch and optional redstone signals.

Desktop › Start › Clock 54 ENTRIES

- **Alarms** · Opens World-time alarms.
  - + Add alarm · Opens a blank alarm editor.
  - [Alarm] / Details
    - Enabled / Disabled · Toggle the alarm.
    - Dismiss / OK · Appears while the alert is pending.
    - Output / signal details · Route, timing, dismiss input and wire acknowledgment.
    - **Edit / Alarm settings**
      - Name · Touch keyboard.
      - Time · Minecraft world time in HHMM.
      - Repeat · Daily or Once.
      - Enabled · Yes or No.
      - Select output · Optional redstone output.
      - Disconnect output · Available after assigning an output.
      - Select dismiss input · Optional fresh input press to acknowledge.
      - Clear dismiss input · Available after assigning an input.
      - Signal · Cycles Constant and Pattern.
      - Length · Constant only. Zero means Until OK.
      - ON / OFF / Total · Pattern only. Total zero means Until OK.
      - Save / Cancel · Save the alarm or discard the draft.
    - Delete
      - Delete alarm? · Delete or Cancel.
- **Timers** · Opens Timers / recent.
  - + Add timer · Opens a blank timer editor. Use Start to save and run it.
  - [Timer] / Details
    - Pause / Resume / Restart · Depends on the current timer state.
    - Cancel timer · Available when running or paused.
    - Dismiss / OK · Appears while the alert is pending.
    - Output / signal details · Route, signal timing, dismiss input and acknowledgment.
    - **Edit / Timer settings** · Available while the timer is not running and has no pending alert.
      - Name · Touch keyboard.
      - Time · Enter the duration in seconds.
      - Clock · Real time or Game time.
      - Select output · Optional redstone output.
      - Disconnect output · Available after assigning an output.
      - Select dismiss input · Optional fresh input press to acknowledge.
      - Clear dismiss input · Available after assigning an input.
      - Signal · Cycles Constant and Pattern.
      - Length · Constant only. Zero means Until OK.
      - ON / OFF / Total · Pattern only. Total zero means Until OK.
      - Start / Save / Cancel · Start a new timer, save edits or discard the draft.
    - Delete
      - Delete timer? · Delete or Cancel.
- **Stopwatch**
  - Start / Stop · Runs or stops the elapsed clock.
  - Lap · Adds a split while running. The lap list can page.
  - Reset · Clears elapsed time and lap history.
  - Real / Game · Change the time base when stopped and reset. Real shows tenths. Game shows days and HH:MM:SS.
- **Settings**
  - UI color · Standard OS palette.
  - Timer history · Cycles 10, 20 and 50 retained results.
  - **Clock status** · World time, source health and errors.
  - About / restart rules · Explains trigger, timing and restart behavior.
- **Status** · Home shortcut to Clock status.
- **[Alarm / timer popup]** · OK or the configured dismiss input acknowledges it.

SOURCE **apps_clock.lua** **documentation_clock.md**

Coffee

Harvest countdown, player input, output routing and counters.

Desktop › Start › Coffee 20 ENTRIES

- **Pause / Resume** · Toggles the current countdown or harvest.
- **Harvest now** · Forces a harvest when an online output is configured.
- **Menu**
  - Settings
    - Player input / Player IO · Assign the player-presence input.
    - Harvest output / Harvest IO · Assign the harvest output.
    - Countdown
      - Step / - / + · 1, 10, 60, 600 or 3600 second adjustments.
      - Save (next) / Cancel · Applies the new duration to the next cycle.
    - Harvest time
      - Step / - / + · 1, 10, 60, 600 or 3600 second adjustments.
      - Save (next) / Cancel · Applies the new duration to the next cycle.
    - UI color · Standard OS palette.
  - Stats / Harvest counts · Shows total and trip counts.
    - Reset trip · Zeros the trip counter.
  - Maintenance
    - Reset timer
      - Reset timer? · Confirm or Cancel. Confirm starts a fresh countdown.
    - Import save
      - Import save? · Confirm or Cancel. Reads countdown_state.txt and imports paused.

SOURCE apps_coffee.lua documentation_coffee.md

Logic Sandbox

Build rules by choosing an IF condition and arranging the THEN actions.

Desktop › Start › Logic Sandbox 102 ENTRIES

- **+ New rule** · Opens a disabled rule for setup.
- **[Saved rule]** · Opens the condition and action summary. A circuit with several rules opens a list.
  - IF / Choose condition
    - Redstone · Pick a wire. Tap When ON or When OFF to change the match.
    - Item count · Select the ME and item, choose Below, Above or Exactly, set Level and Save.
    - Combine / Combine IF
      - All true / Any true / Exactly one · Pick both conditions. Each can open another group.
      - Invert · Pick the condition to reverse.
      - Hold true · Pick the condition and hold time.
    - Change / Change IF · Choose a type, wrap in Combine or Clear the condition.
  - THEN · Opens the list of actions in execution order.
    - + Add / Add action
      - Alarm
        - Name · Sets the popup message. Empty uses the circuit name.
      - Set redstone · Pick an output and set ON or OFF.
      - Wait · Enter the pause in seconds.
    - [Action] · Edit the selected action.
      - Order · Move earlier, move later or remove that action.
      - Set up IF / Set up THEN · Opens the section that needs configuration.
      - Turn on / Turn off · Controls background execution.
      - More
        - Rename · Change the rule name.
        - Wiring · Edit the circuit connections.
        - Delete / Delete? · Delete the circuit or cancel.
- **More**
  - New output · Opens the same IF editor.
    - THEN · Select the wire that follows the condition.
  - Wiring · Opens the circuit list.
- **Wiring**
  - + New circuit · Enter a name. Set opens a new, disabled circuit.
  - [Circuit]
    - OFF - Enable / ON - Disable · Toggles the circuit's background evaluation.
    - **Setup tips** · Appears when block connections need attention.
      - [Tip] · Explains the missing step for that block.
        - Edit / Back · Opens the block editor or returns to the tips.
    - + Add / Add logic node
      - Redstone input / Input · Reads a redstone wire.
      - Item amount · Compares an item count from the selected ME network.
      - AND / OR / NOT / XOR · Combines or inverts signals.
      - Delay · Waits for a source to stay on.
      - If / Then · Runs action blocks in order on a rising condition.
      - Redstone output / Output · Routes a signal to a wire.
      - Wait / Set output / Alarm · Reusable blocks for rules.
      - Output target · A named wire destination for Set output blocks.
    - **Flow / Circuit flow** · Paged text view of conditions, routes and actions. Back returns to the circuit.
    - Menu
      - View flow · Available here when Flow does not fit the circuit footer.
      - Enable circuit / Disable circuit · Turns background evaluation on or off.
      - Check setup · Checks connections and explains missing steps.
      - Rename circuit · Touch keyboard.
      - Delete circuit
        - Delete? · Delete or Cancel.
    - [Node] · Numbered rows identify blocks. Roomy windows show ON, OFF, Waiting, Running, Ready, Action or Alert separately.
      - **Select redstone** · Input, Output and Output target. A saved route shows its address.
      - Clear routing · Available when one of those nodes has an assigned route.
      - **Set item count / Edit count**
        Item amount only. Visible saved counts stay live while the circuit is disabled. Source errors explain an unavailable count.
        - ME / Select ME · Select an AE sensor, side and target.
        - Select item · Live item names and amounts. Select a row to use its identity.
          - Find / Find item
            - Search · Filter by item name or RawName.
            - Refresh · Rebuilds the item list.
            - Manual item · Register an item that is absent from the network.
              - Name / RawName · Enter display and exact raw names.
              - Damage · Enter the item's damage value.
              - Use / Back · Use the identity or return to Find item.
        - Compare / Compare count
          - Under (<) / Over (>) / Exactly (=) · Choose the comparison.
        - Level · Enter the item count to compare against.
        - Save / Cancel · Commit the stock condition or discard the draft.
      - **A / B** · A for all gates. B for AND, OR and XOR. Pick Unwired or a compatible source node.
      - **From** · The source for a Redstone output. Choose Unwired or a compatible node.
      - **Delay editor**
        - When · Choose the signal that must stay on.
        - Wait · Set seconds with up to two decimal places.
        - + Link output · Creates and routes an Output fed by this Delay.
      - **If / Then editor**
        - When · Pick the triggering node. The rule's signal is on while it runs.
        - Then blocks · View the ordered steps for this rule.
          - + Block / Then add block
          - + Wait / + Set output / + Alarm · Create and edit a reusable block.
          - [Existing block] · Reuse a named block here or in another rule.
        - [Step]
          - Edit block · Edit the shared block. Rule returns to the steps.
          - Move earlier / Move later · Reorder this occurrence.
          - Remove step / Remove from rule? · Remove this occurrence or Cancel.
      - **Action block editors**
        - Wait · Pause this rule for the entered decimal seconds.
        - Set output
          - Choose target / Target · Pick an existing named Output target.
            - + New target · Creates a target and opens the redstone picker.
          - Set ON / Set OFF · Changes the value this block sends.
          - Select redstone / saved route · Sets or changes the chosen target's wire.
        - Alarm · Runs as an action in If / Then. Popup title is Alarm.
          - Name · Enter the popup cause. An empty name uses the circuit name.
      - **Output target editor** · Choose or clear a wire using the routing controls above.
      - Popup ON / OFF · Optional alert for other signal nodes. Item amount uses an If / Then Alarm action.
      - Rename node · Other nodes. Alarm uses its Name control above.
      - Setup tip · Item amount or Alarm editors with a missing connection.
      - Delete node
        - Delete? · Delete or Cancel.
- **[Node / Alarm block popup]** · OK acknowledges the alert.
- **Close** · Closes the current window.

SOURCE **apps_logic_sandbox.lua** **documentation_logic_sandbox.md**

Switchboard

IO side presets, timed buttons, custom switch grids and scenes.

Desktop › Start › Switchboard 61 ENTRIES

- **+ Add view / New view**
  - + Empty view
    - Empty view · Set Cols and Rows with the +/- controls.
      - Create / Cancel · Create adds an unwired grid.
  - [IO client]
    - Select side
      - [Available side]
        - 16 switches
          - Create · Adds a 4×4 view with one switch per bundled wire color.
- **[View] / Switch grid**
  - [Routed tile] · Toggles a switch or starts a timed button press. Tapping a timed button again restarts its timer.
  - [Unwired / invalid tile] · Opens that switch's editor.
  - Edit / View settings
    - Rename view · Touch keyboard.
    - Edit switches
      - **[Switch]** · The editor retains the original route and wire color.
        - Rename / Name · Touch keyboard.
        - Color / Button color
          - [Swatch] / IO default / By state · Pick a fixed color, use the wire color or use the state color.
          - Apply / Cancel · Save or discard the color draft.
        - State colors / States
          - Active / Inactive / Pending · Pick a swatch or Inherit from the view. Apply to save.
        - Routing / Route · Assign an IO client, side and Digital or bundled color.
        - Behavior / Mode · Opens Switch mode.
          - Switch · Tap the tile to toggle a steady output.
          - Button · Tap for a timed press. The IO client ends the press locally.
            - Time · Enter seconds with up to two decimal places. The mode screen shows the client's minimum.
        - Disconnect
          - Disconnect? · Confirm or Cancel.
    - State colors / View state colors
      - Active / Inactive / Pending · Pick a swatch or Inherit from app settings. Apply to save.
    - Grid size
      - Cols / Rows · Adjust the grid.
      - Save grid
        - Remove cells? · Confirm or Cancel if the grid is shrinking.
    - All OFF
      - All OFF? · Confirm or Cancel for this view.
    - Move earlier / Move later · Reorders the view on the home page.
    - Delete view
      - Delete view? · Confirm or Cancel.
- **Scenes**
  - [Scene] · Tapping a scene reapplies saved ordinary switch states to matching routes.
  - + New scene / Capture scene
    - All views · Captures routed ordinary switches from all views after naming the scene.
    - [One view] · Captures routed ordinary switches from the selected view after naming it.
  - Edit
    - [Scene]
      - Rename · Touch keyboard.
      - Delete
        - Delete scene? · Delete or Cancel.
- **Settings / App settings**
  - UI color · Preview a swatch, then Apply or Cancel.
  - Background · Preview a swatch, then Apply or Cancel.
  - Button borders · Preview a swatch, then Apply or Cancel.
  - Unwired tiles · Preview a swatch, then Apply or Cancel.
  - Active color · Preview a swatch, then Apply or Cancel.
  - Inactive color · Preview a swatch, then Apply or Cancel.
  - Pending color · Preview a swatch, then Apply or Cancel.
  - Density · Cycles roomy and compact.
  - All switches OFF
    - All OFF? · Confirm or Cancel for all views.

SOURCE **apps_switchboard.lua** **documentation_switchboard.md**

ME monitors

Saved grid and list views for live ME item counts.

Desktop › Start › ME monitors 37 ENTRIES

- **+ Add view**
  - [AE sensor picker] · Select a client, AE card side and ME target.
    - New view layout · Opens after accepting the sensor.
      - List / Grid · Toggle the layout.
      - Items / Cols / Rows · Adjust list size or grid dimensions.
      - Create / Cancel · Create opens the new view.
- **[View]** · Item tiles in a grid or a paged list.
  - [+ Item / Empty tile] · Opens the item picker.
  - [Assigned tile] / Item monitor
    - **Item / Select item**
      - Name / Amount · Sort by item name or stored count.
      - A-Z / Z-A / Low-Hi / Hi-Low · Reverse the current sort.
      - Search / Find · Search display names and raw names.
      - Refresh / Sync · Refresh the picker rows.
      - [Item] · Assigns this item to the chosen tile.
    - Color
      - [Color swatch] · Pick a custom grid tile or list row color.
      - Apply / Auto / Back · Auto restores default colors. Apply saves the preview.
    - Clear · Removes the item assignment.
  - Edit / View settings
    - Change rates / Rates · Toggles signed 5-minute change and net hourly rate.
    - Rename view · Touch keyboard.
    - Edit items / Choose a tile
      - [Tile] · Opens the picker directly.
    - Layout / size
      - List / Grid · Toggle the layout.
      - Items / Cols / Rows · Adjust list size or grid dimensions.
      - Save grid
        - Remove last tiles? · Confirm or Cancel when shrinking.
    - AE source · Changes the view's sensor binding.
    - Source information · Client, side, target, status and age.
    - Delete view
      - Delete view? · Confirm or Cancel.
- **Settings / Monitor settings**
  - UI color · Standard OS palette.
  - Density · Cycles roomy and compact.
  - About · Setup, sensor reads and count formatting.

SOURCE **apps_me_monitor.lua** **documentation_me_monitor.md**

ME storage

Storage dashboards, exact counters and optional drive surveys.

Desktop › Start › ME storage — 20 ENTRIES

- **+ Add system** · Choose an AE source. Accepting it opens the new dashboard.
- **[ME system] / Dashboard** · Bytes, items and types from the bound ME network.
  - **Cells / Cell / Drive inventories**
    - Cell / drive totals · Cell survey totals across the selected live drive inventories.
    - + Add drive · Uses an Inventory Card target for the drive or chest.
    - [Drive] / Drive slots
      - [Cell slot] · Item name, count and size when identifiable.
      - Source · Sensor binding, status and age.
      - Remove
        - Remove drive? · Confirm or Cancel.
  - Edit / System settings
    - Rename · Touch keyboard.
    - Change AE sensor · Changing the binding clears the old drive selection.
    - Source / exact figures · Binding, status, byte/item/type counts and headroom.
    - Drive inventories · Alternate path to the Cells screen.
    - Remove system
      - Remove system? · Confirm or Cancel.
- **Settings / ME settings**
  - UI color · Standard OS palette.
  - About / setup · AE1 card setup and limits of the available readings.

SOURCE apps_me_storage.lua documentation_me_storage.md

Reactors

Reactor sensor readings and separate redstone control per reactor.

Desktop › Start › Reactors 17 ENTRIES

- **+ Add reactor** · Select a compatible sensor target. Use opens the new reactor.
- **[Reactor card]** · The header shows measured activity. The switch shows requested output.
  - Set IO · Shown if the control output is unassigned.
  - ON / OFF · Toggles a mapped output.
  - [Card body] / Reactor details · Heat, EU readings and extra fields when reported.
    - Set IO / ON / OFF · Same output control as the home card.
    - Edit / Reactor settings
      - Rename · Touch keyboard.
      - Sensor target · Changes the monitored reactor target.
      - Control output · Assigns or changes the separate redstone output.
      - Raw readings / Sensor fields · Paged sensor data, including flattened nested fields.
      - Delete reactor
        - Delete reactor? · Confirm or Cancel.
- **Settings / App settings**
  - UI color · Preview a swatch, then Apply or Cancel.
  - Panel color · Preview a swatch, then Apply or Cancel.
  - About readings · Explains heat thresholds, EU counters and sensor limitations.

SOURCE apps_reactors.lua documentation_reactors.md

Solar farm

Finished HV arrivals, panel equivalents and production-sorted farm stock.

Desktop › Start › Solar farm 49 ENTRIES

- **HV output** · Shows completed observation minutes and rates per minute and per hour. Tap for details.
- **[Item / Amount header]** · Where visible, touch to sort. Touch again to reverse.
- **[Item row] / Item overview**
  A single line holds the item, amount and rate when it fits. HV also shows farm panel equivalents and combined net equivalents.
  - Pin item / Edit pin
    - Name · Touch keyboard.
    - Stick · Keeps the pinned row above the sorted list.
    - Item color · Pick a swatch to apply.
    - Drop minimum / Drop percent · Override the global withdrawal filter for this item.
    - Use default filter · Clears the item-specific overrides.
    - Select HV item · HV pin only.
    - Unpin item · Removes the pin.
- **Pin item / Pin overview item** · Opens the item picker.
  - [Farm ME item] · Pins the selected farm item.
  - [HV solar / main ME] · Pins the main-ME HV row.
  - Find · Opens the same filters as the HV picker.
- **Menu / Solar farm menu**
  - ME sources
    - Select farm ME · Supplies the overview's farm inventory.
    - Select main ME (HV) · Supplies the HV output row.
  - **HV panel type / detection** · Opens the Main ME item list.
    - [HV item] · Chooses the exact panel identity.
    - Auto · Restores automatic HV identification.
    - **Find / Find item**
      - Search · Touch keyboard.
      - Sort / Order · Name or amount, ascending or descending.
      - Refresh list · Rebuilds the picker list.
      - Register absent item / Absent item identity
        - Name / RawName · Display name and exact raw name.
        - Damage · Enter the item's damage value.
        - Use item · Uses the registered identity.
  - Graph/change · Cycles 5, 15 and 60 minutes.
  - Rate unit · Cycles per hour, per minute and per second.
  - List sorting / Overview order
    - Production order · Pins come first. Other items group by production stage and recent activity.
    - Item A-Z / Item Z-A
    - Amount high-low / Amount low-high
  - Reset rate learning / Restart learned rates
    - Main / HV only
      - Reset rate learning? · Reset or Cancel. Keeps sources and pins.
    - Farm only
      - Reset rate learning? · Reset or Cancel. Keeps sources and pins.
    - Both ME sources
      - Reset rate learning? · Reset or Cancel. Keeps sources and pins.
  - Withdrawal filter / Ignore big withdrawals
    - Minimum · Global item-count threshold.
    - Percent · Global percentage threshold.
  - UI color · Standard OS palette.
  - Source status · Farm/Main health, age, learning time and HV selection.
  - About rates · Explains finished HV arrivals, panel equivalents and observation gaps.

SOURCE apps_solar_farm.lua documentation_solar_farm.md

IO Scope

Browse IO history and save traces for selected wires.

Desktop › Start › IO Scope 22 ENTRIES

- **Used by apps** · Opens a trace of wires bound by apps.
- **Client side**
  - [IO client]
    - [Side] / Wires
      - Outputs · Trace output lanes on this side.
      - Inputs · Trace input lanes on this side.
- **+ New view** · Name a blank saved view. Set opens its trace.
- **[Saved view] / Trace** · The same trace screen is also opened by live discovery views.
  - [Wire lane] / Wire details · Shows binding, current state and apps using the wire.
    - Remove · Removes the lane from a saved view.
  - ‹ Earlier / Later › · Scrolls the time window.
  - Hold / Live · Freezes the trace or follows the present.
  - Menu / … · Opens Scope menu.
    - Range · Cycles 10, 30, 60 and 120 seconds.
    - All views · Returns to the Scope home screen.
    - Add output · Saved view only.
    - Add input · Saved view only.
    - Rename view · Saved view only.
    - Delete view · Saved view only.
      - Delete view? · Delete or Cancel.
    - Save as view · Discovery views only. Name a snapshot of the current lane selection.
- **Close** · Closes the current window.

SOURCE **apps_io_scope.lua**

Net Scope

Live list of SmartHome radio packets seen and sent by the central OS.

Desktop › Start › Net Scope 17 ENTRIES

- **[Packet row]** · Newest first. Green is received, blue is sent, gray is ignored, red is foreign.
- **[Packet details]** · Direction, type, client, channel, size, relay hops and fields.
  - Type · Returns to the list filtered to this packet type.
  - Client · Returns to the list filtered to this client.
- **Hold / Live** · Freezes the list or follows new packets.
- **Menu / Net Scope menu**
  - Direction · Cycles RX+TX, RX only and TX only.
  - Type
    - [Packet type] · All, or one type seen in the capture.
  - Client
    - [Client] · All, or one client seen in the capture.
  - Ignored/foreign · Shows or hides duplicates and packets not meant for the OS.
  - Render packets · Captures or skips monitor redraw packets.
  - Statistics · Packet and byte totals by type and by client.
  - Clear capture · Empties the capture buffer.
  - UI color · Standard OS palette.
- **Close** · Closes the current window.

SOURCE **apps_net_scope.lua**

Notes

Notes, interactive checklists and Markdown export.

Desktop › Start › Notes 18 ENTRIES

- **+ New note** · Enter a title. Set opens a new note.
- **[Note]**
  - [Text line] · Tap to open line details.
  - [Checkbox] · Tap to toggle it. In Edit lines mode, tap to open its details.
  - **[Line details]** · Shows the text of the selected line or checkbox.
    - Edit · Modify the text with the touch keyboard.
    - Delete
      - Delete? · Delete or Cancel.
  - + Add / Add to note
    - Text line · Type a line and Set to add it.
    - Checkbox · Type a checklist item and Set to add it.
  - Menu / Note menu
    - Edit lines / Done editing · Controls what tapping a checkbox does.
    - Rename note · Touch keyboard.
    - Export Markdown · Writes notes_export_ID.md on the OS computer.
    - Delete note
      - Delete? · Delete or Cancel.
- **Close** · Closes the current window.

SOURCE apps_notes.lua

Screensaver

Fullscreen animations with invisible corner controls and a saved rotation.

Desktop › Start › Screensaver 29 ENTRIES

- **[Top-left 2×2 area]** · Previous design, wrapping from first to last.
- **[Top-right 2×2 area]** · Next design, wrapping from last to first.
- **[Any other touch]** · Closes the fullscreen window. Active alert popups take touch priority.
- **Design rotation** · Each opening advances the design. Settings lists the same names in order.
  - 01 Matrix Rain
  - 02 Matrix Wall
  - 03 Plasma
  - 04 Ripple Pools
  - 05 Rainbow Tiles
  - 06 Silk Waves
  - 07 Kaleidoscope
  - 08 Life Garden
  - 09 Nyan Cat
  - 10 Starflight
  - 11 Northern Lights
  - 12 Lava Lamp
  - 13 Neon Tunnel
  - 14 Fireworks
  - 15 Spiral Ribbons
  - 16 Prism Tide
  - 17 Candy Confetti
  - 18 Sunset Surf
  - 19 Pixel Quilt
  - 20 Orbit Parade
  - 21 DVD Bounce
  - 22 Pac-Man Chase
  - 23 Tetris Rain
  - 24 Rainbow Road
  - 25 Among Us Drift

SOURCE apps_screensaver.lua lib_settings.lua documentation_screensaver.md

Window Presets

Capture, reassign and restore monitor window layouts.

Desktop › Start › Window Presets 16 ENTRIES

- **+ Save layout**
  - This monitor · Name and save the current monitor's layout.
  - All online monitors · Name and save the layout across online monitors.
- **[Preset] / Preview**
  - [Monitor slot] / Monitor preview · Shows source, target and which windows can be restored.
    - Assign / Assign monitor
      - Original · Use the slot's original monitor.
      - Skip this slot
      - [Online monitor] · Assign the saved slot to that monitor.
  - Rename preset · Touch keyboard.
  - Delete preset
    - Delete preset? · Delete or Cancel.
  - Apply
    - Replace layouts? · Shows open, minimized and unavailable counts.
      - Apply / Cancel · Applies the previewed layouts and keeps app data.
- **Close** · Closes the current window.

SOURCE apps_window_presets.lua documentation_desktop.md

Brackets mark context-dependent entries. Colored labels open linked paths.