

# EE 451: Communications Systems

## Homework 3 - FM, PM, FSK, and BPSK

**Topics:** Frequency and phase modulation, FSK, BPSK, Carson's rule **Textbook Reference:** Haykin & Moher, Chapters 4.1-4.5, 7.2-7.4

**Total Points:** 100

---

### Instructions

- Show all work for full credit
  - Include units in all final answers
  - For bandwidth calculations, clearly state which rule or method you're using
  - Sketches should be clearly labeled
- 

### Problem 1: FM Fundamentals (12 points)

A message signal  $m(t) = 2 \cos(2\pi \cdot 1000 \cdot t)$  V modulates an FM carrier with  $f_c = 100$  MHz and frequency sensitivity  $k_f = 10$  kHz/V.

- (a) Write the expression for the instantaneous frequency  $f_i(t)$ . (3 points)
  - (b) What is the maximum frequency deviation  $\Delta f$ ? (3 points)
  - (c) Write the complete FM signal expression  $s(t)$ . You may leave the answer in terms of the integral of  $m(t)$ . (4 points)
  - (d) What is the modulation index  $\beta$  for FM? (2 points)
- 

### Problem 2: Carson's Rule Application (15 points)

An FM broadcast station transmits audio signals with maximum frequency  $f_m = 15$  kHz and maximum frequency deviation  $\Delta f = 75$  kHz (standard FM broadcasting parameters).

- (a) Calculate the modulation index  $\beta$ . (3 points)
  - (b) Use Carson's rule to estimate the FM bandwidth. (4 points)
  - (c) Is this narrowband FM (NBFM) or wideband FM (WBFM)? Justify your answer. (3 points)
  - (d) How does this compare to the bandwidth required for AM broadcasting of the same audio signal? (3 points)
  - (e) What is the advantage of using such a large bandwidth for FM? (2 points)
-

### Problem 3: Narrowband vs. Wideband FM (12 points)

- (a) For NBFM, the criterion is  $\beta \ll 1$ . If  $f_m = 3$  kHz, what is the maximum  $\Delta f$  that qualifies as NBFM? Use  $\beta < 0.3$  as the threshold. (3 points)
  - (b) Estimate the bandwidth of NBFM using the small-angle approximation. (3 points)
  - (c) For WBFM with the same  $f_m = 3$  kHz but  $\Delta f = 30$  kHz, calculate  $\beta$  and the bandwidth using Carson's rule. (4 points)
  - (d) Compare the bandwidth efficiency (in terms of  $\beta$ ) between NBFM and WBFM. (2 points)
- 

### Problem 4: Phase Modulation (12 points)

A PM signal is given by  $s(t) = A_c \cos[2\pi f_c t + k_p m(t)]$  where: -  $A_c = 10$  V -  $f_c = 200$  MHz -  $k_p = 2$  rad/V (phase sensitivity) -  $m(t) = 3 \cos(2\pi \cdot 5000 \cdot t)$  V

- (a) What is the maximum phase deviation  $\Delta\phi$ ? (3 points)
  - (b) Write the expression for the instantaneous phase  $\theta_i(t)$ . (3 points)
  - (c) Find the instantaneous frequency  $f_i(t)$ . (4 points)
  - (d) What is the maximum frequency deviation? (2 points)
- 

### Problem 5: FM vs. PM Relationship (10 points)

- (a) Explain the fundamental difference between FM and PM. How are they related? (4 points)
  - (b) If you integrate a message signal before applying it to a frequency modulator, what type of modulation do you effectively create? (3 points)
  - (c) For the message  $m(t) = \cos(2\pi f_m t)$ , how does the frequency deviation in FM compare to the frequency deviation in PM as  $f_m$  varies? (3 points)
- 

### Problem 6: Binary FSK Fundamentals (15 points)

A binary FSK system transmits data at 9600 bits/s using: - "0" bit:  $f_0 = 1200$  Hz - "1" bit:  $f_1 = 2200$  Hz - Carrier amplitude:  $A = 5$  V

- (a) Write the signal expressions  $s_0(t)$  and  $s_1(t)$  for the two binary symbols. (4 points)
- (b) What is the frequency separation  $\Delta f = |f_1 - f_0|$ ? (2 points)
- (c) Calculate the modulation index  $h = \Delta f \cdot T_b$  where  $T_b$  is the bit duration. (4 points)
- (d) For coherent FSK detection, the minimum frequency separation for orthogonality is  $\Delta f = \frac{1}{2T_b}$ . Is this FSK system using orthogonal tones? (3 points)
- (e) Estimate the bandwidth using Carson's rule, treating FSK as FM with a rectangular baseband signal. (2 points)

---

**Problem 7: Minimum Shift Keying (MSK) (12 points)**

MSK is a special case of continuous-phase FSK (CPFSK) with modulation index  $h = 0.5$ .

- (a) If the bit rate is  $R_b = 10$  kbps, what is the bit duration  $T_b$ ? (2 points)
  - (b) Given  $h = 0.5 = \Delta f \cdot T_b$ , calculate the required frequency separation  $\Delta f$ . (3 points)
  - (c) What are the two frequencies  $f_0$  and  $f_1$  if the center frequency is 1800 Hz? (4 points)
  - (d) Why is MSK preferred over standard FSK in many applications? (3 points)
- 

**Problem 8: Binary Phase Shift Keying (BPSK) (15 points)**

A BPSK system transmits at 1 Mbps with carrier frequency  $f_c = 2.4$  GHz.

- (a) Write the two possible signal expressions for BPSK representing bits “0” and “1”. (4 points)
  - (b) Sketch the constellation diagram for BPSK in the I/Q plane. Label the two signal points. (4 points)
  - (c) What is the phase difference between the two BPSK symbols? (2 points)
  - (d) Calculate the null-to-null bandwidth of the BPSK signal. (3 points)
  - (e) Can BPSK be demodulated using an envelope detector? Why or why not? (2 points)
- 

**Problem 9: Coherent vs. Non-Coherent Detection (10 points)**

- (a) Explain the difference between coherent and non-coherent detection. (3 points)
  - (b) Which modulation schemes can use non-coherent detection: ASK, FSK, BPSK? Explain. (4 points)
  - (c) What is the advantage of coherent detection? What is the disadvantage? (3 points)
- 

**Problem 10: Real-World Application - FM Deviation (12 points - Challenge)**

Commercial FM radio in the US uses: - Maximum frequency deviation:  $\Delta f = 75$  kHz (audio) - Pilot tone for stereo: 19 kHz - Subcarrier for RDS (Radio Data System): 57 kHz - Maximum audio frequency: 15 kHz

- (a) Calculate the modulation index for maximum audio frequency. (3 points)
- (b) Use Carson’s rule to calculate the bandwidth occupied by the FM station. (3 points)
- (c) FM stations are allocated 200 kHz of bandwidth. Does your calculated bandwidth fit? If not, what accounts for the difference? (3 points)

(d) An FM station also has a subcarrier at 67 kHz for SCA (Subsidiary Communications Authorization) services. How does this affect the total deviation and bandwidth? (3 points)

---

**Bonus Problem 1: Bessel Functions in FM (5 points extra credit)**

The FM spectrum consists of infinite sidebands with amplitudes given by Bessel functions  $J_n(\beta)$ .

For single-tone FM with  $\beta = 2$ : -  $J_0(2) = 0.224$  -  $J_1(2) = 0.577$  -  $J_2(2) = 0.353$  -  $J_3(2) = 0.129$  -  $J_4(2) = 0.034$

(a) Sketch the frequency spectrum showing the carrier and first four sidebands on each side. Label amplitudes relative to carrier (assume  $A_c = 10$  V). (3 points)

(b) Notice that  $J_0(2)$  is small. What does this mean about the carrier power in FM compared to AM? (2 points)

---

**Bonus Problem 2: Frequency Deviation Calculation (5 points extra credit)**

For the FM signal  $s(t) = 10 \cos[2\pi \cdot 100 \times 10^6 \cdot t + 50 \sin(2\pi \cdot 1000 \cdot t)]$ :

(a) Identify the carrier frequency  $f_c$ , message frequency  $f_m$ , and the modulation index  $\beta$ . (3 points)

(b) Calculate the frequency deviation  $\Delta f$ . (2 points)

**Hint:** The general form is  $s(t) = A_c \cos[2\pi f_c t + \beta \sin(2\pi f_m t)]$  for single-tone FM.

---

**Submission Instructions:** - Submit a single PDF via Brightspace - Show all derivations and calculations - Include clear sketches with labeled axes - State all assumptions

**Academic Integrity:** - Individual work required - You may use textbook formulas and course notes - Cite any external references