

OPTIONAL 0603 PADS C1–C6 (not populated, DNP): the PCM5100A charge pump and supply decoupling at the chip (C1–C3 on the back, across the pin 1–5 tracks; C4–C6 on the front, across the pin 8/9 and 18–20 tracks).
Leave them EMPTY on PicoGUS: the main board already has these parts (C36, C16, C17, C18, C13/C15) next to the DIP-20.
Fit them only if the adapter is used on a board without them (then also tie CPGND, AGND and DGND together).

TSSOP-20 -> DIP-20 300 mil adapter, PicoGUS THT v1.3.2. Use: U9 (PCM5100A) on PicoGUS THT v1.3.2.
Mapping: TSSOP pin n -> DIP pin n for every pin (net names Pn_<pin name>); nothing else in the signal path.
Board: 10.16 x 25.40 mm, 1 mm chamfer at the pin-1 corner = the body outline of the main-board footprint DIP-20_W7.62mm_TSSOP-20_Adapter (it fits that courtyard).
Assembly: solder the TSSOP first. Then fit two 1x10 round machined pin strips from the BOTTOM (insulator under the board), solder them on the top and cut the tails flush. J1 holes 0.85 mm. The round 0.47 mm pins fit machined DIP sockets (On Shore SA203000) and the 1.0 mm main-board holes.
The 0.85 mm holes take round machined pins only (Preci-Dip 350: 0.64 mm tail; Mill-Max 350: 0.46 mm tail).

J1: two 1x10 round machined pin strips (0.47 mm pins, fit machined sockets)
TSSOP pin n = DIP pin n (1:1); DIP pins counter-clockwise from pin 1 (top view)
Board 10.16 x 25.40 mm, FR4 1.6 mm, 2 layers, outline = Chip Quik PA0035C
PicoGUS THT v1.3.2: U9 PCM5100A on the main-board DIP-20 adapter footprint
PicoGUS

Sheet: /
File: TSSOP20-DIP20-300mil.kicad_sch

Title: TSSOP-20 to DIP-20 adapter (U9)

Size: A4	Date: 2026-10-24	**Rev: v1.3.2**
KiCad E.D.A. 10.0.6		Id: 1/1