







U9 stays SMD (TSSOP-20): PCM5100A/5101A/5102A only exist as SMD

Sheet: /PCM5100 audio/
File: audio.kicad_sch

Title: PicoGUS THT - PCM510x DAC

Size: A4 Date: 2026-09-28

KiCad E.D.A. 10.0.6

Rev: v1.3.0


Id: 2/3

WT CONTROL (U10 = 74AHCT126 @ +5V)

Both outputs are pseudo open-drain (A=GND, OE drives) with pull-ups to +3V3, so the daughterboard never sees 5 V on /RESET or MIDI (some DBs have 3.3 V inputs).
/RESET: low while ISA RESET is high. MIDI: same data as the MIDI-out jack (MPU-401 UART).


WAVEBLASTER HEADER

2x13 male header, 2.54 mm. Daughterboard (female socket) sits over the card; footprint has the standard standoff holes.




DGND 1-11, AGND 15-25:
both to the ground plane

WT SUPPLY DECOUPLING (place at J9)





U10 POWER (+5V) + DECOUPLING (place at U10)




WAVETABLE VOLUME + MIXER


RV1 (dual 10k log) sets the WT level; pins 3/6 = CW end (signal), 1/4 = CCW end (GND). U11 sums PCM and WT at unity gain (inverting, 10k/10k) - no level loss, and the WT knob does not change the PCM level. C22/C23 block DC from the DB. R14/R15 keep them discharged when no DB is fitted. Output: 100R, DC-coupled like v1.2.



U11 SUPPLY: ISA +/-12 V (place C28/C29 at U11)



U7 SPARE GATES (74AHC00)



Derived from the hand386 ISA adapter mixer and the PicoGUS 2.0 WT header Waveblaster (wavetable) daughterboard header, analog WT volume and op-amp mixer

Sheet: /Wavetable & line out/
File: wavetable.kicad_sch

Title: PicoGUS THT - Waveblaster header & line-out mixer

Size: A4 Date: 2026-09-28

KiCad E.D.A. 10.0.6

Rev: v1.3.0

Id: 3/3