Measurement-Free Error Correction scheme in Rydberg atoms

Han Wang[1]

[1]HKUST(GZ)

August 21, 2025

Abstract

Logical qubits can be protected from decoherence by performing quantum error correction. Naturally, the QEC algorithm requires feedback process to specific hardware platform which takes more time and cause extra error and the syndrome generation process requires movement of atoms which also takes much time. In our scheme, we intend to develop a measurement-free and movement-free error correction scheme based on Toric code space[1]. With individually addressable, optically trapped, multi-species Rydberg atoms[2], we perform the multiqubit parity gates to generate syndromes and design a error-correction process without measurement feedback.

Keywords. measurement-free error correction · multi-species array · parity-gate · multi-qubit gate · etc

AMS subject classification. 65M70, 65M12

1 Motivation

(i) In order to eliminate the time required for quantum error correction process, we intend to develop a parity-controlled multiqubit gate to perform one-step syndrome mapping from data qubits to ancilla qubit with global pulse sequence without movement of atoms which takes much time.

(ii) After the syndrome generation process, there is a state-flip in the ancilla qubit state if there is an error in data qubits. We will apply another pulse sequence to manipulate a C_2 NOT gate to fix the error qubit. Thus, we do not need to perform measurement on the ancilla qubit.

1.1 Introduction

1.1.1 Necessity of quantum error correction

The required gate error rate for performing useful algorithms is 10^{-10}[3], [4] while the physical gate error rate in neutral-atom array is 10^{-3}[3], [4]. The physical gate error rate is much larger than the required gate error rate for performing useful algorithms. Thus, we need to perform quantum error correction[5], [6], [7] to protect the logical information from decoherence and errors.

1.1.2 Quantum error correction

Nowadays, performing quantum error correction in neutral atom system is attracting much attention because of the scability, reconfigurability, high connectivity[8], and high gate fidelity (over 99.9%) [9], [10] and long coherence time($>$ 1s)[2], [11], [12].

In quantum error correction[1], we first encode the logical qubit into multiple physical qubits. The redundancy can protect the logical information from decoherence and errors. Then, we perform a syndrome generation process and we use a definition called stabilizer which is a set of operators that can be used to detect errors without disturbing the quantum state to generate syndromes. Then, we measure the syndrome and perform the decoding process. Finally, we perform an error-correction process to correct the errored data qubit.

However, the tradition quantum error correction process requires measurement and feedback process which is time-consuming(movement-100μs[2], [13]; illuminating and collecting-500μs[14], [15]) and can introduce extra error(for example, measurement might result in atom loss) [16].

According to this problem, there are many schemes like self-correcting quantum code(using Hamiltonian to confine to the ground state)[17] and Measurement-free error correction scheme[18]. However, the measurement-free error correction scheme in ref.[18] is still time-consuming because it requires moving atoms to entangling zone and perform gate operation one by one in parity check process(The reported gate time is about 1μs[19] and the movement time is about hundreds of μs.[2], [13]).

In this way, we intend to develop a measurement-free error correction scheme based on Toric code space. With individually addressable, optically trapped, multi-species Rydberg atoms, we perform the movement-free multiqubit parity gates to generate syndromes and design a error-correction process without measurement feedback.

2 Model(Overview)

The figure shown below is the measurement-free error correction model in toric code space. There are totally three species of atoms with green and red dots represent ancilla qubits and the blue dots represents the data qubits.



In the model shown above, we intend to perform an parity gate where data qubits are control qubits and the ancilla qubit is the target qubit. If an Z error occurs in the data qubit, the ancilla qubit in corresponding plaquette(red dots) will flip. If an X error occurs in the data qubit the green dots will flip. Then, we intend to perform a C_2NOT gate where the ancilla qubits acts as control qubits, and the errored data qubit is the target qubit. The C_2NOT gate will correct the errored qubit without measuring process.

2.1 Interactions between atoms

In this multi-qubit platform, we intend a strong dipole-dipole interaction between different atom species and weak van der Waals interaction between atoms of the same species. ($V_{\text{dd}} \gg V_{\text{vdws}}$), where interactions between atoms of the same species are negligible. It largely reduces the error caused by undesirable interactions between data qubits and crosstalk between data qubits and ancilla qubits.

2.2 Why using different atom species?

Based on the multi-qubit CNOT_k gate implementation[20], the fidelity is limited by the undesirable interaction between data qubits. Thus, choosing multi-species Rydberg atoms can overcoming these limits by using strong heteronuclear dipole-dipole interactions via Förster resonances for control and target atoms, while the target atoms are coupled by a weaker van der Waals interaction.

Also, the multi-species Rydberg array can avoid the crosstalk between data qubits and ancilla qubits.

2.3 Effective parity check and error-correction

In our assumption, if there is no error, the data qubits and ancilla qubits should keep invariant after applying the pulse sequence.

For example, if there is an error happens in the middle data qubit 5, different error types(X-error or Z-error) will influence different neighboring ancilla qubits. For example, if an Z-error happens in the data qubit 5, the neighboring ancilla qubits b and c will flip their states. Then, the error-correction process will perform a C_2NOT gate on the errored data qubit 5 with the ancilla qubits b and c as control qubits. If the ancilla qubits are in flipped state, the target data qubit can be corrected to the original state. If we assume that the initial state of the ancilla qubits are $|0\rangle$, the target data qubit will be corrected if the ancilla qubits are in state $|1\rangle$:

2.3.1 Parity-check process

Originally, the parity check process can be performed by using four CNOT-gate respectively in one plaquette. For more than one plaquette, the CNOT gate will be performed in order:





Now, we intend to achieve an one-step parity check process in the whole system with a global pulse sequence applied to the whole system. where the data qubits are control qubits and the ancilla qubits are target qubits. However, the direct parity-gate implementation is hard. We intend to equivalently achieve the parity check process through Hadamard gate and multi-qubit gate where the data qubits are acts as target qubits and the ancilla qubits acts as control qubits.



When considering only one plaquette, the Hadamard gate can be applied to all data qubits in the beginning and in the end of the pulse sequence. Then, we perform a CNOT_4 gate with the ancilla qubits as control qubits and the data qubits as target qubits. Finally, we perform another Hadamard gate on all qubits to equivalently achieve the C_4NOT gate.

However, when we consider more than one plaquette,see the figure shown below, there exists an overlapped data qubits 5. In general syndrome generation process, the multi-qubit gate will be performed in order, which means that the overlapped data qubit 5 will be applied control qubit twice. If two ancilla b and c are in state $|1\rangle$, the data qubit 5 will be flipped twice, which means that the data qubit 5 will be flipped back to the original state.



However, in our scheme, we intend to perform the multi-qubit gate with global pulse sequence in one step. Thus, the overlapped data qubit 5 will be controlled by two ancilla qubits at the same time. if both ancilla qubits are in state $|1\rangle$, the data qubit 5 will be flipped once, which means that the global pulse sequence will not achieve the desired parity check process.

In this way, we intend to flip the unflipped data qubit 5 with an external multiqubit gate followed the previous control gate with ancilla qubits as control qubits and overlapped data qubits as target qubits in parallel.

In order to prove the equivalence, we intend to use 8 qubits for simulation:



2.3.2 Simulation of the parity check process

(i) First gate implementation



In the first gate implementation, we take one plaquette as the minimum unit. When the control qubit initially in state $|0\rangle_c$, the Hamiltonian of target qubits is given by:

$$H_1 = \sum_j \Omega_c\big(|r\rangle_j\langle P| + H.c\big) + \Omega_p(t)\big(|P\rangle_j\langle 1| + |P\rangle_j\langle 0| + H.c.\big) + \Delta\ |P\rangle_j\langle P|$$

Under the condition $\Delta \gg \Omega_c, \Omega_p$, the intermediate state $|P\rangle$ can be adiabatically eliminated. Pulse Ω_c is constant and Ω_p is an adiabatic pulse with $\int \Omega_p(t)^2/(2\Delta) = \pi$. The system contains two dark states with

$$|D_1\rangle = \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle)$$

$$|D_2\rangle = \Omega_c/\sqrt{\Omega_c^2 + 2\Omega_p^2}\left[\frac{|0\rangle + |1\rangle}{\sqrt{2}} - \sqrt{2}\Omega_p/\Omega_c\ |r\rangle\right]$$

The initial state of the system is in the random states of $|\Psi\rangle = \alpha|D_1\rangle + \beta|D_2\rangle$, the state will not change after the whole evolution.

However, when the control qubit is in state $|1\rangle_c$, the Hamiltonian of target qubits is given by:

$$H_2 = H_1 + \sum_j V_{\rm dd}\ |r\rangle_j\langle r|$$

because of the strong interaction between control qubit and target qubits. $V > \Omega_c^2/4\Delta$ will break the EIT condition and the target qubits will go flip through Ranman π-pulse.

(ii) Second gate implementation



In the second gate implementation, we take overlapped qubit and neighboring ancilla qubits as the minimum unit. When control qubit initially in state $|1\rangle_c$, the Hamiltonian of target qubits is given by:

$$H_t = \Omega_{\rm t1}(|R\rangle\langle 1| + H.c.) + \Omega_{\rm t2}(|R\rangle\langle 0| + H.c.)$$

There is a state flip on target qubits. However, when the control qubit is in state $|0\rangle_c$, it will be coupled to the Rydberg state $|R\rangle_c$ and the target qubit will not flip because of the Rydberg blockade effect.

(iii) Now comes to the simulation under the pulse sequence including gate 1 and gate 2:



The number of pulses means that the order of the pulse sequence:



In the pulse shown above, pulse Ω_P and Ω_R are designed to perform gate1 (1-3 in energy level diagram) and the pulse Ω_c and Ω_t are designed to perform the gate2(4-6 in energy level diagram).

The simulation results are shown below: When all qubits in state 0:



When initial state is $|01010101>$:



However, when we apply the Hadamard gate on all qubits, the final state cannot return to the original state. The final state is shown below:



Problem: How to determine the minimum simulation unit? If we assume that the minimum unit is one plaquette, the simulation is not accurate because we do not take the overlapped data qubit into consideration.

If we assume that the minimum unit is two plaquettes, the simulation requires too much time

If we assume that the minimum unit is eight qubits shown above, it is hard to analyse the simulation behavior because it does not contains a whole plaquette for us to analyse the simulation behavior.

It is illustrated in ref.[18] that the multi-qubit gates mostly are not suffucient for performing error correction if the fidelity is lower than the threshold of certain codes.

2.4 Changing the minimum simulation unit

In this section, I changed the minimum simulation to a new unit shown below:



If the data qubits and the ancilla qubits initially in state 0, the control pulses 1,3 are useless, the pulse2 and constanct laser Ω_c will not change the state of the data qubits. After this process, pulse 4 will couple the ancilla qubit to the Rydberg state and pulse 5, 6, 7 will be useless. The state of data qubit will keep invariant. Finally, pulse 8 will bring the ancilla qubit back to the ground state 0.



If the data qubits in state 1 and ancilla qubits in state 0, the ancilla qubit will undergo a similar process and the data qubits will stay in state1.



Now, I intend to apply Hadamard gate on all qubits in the beginning and in the end of the pulse sequence to equivalently achieve the parity check process.

The timesequence is shown below:



When we apply the Hadamard gate on all qubits, the system cannot return to the original state:



In order to analyse the cause of the problem, we set adiabatic pulse Ω_p to be zero, and the state population is:



Thus, the main problem lies in the adiabatic pulse Ω_p.

We take a step-by-step check on the pulse sequence, and we take 3-atom system as an example including two ancilla qubits and one data qubit.

(i) initially, the system is in state $|000\rangle$, we apply Hadamard gate on all qubits and we apply the first pulse Ω_r:





In this process, the ancilla qubits are converted from state $|+\rangle$ to state $|A\rangle = \frac{|0\rangle - \mathrm{im} * |r\rangle}{\sqrt{2}}$.

(ii) Then, we apply the second pulse Ω_p and the third pulse Ω_r:

If one of the ancilla is in state $|1\rangle$, the data qubits will achieve a state transition from $|0\rangle \Rightarrow -|1\rangle$ or $|1\rangle \Rightarrow -|0\rangle$.

If the input state is $|+_A +_T +_A\rangle$, the output state will be:

$$
\begin{aligned}
|0_A 0_T 0_A\rangle &\rightarrow |0_A 0_T 0_A\rangle \\
|0_A 0_T 1_A\rangle &\rightarrow -\,|0_A 1_T 1_A\rangle \\
|0_A 1_T 0_A\rangle &\rightarrow |0_A 1_T 0_A\rangle \\
|0_A 1_T 1_A\rangle &\rightarrow -\,|0_A 0_T 1_A\rangle \\
|1_A 0_T 0_A\rangle &\rightarrow -\,|1_A 1_T 0_A\rangle \\
|1_A 0_T 1_A\rangle &\rightarrow -\,|1_A 1_T 1_A\rangle \\
|1_A 1_T 0_A\rangle &\rightarrow -\,|1_A 0_T 0_A\rangle \\
|1_A 1_T 1_A\rangle &\rightarrow -\,|1_A 0_T 1_A\rangle
\end{aligned}
$$

If the input state is $|+_A -_T +_A\rangle$, the output state will be

$$
\begin{aligned}
|0_A 0_T 0_A\rangle &\rightarrow |0_A 0_T 0_A\rangle \\
|0_A 0_T 1_A\rangle &\rightarrow -\,|0_A 1_T 1_A\rangle \\
-|0_A 1_T 0_A\rangle &\rightarrow -\,|0_A 1_T 0_A\rangle \\
-|0_A 1_T 1_A\rangle &\rightarrow |0_A 0_T 1_A\rangle \\
|1_A 0_T 0_A\rangle &\rightarrow -\,|1_A 1_T 0_A\rangle \\
|1_A 0_T 1_A\rangle &\rightarrow -\,|1_A 1_T 1_A\rangle \\
-|1_A 1_T 0_A\rangle &\rightarrow |1_A 0_T 0_A\rangle \\
-|1_A 1_T 1_A\rangle &\rightarrow |1_A 0_T 1_A\rangle
\end{aligned}
$$

(iii) In the C_2NOT gate process, the control pulse Ω_c will bring a phase $-$im*r. The pulse on the data qubits will bring no phase accumulation.

If the input state is $|+_A -_T +_A\rangle$, the output state will be changed.

$$|0_A 0_T 0_A\rangle \to |0_A 0_T 0_A\rangle \to |0_A 0_T 0_A\rangle$$
$$|0_A 0_T 1_A\rangle \to -\,|0_A 1_T 1_A\rangle \to -\,|0_A 1_T 1_A\rangle$$
$$-|0_A 1_T 0_A\rangle \to -\,|0_A 1_T 0_A\rangle \to -\,|0_A 1_T 0_A\rangle$$
$$-|0_A 1_T 1_A\rangle \to |0_A 0_T 1_A\rangle \to |0_A 0_T 1_A\rangle$$
$$|1_A 0_T 0_A\rangle \to -\,|1_A 1_T 0_A\rangle \to -\,|1_A 1_T 0_A\rangle$$
$$|1_A 0_T 1_A\rangle \to -\,|1_A 1_T 1_A\rangle \to -\,|1_A 0_T 1_A\rangle$$
$$-|1_A 1_T 0_A\rangle \to |1_A 0_T 0_A\rangle \to |1_A 0_T 0_A\rangle$$
$$-|1_A 1_T 1_A\rangle \to |1_A 0_T 1_A\rangle \to |1_A 1_T 1_A\rangle$$

If the initial input state is $|+_A +_T +_A\rangle$, the output state will not change;

$$|0_A 0_T 0_A\rangle \to |0_A 0_T 0_A\rangle \to |0_A 0_T 0_A\rangle$$
$$|0_A 0_T 1_A\rangle \to -\,|0_A 1_T 1_A\rangle \to -\,|0_A 1_T 1_A\rangle$$
$$|0_A 1_T 0_A\rangle \to |0_A 1_T 0_A\rangle \to |0_A 1_T 0_A\rangle$$
$$|0_A 1_T 1_A\rangle \to -\,|0_A 0_T 1_A\rangle \to -\,|0_A 0_T 1_A\rangle$$
$$|1_A 0_T 0_A\rangle \to -\,|1_A 1_T 0_A\rangle \to -\,|1_A 1_T 0_A\rangle$$
$$|1_A 0_T 1_A\rangle \to -\,|1_A 1_T 1_A\rangle \to -\,|1_A 0_T 1_A\rangle$$
$$|1_A 1_T 0_A\rangle \to -\,|1_A 0_T 0_A\rangle \to -\,|1_A 0_T 0_A\rangle$$
$$|1_A 1_T 1_A\rangle \to -\,|1_A 0_T 1_A\rangle \to -\,|1_A 1_T 1_A\rangle$$

Now, I changed the pulsesequence, in the second gate process, we achieve another phase accumulation process:



If the input state is $|+_A -_T +_A\rangle$, the output state will be $|+_A -_T +_A\rangle$.



If the input state is $|+_A +_T +_A\rangle$, the output state will be $|-_A +_T -_A\rangle$.



Now, we concentrate on the dark state $|D\rangle = \frac{|0\rangle - |1\rangle}{\sqrt{2}}$. The laser sequence and dynamic results are shown below:







The interaction hamiltonian between control qubit and target qubits is given by:

$$h_{\mathrm{ct}} = C_3(1 - 3\cos^2\theta_{\mathrm{CT}})|r\rangle\langle r| \otimes |R\rangle\langle R|$$

where $C_3 = 2\pi \times 10\ \mathrm{GHz} \cdot \mu m^3$, for target atoms in Rydberg state $|R\rangle$, $C_6 = 2\pi \times 2036\mathrm{GHZ} \cdot \mu m^6$

2.5 Error-correcting C_2NOT gate construction

In this section, we intend to design a multi-qubit C_2NOT gate to correct the error qubit. The two ancilla qubits acts as a control qubit, and the errored data qubit is the target qubit. The model is shown below:



In this C_2NOT gate model, we assume a unbalanced interaction strength similar to the proposed CNOT_4 gate. The ancilla qubits(green dots) are control qubits and the errored data qubit(blue dot) is the target qubit. The interaction strength satisfies $V_{\text{dd}} \gg V_{\text{vdws}}$, where interactions between atoms of the same species are negligible. The pulse sequence is also shown from (i) to (v). All the pulses can be implemented with square pulse. The gate operation can be understood as follows:

(i) The control qubits are initially in the ground state $|0\rangle_c$. The first π-pulse (i) can couple it to the Rydberg state $|c\rangle_c$ and the target qubit is unchanged due to the strong dipole-dipole interactions.

(ii) The control qubits are initially in state $|1\rangle_c$. The first π-pulse (i) cannot couple the control qubits. Thus, the target qubit can be switched between state $|0\rangle_t$ and $|1\rangle_t$ through pulse sequence (ii) to (iv). The effect of the error-correction process:

$$
\begin{aligned}
|0_A 0_A 0_T\rangle &\to |0_A 0_A 0_T\rangle \\
|0_A 0_A 1_T\rangle &\to |0_A 0_A 1_T\rangle \\
|0_A 1_A 0_T\rangle &\to |0_A 1_A 0_T\rangle \\
|0_A 1_A 1_T\rangle &\to |0_A 1_A 1_T\rangle \\
|1_A 0_A 0_T\rangle &\to |1_A 0_A 0_T\rangle \\
|1_A 0_A 1_T\rangle &\to |1_A 0_A 1_T\rangle \\
|1_A 1_A 0_T\rangle &\to |1_A 1_A 1_T\rangle \\
|1_A 1_A 1_T\rangle &\to |1_A 1_A 0_T\rangle
\end{aligned}
$$

3 Literature Review

(i) Construction of multi-qubit CNOT_k gate through EIT:[21], through optimization of the pulse[22], through adiabatic pulse design[20], [23] and experimental realization:[24], [25]; Parity gate construction through specially designed interaction strength[26].

(ii) Measurement-free fault-tolerant quantum error correction:[18]

(iii) Mid-circuit correction of correlated phase errors using an array of spectator qubits[27]

(iv) mesoscopic Rydberg gate based on EIT:[23]. Experimental realization:[24], [25]

(v) There is a scheme familiar to this work in one plaquette.[20]

Bibliography

[1] O. O. Khalifa, N. Amirah Bt Sharif, R. A. Saeed, S. Abdel-Khalek, A. N. Alharbi, and A. A. Alkathiri, "Digital System Design for Quantum Error Correction Codes," *Contrast Media & Molecular Imaging*, vol. 2021, p. 1101911, 2021, doi: 10.1155/2021/1101911.

[2] D. Bluvstein *et al.*, "Logical quantum processor based on reconfigurable atom arrays," *Nature*, vol. 626, no. 7997, pp. 58–65, Dec. 2023, doi: 10.1038/s41586-023-06927-3.

[3] C. Gidney and M. Ekerå, "How to factor 2048 bit RSA integers in 8 hours using 20 million noisy qubits," *Quantum*, vol. 5, p. 433, Apr. 2021, doi: 10.22331/q-2021-04-15-433.

[4] B. W. Reichardt *et al.*, "Fault-tolerant quantum computation with a neutral atom processor." [Online]. Available: https://arxiv.org/abs/2411.11822

[5] P. W. Shor, “Fault-tolerant quantum computation.” [Online]. Available: https://arxiv.org/abs/quant-ph/9605011

[6] *Proceedings of the Royal Society of London. Series A: Mathematical, Physical and Engineering Sciences*, vol. 452, no. 1954, pp. 2551–2577, Nov. 1996, doi: 10.1098/rspa.1996.0136.

[7] E. Dennis, A. Kitaev, A. Landahl, and J. Preskill, “Topological quantum memory,” *Journal of Mathematical Physics*, vol. 43, no. 9, pp. 4452–4505, Sep. 2002, doi: 10.1063/1.1499754.

[8] I. Cong, H. Levine, A. Keesling, D. Bluvstein, S.-T. Wang, and M. D. Lukin, “Hardware-Efficient, Fault-Tolerant Quantum Computation with Rydberg Atoms.” [Online]. Available: https://arxiv.org/abs/2105.13501

[9] S. J. Evered *et al.*, “High-fidelity parallel entangling gates on a neutral-atom quantum computer,” *Nature*, vol. 622, no. 7982, pp. 268–272, Oct. 2023, doi: 10.1038/s41586-023-06481-y.

[10] M. Xue, S. Xu, X. Li, and X. Li, “High-fidelity and robust controlled-<mml:math xmlns:mml="http://www.w3.org/1998/Math/MathML"><mml:mi>Z</mml:mi></mml:math> gates implemented with Rydberg atoms via echoing rapid adiabatic passage,” *Physical Review A*, vol. 110, no. 3, Sep. 2024, doi: 10.1103/physreva.110.032619.

[11] J. Z. Ludmir, Y. Huo, N. S. DiBrita, and T. Patel, “Modeling and Simulating Rydberg Atom Quantum Computers for Hardware-Software Co-design with PachinQo.” [Online]. Available: https://arxiv.org/abs/2412.07181

[12] K. Wintersperger *et al.*, “Neutral atom quantum computing hardware: performance and end-user perspective,” *EPJ Quantum Technology*, vol. 10, no. 1, Aug. 2023, doi: 10.1140/epjqt/s40507-023-00190-1.

[13] D. Bluvstein *et al.*, “A quantum processor based on coherent transport of entangled atom arrays,” *Nature*, vol. 604, no. 7906, pp. 451–456, Apr. 2022, doi: 10.1038/s41586-022-04592-6.

[14] M. A. Norcia *et al.*, “Midcircuit Qubit Measurement and Rearrangement in a <mml:math xmlns:mml="http://www.w3.org/1998/Math/MathML" display="inline"><mml:mrow><mml:mmultiscripts><mml:mrow><mml:mi>Yb</mml:mi></mml:mrow><mml:mprescripts/><mml:none/><mml:mrow><mml:mn>171</mml:mn></mml:mrow></mml:mmultiscripts></mml:mrow></mml:math> Atomic Array,” *Physical Review X*, vol. 13, no. 4, Nov. 2023, doi: 10.1103/physrevx.13.041034.

[15] T. M. Graham *et al.*, “Midcircuit Measurements on a Single-Species Neutral Alkali Atom Quantum Processor,” *Physical Review X*, vol. 13, no. 4, Dec. 2023, doi: 10.1103/physrevx.13.041051.

[16] I. I. Beterov and M. Saffman, “Rydberg blockade, Förster resonances, and quantum state measurements with different atomic species,” *Phys. Rev. A*, vol. 92, no. 4, p. 42710, Oct. 2015, doi: 10.1103/PhysRevA.92.042710.

[17] B. Yoshida, "Feasibility of self-correcting quantum memory and thermal stability of topological order," *Annals of Physics*, vol. 326, no. 10, pp. 2566–2633, Oct. 2011, doi: 10.1016/j.aop.2011.06.001.

[18] S. Heußen, D. F. Locher, and M. Müller, "Measurement-Free Fault-Tolerant Quantum Error Correction in Near-Term Devices," *PRX Quantum*, vol. 5, no. 1, Feb. 2024, doi: 10.1103/prxquantum.5.010333.

[19] H. Levine *et al.*, "High-Fidelity Control and Entanglement of Rydberg-Atom Qubits," *Physical Review Letters*, vol. 121, no. 12, Sep. 2018, doi: 10.1103/physrevlett.121.123603.

[20] A. M. Farouk, I. I. Beterov, P. Xu, S. Bergamini, and I. I. Ryabtsev, "Parallel Implementation of CNOTN and C2NOT2 Gates via Homonuclear and Heteronuclear Förster Interactions of Rydberg Atoms," *Photonics*, vol. 10, no. 11, 2023, doi: 10.3390/photonics10111280.

[21] J. M. Auger, S. Bergamini, and D. E. Browne, "Blueprint for fault-tolerant quantum computation with Rydberg atoms," *Phys. Rev. A*, vol. 96, no. 5, p. 52320, Nov. 2017, doi: 10.1103/PhysRevA.96.052320.

[22] J. Kazemi, M. Schuler, C. Ertler, and W. Lechner, "Multi-Qubit Parity Gates for Rydberg Atoms in Various Configurations." [Online]. Available: https://arxiv.org/abs/2506.09686

[23] C. Dlaska, K. Ender, G. B. Mbeng, A. Kruckenhauser, W. Lechner, and R. van Bijnen, "Quantum Optimization via Four-Body Rydberg Gates," *Phys. Rev. Lett.*, vol. 128, no. 12, p. 120503, Mar. 2022, doi: 10.1103/PhysRevLett.128.120503.

[24] C.-Y. Guo, L.-L. Yan, S. Zhang, S.-L. Su, and W. Li, "Optimized geometric quantum computation with a mesoscopic ensemble of Rydberg atoms," *Phys. Rev. A*, vol. 102, no. 4, p. 42607, Oct. 2020, doi: 10.1103/PhysRevA.102.042607.

[25] K. McDonnell, L. F. Keary, and J. D. Pritchard, "Demonstration of a Quantum Gate Using Electromagnetically Induced Transparency," *Phys. Rev. Lett.*, vol. 129, no. 20, p. 200501, Nov. 2022, doi: 10.1103/PhysRevLett.129.200501.

[26] F. Q. Guo, S. L. Su, W. Li, and X. Q. Shao, "Parity-controlled gate in a two-dimensional neutral-atom array." [Online]. Available: https://arxiv.org/abs/2405.19564

[27] K. Singh, C. E. Bradley, S. Anand, V. Ramesh, R. White, and H. Bernien, "Mid-circuit correction of correlated phase errors using an array of spectator qubits," *Science*, vol. 380, no. 6651, pp. 1265–1269, 2023, doi: 10.1126/science.ade5337.