

Decentralized Stability Certificates in IBR-Dominated Grids

The Role of the Network State

Zhimeng Wang¹, Sushobhan Chatterjee¹, Sijia Geng¹, Richard Pates², Enrique Mallada¹

¹Department of Electrical and Computer Engineering, Johns Hopkins University


²Department of Automatic Control, Lund University, Sweden

PowerUp 2026

September 9, 2026




Motivation



Conventional grids


- Centralized, dispatchable generation
- Inherent inertial response
- Stronger voltage support



IBR-rich grids

- Distributed, variable generation
- Control-based frequency responses
- Control-dependent voltage support

Oscillation Events Involving IBRs



Source: NREL, Shahil Shah

[TPWRS 23] Cheng et al., "Real-World Sub-synchronous Oscillation Events in Power Grids With High Penetrations of Inverter-Based Resources," IEEE TPWRS 2023


IBR-related Subsynchronous Oscillations

- **When do SSOs occur?**
 - **Weak grids** (e.g. high impedance with GFLs)
 - **Clusters of IBRs in electrically remote areas**
 - Following controller, topology, or operating-point changes
- **What do SSOs depend on?**
 - **Network structure:** line parameters, topology
 - **Control configuration:** GFL vs GFM, PLL dynamics, outer/plant controllers,
 - **Operating point:** voltage setpoints, generation dispatch, the resulting power flow patterns


Broader goal: Scalable assessment of IBR-related small-signal stability under changing grid conditions.

Conventional Impedance-Based Stability Analysis

- Impedance models **can capture SSOs**
 - At the Point of Interconnection, stability can be analyzed by comparing inverter and grid impedances.
 - **Nyquist loop-gain criterion** $L(s) = \frac{Z_{grid}(s)}{Z_{IBR}(s)}$ explains why weak grids (high Z_{grid}) are more prone to instability.




$$V_{PCC}(s) = \frac{1}{1 + \frac{Z_{grid}(s)}{Z_{IBR}(s)}} V_{grid}(s).$$



Challenges of Impedance Stability Analysis


- Z_{IBR}^i depends on:
 - Vendor technology
 - Setpoints (P_i, Q_i)
- Z_{grid}^i depends on:
 - Network topology
 - Power flows (P_{net}, Q_{net})
 - Other connected devices



$$Z_{grid}^i(s) \neq Z_{grid}^j(s)$$

Robust, Decentralized, Small-Signal Analysis

- **Goal:** Develop small-signal stability analysis methods that account for **IBR dynamics & network operating conditions**.
- **A useful framework should:**
 - Support device-level assessment using *local* models or measurements
 - *Explicitly* account for network structure and operating point
 - Identify certified stable operating regions for controller tuning and dispatch



Related Literature

Work	Coordinates	Operating Conditions	Info Requirements	Other Properties
[1]	dq-voltage and current: $v^{d/q}, i^{d/q}$	$\theta_i \approx \theta_j, v_i \approx v_j $, or implicit	local	IQC based
[2]	real power and freq: P, ω	decoupled power flows	local	IQC adjacent, exploits model structure
[3], [4]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	passivity, Port Hamiltonian, microgrids
[5]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	general IBR models, line dynamics
[6]	dq-voltage and current $v^{d/q}, i^{d/q}$	$\theta_i \approx \theta_j, v_i \approx v_j $	local	passivity based
[7]	real power and phases: P, θ	$\theta_i \approx \theta_j, v_i \approx v_j $	local	diagonalization, line dynamics
[8]	power and polar voltages: P, Q, v , θ	decoupled power flows	local	IQC adjacent, exploits model structure
[9]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	gain and phase, line dynamics
[10]	power and polar voltages: P, Q, v , θ	$\theta_i \approx \theta_j$	local	passivity + FVT, line dynamics
[11]	dq-voltage and current: $v^{d/q}, i^{d/q}$	implicit	distributed	DW Shells

[1] Vorobev, P., Chevalier, S., and Turitsyn, K., *Decentralized Stability Rules for Microgrids*, IEEE ACC, 2019.

[2] Pates, R., and Mallada, E., *Robust Scale-Free Synthesis for Frequency Control in Power Systems*, IEEE Transactions on Control of Network Systems, 2019.

[3] Farokhian Firuzi, M., Roosta, A., and Gitizadeh, M., *Stability Analysis and Decentralized Control of Inverter-Based AC Microgrids*, Protection and Control of Modern Power Systems, 2019.

[4] Nandanoori, S. P., et al., *Distributed Small-Signal Stability Conditions for Inverter-Based Unbalanced Microgrids*, IEEE Transactions on Power Systems, 2020.

[5] Huang, L., Xin, H., and Dörfler, F., *H ∞ Control of Grid-Connected Converters: Design, Objectives, and Decentralized Stability Certificates*, IEEE Transactions on Smart Grid, 2020.

[6] Watson, J. D., and Lestas, I. Control of interlinking converters in hybrid ac/dc grids: Network stability and scalability. IEEE Transactions on Power Systems, 2020.

[7] Groß, D., *Compensating Network Dynamics in Grid-Forming Control*, IEEE Allerton Conference on Communication, Control, and Computing, 2022.

[8] Siahhaan, Z., Mallada, E., and Geng, S., *Decentralized Stability Criteria for Grid-Forming Control in Inverter-Based Power Systems*, IEEE PES General Meeting, 2024.

[9] Huang, L., et al., *Gain and Phase: Decentralized Stability Conditions for Power Electronics-Dominated Power Systems*, IEEE Transactions on Power Systems, 2024.

[10] Häberle, V., et al., *Decentralized Parametric Stability Certificates for Grid-Forming Converter Control*, arXiv:2503.05403, 2025.

[11] Huang, L., et al., *Geometric Decentralized Stability Certificate for Power Systems Based on Projecting DW Shells*, arXiv:2508.17033, 2025.

Related Literature

Work	Coordinates	Operating Conditions	Info Requirements	Other Properties
[1]	dq-voltage and current: $v^{d/q}, i^{d/q}$	$\theta_i \approx \theta_j, v_i \approx v_j $, or implicit	local	IQC based
[2]	real power and freq: P, ω	decoupled power flows	local	IQC adjacent, exploits model structure
[3], [4]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	passivity, Port Hamiltonian, microgrids
[5]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	general IBR models, line dynamics
[6]	dq-voltage and current $v^{d/q}, i^{d/q}$	$\theta_i \approx \theta_j, v_i \approx v_j $	local	passivity based
[7]	real power and phases: P, θ	$\theta_i \approx \theta_j, v_i \approx v_j $	local	diagonalization, line dynamics
[8]	power and polar voltages: P, Q, v , θ	decoupled power flows	local	IQC adjacent, exploits model structure
[9]	dq-voltage and current $v^{d/q}, i^{d/q}$	implicit	distributed	gain and phase, line dynamics
[10]	power and polar voltages: P, Q, v , θ	$\theta_i \approx \theta_j$	local	passivity + FVT, line dynamics
[11]	dq-voltage and current: $v^{d/q}, i^{d/q}$	implicit	distributed	DW Shells
this work + [12]*	power and polar voltages: P, Q, v , θ	explicit	local	passivity based

[1] Vorobev, P., Chevalier, S., and Turitsyn, K., *Decentralized Stability Rules for Microgrids*, IEEE ACC, 2019.

[2] Pates, R., and Mallada, E., *Robust Scale-Free Synthesis for Frequency Control in Power Systems*, IEEE Transactions on Control of Network Systems, 2019.

[3] Farokhian Firuzi, M., Roosta, A., and Gitizadeh, M., *Stability Analysis and Decentralized Control of Inverter-Based AC Microgrids*, Protection and Control of Modern Power Systems, 2019.

[4] Nandanoori, S. P., et al., *Distributed Small-Signal Stability Conditions for Inverter-Based Unbalanced Microgrids*, IEEE Transactions on Power Systems, 2020.

[5] Huang, L., Xin, H., and Dörfler, F., *H[∞] Control of Grid-Connected Converters: Design, Objectives, and Decentralized Stability Certificates*, IEEE Transactions on Smart Grid, 2020.

[6] Watson, J. D., and Lestas, I. Control of interlinking converters in hybrid ac/dc grids: Network stability and scalability. IEEE Transactions on Power Systems, 2020.

[7] Groß, D., *Compensating Network Dynamics in Grid-Forming Control*, IEEE Allerton Conference on Communication, Control, and Computing, 2022.

[8] Siahaan, Z., Mallada, E., and Geng, S., *Decentralized Stability Criteria for Grid-Forming Control in Inverter-Based Power Systems*, IEEE PES General Meeting, 2024.

[9] Huang, L., et al., *Gain and Phase: Decentralized Stability Conditions for Power Electronics-Dominated Power Systems*, IEEE Transactions on Power Systems, 2024.

[10] Häberle, V., et al., *Decentralized Parametric Stability Certificates for Grid-Forming Converter Control*, arXiv:2503.05403, 2025.


[11] Huang, L., et al., *Geometric Decentralized Stability Certificate for Power Systems Based on Projecting DW Shells*, arXiv:2508.17033, 2025.

[12] J. Niehues, R. Delabays, A. Büttner, and F. Hellmann, *Small-signal stability of power systems with voltage droop*, IEEE Trans. Power Systems, 2025.

Port-based Network Model


- **IBR Model:** $G_i(s)$

- GFM converter with filtered droop control
- Fast inner-loop dynamics are neglected
- Linearized power and log-polar voltage coordinates: $\Delta P_i, \Delta Q_i, \Delta \ln|v_i|, \Delta \theta_i$




- **Transmission System:** $N_e(s)$, $e: = \{i, j\}$

- Lossless inductive lines $b_e = 1/L_e\omega_0$
- Linearized power and log-polar voltage coordinates: $\Delta P_{ij/ji}, \Delta Q_{ij/ji}, \Delta \ln|v_{i/j}|, \Delta \theta_{i/j}$
- Electromagnetic transients neglected



Network Interconnection: $G(s) \#_M N_E(s)$



State-aware Decentralized Stability Certificate

Theorem (Main result)

The feedback interconnection $G(s) \#_M N_E(s)$ is internally stable if the following holds:

For each line $e = \{i, j\} \in E$, there exists d_e such that

$$\left(2 \frac{d_e}{b_e |v_i| |v_j|} - \frac{2}{\cos \theta_{ij}}\right) \sqrt{\left(\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|}\right)^2 + 4} + \left(\frac{d_e}{b_e |v_i| |v_j|}\right)^2 - \frac{2}{\cos \theta_{ij}} \frac{d_e}{b_e |v_i| |v_j|} + 4 \geq 0,$$

where $\sum_{e: i \in e} d_e = \frac{1}{k_{q,i}}$.

(line-wise inequalities with bus-wise allocation)

Understanding Stability Certificates

- Main theorem requires

$$\left(2 \frac{d_e}{b_e |v_i| |v_j|} - \frac{2}{\cos \theta_{ij}}\right) \sqrt{\left(\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|}\right)^2 + 4} + \left(\frac{d_e}{b_e |v_i| |v_j|}\right)^2 - \frac{2}{\cos \theta_{ij}} \frac{d_e}{b_e |v_i| |v_j|} + 4 \geq 0.$$


- Two key quantities
 - Normalized **reactive power imbalance**

$$\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|} = \frac{|v_i|}{|v_j|} - \frac{|v_j|}{|v_i|}.$$

- **Line loading**

$$\cos \theta_{ij} = \sqrt{1 - \left(\frac{P_{ij}}{b_e |v_i| |v_j|}\right)^2}$$

- Key take-away:
 - Larger voltage imbalance and heavier line loading require more conservative reactive droop gains.



Understanding Stability Certificates

- Two key *detrimental* quantities
 - Normalized *reactive power imbalance*

$$\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|} = \frac{|v_i|}{|v_j|} - \frac{|v_j|}{|v_i|}$$


- Line loading*

$$\cos \theta_{ij} = \sqrt{1 - \left(\frac{P_{ij}}{b_e |v_i| |v_j|} \right)^2}$$

- Simplifying assumptions:

- a. **Equal terminal voltages**

$$|v_i| = |v_j| \Rightarrow \max(k_{q,i}, k_{q,j}) < \frac{\cos \theta_{ij}}{2(1 - \cos \theta_{ij}) b_e |v_i| |v_j|}$$



Understanding Stability Certificates

- Two key *detrimental* quantities
 - Normalized *reactive power imbalance*

$$\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|} = \frac{|v_i|}{|v_j|} - \frac{|v_j|}{|v_i|}.$$

- Line loading*

$$\cos \theta_{ij} = \sqrt{1 - \left(\frac{P_{ij}}{b_e |v_i| |v_j|} \right)^2}$$

- Simplifying assumptions:

- a. **Equal terminal voltages**


$$|v_i| = |v_j| \Rightarrow \max(k_{q,i}, k_{q,j}) < \frac{\cos \theta_{ij}}{2(1 - \cos \theta_{ij}) b_e |v_i| |v_j|}.$$

- b. **Small phase differences**

$$\cos \theta_{ij} = 1 \Rightarrow \max(k_{q,i}, k_{q,j}) < f(|Q_{ij} - Q_{ji}|).$$

- a. + b. **Zero power flows** $\max(k_{q,i}, k_{q,j}) < \infty$.

- Zero power flow o.p.:** certificate satisfied for any finite k_q .
- Other o.p.:** *line loading* and *voltage imbalance* impose a finite, state-dependent gain limit.




Proof Sketch of Main Result

- **Step 1:** Change voltage coordinates

$$\Delta \ln |v| \rightarrow \Delta \ln \dot{|v|}$$

leading to loop transformation:

$$(i) \quad G(s) \#_M N_E(s) \rightarrow G'(s) \#_M \frac{1}{s} J_E$$



$$N_e(s) = J_e \text{diag}\left(\frac{1}{s}, 1, \frac{1}{s}, 1\right)$$

Proof Sketch of Main Result

- **Step 1:** Change voltage coordinates

$$\Delta \ln |v| \rightarrow \Delta \ln \dot{|v|}$$

leading to loop transformation:

$$(i) \quad G(s) \#_M N_E(s) \rightarrow G'(s) \#_M \frac{1}{s} J_E$$

- **Step 2:** Loop transform to compensate lack of passivity of J_e s.t.


$$J_e + D_e \succeq 0$$

leading to loop transformation:

$$(ii) \quad G'(s) \#_M \frac{1}{s} J_E \rightarrow \hat{G}(s) \#_M \hat{N}_E(s)$$

$$G'_i(s) = \begin{bmatrix} \frac{k_{p,i}}{\tau_{\omega,i}s+1} & 0 \\ 0 & \frac{k_{q,i}s}{\tau_{v,i}s+1} \end{bmatrix}$$

$$G'(s) = \text{blockdiag}(G'_i(s))$$



$$J_E = \text{blockdiag}(J_e)$$

$$J_e := b_e |v_i| |v_j| \begin{bmatrix} \cos \theta_{ij} & \sin \theta_{ij} & -\cos \theta_{ij} & \sin \theta_{ij} \\ \sin \theta_{ij} & 2 \frac{|v_i|}{|v_j|} - \cos \theta_{ij} & -\sin \theta_{ij} & -\cos \theta_{ij} \\ -\cos \theta_{ij} & -\sin \theta_{ij} & \cos \theta_{ij} & -\sin \theta_{ij} \\ \sin \theta_{ij} & -\cos \theta_{ij} & -\sin \theta_{ij} & 2 \frac{|v_j|}{|v_i|} - \cos \theta_{ij} \end{bmatrix}$$

linearized power flows

Proof Sketch of Main Result

- **Step 1:** Change voltage coordinates

$$\Delta \ln |v| \rightarrow \Delta \ln \dot{|v|}$$

leading to loop transformation:

$$(i) \quad G(s) \#_M N_E(s) \rightarrow G'(s) \#_M \frac{1}{s} J_E$$

- **Step 2:** Loop transform to compensate lack of passivity of J_e s.t.

$$J_e + D_e \succeq 0$$

leading to loop transformation:


$$(ii) \quad G'(s) \#_M \frac{1}{s} J_E \rightarrow \hat{G}(s) \#_M \hat{N}_E(s)$$

- **Step 3:** Int. Stab. of $\hat{G}(s) \#_M \hat{N}_E(s)$

- **Step 4:** Connect back to original system

$$\hat{G}(s) \#_M \hat{N}(s) \xrightarrow{\text{I.S.}} G'(s) \#_M \frac{1}{s} J_E \xrightarrow{\text{I.S.}} G(s) \#_M N_E(s)$$


$$G'_i(s) = \begin{bmatrix} \frac{k_{p,i}}{\tau_{\omega,i}s+1} & 0 \\ 0 & \frac{k_{q,i}s}{\tau_{v,i}s+1} \end{bmatrix}$$



$$D_E = \text{blockdiag}(D_e) \quad D_e = \begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & d_e & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & d_e \end{bmatrix}$$



Numerical Illustration

- Operating point: $\cos \theta_{ij} = 0.92$, $\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|} = 0.059$.
- Control gains: ★ $(k_{q,i}, k_{q,j}) = (0.3, 0.3)$ ☆ $(k_{q,i}, k_{q,j}) = (1.1, 1.0)$



Numerical Illustration

- Operating point: $\cos \theta_{ij} = 0.92$, $\frac{Q_{ij} - Q_{ji}}{b_e |v_i| |v_j|} = 0.059$.
- Control gains: ★ $(k_{q,i}, k_{q,j}) = (0.3, 0.3)$ ☆ $(k_{q,i}, k_{q,j}) = (1.1, 1.0)$



Summary

Conclusions

- We derived **decentralized stability conditions** that account for the **role of the network state** in small signal stability.
- The resulting stability certificates are **local**, linking controller tuning directly to measurable network quantities.
- Analysis makes explicit the **importance of line loading** and **reactive power mismatch** on stability conditions and tighten admissible voltage-droop gains.
- Stability certificates can be **readily integrated in dispatch** and enable **state-aware IBR tuning**.

Extensions and Future Work

- Broader models: Networks with heterogeneous R/X ratios, heterogeneous GFM/GFL dynamics
- Beyond stability: Performance specification
- Operational integration: Stability-constrained dispatch