Quantum Neural Networks

Theory, Architectures, and Applications

1 Background

Classical machine learning has gained huge success in recent years especially deep learning models such as multi-layer perceptrons (MLP), Convolution Neural Networks (CNN), Recurrent Neural Netowrks (RNN), Transformers, and Graph Neural Netowrks (GNN). These architectures, due to its inductive bias and with development of hardware accelerators, have been applied in many fieds such as image processing, audio-speech processing, language modeling, and fraud detection. However, as the models are getting larger and larger, the computing power required is also growing exponentially. Governments and private companies are spending billions of dollar on building data center to satisfy the compute needs of now.

On the other hand, a new paradigm of computing started to shine on the stage – quantum computing.

2 Classical Neural Networks

3 Quantum Neural Networks

3.1 Basics of Quantum Computing

If we have multiple qubits, let's say N qubits. Each qubit, individually is operated by a quantum gate $U_1, U_2, \cdots, U_N$. Then the operation matrix on the entire quantum state is

$$U = U_1 \otimes U_2 \otimes U_3 \otimes \cdots \otimes U_N$$

CNOT gate is an interesting gate that takes 2 qubits as input. Its main purpose is to produce conditional independence between these 2 qubits. In these 2 qubits, one is target and the other is control. The logic is:

$$|c, t\rangle \xrightarrow{\text{CNOT}} |c, t \oplus c\rangle$$

That is flipping the target qubit if the control qubit is 1, otherwise do nothing. For example, if we let q_0 be the target and q_1 be the control and we use little-endian format $|q_1 q_0\rangle$.

$$\begin{aligned}
|00\rangle &\to |00\rangle \\
|01\rangle &\to |01\rangle \\
|10\rangle &\to |11\rangle \\
|11\rangle &\to |10\rangle
\end{aligned}$$

The operation matrix of CNOT gate is therefore:

$$CNOT_{q_1 \to q_0} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix}$$

For example,

$$CNOT_{q_1 \to q_0} |10\rangle = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \begin{bmatrix} 0 \\ 0 \\ 1 \\ 0 \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ 0 \\ 1 \end{bmatrix} = |11\rangle$$

Please be aware that if q_0 is the control and q_1 is the target, then

$$CNOT_{q_0 \to q_1} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix}$$

For example,

$$CNOT_{q_0 \to q_1} |01\rangle = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \times \begin{bmatrix} 0 \\ 1 \\ 0 \\ 0 \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ 0 \\ 1 \end{bmatrix} = |11\rangle$$

Then, how is entanglment produced using CNOT gate? In Figure 1, we have two qubits, both in $|0\rangle$ as initial state. Then, one of them undergo Hadmard operation, which makes the state become:

$$|\psi\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |01\rangle)$$

After applying a CNOT gate on these 2 qubits, we have:

$$CNOT_{q_0 \to q_1} |\psi\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

Now, these 2 qubits are entangled! This means that if we know the state of one of the qubits, we immediately know the state of the other without measuring it.

Rule of thumb. For a two-qubit syste:




Figure 1: How entanglment is produced in bell state

$$|\psi_1\psi_0\rangle = a\,|00\rangle + b\,|01\rangle + c\,|10\rangle + |11\rangle$$

The quickest way to check if these two qubits are entangled is:

$$\begin{cases} ad - bc \neq 0, & \text{entangled} \\ ad - bc = 0, & \text{product state/non-entangled} \end{cases} \tag{3.1}$$

3.2 Dissection of QNN

Similar to classical neural networks, quantum neural networks (QNN) also tries to universally approximate functions but in a foundamental different way. Figure 2 shows a **3-qubit** circuit architecture of a standard quantum neural networks. Simply speaking, it is composed of layers of rotation gate (X,Y,Z) and CNOT gate. In the end, the each wire has a measurement gate (usually Z-basis). Let's look at each gate one by one. Firstly, there are three types of




Figure 2: A standard quantum neural network

rotation gate R_x, R_y, R_z. Any single-qubit gate is a 2×2 unitary matrix and these three matrices, variants of Pauli-matrices, rotates the vector in the bloch sphere about x, y, z axis by θ degrees. Their mathmatical definition is as follows:

$$R_x(\theta) \equiv e^{-i\theta X/2} = \cos(\frac{\theta}{2})I - i\sin(\frac{\theta}{2})X = \begin{bmatrix} \cos(\frac{\theta}{2}) & -i\sin(\frac{\theta}{2}) \\ -i\sin(\frac{\theta}{2}) & \cos(\frac{\theta}{2}) \end{bmatrix}. \tag{3.2}$$

$$R_y(\theta) \equiv e^{-i\theta Y/2} = \cos(\frac{\theta}{2})I - i\sin(\frac{\theta}{2})Y = \begin{bmatrix} \cos(\frac{\theta}{2}) & -\sin(\frac{\theta}{2}) \\ \sin(\frac{\theta}{2}) & \cos(\frac{\theta}{2}) \end{bmatrix}. \tag{3.3}$$

$$R_z(\theta) \equiv e^{-i\theta Z/2} = \cos(\frac{\theta}{2})I - i\sin(\frac{\theta}{2})Z = \begin{bmatrix} e^{-i\theta/2} & 0 \\ 0 & e^{i\theta/2} \end{bmatrix}. \tag{3.4}$$

Controlled-NOT (CNOT) gate has two input qubits, known as control qubit and target qubit, respectively. In terms of the computational basis, the action of CNOT is given by $|c\rangle |t\rangle \rightarrow |c\rangle |t \oplus c\rangle$. That is if the control qubit is set to $|1\rangle$ then the target qubit is flipped, otherwise the target qubit is left alone. Thus, in the computational basis $|contro, target\rangle$ the matrix representation of CNOT is:

$$\begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix}.$$

For example, if a two-qubit system is in state $|11\rangle$, which in basis vector is $\begin{bmatrix}0\\0\\0\\1\end{bmatrix}$. Here we follow little-endian (LSB)convention ($|q_1 q_0\rangle$) and let $|q_0\rangle$ be the control qubit and $|q_1\rangle$ be the target qubit. When a CNOT gate is applied to it:

$$\begin{bmatrix}1&0&0&0\\0&0&0&1\\0&0&1&0\\0&1&0&0\end{bmatrix} \times \begin{bmatrix}0\\0\\0\\1\end{bmatrix} = \begin{bmatrix}0\\1\\0\\0\end{bmatrix} = |01\rangle$$

$$CNOT\,|11\rangle \rightarrow |01\rangle$$

These three rotation gates and CNOT gate are also known universal gates in quantum computer, similar to NOR and NAND in classical computer. Any unitary matrix can be decomposed to sequenec of rotation gates and CNOT gate. Similar to classical neural network, quantum neural network also has input, hidden and output layers, which corresponds to encoding, rotation and entanglment in Hilbert Space, and measurement. Let's look at them one by one.

3.3 Input Layer: Encoding

For most of machine learning tasks, the data is classical. Therefore, we need a way to encode the classical data into quantum states. Three main encoding approaches are:

1. **Amplitude Encoding**
2. **Basis Encoding**
3. **Angular Encoding**

Of course, there are other more advanced encoding such as Pauli Encoding and IQP Encoding but it's not in the scope of this article. Here, we first talk about the most common encoding method - **Angular Encoding** because it's the easiest to prepare from engineering perspective. Just as the name suggests, the classical data x_i is mapped into a rotation angle using rotation gates. Figure 3 shows how a 3-dimension input vector is embedded into a quantum circuit. Each qubit, represented by a single line here, starts with 0 basis state $|0\rangle$. Then qubit is followed by a rotation gate (can be R_x, R_y, R_z). These rotation gates will then be parametrized by the input values x_1, x_2, x_3. For example, for the first qubit (little-endian), the starting state is $|0\rangle = \begin{bmatrix}1\\0\end{bmatrix}$. Then the rotation gate, let's say R_x, is parametrized by x_1:

$$R_x(x_1) = \begin{bmatrix}\cos(\frac{x_1}{2}) & -i\sin(\frac{x_1}{2})\\ -i\sin(\frac{x_1}{2}) & \cos(\frac{x_1}{2})\end{bmatrix}.$$

Then the qubit is operated as:

$$R_x(x_1)\,|0\rangle = \begin{bmatrix}\cos(\frac{x_1}{2}) & -i\sin(\frac{x_1}{2})\\ -i\sin(\frac{x_1}{2}) & \cos(\frac{x_1}{2})\end{bmatrix} \times \begin{bmatrix}1\\0\end{bmatrix} = \begin{bmatrix}\cos(\frac{x_1}{2})\\ -i\sin(\frac{x_1}{2})\end{bmatrix}$$

This is equivalent to:

$$|0\rangle \rightarrow \cos(\frac{x_1}{2})\,|0\rangle + (-i\sin(\frac{x_1}{2}))\,|1\rangle$$

If you use R_y, then you will have:

$$R_y(x_1)\,|0\rangle = \begin{bmatrix} \cos(\frac{x_1}{2}) & -\sin(\frac{x_1}{2}) \\ \sin(\frac{x_1}{2}) & \cos(\frac{x_1}{2}) \end{bmatrix} \times \begin{bmatrix} 1 \\ 0 \end{bmatrix} = \begin{bmatrix} \cos(\frac{x_1}{2}) \\ \sin(\frac{x_1}{2}) \end{bmatrix}$$

Similarly, for the rest of input values x_2, x_3, x_4, the quantum states of the qubits become (assume we use R_x):

$$q_1(x_2) = \begin{bmatrix} \cos(\frac{x_2}{2}) \\ -i\sin(\frac{x_2}{2}) \end{bmatrix}, \quad q_2(x_3) = \begin{bmatrix} \cos(\frac{x_3}{2}) \\ -i\sin(\frac{x_3}{2}) \end{bmatrix}$$




Figure 3: Input layer of a QNN using angluar encoding.

If we look at the 3-qubit system holistically, which is also known as product state, the state transitions from $|000\rangle$ to $|q_2q_1q_0\rangle$. Mathmatically as follows:

$$\begin{bmatrix} 1 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \end{bmatrix} \xrightarrow{\text{angle encoding}} \begin{bmatrix} \cos(\frac{x_3}{2}) \\ -i\sin(\frac{x_3}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{x_2}{2}) \\ -i\sin(\frac{x_2}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{x_1}{2}) \\ -i\sin(\frac{x_1}{2}) \end{bmatrix}$$

This is equivalent to:

$$|q_2q_1q_0\rangle = |q_2\rangle \otimes |q_1\rangle \otimes |q_0\rangle$$

The statevector of entire circuit can be rewritten into tensor product of statevector of each single qubit becuase entanglement has not yet formed.

The tensor product of three 2×1 vectors is a 8×1 vector, which is expanded as follows:

$$\psi(x_3, x_2, x_1) = \begin{bmatrix} \cos(\frac{x_3}{2})\cos(\frac{x_2}{2})\cos(\frac{x_1}{2}) \\ -i\cos(\frac{x_3}{2})\cos(\frac{x_2}{2})\sin(\frac{x_1}{2}) \\ -i\cos(\frac{x_3}{2})\sin(\frac{x_2}{2})\cos(\frac{x_1}{2}) \\ -\cos(\frac{x_3}{2})\sin(\frac{x_2}{2})\sin(\frac{x_1}{2}) \\ -i\sin(\frac{x_3}{2})\cos(\frac{x_2}{2})\cos(\frac{x_1}{2}) \\ -\sin(\frac{x_3}{2})\cos(\frac{x_2}{2})\sin(\frac{x_1}{2}) \\ -\sin(\frac{x_3}{2})\sin(\frac{x_2}{2})\cos(\frac{x_1}{2}) \\ i\sin(\frac{x_3}{2})\sin(\frac{x_2}{2})\sin(\frac{x_1}{2}) \end{bmatrix}$$

If we look each qubit individually, the encoding is a 2×2 matrix. However, if we look the encoding holistically on the entire 3 qubit system, it's a $2^3 \times 2^3 = 8 \times 8$ matrix, which is also a tensor product of all three rotation matrices:

$$\begin{bmatrix} \cos(\frac{x_3}{2}) & -i\sin(\frac{x_3}{2}) \\ -i\sin(\frac{x_3}{2}) & \cos(\frac{x_3}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{x_2}{2}) & -i\sin(\frac{x_2}{2}) \\ -i\sin(\frac{x_2}{2}) & \cos(\frac{x_2}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{x_1}{2}) & -i\sin(\frac{x_1}{2}) \\ -i\sin(\frac{x_1}{2}) & \cos(\frac{x_1}{2}) \end{bmatrix}$$

This makes sense becuase with 3 qubits, the quantum state is in $\mathbb{C}^2 \otimes \mathbb{C}^2 \otimes \mathbb{C}^2 = \mathbb{C}^8$ and the operation shall also be a 8×8 matrix as follows. To make it readable, let's define:

$$c_j = \cos\left(\frac{x_j}{2}\right), \qquad s_j = \sin\left(\frac{x_j}{2}\right), \qquad j = 1, 2, 3, 4.$$

$$U = R_x(x_3) \otimes R_x(x_2) \otimes R_x(x_1)$$

The matrix is as follows:

$$\begin{bmatrix} c_3c_2c_1 & -ic_3c_2s_1 & -ic_3s_2c_1 & -c_3s_2s_1 & -is_3c_2c_1 & -s_3c_2s_1 & -s_3s_2c_1 & is_3s_2s_1 \\ -ic_3c_2s_1 & c_3c_2c_1 & -c_3s_2s_1 & -ic_3s_2c_1 & -s_3c_2s_1 & -is_3c_2c_1 & is_3s_2s_1 & -s_3s_2c_1 \\ -ic_3s_2c_1 & -c_3s_2s_1 & c_3c_2c_1 & -ic_3c_2s_1 & -s_3s_2c_1 & is_3s_2s_1 & -is_3c_2c_1 & -s_3c_2s_1 \\ -c_3s_2s_1 & -ic_3s_2c_1 & -ic_3c_2s_1 & c_3c_2c_1 & is_3s_2s_1 & -s_3s_2c_1 & -s_3c_2s_1 & -is_3c_2c_1 \\ -is_3c_2c_1 & -s_3c_2s_1 & -s_3s_2c_1 & is_3s_2s_1 & c_3c_2c_1 & -ic_3c_2s_1 & -ic_3s_2c_1 & -c_3s_2s_1 \\ -s_3c_2s_1 & -is_3c_2c_1 & is_3s_2s_1 & -s_3s_2c_1 & -ic_3c_2s_1 & c_3c_2c_1 & -c_3s_2s_1 & -ic_3s_2c_1 \\ -s_3s_2c_1 & is_3s_2s_1 & -is_3c_2c_1 & -s_3c_2s_1 & -ic_3s_2c_1 & -c_3s_2s_1 & c_3c_2c_1 & -ic_3c_2s_1 \\ is_3s_2s_1 & -s_3s_2c_1 & -s_3c_2s_1 & -is_3c_2c_1 & -c_3s_2s_1 & -ic_3s_2c_1 & -ic_3c_2s_1 & c_3c_2c_1 \end{bmatrix} \tag{3.5}$$

Please be aware that since we use little-endian convention, the tensor product of operation matrix follows the same order as the qubit. If our initial state is $|0\rangle$, then the resulting state is the first column of this matrix. In fact, the matrix is

$$U_{\mathbf{b},\mathbf{b}'} = (-i)^{d_H(\mathbf{b},\mathbf{b}')} \prod_{j:b_j=b'_j} c_j \prod_{j:b_j\neq b'_j} s_j$$

where $d_H(\mathbf{b}, \mathbf{b}')$ is Hamming distance between target state and initial state.
Before concluding angle encoding, there is one more thing - **scaling**. As you might have observed, the trignometric functions are all periodic (2π) meaning that

$$|\psi(x)\rangle = |\psi(x + 2\pi)\rangle$$

If the range of classical data is larger than 2π, then two different classical values will be mapped to the same quantum state, causing information loss. Therefore, scaling must be conducted such that the input values, before encoding, must be between 0 and π. This is becuase the periodicity of cosine and sine functions are 2π, so the periodicity in $\cos(\frac{x}{2})$ is π. A simple and most common way to do scaling is as follows:

$$\theta = \pi \frac{x - x_{min}}{x_{max} - x_{min}}$$

Now, the features are mapped into a non-repeatitive and continuous angle space. Finally, there are many variants of angle encoding such as XYZ encoding, data-reuploading, multiscale, and adaptive encoding. What has to be aware of is that encoding can have notrivial impact on the representation capacity of the model.

3.4 Hidden Layer - Rotation

Now, after angle encoding, each qubit is in the state

$$|\psi\rangle \cos(\frac{x_i}{2}) |0\rangle + (-i \sin(\frac{x_i}{2})) |1\rangle = \begin{bmatrix} \cos(\frac{x_1}{2}) \\ -i \sin(\frac{x_1}{2}) \end{bmatrix}.$$

Then, this qubit will go through another rotation gate, let's say R_x, which is parametrized by θ, resembling the weight in classical neural networks. The state becomes:

$$R_x(\theta) |\psi\rangle = \begin{bmatrix} \cos(\frac{\theta}{2}) & -i \sin(\frac{\theta}{2}) \\ -i \sin(\frac{\theta}{2}) & \cos(\frac{\theta}{2}) \end{bmatrix} \times \begin{bmatrix} \cos(\frac{x_i}{2}) \\ -i \sin(\frac{x_i}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{\theta}{2}) \cos(\frac{x_i}{2}) - \sin(\frac{\theta}{2}) \sin(\frac{x_i}{2}) \\ -i \sin(\frac{\theta}{2}) \cos(\frac{x_i}{2}) - i \cos(\frac{\theta}{2}) \sin(\frac{x_i}{2}) \end{bmatrix}$$

Using following trignometric identity, we can further simplify.

$$\cos(A + B) = \cos(A) \cos(B) - \sin(A) \sin(B)$$
$$\sin(A + B) = \sin(A) \cos(B) + \cos(A) \sin(B)$$

$$\begin{bmatrix} \cos(\frac{\theta}{2}) \cos(\frac{x_i}{2}) - \sin(\frac{\theta}{2}) \sin(\frac{x_i}{2}) \\ -i \sin(\frac{\theta}{2}) \cos(\frac{x_i}{2}) - i \cos(\frac{\theta}{2}) \sin(\frac{x_i}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{\theta + x_i}{2}) \\ -i \sin(\frac{\theta + x_i}{2}) \end{bmatrix}$$

For example, in Figure 4, the first qubit becomes:

$$|q_0\rangle = \begin{bmatrix} \cos(\frac{\theta_1 + x_1}{2}) \\ -i \sin(\frac{\theta_1 + x_1}{2}) \end{bmatrix}.$$

For the rest of qubits, the states becomes:

$$q_1 = \begin{bmatrix} \cos(\frac{\theta_2 + x_2}{2}) \\ -i \sin(\frac{\theta_2 + x_2}{2}) \end{bmatrix}, \quad q_2 = \begin{bmatrix} \cos(\frac{\theta_3 + x_3}{2}) \\ -i \sin(\frac{\theta_3 + x_3}{2}) \end{bmatrix}$$

The entire 3-qubit system then becomes the tensor product of these four vectors:

$$\psi_{q_3q_2q_1} = \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_2+x_2}{2}) \\ -i\sin(\frac{\theta_2+x_2}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix}$$

Which can be expaned as:

$$\begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} \tag{3.6}$$

Similarily, the operation matrix on these 3-qubits system is also the tensor product of these three 2×2 matrices:

$$U_{hidden} = \begin{bmatrix} \cos(\frac{\theta_3}{2}) & -i\sin(\frac{\theta_3}{2}) \\ -i\sin(\frac{\theta_3}{2}) & \cos(\frac{\theta_3}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_2}{2}) & -i\sin(\frac{\theta_2}{2}) \\ -i\sin(\frac{\theta_2}{2}) & \cos(\frac{\theta_2}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_1}{2}) & -i\sin(\frac{\theta_1}{2}) \\ -i\sin(\frac{\theta_1}{2}) & \cos(\frac{\theta_1}{2}) \end{bmatrix}$$

Similarily, if we define:

$$c_j = \cos(\frac{\theta_j}{2}), \quad s_j = \sin(\frac{\theta_j}{2}), \quad j = 1, 2, 3, 4$$

Then, this 8×8 matrix is the same as Eq. (3.5)




Figure 4: First hidden layer of rotation gates

3.5 Hidden Layer - Entanglement

What's getting more interesting is the CNOT gate in the next layer. If we only apply rotation gates on each qubit separately, there is no interactions between qubits. CNOT gate allows

interactions between qubits so that information can be passed across qubits instead of just staying at only a single qubit. A good analogy is that in classical neural networks, each neuron takes all the neurons in the previous layer as inputs, if we assume fully-connected layers.

Although we have a 3-qubit system, but let's look at the first two qubits q_0, q_1. In Figure 5, after encoding layer and first rotation layer, the state of each qubit is:

$$\begin{aligned} |q_0\rangle &= \cos(\frac{\theta_1 + x_1}{2}) |0\rangle + (-i \sin(\frac{\theta_1 + x_1}{2})) |1\rangle \\ |q_1\rangle &= \cos(\frac{\theta_2 + x_2}{2}) |0\rangle + (-i \sin(\frac{\theta_2 + x_2}{2})) |1\rangle \end{aligned} \tag{3.7}$$




Figure 5: CNOT gate layer on two qubits after rotation gates

The state of entire system is:

$$|q_1 q_0\rangle = \begin{bmatrix} \cos(\frac{\theta_1+x_1}{2}) \cos(\frac{\theta_2+x_2}{2}) \\ -i \cos(\frac{\theta_2+x_2}{2}) \sin(\frac{\theta_1+x_1}{2}) \\ -i \cos(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \\ -\sin(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \end{bmatrix} \tag{3.8}$$

If we apply a CNOT gate on these two qubits, then we have:

$$CNOT\,|q_1 q_0\rangle = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \times \begin{bmatrix} \cos(\frac{\theta_1+x_1}{2}) \cos(\frac{\theta_2+x_2}{2}) \\ -i \cos(\frac{\theta_2+x_2}{2}) \sin(\frac{\theta_1+x_1}{2}) \\ -i \cos(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \\ -\sin(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{\theta_1+x_1}{2}) \cos(\frac{\theta_2+x_2}{2}) \\ -\sin(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \\ -i \cos(\frac{\theta_1+x_1}{2}) \sin(\frac{\theta_2+x_2}{2}) \\ -i \cos(\frac{\theta_2+x_2}{2}) \sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} \tag{3.9}$$

As you might observe, the second element and the fourth element of state vector got swapped. Now, these two qubits are entangled! This means that the system cannot be rewriten into a tensor product of two single qubit anymore. You can easily verify this by yourself using Eq. 3.1.

$$CNOT\,|q_1 q_0\rangle \neq |q_1\rangle \otimes |q_0\rangle$$

Now, if take the third qubit into consideration and look at the entire system, the operation matrix is:

$$U_{entangle} = I \otimes CNOT_{q_0 \to q_1} \tag{3.10}$$

where I is 2×2 identity matrix. To expand, we have

$$
\begin{aligned}
U_{entangle} &= \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \otimes \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \\
&= \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \end{bmatrix}
\end{aligned}
\tag{3.11}
$$




Figure 6: Entanglement layer in QNN

Then, we can apply this matrix 3.11 on the statevector we derived from Eq 3.6:

$$
\begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \end{bmatrix} \times \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix}
\tag{3.12}
$$

Please notice that the original order $(1, 2, 3, 4, \quad 5, 6, 7, 8)$ becomes $(1, 4, 3, 2, \quad 5, 8, 7, 6)$. For every "subgroup", the second and fourth element are swapped.
Then, as Figure 6 shows, we apply CNOT gate on the second and third qubits q_1, q_2, the

operation matrix is:

$$U_{entangle} = CNOT_{q_1 \to q_2} \otimes I$$

$$= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \otimes \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \end{bmatrix}$$

Then, we apply this matrix on the statevector:

$$\begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \end{bmatrix} \times \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} \tag{3.13}$$

If you look carefully, What happens is that compare with Eq. 3.12, swapping happens as follows:

$$3 \leftrightarrow 7, \quad 4 \leftrightarrow 8$$

As you might observe, you can apply a CNOT gate on any of the two qubits (e.g., q_0, q_2) and CNOT gates are essentially just permutation matrix that induces a permutation of amplitude in statevector. The magic is that all these four qubits are entangled meaning the statevector is not simply a tensor product of four single-qubit statevector:

$$|q_2 q_1 q_0\rangle \neq |q_2\rangle \otimes |q_1\rangle \otimes |q_0\rangle$$

3.6 Information Propogation through CNOT Gates

The importance of CNOT gate is allowing information be propogatied from control qubit to target qubit, if we measure in Z-basis. Let's look at a 2-qubit system first. Previously, we have derived states of 2-qubit system in Eq. 3.8 that after a layer of encoding and rotation.

The probability of observing $q_1 = 0$ is as follows.

$$\begin{aligned} \text{Let} \quad \alpha = \frac{x_1 + \theta_1}{2}, \quad \beta = \frac{x_2 + \theta_2}{2} \\ P(|q_1\rangle = |0\rangle) &= \cos^2(\alpha)\cos^2(\beta) + \cos^2(\beta)\sin^2(\alpha) \\ &= \cos^2(\beta)(\cos^2(\alpha) + \sin^2(\alpha)) \\ &= \cos^2(\beta) = \cos(\frac{x_2 + \theta_2}{2}) \end{aligned} \tag{3.14}$$

As you can see, the probability of each state in q_1 is a function of $x2$ and θ_2:

$$P(|q_1\rangle = |0\rangle) = f(x_2, \theta_2)$$

However, after a CNOT gate, the statevector becomes Eq. 3.9. The The probability of observing $q_1 = 0$ becomes as follwoing.

$$\begin{aligned} P(|q_1\rangle = |0\rangle) &= \cos^2(\alpha)\cos^2(\alpha) + \sin^2(\alpha)\sin^2(\beta) \\ &= \cos^2(\frac{x_1 + \theta_1}{2})\cos^2(\frac{x_2 + \theta_2}{2}) + \sin^2(\frac{x_1 + \theta_1}{2})\sin^2(\frac{x_2 + \theta_2}{2}) \\ &= f(x_1, x_2, \theta_1, \theta_2) \end{aligned} \tag{3.15}$$

Now, as you can see, the probability amplitude of q_1 becomes a function of $x_1, x_2, \theta_1, \theta_2$! The information from q_0, the first qubit, both input value x_1 and parameters θ_1 are passed down to q_1. This gives the circuits much greater expressivity. However, another thing to notice is that the probability of q_0 does not change before or after CNOT gate.

$$P(|q_0\rangle = |0\rangle) = \cos^2(\frac{\theta_1 + x_1}{2}) \tag{3.16}$$

Intrestingly, the infomration did not pass from target to control. However, this is given we measure in Z-basis. Measurement in other basis will lead to different sitautions.
Again, if we compare with classical neural networks, it's a function of all the input values as Eq. 3.17 shows. This is also knonw as fully connected layers. If the output of a classical Nueral Networks is function of only a single input x_i, it will not be able learn the latent structure of the data, significantly harming the expressivity. The entanglement layer tries to do the similar thing.

$$\begin{aligned} f_{NN} &= f(\sigma(W^T X + b)) \\ &= f(\sigma(\sum_{n=1}^{N} w_n x_n + b)) \\ &= f(x_1, x_2, \cdots, x_N, W) \end{aligned} \tag{3.17}$$

Now, let's look at the 3-qubit system. Before the entanglment layer, the probability of observing the fourth qubit $|q_2\rangle = |0\rangle$ can be derived from Eq. 3.6 as follows:

$$\begin{aligned}
\text{Let} \alpha_j &= \frac{x_j + \theta_j}{2}, \quad j = 1, 2, 3 \\
P(q_2 = 0) &= |\psi_{000}|^2 + |\psi_{001}|^2 + |\psi_{010}|^2 + |\psi_{011}|^2 \\
&= \cos^2(\alpha_3)\cos^2(\alpha_2)\cos^2(\alpha_1) + \cos^2(\alpha_3)\cos^2(\alpha_2)\sin^2(\alpha_1) \\
&+ \cos^2(\alpha_3)\sin^2(\alpha_2)\cos^2(\alpha_1) + \cos^2(\alpha_3)\sin^2(\alpha_2)\sin^2(\alpha_1) \\
&= \cos^2(\alpha_3)[\cos^2(\alpha_2)(\cos^2(\alpha_1) + \sin^2(\alpha_1)) + \sin^2(\alpha_2)(\cos^2(\alpha_1) + \sin^2(\alpha_1))] \\
&= \cos^2(\alpha_3) \\
&= \cos^2(\frac{\theta_3 + x_3}{2})
\end{aligned} \tag{3.18}$$

As you can see, without CNOT (entanglement) layer, regardless how many rotation gate you add to the third qubit q_2 (this also applied to other qubits), the probability amplitude for each qubit is just a function of its encoding input x_3 and the parameters of the rotation gate in its own path θ_3. Mathmatically, it's $P(q_2 = 0) = f(\theta_3, x_3)$ The information will never be propagated across the lines. However, after the first entanglement layer, according to Eq. 3.13, the the probability amplitude of $|q_3\rangle = |0\rangle$ becomes as follows:

$$\begin{aligned}
P(q_2 = 0) &= \cos^2(\alpha_3)\cos^2(\alpha_2)\cos^2(\alpha_1) + \cos^2(\alpha_3)\sin^2(\alpha_2)\sin^2(\alpha_1) \\
&+ \sin^2(\alpha_3)\sin^2(\alpha_2)\cos^2(\alpha_1) + \sin^2(\alpha_3)\cos^2(\alpha_2)\sin^2(\alpha_1) \\
&= \cos^2(\alpha_3)[\cos^2(\alpha_2)\cos^2(\alpha_1) + \sin^2(\alpha_2)\sin^2(\alpha_1)] \\
&+ \sin^2(\alpha_3)[\sin^2(\alpha_2)\cos^2(\alpha_1) + \cos^2(\alpha_2)\sin^2(\alpha_1)] \\
&= \frac{\cos^2(\alpha_3)}{2}[1 + \cos(2\alpha_2)\cos(2\alpha_1)] + \frac{\cos^2(\alpha_3)}{2}[1 - \cos(2\alpha_2)\cos(2\alpha_1)] \\
&= \frac{1}{2}[1 + \cos(2\alpha_3)\cos(2\alpha_2)\cos(2\alpha_1)] \\
&= \frac{1}{2}[1 + \cos(\theta_3 + x_3)\cos(\theta_2 + x_2)\cos(\theta_1 + x_1)] \\
&= \frac{1}{2}[1 + \prod_{j=1}^{3}\cos(\theta_j + x_j)]
\end{aligned} \tag{3.19}$$

If we look back at, it's clear that

$$\begin{aligned}
P_{\text{before}}(q_2 = 0) &= \cos^2(\frac{\theta_3 + x_3}{2}) \\
P_{\text{after}}(q_2 = 0) &= \frac{1}{2}[1 + \prod_{j=1}^{3}\cos(\theta_j + x_j)]
\end{aligned} \tag{3.20}$$

Now, you can clearly see what magic the entanglment layer has done. If you measure q_3 before entanglment, its probability amplitude is determined by only θ_4, x_4 whereas after entanglment it's determined by all the inputs and parameters. As said before, after entanglment, the statevector cannot be rewritten into tensor product of statevector of each single qubit.

Therefore, all the computation after this point will be holistic, meaning that we need to do $(2^n \times 2^n) \times (2^n \times 1)$ matrix-vector calculation at each layer, which is a big challenge for classical computer. Imagine if you have 30 qubits, the dimension is 1,073,741,924. None of the CPUs, GPUs, or TPUs has enough RAM to do this calculation. However, it can be easily done by a qunatum computer, in fact IBM machines such as Nighthawk or Heron family offer 120 qubits and this number will be increasing in the next couple of years. In terms of large matrix calculation, the quantum advantage is clear.
Alright, let's keep watching how this quantum neural network evolve. As Figure 7 shows, another rotation layer is applied after entanglement layer, as the second hidden layer. The rotation gates are parametrized as $\theta_4, \theta_5, \theta_6$ respectively. The operation matrix of this layer




Figure 7: Quantum Neural Network with 2 hidden layers

is then:

$$
\begin{aligned}
U_{hidden} &= R_x(\theta_6) \otimes R_x(\theta_5) \otimes R_x(\theta_4) \\
&= \begin{bmatrix} \cos(\frac{\theta_6}{2}) & -i\sin(\frac{\theta_6}{2}) \\ -i\sin(\frac{\theta_6}{2}) & \cos(\frac{\theta_6}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_5}{2}) & -i\sin(\frac{\theta_5}{2}) \\ -i\sin(\frac{\theta_5}{2}) & \cos(\frac{\theta_5}{2}) \end{bmatrix} \otimes \begin{bmatrix} \cos(\frac{\theta_4}{2}) & -i\sin(\frac{\theta_4}{2}) \\ -i\sin(\frac{\theta_4}{2}) & \cos(\frac{\theta_4}{2}) \end{bmatrix} \\
&= \begin{bmatrix}
c_6c_5c_4 & -ic_6c_5s_4 & -ic_6s_5c_4 & -c_6s_5s_4 & -is_6c_5c_4 & -s_6c_5s_4 & -s_6s_5c_4 & is_6s_5s_4 \\
-ic_6c_5s_4 & c_6c_5c_4 & -c_6s_5s_4 & -ic_6s_5c_4 & -s_6c_5s_4 & -is_6c_5c_4 & is_6s_5s_4 & -s_6s_5c_4 \\
-ic_6s_5c_4 & -c_6s_5s_4 & c_6c_5c_4 & -ic_6c_5s_4 & -s_6s_5c_4 & is_6s_5s_4 & -is_6c_5c_4 & -s_6c_5s_4 \\
-c_6s_5s_4 & -ic_6s_5c_4 & -ic_6c_5s_4 & c_6c_5c_4 & is_6s_5s_4 & -s_6s_5c_4 & -s_6c_5s_4 & -is_6c_5c_4 \\
-is_6c_5c_4 & -s_6c_5s_4 & -s_6s_5c_4 & is_6s_5s_4 & c_6c_5c_4 & -ic_6c_5s_4 & -ic_6s_5c_4 & -c_6s_5s_4 \\
-s_6c_5s_4 & -is_6c_5c_4 & is_6s_5s_4 & -s_6s_5c_4 & -ic_6c_5s_4 & c_6c_5c_4 & -c_6s_5s_4 & -ic_6s_5c_4 \\
-s_6s_5c_4 & is_6s_5s_4 & -is_6c_5c_4 & -s_6c_5s_4 & -ic_6s_5c_4 & -c_6s_5s_4 & c_6c_5c_4 & -ic_6c_5s_4 \\
is_6s_5s_4 & -s_6s_5c_4 & -s_6c_5s_4 & -is_6c_5c_4 & -c_6s_5s_4 & -ic_6s_5c_4 & -ic_6c_5s_4 & c_6c_5c_4
\end{bmatrix}
\end{aligned}
$$

The new statevector becomes:

$$U_{hidden} \times \begin{bmatrix} \cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\sin(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ i\sin(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\sin(\frac{\theta_2+x_2}{2})\cos(\frac{\theta_1+x_1}{2}) \\ -i\cos(\frac{\theta_3+x_3}{2})\cos(\frac{\theta_2+x_2}{2})\sin(\frac{\theta_1+x_1}{2}) \end{bmatrix} \tag{3.21}$$

Firstly, let's define:

$$\begin{aligned} C_1 &= \cos(\frac{\theta_1+x_1}{2}), \quad S_1 = \sin(\frac{\theta_1+x_1}{2}) \\ C_2 &= \cos(\frac{\theta_2+x_2}{2}), \quad S_2 = \sin(\frac{\theta_2+x_2}{2}) \\ C_3 &= \cos(\frac{\theta_3+\theta_6+x_3}{2}), \quad S_3 = \sin(\frac{\theta_3+\theta_6+x_3}{2}) \\ c_j &= \cos(\frac{\theta_j}{2}), \quad s_j = \sin(\frac{\theta_j}{2}) \end{aligned}$$

$$|q_2q_1q_0\rangle = \begin{bmatrix} C_3c_5(c_4C_2C_1 + is_4S_2S_1) + S_3s_5(ic_4S_2C_1 + s_4C_2S_1) \\ C_3c_5(-is_4C_2C_1 - c_4S_2S_1) + S_3s_5(s_4S_2C_1 + ic_4C_2S_1) \\ C_3s_5(-ic_4C_2C_1 + s_4S_2S_1) + S_3c_5(-c_4S_2C_1 + is_4C_2S_1) \\ C_3s_5(-s_4C_2C_1 + ic_4S_2S_1) + S_3c_5(is_4S_2C_1 - c_4C_2S_1) \\ S_3c_5(-ic_4C_2C_1 + s_4S_2S_1) + C_3s_5(-c_4S_2C_1 + is_4C_2S_1) \\ S_3c_5(-s_4C_2C_1 + ic_4S_2S_1) + C_3s_5(is_4S_2C_1 - c_4C_2S_1) \\ S_3s_5(-c_4C_2C_1 - is_4S_2S_1) + C_3c_5(-ic_4S_2C_1 - s_4C_2S_1) \\ S_3s_5(is_4C_2C_1 + c_4S_2S_1) + C_3c_5(-s_4S_2C_1 - ic_4C_2S_1) \end{bmatrix} \tag{3.22}$$

3.7 Output Layer: Measurement

4 Fourier Analysis of Quanutm Neural Networks and Expressivity

4.1 Basics of Fourier Series and Fourier Transform

4.2 Quantum Neural Network as a Partial Fourer Series

4.3 Expressivity