


MINI-UNIVERSE

User Manual



Thank you for purchasing the MINI-UNIVERSE. This pedal is a pure-digital product, it provides 9 types of reverbs. It's like a big universe inside this machine. We do our best to develop this pedal, I hope you like it.

II.Attentions

The power supply:

Please use 9V(+ -10%) adapter (negative inside and positive outside), otherwise it may cause equipment damage. Please unplug the power when not in use or during thunderstorm weather.

The connection:

Be sure to turn off the power of related equipment before connecting or disconnecting the device.

The electrical interference:


The electromagnetic wave of radio, television and other equipment may cause interference to the equipment, so please try to stay away from radio , television and other equipment.

The location:

To avoid deformation, discoloration, or other serious damage, do not expose this unit to the following conditions:

- a.Heat sources
- b.Magnetic fields
- c.Sunlight
- d.High temperature or moist district
- e.Excessively dusty or dirty locations
- f.Strong vibrations or shocks

- This product is a compact metal appearance design.
- There are 9 reverbs in total, it can be adapted to a variety of music.
- MINI-UNIVERSE will let you get warm and natural timbre, also it has dynamic response.
- High performance digital signal processor, to provide you with a nuanced sound.



①Power jack:

Please use 9V DC adapter (negative inside and positive outside).

②USB jack:

Support power supply, suggest to use 5V 1A adapter.

③DECAY knob:

Adjust the duration of echo.

④TYPE knob:

Select different reverb by dialing this knob, there are 9 gears, please look the Timbre introduction.

⑤MIX knob:

Adjust the ratio of wet and dry.

⑥PARAM1 knob:

in different timbre, the function of the knob is not exactly the same, please see the Timbre introduction.

⑦PARAM2 knob:

Please see the Timbre introduction.

⑧PARAM3 knob:

Please see the Timbre introduction.

⑨Output jack:

1/4" MONO audio output jack.

⑩LED:

The LED lights up when the effect pedal is enabled, or goes out in bypass mode.

⑪Input jack:

1/4" MONO audio input jack.

⑫Footswitch:

Enable/bypass the MINI-UNIVERSE by tap the footswitch.

IV. Timbre introduction

EN

GEAR1: ROOM reverb simulates a relatively small, simple- structured room sound where many reflections are absorbed by soft material in the room, and sound is reflected by walls.

PARAM1: HIGH pass, only used to regulate wet sound.

PARAM2: LOW pass, only used to regulate wet sound.

PARAM3: DRIFT, the pitch of wet sound produces as small cyclical rise and fall, you will hear vintage and charming background sound.

GEAR2: HALL reverb gives a wide, slightly scattering feeling, it simulates a grand ambient sound.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: DRIFT.

GEAR3: PLATE reverb is a reverb created in a large metal container, this is a very bright and powerful sound.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: DRIFT.

GEAR4: SPRING is a common type of reverberation. The sound signal is transmitted to the spring tank, and the pickup picks up the resonant sound of

the spring tank, to mimics the reverberation effect produced in space.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: DWELL, control the number of springs.

GEAR5: SHIMMER, there is a pitch-shift sound in the wet sound. Adjust the pitch of the pitch-shift sound, you can get the dissonant interval, create a scary background sound. You also can get the harmonic interval, it's a wonderful sound, a resplendent and unearthly ambience. The Amount param allow for a range of shimmer effects from laid-back and subtle to full-blown majestic splendor.

PARAM1: HIGH pass.

PARAM2: PITCH, Adjust the pitch of the pitch-shift sound, the minimum value is the same as the original sound, the maximum value is two octaves above the original sound.

PARAM3: AMOUNT, adjust the amount of pitch-shift sound.

GEAR6: CLOUD reverb is a gorgeous large ambient reverberation, it sounds like the music come from all sides of the cloud. Cloud reverb can take any modest guitar or synth sound and turn it into a gorgeous ensemble.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: DIFFUSION, softens the early reflections to create a more diffused reverb. As Diffusion is increased the reverb is smoothed and softened, the delay and reverberation mix together more naturally.

GEAR7: BLOOM reverb, more diffusion blocks were added to reverbs to smooth out the sound. A side effect of this was the tendency of the reverbs to have a slowly building envelope that "bloomed", experiment with short Decay times and higher Length values, and then longer Decay times with lower length values to get a feel for how these two portions of the reverb interact and complement each other.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: LENGTH, adjusts the length of the "bloom" portion, higher levels will result in longer bloom times.

GEAR8: SWELL reverb, the Swell machine brings in the reverb gradually behind the dry signal for subtle evolving textures, like having a volume pedal on the wet sound.

PARAM1: HIGH pass.

PARAM2: LOW pass.

PARAM3: RISETIME,adjusts the rise time of the swelled signal, I suggest you choose shorter times for single-line soloing or longer times for ambient chord work.

GEAR9: LOFI reverb,LOFI means low-fidelity, it is a mystical, profound,especial sound, a charming sense of nostalgia and unique white noise, it is suitable for vintage music.

PARAM1: SAMPLE RATE,only used to regulate wet sound.

PARAM2: WHITE NOISE.

PARAM3: DRIFT.

V. Technical parameter

EN

Input	Standard 1/4 " jack-MONO/TS
Output	Standard 1/4 " jack-MONO/TS
Power supply 1	DC9V $\geq$ 300mA 
Power supply 2	USB 5V $\geq$ 300mA
Size	112(L)X68(W)X40(H)mm
Weight	About 236g

Disclaimer: Specifications are subject to change without notice.

★ Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement

The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located for operating in conjunction with any other antenna or transmitter.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.

感谢您购买我司产品，MINI-UNIVERSE是一款功能强大的数字建模混响效果器，仿佛在效果器里装了一个大大的宇宙，提供不可比拟的深度和空间感的顶级混响效果，为您带来极具音乐灵感的混响体验。我们尽最大的努力为您提供这块高品质的效果器，希望您能喜欢它。

二.注意事项

■ 电源供应：

请使用正确的电源适配器，适配器使用内负外正的9V电源，否则可能会导致设备损坏。在不需要使用本设备或雷雨天气时请拔下电源。

■ 连接：

当连接或断开设备前，请先关闭其他相关设备。

■ 电器干扰：


收音机、电视机等电磁波可能会对设备使用造成干扰，因此请尽量远离收音机和电视机等设备。

■ 放置场所：

为防止变形、变色和其他方面等对产品造成损坏，请避免以下情况：

- a. 热源
- b. 磁场
- c. 阳光直射
- d. 高温潮湿
- e. 多尘或不洁地方
- f. 强烈震荡或摇晃

- 简洁、高档的金属外观设计。
- 一共9种混响音色，适用于大部分音乐风格和乐器。
- MINI-UNIVERSE会让你得到温暖、自然的音色，而且它有良好的动态响应。
- 高性能数字信号处理器，细致入微的混响声音。



- ①**电源接口**：使用9V直流变压器（外正内负）。
- ②**USB 接口**：支持5V供电，建议使用5V 1A适配器。
- ③**DECAY 旋钮**：调整回声效果的持续时间。
- ④**TYPE 旋钮**：通过此旋钮可选择不同的混响音色，一共9个档位，请看音色介绍。
- ⑤**MIX 旋钮**：调节干声和混响湿音的音量比例。
- ⑥**PARAM1 旋钮**：在不同的混响音色下，旋钮功能不完全一样，请看音色介绍。
- ⑦**PARAM2 旋钮**：在不同的混响音色下，旋钮功能不完全一样，请看音色介绍。
- ⑧**PARAM3 旋钮**：在不同的混响音色下，旋钮功能不完全一样，请看音色介绍。
- ⑨**输出接口**：1/4"单声道音频输出接口。
- ⑩**LED 灯**：指示效果器状态。灯亮，表示效果开启；灯灭，表示直通状态。
- ⑪**输入接口**：1/4"单声道音频输入接口。
- ⑫**踩钉**：激活效果器或切换到直通状态。

档位1: ROOM, 房间混响模拟结构简单的房间声音, 其中许多反射被房间中的软材料吸收, 声音被墙壁反射。

PARAM1: HIGH PASS高通, 仅作用于湿音。

PARAM2: LOW PASS低通, 仅作用于湿音。

PARAM3: DRIFT, 使混响湿音产生音调的小幅度周期性升高降低, 得到一种复古迷人的背景声音。

档位2: HALL, 大厅混响给人一种宽阔的, 轻微散射的感觉。它能模拟宏大的环境声音。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: DRIFT。

档位3: PLATE, 板式混响是创建在一个大型金属材料上的, 是一个非常明亮和强散射性的声音。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: DRIFT。

档位4: SPRING, 弹簧混响是常见的混响类型, 声音信号放大到弹簧上, 然后拾音器捕捉到弹簧的共振声, 从而形成人们在空间中听到的混响, 弹簧混响的特点是来自弹簧的独特颤抖感。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: DWELL, 控制弹簧的数量。

档位5: SHIMMER, 微光混响, 是一种在混响湿音中存在音高偏移的声音。通过PITCH旋钮的调节, 可调整微光声音的音高, 可调出不和谐音程, 营造出恐怖的背景声音, 这是非常创造性的用法; 也可调出和谐音程, 创造出一种自带美颜的声音, 在混响尾音部分会听到犹如微光汲汲传动的美妙声音, 如一种天堂中的声音, 给人感觉像在开阔的土壤上, 遇见日出从微光到全面灿烂的过程。

PARAM1: HIGH PASS。

PARAM2: PITCH, 调节微光声音的音高, 最小值为音高跟原声一致, 最大值为比原声高两个八度。

PARAM3: AMOUNT数量, 控制微光声音的用量。

档位6: CLOUD, 云混响, 一种华丽的大型环境混响, 听起来像是声音从云层卷积而来, 仅仅弹一个音符, 在混响湿音中就出现非常多的声音从各处传来, 声音听起来非常宽广。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: DIFFUSION, 扩散度, 可调节环境维度感, 当旋钮被顺时针扭大时, 早期反射的混响湿音被软化, 听起来更平滑, 模糊了延迟和混响之间的界限。

档位7: BLOOM, 绽放混响, 更多的扩散效果加入到混响效果中, 以得到一种逐渐绽放的感觉。建议用户可尝试用更短的DECAY和更长的LENGTH, 或者是更长的DECAY和更短的LENGTH, 来感受这两个参数如何互动与相互补充, 从而得到您想要的一种氛围。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: LENGTH, 控制绽放效果的时间长度。

档位8: SWELL, 膨胀混响, 在干信号之后逐渐带入混响效果, 两个信号间进行自然的衔接, 以获得轻微的上升效果和演变氛围感, 就像有个可以控制混响湿音的音量踏板。

PARAM1: HIGH PASS。

PARAM2: LOW PASS。

PARAM3: RISETIME上升时间, 往顺时针调节旋钮时, 上升时间会变长, 听觉上的膨胀效果会减弱, 适合用于演奏和弦节奏; 反之上升时间变短时候, 适合用于演奏旋律。

档位9: LOFI, 低保真混响, 是一种神秘的、深邃的、复古的、特别的声音。拥有逼真的Lofi质感、温暖迷人的怀旧氛围和独特的白噪音, 适合复古风格的音乐。

PARAM1: SAMPLE RATE采样率, 仅作用于湿音。

PARAM2: NOISE白噪声。

PARAM3: DRIFT。

输入	标准1/4 " 单声道接口/TS
输出	标准1/4 " 单声道接口/TS
电源供给1	DC9V $\geq$ 300mA 
电源供给2	USB 5V $\geq$ 300mA
尺寸	112(L)X68(W)X40(H)mm
重量	约236g
修订	2023-06-18

免责声明：参数更新恕不另行通知。