Connectors



Power (IO board)



3PDT w/ LED Indicator (switch board)



Explanation of input/battery switching, switch terminal grounding rationale:
https://www.freestompboxes.org/viewtopic.php?t=32540

Briefly:
- Input RING is connected to negative supply, input SLEEVE is connected to circuit ground.
- When an input cable is not plugged in, the effect circuit is open (off).
- When a TS input cable is plugged in, RING shorts to SLEEVE and completes the circuit from negative supply to ground, energizing the circuit.
- Note that a TRS cable will not complete the circuit, and the effect will remain off.

Battery vs DC supply switching works similarly:
- When a DC source is not plugged into the jack, a BATTERY_POS is connected to the DC_SHIELD net.
- When a DC source is plugged in, the switch opens the battery circuit to providing an alternate positive supply.

Otherwise:
- Output tip switch (signal) IS NOT grounded, as grounding the output of the circuit when energized could damage components.
- Input tip switch (signal) IS grounded, to prevent an output signal from being produced when no input signal is present.

Signal flow explanation

Footswitch on:
1. ->input (io pcb)
2. input_tip_io -(S1)-> input_tip_sw -> effect_input_sw
3. effect_input_sw -(S2)-> effect_input_io
4. effect_input_io -(E1)-> effect pcb
5. effect pcb -(E1)-> effect_output_io
6. effect_output_io -(S2)-> effect_output_sw -> output_tip_sw
7. output_tip_sw -(S1)-> output_tip_io
8. ->output (io pcb)

Footswitch off:
1. ->input (io pcb)
2. input_tip_io -(S1)-> input_tip_sw -> output_tip_sw
3. output_tip_sw -(S1)-> output_tip_io
4. ->output (io pcb)

github.com/whbeers/noise_floor

Sheet: /
File: noise_floor.kicad_sch

Title: Noise Floor Interface Boards

Size: A4	Date: 2023-03-04	**Rev: v0.07**
KiCad E.D.A. kicad 7.0.0-da2b9df05c~171~ubuntu22.04.1		Id: 1/1