



Where the Microseconds Go

Input and Audio Latency in AC Native OS

@jeffrey

Aesthetic.Computer

ORCID: 0009-0007-4460-4913

working draft — not for citation

March 2026 · 99d2e1716

Index

1. Introduction	4
2. The Keypress Path	7
3. The Audio Path	10
3.1 Why two configurations	11
4. Current vs. Theoretical Floor	13
5. Wayland, Direct KMS, and Display	16
6. The notepat Latency History	18
6.1 Phase 1: Make the speakers play at all (Apr 14–15)	18
6.2 Phase 2: The Goldilocks dither saga (Apr 15–16)	20
6.3 Phase 3: Format and signal level (Apr 15–16)	21
6.4 Phase 4: Synth quality and perceptual tightness (Apr 17–21)	22

6.5 Phase 5: NuPhy analog input (Apr 18–20)	24
6.6 Phase 6: macOS port latency arc (Apr 18)	25
6.7 Phase 7: Boot acceleration (Apr 20)	27
6.8 What the history says	27
7. What is Left to Squeeze	29
8. Conclusion	31

1. Introduction

Parag, an IRQ — an *interrupt request* — is the hardware equivalent of someone tapping the CPU on the shoulder mid-sentence. Every modern CPU is, by default, ignoring almost everything. It runs whatever the kernel's scheduler last placed in front of it, and only stops when a wire is pulled. The keyboard controller pulls a wire when a key changes; the sound card pulls a wire when its DMA buffer has shifted enough samples out the speaker amplifier that it is about to run dry. The kernel responds with an *interrupt service routine* (ISR), reads the device's status, and either consumes the event or wakes a userspace process that was waiting. That, in five sentences, is the entire mechanism by which a press of the spacebar eventually becomes a sound: a piece of physics (the key bottoming out closes a circuit) becomes a USB transaction, becomes an IRQ, becomes a wakeup, becomes a synth voice, becomes another DMA buffer, becomes a vibration in the air.

The interesting question, the one you actually

asked, is: how long does that path take, and how much of the time is spent on things we cannot avoid versus things we have chosen to put in the way? This paper answers that question for AC Native OS [Jeffrey, 2026b], the bare-metal Linux build that powers the chromatic-keyboard piece *notepat* [Jeffrey, 2026a]. The system was designed from the start as a musical instrument: the relevant performance metric is not throughput but the latency of a single keypress reaching the DAC, and the jitter on that latency. Wessel and Wright argued in 2002 that any tool intended for intimate musical control should keep this number below 10 ms [Wessel and Wright, 2002]; McPherson and colleagues showed in 2016 that most general-purpose computing stacks are nowhere close [McPherson et al., 2016], motivating the dedicated Bela platform [Jack et al., 2018, Augmented Instruments Lab, 2025]. AC Native OS is not Bela. It runs on whatever surplus laptop you flash it onto. But its design intent is the same: minimize the layers between the key and the DAC, and put visible numbers next to each one that remains.

I describe the keypress path (§2), the audio path (§3), the current measured numbers against the theoretical floor (§4), the role of Wayland and the direct-KMS alternative (§5), the commit history of `notepat` latency improvements (§6), and what is left to squeeze (§7).

2. The Keypress Path

In `fedac/native/src/input.c`, the chain from key to userspace runs as follows:

1. The user closes a key contact. Mechanical latency (debounce, scan-matrix sweep) is set by the keyboard's own microcontroller — typically 1–5 ms.
2. The keyboard schedules a USB HID input report. The polling interval is 8 ms on legacy low-speed devices, 1 ms on full-speed devices, and 125 μ s on high-speed gaming keyboards (NuPhy analog HE, used by the development unit, polls at 1 kHz).
3. The xHCI host controller raises an IRQ when the URB completes. The Linux ISR runs in tens of microseconds.
4. The USB HID driver decodes the report and posts an `input_event` via the `evdev` subsystem [Linux Kernel Documentation, 2026b], which makes it readable on `/dev/input/event*`.
5. AC Native OS's main loop, blocking in `poll()` on those file descriptors, wakes inside another tens of microseconds. The event is dispatched

to the active piece’s `act()` function via the QuickJS bridge [Bellard, 2024].

6. The piece updates state. If the event triggers a note, it calls `system.sound.play()`, which posts a voice descriptor to a lock-protected ring shared with the audio thread.

The hardware floor on this path is the USB poll interval (1 ms on a typical keyboard, 125 μ s on a gaming keyboard). Everything else is microseconds of kernel work plus a single context switch into the ac-native main loop. The runtime carries an extra subtlety: the NuPhy analog keyboard reports both as a generic HID keyboard and as a vendor-specific hidraw device that streams continuous pressure values. AC Native OS reads the hidraw stream for analog pressure but suppresses the duplicate evdev events, since processing both would double-trigger every note (`input.c:478`).

When a Wayland compositor is in the loop, step 5 changes: the compositor reads evdev via `libinput` [Hutterer, 2026], decides which client has focus, and serializes the event into a `wl_keyboard.key` message on the per-client Wayland socket [Högenauer et al.,

2025]. The client wakes, dispatches it through `wl_display_dispatch`, and only then does the piece see it. Each hop is one socket write plus one context switch — typically under $200\mu\text{s}$ on a quiet system, but the worst case is bounded by the compositor’s own scheduling, not by the input stack. Comments in `input.c:1135` note that when no compositor advertises a seat, `ac-native` falls back to reading `evdev` directly — the lower-latency path.

3. The Audio Path

Audio in AC Native OS is ALSA [ALSA Project, 2026] all the way down. The configuration in `fedac/native/src/audio.h:11` declares:

```
#define AUDIO_SAMPLE_RATE 192000
#define AUDIO_PERIOD_SIZE 192 // ~1ms at 192kHz
```

The audio thread runs a tight loop: render `period_frames` samples of mixed synth output into a buffer, then call `snd_pcm_writei()` to hand them to the codec. The codec's DMA engine consumes those samples on its own clock; when it has shifted out one full period, it raises an IRQ and the kernel wakes `snd_pcm_writei` so the next period can be written. The rendering and writing are double-buffered, so end-to-end latency is approximately $period \times number-of-periods-in-buffer$.

AC Native OS configures four periods of buffer (`audio.c:2275`). At the design rate this is 4 ms of audio in flight at any moment, plus the analog delay of the codec and amplifier (typically <1 ms).

3.1 Why two configurations

The codec landscape on x86_64 laptops splits cleanly. Older HDA-direct codecs (Realtek ALC257 on a ThinkPad X13, e.g.) accept 192-frame periods without complaint. Newer Intel SoCs (Tiger Lake and later) route audio through Sound Open Firmware (SOF) [Sound Open Firmware Contributors, 2026], a coprocessor that runs DAPM (Dynamic Audio Power Management) state machines. Commit 3e3608733 (*native: SOF-aware audio period sizing*) records the discovery: with a 1ms period and 4ms buffer the SOF firmware logged *10,686 sdmode toggles per boot* on a Framework Laptop 13 G7 with the MAX98360A speaker amp — a DAPM amp-storm that desynchronized the speaker and produced silence. The fix was to detect SOF and back off the period to 10ms (480 frames at 48kHz) with a 40ms buffer.

Even that turned out to be too tight: commit ec143aca7 (*native: bigger SOF buffer 20ms/80ms*) records continuing XRUN messages with short writes of 96 frames out of 480, indicating the buffer was draining faster than the

userspace mixer could refill it under boot-time load. The current production setting on SOF hardware is a 20 ms period in an 80 ms buffer.

This is the central asymmetry of audio latency on modern laptops: *the kernel can do better, but the firmware cannot*. SOF is not a Linux limitation. It is a hardware-vendor decision to put a coprocessor between the OS and the DAC, and that coprocessor's state machine has its own latency floor.

4. Current vs. Theoretical Floor

Table 1 sums the path. The upper section is the current measured/derived state; the middle is the floor set by physics and minimum kernel work; the lower row is the gap.

Stage	Current	Floor
Key contact + scan	1–5 ms	1 ms
USB HID poll	0.125–1 ms	0.125 ms
Kernel ISR + evdev	<50 μ s	<50 μ s
poll() wake $\rightarrow$ piece	<100 μ s	<100 μ s
QuickJS dispatch + synth voice	<100 μ s	<50 μ s
Voice $\rightarrow$ next ALSA period	up to 1 period	0 (best case)
ALSA buffer drain	4 ms (HDA)	1–2 ms
	80 ms (SOF)	80 ms
DAC + amp	<1 ms	<1 ms
Total (HDA-direct)	$\sim$3–4 ms	$\sim$2 ms
Total (SOF)	$\sim$12–22 ms	$\sim$82 ms*

Table 1: Latency budget, key-to-DAC. *SOF floor is dominated by the firmware buffer ac-native cannot shrink without losing audio.

The HDA-direct number sits within the 5 ms threshold below which McPherson et al. showed users cannot reliably distinguish action from sound [McPherson et al., 2016]. The SOF num-

ber does not. There is no software fix on the Linux side: shrinking the SOF buffer reintroduces the DAPM amp-storm. The only paths to a smaller SOF floor are (a) firmware changes upstream, (b) a kernel patch that reroutes the DAPM events out of the audio fast path, or (c) selecting hardware whose codec is HDA-direct.

For comparison, the notepat macOS port (fedac/native/macos/) on Apple Silicon shipped with two backends so they could be A/B tested. The numbers from the AC_LATENCY_TEST=40 benchmark in commit c6e740192, with AC_AUDIO_BUFFER=32:

Backend	min	median	mean	max
SDL3 [Lantinga et al., 2025]	1.42	6.47	5.99	7.32
CoreAudio direct	0.08	0.65	0.58	0.80

Table 2: Mac key-to-sample latency in milliseconds (commit c6e740192).

That is roughly a $10\times$ reduction from the same hardware, same buffer size, same synthesizer. The commit message draws the conclusion in plain language: *“the bottleneck wasn’t the buffer*

size, it was SDL3's audio stream layering its own schedule on top of CoreAudio's pipeline." The number 0.65 ms is below the underlying CoreAudio scheduling floor we earlier believed in, because that floor turned out to be SDL's own in-direction. This is the cleanest single example of the thesis of this paper: each layer between hardware and the app costs a buffer turnaround, and the layer is often invisible until you remove it.

5. Wayland, Direct KMS, and Display

Wayland does not touch audio — it is a display and input protocol. The audio path described above runs identically with or without a compositor. So the question “does Wayland add audio latency” has a clean answer: no. The PipeWire/PulseAudio user-space audio servers *would* add 5–20 ms of resampling and buffering, but ac-native deliberately bypasses them. ALSA hw-direct.

Wayland does add input latency, but only marginally: the compositor’s libinput thread reads evdev on its own schedule and forwards events through the wl_keyboard protocol to the focused client. On a quiet system this is sub-millisecond. `input.c:441,478` record a sharper concern: when ac-native runs as a Wayland client, the compositor *grabs* the input devices, and reading them in parallel via evdev produces double-counted keys and progressively drifting cursor positions. The fix is conditional — if a Wayland seat is advertised, evdev is suppressed; otherwise (`input.c:1135`) ac-native reads evdev

directly.

Display is where Wayland costs the most. A compositor inserts an additional buffer (the client renders into a `wl_buffer`, the compositor composites it, then queues a KMS pageflip), which costs one vsync period — 16.7ms at 60 Hz. AC Native OS ships `drm-display.c` (987 lines) as the no-compositor option: `ac-native` talks directly to DRM/KMS [Linux Kernel Documentation, 2026a] and pageflips its own framebuffer, cutting that frame out of the loop. `wayland-display.c` (394 lines) exists for the case where the OS is embedded in someone else's desktop session.

The general rule: each layer between hardware and the application costs either a context switch (μ s, free) or a buffer turnaround (one frame or one period, audible/visible). AC Native OS's design is to make the buffering layers *optional*, not structural.

6. The notepat Latency History

The chromatic keyboard piece `notepat` is the canonical instrument that runs on AC Native OS. Its current feel is the result of about ten days of dense, often-painful debugging in April 2026, recorded as 40+ commits across `audio.c`, `input.c`, and `notepat.mjs`. Read in order, the commits split into seven phases, each of which moved one specific number. Reading them as a sequence is the most honest answer to “where does the present latency come from” — because almost none of the work was clever DSP or kernel hacking. It was identifying which layer was secretly buffering, and removing or tuning it.

6.1 Phase 1: Make the speakers play at all (Apr 14–15)

Before latency could even be measured, the SOF-based Framework Laptop 13 (G7) had to actually emit sound. The relevant log line at the time was “*everything else correct, but no audio.*” Commits `8e1663d72`, `6247baf17`, `cad9313e4`, `410c78476`, `0d423b19f`, `1c95ab767` walked through

ChromeOS's UCM (Use Case Manager) configuration — enumerating PCMs, picking the speaker verb, fixing the namespace prefix — to get audio routed to the right output at all. 877c2336d stopped enabling UCM Headphones at boot (was silencing speakers). e851f5dce stopped the mixer walk from re-enabling the headphone jack switch (was silencing the speaker amp). eb960efd9 forced runtime power management off after the card probed.

Then the breakthrough: 3e3608733 (**Apr 14, *native: SOF-aware audio period sizing***). The commit message names the bug exactly:

Root cause of silent G7 speakers with everything else correct: the old audio.c config hardcoded ~1ms ALSA period (rate/1000 frames) + 4ms total buffer. Works fine on HDA-direct codecs (ThinkPad X13 etc.) but on SOF+MAX98360A the boot log shows 10,686 sdmode toggles per boot — once per period, matching the ~5ms toggle spacing exactly.

The 1 ms period that was a feature on HDA hard-

ware was actively breaking SOF: at 4 ms buffer depth, the 16 ms paint-loop submission cadence missed every period, the stream underran constantly, and the MAX98357A amplifier's DAPM event handler flipped SD_MODE high and low faster than the chip could stabilize. Detection of SOF (presence of `sound/soc/sof` card and absence of legacy HDA codec97) and a bump to 10 ms period / 40 ms buffer fixed it.

6.2 Phase 2: The Goldilocks dither saga (Apr 15–16)

Once audio was reaching the amp, a second SOF bug emerged: the silence detector inside the SOF DSP would gate the speaker pipeline whenever the buffer fell below a few dB FS, even briefly. Sustained tones cut off mid-note. The fix was to inject inaudible keepalive dither.

319732304 (Apr 15, evening) injected ± 1 LSB dither when the buffer would otherwise be all zeros. *“Should be inaudible; enough to hold the SSP1 BE DAI active.”*

e075ebac5 (Apr 15, ~ 1 h later) bumped to ± 160 .

The ± 1 dither extended the sustain only to 96 s before the silence detector gave up.

7add48bb5 (Apr 15, evening) reduced back to ± 1 .
“ ± 160 was audible as a 24 kHz fizz.”

ec143aca7 (Apr 16) settled on ± 32 (“-72 dBFS at S32_LE, still inaudible”) and at the same time raised the SOF period/buffer from 10/40 ms to **20/80 ms**: the 10 ms buffer was too tight, producing XRUNs and short writes (96 of 480 frames).

This is the latency floor for SOF hardware in the current codebase: 80 ms of buffering, sitting on top of a firmware that requires it. No cleverness in the synth or the JS layer can recover those milliseconds.

6.3 Phase 3: Format and signal level (Apr 15–16)

f246470ea preferred plughw: for the speaker PCM and logged the negotiated format. 72476348f negotiated **S32_LE** for the SOF path (the topology accepts it; converting in userspace eliminated

a class of crunchy/quiet artifacts that had been misdiagnosed as XRUNs). 474237ee4 added a tanh soft-limiter and shaped dither for cleaner peak handling. b7ab5a5de, c28b18eef, f6ca477f9, 153ce7c09 are the loudness arc: -80 dB attenuation bug fix, then $+4$ dB peak via a 0.85 soft-clip knee, then default volume tuning on SOF (which came up quieter than HDA). None of these are latency commits per se, but several of them were attempts to fix what *sounded* like latency (sluggish notes, late-arriving transients) and turned out to be amplitude or format problems.

6.4 Phase 4: Synth quality and perceptual tightness (Apr 17–21)

A note's perceived onset latency depends as much on the transient shape of the synthesized voice as on the audio buffer. cf3ca7f43 replaced the noise-based default voice with a Karplus-Strong plucked string — a delay-line waveguide whose first half-cycle has the entire excitation in it, so the attack lands inside the first millisecond regardless of buffer size. 3928613fe extracted a shared `synth_core` so the same model set runs on

both bare-metal Linux and the macOS port (parity makes A/B testing meaningful). 803188b95 fixed harp loudness and sustain, 93b3568b0 keyed Shift-pluck on duration, 6a5e6cf3e added a master volume + drive (tanh soft-sat) FX block.

The two perceptual-only commits are worth calling out:

608a746fb (Apr 21, *reverse replay is locked to visual cursor + capture pauses*). Visual feedback was drifting against the audio playback; the commit pinned the visual cursor directly to elapsed-since-press wall-clock time and paused the capture ring during reverse hold. The synth's audio latency did not change, but the user-reported “hjanky” feel went away.

7a2e69f92 (Apr 21, *wobble/flange FX + snap-release*). Made the envelope's release *snap* to zero instead of easing back over ~20 frames. Quote from the commit: “*those ~333ms of sweeping visual had no sound behind them. User reported this as ‘extra dead silent time at the end of every reverse*

gesture’ and noted it made the snap-back feel unresponsive.” A pure perceptual fix — no audio latency reduction, but the instrument felt 333 ms faster on release.

6.5 Phase 5: NuPhy analog input (Apr 18–20)

The NuPhy HE is an analog Hall-effect keyboard that exposes per-key pressure values via a vendor hidraw report alongside its standard HID keyboard interface. Three commits matter:

d8b28e65c simplified the evdev filter to suppress NuPhy keys when the hidraw stream is active. Without this, every key fired twice (once from evdev, once from the analog handler), audible as a flam.

f27960700 added analog smoothing, a dark theme, and boot performance and media-key fixes in one batch.

18880d7a8 (Apr 20, *velocity-capture + pressure smoothing + NuPhy badge/gauge*). Diagnosed audible popping on sustained sine

tones: “raw pressure samples arrive at driver-specific ADC step rates and the sim loop was writing every raw value straight into `synth.update()` each frame, so discrete pressure steps produced audible clicks.” Fix: a one-pole lowpass ($\alpha=0.20$, ~ 80 ms time constant) plus rate-limit `synth.update()` to changes $>0.5\%$. This is the single commit where input-side latency was deliberately *added* (80 ms of pressure smoothing) to remove an audio artifact. The note onset path is unchanged — key-down still triggers the synth voice on the same frame.

6.6 Phase 6: macOS port latency arc (Apr 18)

The macOS port (`fedac/native/macos/`, SDL3 + CoreAudio) gave us the cleanest A/B benchmark of the whole project — and the most surprising finding.

04dea9da7 (Apr 18, 16:53) requested a 128-frame device buffer via `SDL_HINT_AUDIO_DEVICE_SAMPLE_FREQUENCY`. CoreAudio’s default was 2048–4096 frames

(40–85 ms). 128 frames at 48 kHz is ~ 2.7 ms.

c8256aa29 (Apr 18, 17:13) added the `AC_LATENCY_TEST=n` benchmark: vsync off, n back-to-back key-press injections, with rearm/settle between each, prints min/median/mean/max + sample list. Tightened the buffer to 64 frames. Median held at ~ 6.4 ms; jitter ceiling fell from ~ 11 ms to ~ 7 ms. The commit message concluded “*smaller buffers don’t lower the median further but can hit the min*” — which we interpreted as the CoreAudio pipeline floor.

c6e740192 (Apr 18, 17:32) tested that conclusion. A direct `kAudioUnitSubType_DefaultOutput` backend was added alongside the SDL3 one, with `kAudioDevicePropertyBufferSize` set on the device before AU instantiation. The benchmark in Table 2 dropped the median from 6.47 ms to 0.65 ms — a $10\times$ improvement that no buffer-size tweak had been able to reach. The bottleneck was not CoreAudio. It was SDL3’s audio-stream abstraction layering its own schedule on top.

This is the pattern of the entire project condensed into 39 minutes of git history: a buffering layer that no one named was costing more than the layer that was named. The fix was to remove it.

6.7 Phase 7: Boot acceleration (Apr 20)

Latency to *first* note also includes how fast the OS reaches a playable state from cold. bc16acb76 backgrounded diagnostic dumps and ran USB mount/GPU wait in parallel during init. 11c6a6ff8 cut the startup-fade boot animation from 3s to 2s with a matrix-rain background, and explicitly framed the change as “*boot into notepat faster.*” Time from power button to interactive note dropped to 7.3s. None of this is per-keypress latency, but it sets the threshold above which the device feels like a tool versus a toy.

6.8 What the history says

These seven phases describe maybe 40 commits across nine days, almost all of them merged on the same branch as ordinary product work.

There is no separate “latency project.” The numbers got better because every time a user-reported feel issue (*popping, crunchy, dead silent time, hjanky*) was investigated, the investigation forced a layer to become visible. Sometimes the answer was buffer size; more often it was a firmware silence detector, an unwanted abstraction, an envelope shape, or a duplicated input device. The instrument is fast not because it was optimized, but because each obstruction was identified and removed in turn.

7. What is Left to Squeeze

- **Direct evdev grab on Wayland.** Currently when a compositor is present, ac-native disables evdev to avoid double-input. A small refactor would let ac-native take an exclusive grab via `EVIOCGRAB` and skip the Wayland keyboard hop entirely while remaining a Wayland client for display. Saves $\sim 200\mu\text{s}$ and eliminates an entire scheduling boundary.
- **ALSA mmap mode.** `snd_pcm_writei` copies frames into the kernel's ring; `snd_pcm_mmap_writei` maps the ring into userspace and removes the copy. On HDA paths this could trim a fraction of a millisecond. On SOF the firmware buffer dominates so the change is invisible.
- **IRQ thread priority and CPU pinning.** Linux RT throttling and IRQ-thread priorities are at default values. Pinning the audio thread to a single CPU and elevating the relevant IRQ thread to `SCHED_FIFO` would tighten the jitter ceiling, though probably not the median. The cost is making the system less polite to other workloads, which on a single-piece appliance is

acceptable.

- **High-poll-rate keyboards.** A 1 kHz USB polling rate is already standard on the development NuPhy. Moving to an 8 kHz polling keyboard shaves another ~ 0.5 ms in the worst case.
- **HDA-only build.** An option flag at build time to refuse SOF hardware would let the synth use a 1 ms period unconditionally. This is a hardware-selection decision dressed up as a software switch, but it is honest about the trade.

None of these will produce a dramatic step change. They will each save microseconds to a few milliseconds. The dramatic step changes are behind us: removing PulseAudio (saved ~ 10 ms), removing the desktop compositor for direct KMS (saved one frame), tuning the ALSA period to the codec's ceiling (took the audio buffer from a default 23 ms or worse down to 4 ms on HDA), and identifying the SOF DAPM trap (which prevented an entire class of laptops from working at all).

8. Conclusion

So, Parag: an interrupt is a wire that the CPU has agreed to listen to. The keyboard pulls one when a key changes. The sound card pulls one when its DMA buffer is about to run dry. Between those two events the kernel does roughly $100\ \mu\text{s}$ of work and userspace does another $100\ \mu\text{s}$ — those are not the latency. The latency is the buffers we keep in flight to absorb scheduling jitter, plus whatever firmware sits between the OS and the silicon. On a ThinkPad with HDA-direct audio, AC Native OS is at $\sim 3\text{--}4\ \text{ms}$ key-to-DAC, against a $\sim 2\ \text{ms}$ physics floor. On a Framework with SOF, the floor itself is $\sim 80\ \text{ms}$. Wayland adds nothing to audio, a fraction of a millisecond to input, and one vsync to display — which is why ac-native ships a direct-KMS path for the cases where that vsync matters.

The right question for an instrument is never “how low can the average go,” it is “how predictable is the worst case.” That is what the recent work has been about. The audible thresholds ($10\ \text{ms}$ for intimate musical control, $20\ \text{ms}$

before the action-sound bond starts to break) are met on the hardware we recommend. They are not yet met on every laptop in a thrift bin — not because the kernel cannot deliver, but because the firmware sometimes will not let it.

Acknowledgments. For Parag, who asked the question that made this paper worth writing. The numbers in this paper are derived from the public commit history of the `aesthetic-computer` repository as of April 2026.

ORCID: 0009-0007-4460-4913

References

ALSA Project. Advanced linux sound architecture (alsa) project, 2026. URL <https://www.alsa-project.org/>.

Augmented Instruments Lab. Bela: Real-time audio and sensors for embedded systems, 2025. URL <https://bela.io/>.

Fabrice Bellard. Quickjs javascript engine, 2024. URL <https://bellard.org/quickjs/>.

Kristian Högenauer et al. Wayland protocol specification, 2025. URL <https://wayland.freedesktop.org/>.

Peter Hutterer. libinput — a library to handle input devices, 2026. URL <https://www.freedesktop.org/wiki/Software/libinput/>.

Robert Jack, Giulio Moro, and Andrew McPherson. Sub-millisecond latency audio with bela. In *Audio Engineering Society Convention 144*, 2018.

@jeffrey. notepat.com: From keyboard toy to

system front door, 2026a. Companion paper on the chromatic keyboard piece.

@jeffrey. Ac native os '26: A bare-metal creative computing operating system, 2026b. Companion paper describing the bare-metal Linux build.

Sam Lantinga et al. Simple directmedia layer 3.0, 2025. URL <https://libSDL.org/>.

Linux Kernel Documentation. Linux drm/kms subsystem documentation, 2026a. Documentation/gpu/drm-kms.rst.

Linux Kernel Documentation. Linux input subsystem user-space api (evdev), 2026b. Documentation/input/input.rst.

Andrew McPherson, Robert Jack, and Giulio Moro. Action-sound latency: Are our tools fast enough? In *Proceedings of the International Conference on New Interfaces for Musical Expression (NIME)*, pages 20–25, 2016.

Sound Open Firmware Contributors. Sound open firmware project, 2026. URL <https://thesofproject.github.io/latest/index.html>.

David Wessel and Matthew Wright. Problems and prospects for intimate musical control of computers. In *Computer Music Journal*, volume 26, pages 11–22, 2002.