



IP Media Device Management Protocol User Guide

Version 2.0

Revision 1.0

2013-12



<http://www.hikvision.com/>

COPYRIGHT ©2009, Hikvision Digital Technology Co., Ltd

Revision History	Description	Date
Version 1.0 Revision 1	Initial version	2009-6
Version 1.0 Revision 2	Finished the Mandatory services	2009-8
Version 1.0 Revision 3	Corrections, expanded services	2009-10
Version 1.0 Revision 4	Corrections, updates services and resources	2009-11
Version 1.0 Revision 5	Protocol revision	2009-12
Version 1.0 Revision 5.1	Corrections, amend PTZ service and resources	2010-01
Version 1.0 Revision 5.2	Update the /PTZ/channels/ID/PTZControl resources	2010-01
Version 1.0 Revision 5.3	Amend the DDNS related resources; add the /Security/adminAccess resources	2010-02
Version 1.0 Revision 5.4	The <Zeroconf> tag is supported in the block XML of "/System/Network/interfaces/ID/discovery". Add the "/System/logging" The <pulseDuration> tag is supported in the block XML of "IO/outputs/ID". The <pulseDuration> tag is not supported in the block XML of "IO/outputs/ID/trigger". Modify some parameter values in Audio Service. The <enabled> can be configured in the <Audio> of the block XML "/Streaming/channels/ID"	2010-04
Version 1.0 Revision 5.5	<videoResolution> is replaced with <videoResolutionWidth> and <videoResolutionHeight> in the /Streaming/channels/ID	2010-05
Version 1.0 Revision 5.6	Redefine the mean of ID in the URI :/Event/triggers/ID/notifications/ID , it just a sequence number of a trigger or a notification .	2010-06
Version 1.0 Revision 5.7	Add resource "Custom/HiKCGI/Event/ schedule/ ID". The <dynamicIP> tag is supported in the block XML of "/Network/interfaces/ID/ pppoe"	2010-09
Version 1.0	New resource /System/Storage is defined	2011-01

Revision 5.8	<p>New service /PTZCtrl is defined</p> <p>New service /Image is defined</p> <p>New service /Record is defined</p> <p>Service is Custom/HIKCGI/Event/ schedule/ ID is redefined to: /Event/schedule/ ID.</p>	
<p>Verison 1.0</p> <p>Revision 5.9</p>	<p>New service /Network/interfaces/ID/Adapter is defined</p> <p>Service /Event/notification/mailing/ID definition is updated , to support multi email receivers</p> <p>New service /Image/channels/<ID>/NosiseReduceExt is defined</p> <p>New service /Image/channels/<ID>/Scene is defined</p> <p>New service /Image/channels/<ID>/EPTZ is defined</p> <p>New service /Image/channels/<ID>/PTZ is defined</p> <p>New service /Image/channels/<ID>/EIS is defined</p> <p>Service /Image/channels/<ID>/IrcutFilter has been replaced by /Image/channels/<ID>/IrcutFilterExt,and the IrcutFilterTime can't meet the need of setting in both directions.It needs to explain the unit of time in notes.</p> <p>Service /Image/channels/<ID>/WDR has been replaced by /Image/channels/<ID>/WDRExt. The new service adopt <mode> tag, support a level, and can by extended by other level.</p> <p>Comments were added on the service /Image/channels/<ID>/HLC.</p> <p>All sub-branches were list in the service /Image/channels</p> <p>Added Id to the NFS xml block.</p>	2012-03

	<p>Added <exposureMode> tag and <WDREnabled> tag to the service video,</p> <p>PTZ were extended to HIKCGI.</p> <p>Added FTP、HTTP and PTZ to Linking Method.</p> <p>Added <enabled> tag, <privacymaskName> tag and <maskType> tag to service /Video/inputs/channels/ID/privacyMask/regions/ID</p> <p>Service /System/Storage/volumes/ID/URL was revised as /System/Storage/volumes/ID/Format</p> <p>IR was reached agreement.</p> <p>No index was used in tag <ZoomLimitRatio>.</p> <p>The new <mode> tag in service /Image/channels/<ID>/WDRExt was optional.</p> <p>Add MULTI-AREA option to the tag <BLCMode> in service /Image/channels/<ID>/BLS.</p> <p>New service /Image/channels/<ID>/HLC is defined.</p> <p>New service /Image/channels/<ID>/ChromaSuppress is defined.</p> <p>New service /Image/channels/<ID>/ZoomLimit is defined.</p> <p>New service /Image/channels/<ID>/ExpComp is defined.</p> <p>Delete /PSIA/Custom/HIK/PTZ/channels/ID/patterns, /PSIA/Custom/HIK/PTZ/channels/ID/ptzlimiteds, and /PSIA/Custom/HIK/PTZ/channels/ID/timetasks in PTZ.</p>	
Verison 2.0	New service /Smart branch is defined	2013-11

Revision 1.0	<p>New service /Streaming/channels/<ID>/dynamicCap is defined.</p> <p>The new <SVC> tag in service /Streaming/channels/<ID> is optional.</p> <p>Added <panSupport> tag, <tiltSupport> tag and <zoomSupport> tag to service /Streaming/channels/<ID> was optional.</p> <p>New service /MotionDetectionExt/<ID> is defined</p> <p>New service /MotionDetectionExt/<ID>/switch is defined</p> <p>New service /MotionDetectionExt/<ID>/regions is defined</p> <p>New service /MotionDetectionExt/<ID>/regions/<ID> is defined</p> <p>New service /PTZCtrl/channels/<ID>/onpushfoucs/start is defined.</p> <p>New service /PTZCtrl/channels/<ID>/onpushfoucs/reset is defined.</p> <p>New service /PTZCtrl/channels/<ID>/position3D is defined.</p>	
--------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	--



<http://www.hikvision.com/>

© COPYRIGHT, Hikvision Digital Technology Co., Ltd

Notices

The information in this documentation is subject to change without notice and does not represent any commitment on behalf of HIKVISION. HIKVISION disclaims any liability whatsoever for incorrect data that may appear in this documentation. The product(s) described in this documentation are furnished subject to a license and may only be used in accordance with the terms and conditions of such license.

Copyright © 2009-2014 by HIKVISION. All rights reserved. **This documentation is issued in strict confidence and is to be used only for the purposes for which it is supplied.** It may not be reproduced in whole or in part, in any form, or by any means or be used for any other purpose without prior written consent of HIKVISION and then only on the condition that this notice is included in any such reproduction. No information as to the contents or subject matter of this documentation, or any part thereof, or arising directly or indirectly therefrom, shall be given orally or in writing or shall be communicated in any manner whatsoever to any third party being an individual, firm, or company or any employee thereof without the prior written consent of HIKVISION. Use of this product is subject to acceptance of the HIKVISION agreement required to use this product. HIKVISION reserves the right to make changes to its products as circumstances may warrant, without notice.

This documentation is provided “as-is,” without warranty of any kind. Please send any comments regarding the documentation to:
overseabusiness@hikvision.com

Find out more about HIKVISION at www.hikvision.com

Contents

Contents	I
1 Scope	1
2 References	1
3 Definitions and abbreviations	2
3.1 Definitions	2
3.2 Abbreviations	2
4 Architecture and Transmission Mechanism	2
4.1 REST and HTTP Methods	3
4.2 XML	3
4.3 Resources overview	4
4.4 Protocol URL	5
4.5 Messages	6
4.5.1 Connection Header Field	6
4.5.2 Authorization and WWW-Authenticate Header Fields	6
4.5.3 Entity Body	6
4.5.4 Operations	7
4.5.5 Error Handling	8
4.6 Namespaces	13
4.7 Security	13
5 Device discovery	13
6 Resource Description	14
6.1 Resource Description Outline	14
6.2 Built-in Types	15
6.3 Annotation	16
7 Special Resources	16
7.1 index	16
7.2 indexr	17
7.3 description	17
7.4 capabilities	17
8 Services and General Resources	20
8.1 System	20
8.1.1 Device Information	20
8.1.2 Configuration file(s)	21
8.1.3 Factory default	22
8.1.4 Firmware upgrade	22
8.1.5 Reboot	22
8.1.6 Status	23
8.1.7 Time	23
8.1.8 LocalTime	24
8.1.9 TimeZone	24
8.1.10 NtpServers	25
8.1.11 NtpServer	26

8.1.12	Log	27
8.1.13	Storage	29
8.2	Network	32
8.2.1	Interfaces	32
8.2.2	Interface	32
8.2.3	IPAddress	33
8.2.4	Wireless	34
8.2.5	DetectedWirelessList	35
8.2.6	DetectedWireless	36
8.2.7	Discovery	36
8.2.8	PPPoE	37
8.2.9	DDNS	38
8.2.10	NFSList	38
8.2.11	NFS	39
8.2.12	Adapter	40
8.2.13	Examples	40
8.3	IO	42
8.3.1	Status	43
8.3.2	Inputs	43
8.3.3	Input	44
8.3.4	Input status	44
8.3.5	Outputs	45
8.3.6	Output	45
8.3.7	Output status	46
8.3.8	Output trigger	46
8.4	Video	47
8.4.1	Input	47
8.4.2	Input channels	47
8.4.3	Input channel	48
8.4.4	Input channel overlay texts	49
8.4.5	Input channel overlay text	50
8.4.6	Input channel channelNameOverlay	50
8.4.7	Input channel privacyMask	51
8.4.8	Input channel privacyMask regions	52
8.4.9	Input channel privacyMask region	53
8.4.10	Input channel shelterAlarm	55
8.4.11	Input channel shelterAlarm regions	55
8.4.12	Input channel shelterAlarm region	56
8.4.13	Input channel osdDatetime	57
8.5	Audio	58
8.5.1	Channels	58
8.5.2	Channel	59
8.6	Two way audio	59
8.6.1	Open	59

8.6.2	Close	60
8.6.3	Send data.....	60
8.6.4	Receive data	61
8.7	Serial	61
8.7.1	Ports	61
8.7.2	Port	62
8.7.3	Command	63
8.7.4	Transparent channel open	63
8.7.5	Transparent channel close	64
8.7.6	Transparent channel send data.....	64
8.7.7	Transparent channel receive data.....	64
8.8	Security	65
8.8.1	Users	65
8.8.2	User	66
8.8.3	adminAccess	67
8.9	Streaming	67
8.9.1	Status.....	68
8.9.2	Channels.....	68
8.9.3	Channel.....	69
8.3.1	Dynamic capabilities	74
8.9.4	Channel status	76
8.9.5	Picture	76
8.9.6	Request keyframe	77
8.10	Motion Detection	77
8.10.1	One channel motion detection.....	78
8.10.2	Motion detection regions	79
8.10.3	Motion detection region	80
8.10.4	Motion Detection Example	81
8.10.5	/MotionDetectionExt/<ID>	83
8.10.6	/MotionDetectionExt/<ID>/switch	84
8.10.7	/MotionDetectionExt/<ID>/regions	85
8.10.8	/MotionDetectionExt/<ID>/regions/<ID>	86
8.11	Event	87
8.11.1	Triggers	88
8.11.2	Trigger	89
8.11.3	Trigger notifications	90
8.11.4	Trigger notification	91
8.11.5	Schedule	92
8.11.6	Schedule/ID	93
8.11.7	Notification	94
8.11.8	Mails notification	95
8.11.9	Mail notification	96
8.11.10	HTTP Hosts	97
8.11.11	HTTP Host.....	97

8.11.12	Notification alertStream	98
8.11.13	Event Triggering Examples	100
8.12	PTZ	102
8.12.1	Channels	102
8.12.2	Channel	103
8.12.3	Patrols	104
8.12.4	Patrol	104
8.12.5	Patrol keyPoints	105
8.12.6	Patrol keyPoint	106
8.12.7	PTZControl	107
8.13	PTZCtrl	108
8.13.1	/PTZCtrl/channels	108
8.13.2	/PTZCtrl/channels/<ID>	109
8.13.3	/PTZCtrl/channels/<ID>/homeposition	110
8.13.4	/PTZCtrl/channels/<ID>/homeposition/goto	111
8.13.5	/PTZCtrl/channels/<ID>/continuous	111
8.13.6	/PTZCtrl/channels/<ID>/momentary	111
8.13.7	/PTZCtrl/channels/<ID>/relative	112
8.13.8	/PTZCtrl/channels/<ID>/absolute	112
8.13.9	/PTZCtrl/channels/<ID>/digital	113
8.13.10	/PTZCtrl/channels/<ID>/status	114
8.13.11	/PTZCtrl/channels/<ID>/presets	114
8.13.12	/PTZCtrl/channels/<ID>/presets/<ID>	115
8.13.13	/PTZCtrl/channels/<ID>/presets/<ID>/goto	116
8.13.14	/PTZCtrl/channels/<ID>/patrols	116
8.13.15	/PTZCtrl/channels/<ID>/patrols/<ID>	117
8.13.16	/PTZCtrl/channels/<ID>/patrols/<ID>/start	118
8.13.17	/PTZCtrl/channels/<ID>/patrols/<ID>/stop	118
8.13.18	/PTZCtrl/channels/<ID>/patrols/<ID>/pause	119
8.13.19	/PTZCtrl/channels/<ID>/patrols/<ID>/status	119
8.13.20	/PTZCtrl/channels/<ID>/patrols/<ID>/schedule	120
8.13.21	/PTZCtrl/channels/<ID>/patterns	120
8.13.22	/PTZCtrl/channels/<ID>/patterns/<ID>	121
8.13.23	/PTZCtrl/channels/<ID>/patterns/<ID>/recordstart	121
8.13.24	/PTZCtrl/channels/<ID>/patterns/<ID>/recordstop	122
8.13.25	/PTZCtrl/channels/<ID>/patterns/<ID>/run	122
8.13.26	/PTZCtrl/channels/<ID>/patterns/<ID>/stop	122
8.13.27	/PTZCtrl/channels/<ID>/PTZOSDDisplay	123
8.13.28	/PTZCtrl/channels/<ID>/parkaction	123
8.13.29	/PTZCtrl/channels/<ID>/ptzlimiteds	124
8.13.30	/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>	125
8.13.31	/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/setstart	126
8.13.32	/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/set	126
8.13.33	/PTZCtrl/channels/<ID>/saveptzpoweroff	126

8.13.34	/PTZCtrl/channels/<ID>/timetasks	127
8.13.35	/PTZCtrl/channels/<ID>/timetasks/<ID>	128
8.13.36	/PTZCtrl/channels/<ID>/timetasks /<ID>/copytask.....	129
8.13.37	/PTZCtrl/channels/<ID>/auxcontrol.....	130
8.13.38	/PTZCtrl/channels/<ID>/onpushfoucs/start	130
8.13.39	/PTZCtrl/channels/<ID>/onpushfoucs/reset	131
8.13.40	/PTZCtrl/channels/<ID>/position3D	131
8.14	Image.....	132
8.14.1	/Image/channels	132
8.14.2	/Image/channels/<ID>.....	132
8.14.3	/Image/channels/<ID>/resetImage.....	134
8.14.4	/Image/channels/<ID>/restoreImageparam	134
8.14.5	/Image/channels/<ID>/Focus.....	134
8.14.6	/Image/channels/<ID>/LensInitialization	135
8.14.7	/Image/channels/<ID>/ImageFlip	136
8.14.8	/Image/channels/<ID>/ImageFreeze	136
8.14.9	/Image/channels/<ID>/proportionalpan	137
8.14.10	/Image/channels/<ID>/WDRExt	137
8.14.11	/Image/channels/<ID>/BLC.....	138
8.14.12	/Image/channels/<ID>/Imageenhancement	139
8.14.13	/Image/channels/<ID>/IrcutFilterExt	139
8.14.14	/Image/channels/<ID>/NoiseReduceExt.....	140
8.14.15	/Image/channels/<ID>/DSS	141
8.14.16	/Image/channels/<ID>/WhiteBlance	142
8.14.17	/Image/channels/<ID>/Exposure.....	143
8.14.18	/Image/channels/<ID>/Sharpness.....	143
8.14.19	/Image/channels/<ID>/Iris	144
8.14.20	/Image/channels/<ID>/Shutter.....	145
8.14.21	/Image/channeles/<ID>/Gain	145
8.14.22	/Image/channeles/<ID>/GamaCorrection	146
8.14.23	/Image/channels/<ID>/powerLineFrequency	146
8.14.24	/Image/channels/<ID>/Color	147
8.14.25	/Image/channels/<ID>/Scene	148
8.14.26	/Image/channels/<ID>/EPTZ	148
8.14.27	/Image/channels/<ID>/PTZ.....	149
8.14.28	/Image/channels/<ID>/EIS	149
8.14.29	/Image/channels/<ID>/HLC.....	150
8.14.30	/Image/channels/<ID>/ChromaSuppress.....	151
8.14.31	/Image/channels/<ID>/ZoomLimit.....	151
8.14.32	/Image/channels/<ID>/ExpComp	152
8.14.33	/Image/channels/<ID>/IrLight.....	152
8.14.34	/Image/channels/<ID>/WDR(1.5.8 old version)	153
8.14.35	/Image/channels/<ID>/NoiseReduce(1.5.8 old version).....	154
8.14.36	/Image/channels/<ID>/IrcutFilter(1.5.8 old version)	154

8.15	/Record.....	155
8.15.1	/Record/Schedule	155
8.16	Smart.....	156
8.16.1	/Smart/Capabilities	156
8.16.2	/Smart/ROI/channels/ID.....	157
8.16.3	/Smart/ROI/channels/<ID>/regions.....	158
8.16.4	/Smart/ROI/channels/<ID>/regions/<ID>	158
8.16.5	/Smart/ROI/channels/<ID>/facetrace.....	159
8.16.6	/Smart/ROI/channels/<ID>/objecttrace	160
8.16.7	/Smart/FaceDetect/<ID>	160
8.16.8	/Smart/IntelliTrace/<ID>.....	161
8.16.9	/Smart/IntelliTrace/<ID>/ZoomRatial	162
8.16.10	/Smart/FieldDetection/<ID>.....	162
8.16.11	/Smart/FieldDetection/<ID>/regions.....	163
8.16.12	/Smart/FieldDetection/<ID>/regions/<ID>	164
8.16.13	/Smart/DefocusDetection/<ID>.....	165
8.16.14	/Smart/AudioDetection/channels/<ID>	166
8.16.15	/Smart/AudioDetection/channels/<ID>/Status	166
8.16.16	/Smart/SceneChangeDetection/<ID>	167
Annex A (normative):.....		168
A.0 hik.xsd.....		168

1 Scope

This specification defines a HTTP-based application programming interface that enables physical security and video management systems to communicate with IP media devices in a particular way.

With regard to Media Streaming, please refer to “develop API of RTSP protocol”.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.

- [1] RFC2616 Hypertext Transfer Protocol-HTTP/1.1
- [2] W3C XML 1.0 specification
- [3] W3C Character encodings
- [4] RFC 2396 Uniform Resource Identifiers (URI): Generic Syntax and Semantics
- [5] RFC 2617 HTTP Authentication:Basic and Digest Access Authentication
- [6] International Electrotechnical Commission “ISO/IEC standard on UPnP device architecture makes networking simple and easy”, 2008-12-09. Retrieved on 2009-05-07.
- [7] International Organization for Standardization “ISO/IEC standard on UPnP device architecture makes networking simple and easy”, 2008-12-10. Retrieved on 2009-05-07.
- [8] UPnP Forum “UPnP Specifications Named International Standard for Device Interoperability for IP-based Network Devices”, 2009-02-05. Retrieved on 2009-05-07.

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

Special Resources: “index”, “indexr”, “description” and “capabilities” resources, that are contained in all Services and General Resources, and provide a special description for these resources.

Services: a set of resources consisting of relevant General Resources.

General Resources: physical resources that supported by the devices.

Node: Services and General Resources.

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

FQDN	Fully Qualified Domain Name
REST	REpresentational State Transfer
IO	Input/Output
UPnP	Universal Plug and Play

4 Architecture and Transmission Mechanism

The IP Media Device Management Protocol is based on REST architecture. The management and control interfaces defined in this specification are treated as resources utilizing the REpresentational State Transfer (REST) architecture. This architecture facilitates users by grouping related resources within hierarchical namespaces, and is more flexible for service discovery and future expansion.

REST architecture consists of clients and servers, among which clients initiate request to servers, while servers handle requests and response accordingly. Requests and responses are established via the transmission of “representations” of “resources”. REST architecture need to be based on an Application Layer protocol which provides various of standard communication formats for applications based on the transfer of meaningful representational state. HTTP[1] has a very rich vocabulary in terms of verbs(or “methods”),

URIs, request and response headers, Internet media types, HTTP request and response codes etc. In addition, HTTP also has some features particularly suitable for REST architecture. So HTTP is used as external Application Layer protocol in this specification. In the architecture, clients are physical security and video management systems; servers are IP media devices.

This specification also contains full XML schema for the introduced resources.

4.1 REST and HTTP Methods

The following table shows how HTTP verbs are typically used to implement a web service based on REST architecture.

Table 1

Resource	GET	PUT	POST	DELETE
Collection URI, such as http://webServer/resources	List the members of collection, complete with their member URIs for further navigation.	Meaning defined as “ replace the entire collection with another collection”.	Create a new entry in the collection where the ID is assigned automatically by the collection. The ID created is usually included as part of the data returned by this operation.	Meaning defined as “ delete the entire collection”.
Member URI, such as http://webServer/resources/7416	Retrieve a representation of the addressed member of the collection expressed in an appropriate MIME type.	Update the addressed member of the collection or create it with the specified ID.	Treat the addressed member as a collection in its own right and create a new subordinate of it.	Delete the addressed member of the collection.

4.2 XML

A device must support the syntax defined by W3C XML 1.0 specification [2] and UTF-8 character set [3]. All XML files must adopt UTF-8 encoding according to RFC3629. Additionally, all resources share a common XML schema as defined in Annex.

Any resources can specify separate input and output XML Documents. If a specific data

structure is defined inside these documents, then they must be specified as XML Schema Documents (xsd) in Annex.

Lists contained in XML blocks will be represented in the format of <XXXList>, and each <XXXList> tag may contain one or more nodes.

4.3 Resources overview

Three kinds of resources are defined in this specification. They are “Special Resources”, “Services” and “General Resources”. Related General Resources are grouped by Services. Services and General Resources contain Special Resources. Figure 1 shows their relationship.




Figure 1

The “index”, “indexr”, “description” and “capabilities” are defined as Special Resources in this specification. Both “index” and “description” will be mandatorily included by each node, and both “indexr” and “capabilities” will be optionally included by each node. For more detailed description see Section 6.

Services defined in this specification are divided into different services categories. Each category has its own name spaces (see Section 4.6 for the name space definitions). The following services are defined:

Table 2

Services	Description	Reference
System	Configure and operate the general system functions.	8.1
Network	Configure network interfaces.	8.2
IO	Configure the Input/Output (IO).	8.3
Video	Handle video-related configuration.	8.4
Audio	Configure the Audio.	8.5
Two way audio	Control two ways audio.	8.6
Serial	Configure and control the Serial ports.	8.7

Services	Description	Reference
Security	Provide Security functions.	8.8
Streaming	Configure and control the streaming media content.	8.9
Motion Detection	Configure and control the motion detection of the device	8.10
Event	Provide event notification functions.	8.11
PTZ	Control the device pan tilt and zoom.	8.12
PTZCtrl	Configure and control PTZ.	8.13
Image	Configure front-end parameters.	8.14
Record	Configure recording schedule.	8.16
Smart	Configure smart event parameters.	8.16

4.4 Protocol URL

The URL scheme is used to locate device resources via a specific protocol in the network. This section defines the syntax and semantics for http(s) URLs.

```
<protocol>://<host>[:port][abs_path [?query]]
```

protocol: URL scheme for the particular request. The http and https protocols are allowed in this specification.

host: The host field refer to the hostname, IP address, or the FQDN of an IP device.

port: The port field refer to the port number of that host on which the identified resource is located at the IP device listening for TCP connections. If the port is empty or not given, the default port is assumed. For HTTP, the default port 80. For HTTPS, the default port 443.

abs_path: The Request-URI [1] for the resources is abs_path [4]. The abs_path in this specification is most often of the form “[/Services][/General Resources][/Special Resources]”, which is suitable for resources to update or restore device configurations. “ID” which appears in the abs_path identifies one resource of a list resource in this specification.

query: The query field is a string of information to be interpreted by the resource. It can include some resource-related parameters. It must be listed in name-value pair syntax (p1=v1&p2=v2&...&pn=vn). Each resource can define a set of parameters. Defining input data which is specific to the resource will be prior than query usage.

4.5 Messages

HTTP messages are used for communication between physical security and video management systems and IP media devices in this specification. In order to configure and control the device, some provisions are specified for these HTTP message.

4.5.1 Connection Header Field

Devices that implement HTTP/1.1 should support persistent connections in order to meet video management systems or client applications' requirements that issue multiple HTTP(s) transactions. HTTP/1.1 is implemented and utilized according to RFC 2616 in the IP devices. For a video management system or client application that uses persistent connection for multiple transactions, it is required to implement "Connection: Keep-Alive" HTTP header field, while also adopt the "Connection: close" HTTP header field for the last transaction of the persistent connection. This process will assume that the application can identify the last request in a sequence of multiple requests.

4.5.2 Authorization and WWW-Authenticate Header Fields

When a video management system or client application sends any request to the device, it must be authenticated by means of Basic Access [5] according to RFC 2617, and thus all the devices are required to support Basic Access. Authorization header field is sent along with each request, and if a user is authenticated, the request will follow the normal execution flow. If client HTTP request is with no authentication credentials, unauthorized HTTP response (401) will be returned with WWW-Authenticate header field.

4.5.3 Entity Body

The Content-Type entity-header field indicates the media type of the entity body. The Content-Type may be designated as "application/xml; charset='UTF-8'", "application/octet-stream", etc.

For configuration information, the Content-Type is usually "application/xml; charset='UTF-8'". For example,

HTTP Request Message:

```
GET /System/status HTTP/1.1
```

```
...
```

HTTP Response Message:

HTTP/1.1 200 OK

...

Content-Type: application/xml; charset="UTF-8"

...

<?xml version="1.0" encoding="UTF-8"?>

<DeviceStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">

...

</DeviceStatus>

For data(i.e. firmware, configuration file, etc.), the Content-Type may be "application/octet-stream". For example,

HTTP Request Message:

PUT /System/configurationData HTTP/1.1

...

Content-Type: application/octet-stream

...

[proprietary configuration file data content]

HTTP Response Message:

HTTP/1.1 200 OK

...

Content-Type: application/xml; charset="UTF-8"

...

<?xml version="1.0" encoding="UTF-8"?>

<ResponseStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">

...

</ResponseStatus>

4.5.4 Operations

Different resources will specify different operation.

- The "set device configuration" resources use PUT operation. If there is an XML block parameter for the request, the inbound XML format is defined according to a resource-special XML schema. Request status will be returned by the XML response information of the device, and can be used for indicating the PUT operation status. The responded XML format is defined by "XML Response Schema" (please refer to section 4.5.5 for detail description). After the device configuration is updated successfully, it will return an XML response with status

code “OK”; while another status code will be used for indicating unsuccessful operations. In either case, the device only responds after it is ready to continue normal operation, i.e. accepting streaming request, receiving configuration commands, etc.

- The “get device configuration” resources use GET operation. After a successful GET operation, the result will be returned in XML format according to the resource description. For an unsuccessful request (i.e. users is not authenticated), the result will be returned in XML format according to “XML Response Schema”.
- Resources to create device configurations information will use the POST operation. If there is an XML block parameter for the request, the inbound XML format is defined according to a resource-special XML schema. The request status will be indicated by the XML response information returned from the device, and can be used to indicate the status of the POST operation. This XML format is defined according to “XML Response Schema” (see section 4.5.5 for details). After successfully creating the data, the device returns an XML response with status code “OK”. A separate status code is used for unsuccessful operations.
- Resources to delete device configurations information will use the Delete operation. If successful, the result will be returned an XML response with status code “OK”. A separate status code is used for unsuccessful operations. This XML format is defined according to “XML Response Schema” (see section 4.5.5 for details).
- Data uploading resources (i.e. firmware upgrade, import configuration, etc.) will use PUT operation. The content of the data will be stored in the body of the HTTP request. If successful, the result will be returned an XML response with status code “OK”. A separate status code is used for unsuccessful operations. This XML format is defined according to “XML Response Schema” (see section 4.5.5 for details).
- Data receiving resources (i.e. export configuration file) use GET operation. If successful, the result will be returned the data according to the resource description. An XML block is used for unsuccessful operations. This XML format is defined according to “XML Response Schema” (see section 4.5.5 for details).
- For Special Resources, GET operation will be used. For more detailed description see Section 6.

If there is an XML block for the HTTP request or response, the Content-Type and Content-Length will be set in the headers of the HTTP message.

4.5.5 Error Handling

As with any other protocol, errors may occur during communications, protocol or message processing, and the specification classifies error handling into categories below:

- Protocol Errors, which are result of an incorrectly formed protocol message. Protocol Errors may contain header value or be received in an not expected or experience a socket timeout. To indicate and interpret protocol error, HTTP protocol has defined a set of standard status codes [e.g., 1xx, 2xx, 3xx, 4xx, 5xx]. According to this specification, the IP devices will use appropriate HTTP protocol defined status codes for error reporting and when received handle accordingly.
- Application Errors, which are generated as a result of REST operations errors. All such application errors must be reported and handled through HTTP messages. The following table indicates the mapping relationship between HTTP status codes and REST operations, and also the information contained in response header and bodies.

Table 3

HTTP Status Codes	REST Meaning	GET	PUT	POST	DELETE
200	“OK”-The request has succeeded. Header Notes: None Body Notes: The requested resource will be returned in the body.	√	√		√
201	“Created”- The request has created a new resource. Header Notes: The Location header contains the URI of the newly created resource. Body Notes: The response returns an entity describing the newly created resource.		√	√	
204	“No Content” – The request succeeded, but there is no data to return. Header Notes: None Body Notes: No body is allowed.		√		√
301	“Moved Permanently” – The requested resource has moved permanently. Header Notes: The Location Header contains the URI of the new location. Body Notes: The body may contain the new resource location.	√			

HTTP Status Codes	REST Meaning	GET	PUT	POST	DELETE
302	<p>“Found” – The requested resource should be accessed through this location, but the resource actually lives at another location. This is typically used to set up an alias.</p> <p>Header Notes: The Location header contains the URI of the resource.</p> <p>Body Notes: The body may contain the new resource location.</p>	√			
400	<p>“Bad Request” – The request was badly formed. This is commonly used for creating or updating a resource, but the data was incomplete or incorrect.</p> <p>Header Notes: The Reason-Phrase sent with the HTTP status header may contain information on the error.</p> <p>Body Notes: The response may contain more information of the underlying error that occurred in addition to the Reason-Phrase.</p>		√	√	
401	<p>“Unauthorized” – The request requires user authentication to access this resource. If the request contains invalid authentication data, this code is sent.</p> <p>Header Notes: At least one authentication mechanism must be specified in the WWW-Authenticate header. The Reason-Phrase sent with the HTTP status header may contain information on the error.</p> <p>Body Notes: The response may</p>	√	√	√	√

HTTP Status Codes	REST Meaning	GET	PUT	POST	DELETE
	contain more information of the underlying error that occurred in addition to the Reason-Phrase.				
403	<p>“Forbidden” – The request is not allowed because the server is refusing to fill the request. A common reason for this is that the device does not support the requested functionality.</p> <p>Header Notes: The Reason-Phrase sent with the HTTP status header may contain information on the error.</p> <p>Body Notes: The response may contain more information of the underlying error that occurred in addition to the Reason-Phrase.</p>	√	√	√	√
404	<p>“Not Found” – The requested resource does not exist.</p> <p>Header Notes: None</p> <p>Body Notes: None</p>	√	√	√	√
405	<p>“Method Not Allowed” – The request used an HTTP method that is not supported for the resource because the specification does not allow this method. If the device does support the functionality but it is a valid operation (that has been defined in this specification), then 403 is returned.</p> <p>Header Notes: The Allow header lists the supported HTTP methods for this resource.</p> <p>Body Notes: None</p>	√	√	√	√
500	<p>“Internal Server Error” - An internal server error has occurred.</p> <p>Header Notes: None</p> <p>Body Notes: None</p>	√	√	√	√

HTTP Status Codes	REST Meaning	GET	PUT	POST	DELETE
503	<p>“Service Unavailable” – The HTTP Server is up, but the REST service is not available. Typically this is caused by too many client requests.</p> <p>Header Notes: The Retry-After header suggests to the client when to try resubmitting the request.</p> <p>Body Notes: None</p>	√	√	√	√

Responses to many resources calls contain data in XML format. XML Response Schema is defined in Annex. XML Response Schema consists of the following sections:

- requestURI - the URI of the corresponding HTTP request message
- statusCode - indicating the status of the REST operations.

Table 4

statusCode	Description
1	“OK” - indicate a successful operation is done (remark: if the request contains some parameters that are not supported, the device will ignore those parameters and return OK as statusCode)
2	“Device Busy” - for a command which cannot be processed at that time (i.e. if the device receives a reboot command during upgrading process)
3	“Device Error” - if the device can not perform the request for a hardware error. An error message in statusString format to indicate operation failure
4	“Invalid Operation” - either if the operation is not supported by the device, or if the user has not passed the authentication, or if the user does not have enough privilege for this operation
5	“Invalid XML Format” - if the XML format is not recognized by the system. There will be statusString returned to represent different errors
6	“Invalid XML Content” - an incomplete message or a message containing an out-of-range parameter. Relative statusString will be return.
7	“Reboot Required” - If a reboot is required before the operation taking effect

- statusString – error type for the not completed operation.
- id – Return the ID created by the device in POST operation

4.6 Namespaces

The namespace `xmlns:hik="http://www.hikvision.com/ver10/XMLSchema"` is used in this specification.

The following namespaces are referenced by this specification:

- `xmlns:xs="http://www.w3.org/2001/XMLSchema"`
- `xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"`
- `xmlns:xlink="http://www.w3.org/1999/xlink"`

4.7 Security

User-based access control is adopted in this specification. Security policy configuration in this specification based on three different user levels.

- Administrator – the privilege can access all supported resources on IP device.
- Operator – the privilege can access some general-level and higher-level resources. See the Resource Description of each resource for details.
- Viewer – the privilege can only access some general-level resources. See the Resource Description of each resource for details.

In order to access all supported resources, one account with Administrator privilege level must be active at all times. A default user account “admin” is provided by all IP devices. It has an Administrator user level, and must not be deleted. Its default password is “12345”.

5 Device discovery

The IP devices support Universal Plug and Play (UPnP) technology to discovery/locate themselves. A UPnP compatible device will automatically announce its network address, supported devices and services types when connected to a network, and therefore becoming “plug-and-play” by allowing clients recognize those information and begin using this device immediately.

The UPnP architecture supports zero-configuration networking, and the device can dynamically join a network, obtain IP address, announce its name, convey its capabilities upon request, and gets the on-line status and capabilities of other devices. DHCP and DNS servers are optional and are only used if they are available on the network. Devices can leave the network automatically without leaving any unwanted status information behind. UPnP was published as a 73-part International Standard, ISO/IEC 29341, in December, 2008 [6][7][8].

The foundation for UPnP networking is IP addressing. When a device is connected to the network for the first time, its Dynamic Host Configuration Protocol (DHCP) client will search for a DHCP server. If the device successfully get its domain name via DNS server or DNS forwarding, then it should use this domain name for the following network operations; if the network is unmanaged and no DHCP server is found, the device must assign an address for itself, which is known as “AutoIP” of the UPnP Device Architecture [9][10], and use this IP address for the following network operations.

Once given an IP address, the Discovery process will be executed in UPnP networking. The UPnP discovery protocol is also known as Simple Service Discovery Protocol (SSDP). When a device is added to the network, SSDP allows that device to announce its services to the control points on the network. Similarly, when a control point is added to the network, SSDP allows that control point to search for relative devices on the network. During the above searching or announcing process, a discovery message which contains essential device specifics or one of its services will be transferred, for example, device type, identifier, and a pointer to more detailed information.

After a control point has discovered a device, the control point still needs more operations to request more information about the device or to interact with it. An HTTP GET request for mandatory index Special Resource will return a list of the resources supported by the device.

Remark: the index resource will only return the first level resources of a node, while the indexr Special Resource will return a complete folder list in tree structure with the current resource as root folder.

6 Resource Description

6.1 Resource Description Outline

Each resource in this specification is defined using the following format.

Resource_URI		Type	Version
Operation_Name		User Lever	
Description	Description of the operation.		
Query	Indicates the name/value pairs (p1, p2, p3,...,pn) for the resource.		
Inbound Data	Indicates inbound data for the resources.		
Success Return	the Type (if present) and the name of XML Data Block		
Notes: describes any special processing rules for the resource.			

Type refers to “Special Resource”, “Service” and “General Resource”.

Version is used to determine the version of the protocol. The version number shall be set to “1.0” in this specification.

Operation_Name refers to “GET”, “PUT”, “POST” and “DELETE”.

Inbound Data includes three types as follows:

- NONE –no input data
- DataBlock – the name of an XML Data Block. Datablocks used here must be defined according to the specification.
- Mime type – mime type for the input data in the HTTP payload. Remark: “application/ xml” is not a valid mime type.

If a device does not support particular XML tags or blocks, then it may not be supported by the resource operations.

Generally, if a field is not provided in the inbound XML, then its current values shall not be modified in the device’s repository.

If a required field did not exist in the device’s repository, then it must be provided in the applicable resource operations.

Success Return and Error Return detailed description see Section 4.5.5.

6.2 Built-in Types

Table 5

Type	Description
BaudRate	A positive numerical value indicating the data transmission rate in symbols per second. Value is ≥ 0 . Example: 9600
Color	RGB triplet in hexadecimal format (3 bytes) without the preceding "0x". Example: “FF00FF”
Coordinate	A positive numerical value in pixels. A coordinate pair of 0,0 (x,y) indicates the bottom-left corner of the video image. Value is ≥ 0 . Maximum value is dependent on video resolution.
FPS	Frame rate multiplied by 100. Example: 2500 [PAL]
IPv4 Address	Notation is xxx.xxx.xxx.xxx Example: 3.137.217.220
MAC	MAC Address Notation is aa:bb:cc:dd:ee:ff with 6 hex bytes.

6.3 Annotation

The XML Data Blocks described in this document contains annotations for the field's properties. Please refer to the XML schema definitions for detail description.

The following annotation content is inserted into the comments to describe the data carried in the field:

Table 6

Annotation	Description
req	Required field.
opt	Optional field. For data uploaded to the device, if the field is present but the device does not support it, it should be ignored.
dep	This field is required depending on the value of another field.
ro	Read-only. For XML data that is both read and written to the device, this field is only present in XML returned from the device. If this field is present in XML uploaded to the device, it should be ignored.
wo	Write-only. This field is only present in XML that can be uploaded to the device. This field should never be present in data returned from the device. [This is used for uploading passwords].
xs:<type>	A type defined in XML Schema Part 2: Datatypes Second Edition, see http://www.w3.org/TR/xmlschema-2

Remark: optional XML structures may contain required fields for the operation, which mean that even if the entire XML block is optional, some of its contained fields may still be necessary if required.

7 Special Resources

7.1 index

index		Special Resource	v1.0
GET		Viewer	
Description	Enumerate child resources of a resource.		
Query	None		
Inbound Data	None		
Success Return	hik:ResourceList ResourceList		
Notes: Returns a non-recursive resource listing of all child resources.			

7.2 indexr

indexr		Special Resource	v1.0
GET		Viewer	
Description	Enumerate child resources of a resource.		
Query	None		
Inbound Data	None		
Success Return	hik:ResourceList ResourceList		
Notes: Returns a recursive resource listing of all child resources.			

7.3 description

description		Special Resource	v1.0
GET			Viewer
Description	Describe the corresponding resource		
Query	None		
Inbound Data	None		
Success Return	hik:ResourceDescription ResourceDescription		
Notes: <version> set the version of resource. In this specification, its value is “1.0”.			

A version attribute is included in the description. This means resources with different versions may exist within the same Services. In that case, the version of Services is the version of the contained resource with the lowest version, and all resources in the Services container must be backward compatible. If any resource of a Service container can not maintain backward compatibility with previous versions, a new Services version should be introduced.

7.4 capabilities

capabilities		Special Resource v1.0
GET		Viewer
Description	Describe the capabilities of the corresponding resource	
Query	None	
Inbound Data	None	
Success Return	the XML Data Block resource-specified	
Notes:		

For the General Resource, which inbound data is specified as an XML payload, the

Special Resource (capabilities) is provided for video management systems or client applications to query an IP device and understand what XML tags are supported.

“Capabilities” is essentially an XML instance of the corresponding General Resource XML Data Block. “Capabilities” must contain the acceptable values for each attribute.

While XML Schema Document are also required of any XML data defined by this specification and xsd documents are capable of defining the acceptable range of values for any attribute, using a global xsd to define capacities would imply that all devices support the same options for any parameter. By allowing devices to respond to the capabilities request, each device can support different values for any attribute, within the constraints of the schema.

Table 7

Capabilities Attribute	Description	Syntax	Applicable XML Data Types
min	The minimum character length for a string, or the minimum numerical value of a number	Examples: min="0" min="19" min="-74"(numerical only) min="1.6"	All except fixed data types ¹⁾
max	The maximum character length for a string, or the maximum numerical value of a number	Examples: max="4" max="37" max="8192" max="14.61"	All except fixed data types ¹⁾
range	Indicates the possible range of numerical values within the “min” and “max” attributes of an element. This attribute should only be used if the possible value for an XML element does not include the entire numerical range between “min” and “max” attributes	Ranges are listed in numerical order separated by a “,” character. A range has the form “x~y” where x is the range floor and y is the range ceiling. Single numbers may also be used. Example: if an XML element supports values 0, 456, 1674 to 2009 and 2012, the syntax would be: range="0, 456, 1674~2009, 2012"	All numerical data types

Capabilities Attribute	Description	Syntax	Applicable XML Data Types
opt	Lists the supported options for a CodeID data type. Required for XML elements with a CodeID data type. This attribute should not be used for any other data type	If all options are supported, the syntax is "all". Otherwise, supported options are listed separated by a ", " character. Examples: opt="all" opt="1, 4, 6, 7"	CodeID
def	Indicates the default value of the XML element. If the element has not default value, this attribute should not be used	Examples: def="7416" def="ace"	All data types
reqReboot	Indicates if configuration of this XML element requires a device reboot before taking effect. If an element does not require a boot, this attribute should not be used	reqReboot="true"	All data types
dynamic	Indicates if an XML element has dynamic capabilities dependent on other XML configuration. For example, if an element's data range changes based on another element's configured value, this attribute must be used. In this case, the element's capability attributes must always reflect the current device configuration	dynamic="true"	All data types
Size	Indicates the maximum number of entries in an XML List. This attribute is only applicable to XML list elements. This attribute should not be used for any other type of element	Example: If a device supports 16 users the example would be <UserList size="16"> <User> ... </UserList>	Only supported for list elements

1) Fixed, pre-defined data types do not need certain capability attributes because their formats/data ranges are already defined.

Special Resources do not contain themselves.

The requestURIs “/index”, “/indexr”, “/description” are required.

8 Services and General Resources

8.1 System

/System	Service v1.0
Notes:	

8.1.1 Device Information

/System/deviceInfo		General Resource v1.0
GET		Viewer
Description	It is used to get device information.	
Query	None	
Inbound Data	None	
Success Return	DeviceInfo	
PUT		Administrator
Description	It is used to update device information.	
Query	None	
Inbound Data	DeviceInfo	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Some fields are read-only and may not be set. If these fields are present in the inbound XML block, they are ignored.		
For the <DeviceInfo> uploaded to the device during a PUT operation, all fields are considered optional and any fields that are not present in the inbound XML are not changed on the device. This allows setting of the fields individually without having to load the entire XML block to the device.		
<deviceDescription> is a description of the device as defined in RFC1213.		
For IPC the <deviceDescription> value is IPCamera;		
For IP speed Dome the <deviceDescription> value is IPDome;		
For DVR or DVS the <deviceDescription> value is DVRDVS;		

<deviceLocation> is the location of the device as defined in RFC1213
 <systemContact> is the contact information for the device as defined in RFC1213.

DeviceInfo XML Block

```
<DeviceInfo version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <deviceName>      <!-- req, xs:string -->      </deviceName>
  <deviceId>         <!-- req, xs:integer, "1-255"--> </deviceId>
    <!-- Note: The following are read-only parameters -->
  <deviceDescription> <!-- ro, req, xs:string --> </deviceDescription>
  <deviceLocation>   <!-- ro, req, xs:string --> </deviceLocation>
  <systemContact>    <!-- ro, req, xs:string --> </systemContact>
  <model>            <!-- ro, req, xs:string --> </model>
  <serialNumber>     <!-- ro, req, xs:string --> </serialNumber>
  <macAddress>       <!-- ro, req, xs:string; --> </macAddress>
  <firmwareVersion>  <!-- ro, req, xs:string --> </firmwareVersion>
  <firmwareReleasedDate> <!-- ro, opt, xs:string --> </firmwareReleasedDate>
  <bootVersion>      <!-- ro, opt, xs:string --> </bootVersion>
  <bootReleasedDate> <!-- ro, opt, xs:string --> </bootReleasedDate>
  <hardwareVersion>  <!-- ro, opt, xs:string --> </hardwareVersion>
</DeviceInfo>
```

8.1.2 Configuration file(s)

/System/configurationFile		General Resource v1.0
GET		Administrator
Description	It is used to get device's configuration file(s).	
Query	None	
Inbound Data	None	
Success Return	Opaque Data	
PUT		Administrator
Description	It is used to update device's configuration file(s).	
Query	None	
Inbound Data	Opaque Data	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Configuration file is device-dependant – it may be binary or any other format.		
Should reboot device after configuration file is applied.		

8.1.3 Factory default

/System/factoryDefault		General Resource v1.0
PUT		Administrator
Description	It is used to reset the configuration for the device to the factory default.	
Query	mode	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: Two factory reset modes are supported: “full” resets all device parameters and settings to their factory values. “basic” resets all device parameters and settings except the values in Network Service. The default mode is “full”. The device should be rebooted after it is reset.		

8.1.4 Firmware upgrade

/System/firmwareUpgrade		General Resource v1.0
PUT		Administrator
Description	It is used to upgrade the firmware of the device.	
Query	None	
Inbound Data	Opaque Data	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
The device should be rebooted after the upgrade is completed.		

8.1.5 Reboot

/System/reboot		General Resource v1.0
PUT		Administrator
Description	It is used to reboot the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
ResponseStatus is returned before the device proceeds to reboot.		

8.1.6 Status

/System/status		General Resource	v1.0
GET		Viewer	
Description	It is used to get the status information of the device.		
Query	None		
Inbound Data	None		
Success Return	DeviceStatus		
Notes:			

DeviceStatus XML Block

```
<DeviceStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <currentDeviceTime> <!-- req, xs:datetime --> </currentDeviceTime>
  <deviceUpTime> <!-- req, xs:integer, seconds --> </deviceUpTime>
  <CPUList> <!-- req -->
    <CPU>
      <cpuDescription> <!-- req, xs:string --> </cpuDescription>
      <cpuUtilization> <!-- req, xs:integer, percentage 0..100 --> </cpuUtilization>
    </CPU>
  </CPUList>
  <MemoryList> <!-- req -->
    <Memory>
      <memoryDescription> <!-- req, xs:string --> </memoryDescription>
      <memoryUsage> <!-- req, xs:float, in MB --> </memoryUsage>
      <memoryAvailable> <!-- req, xs:float, in MB--> </memoryAvailable>
    </Memory>
  </MemoryList>
</DeviceStatus>
```

8.1.7 Time

/System/time		General Resource v1.0
GET		Viewer
Description	It is used to get the device time information.	
Query	None	
Inbound Data	None	
Success Return	Time	
PUT		Administrator

Description	It is used to update the device time information.
Query	None
Inbound Data	Time
Success Return	hik:ResponseStaus ResponseStatus
Notes: If <timeMode> is present and set to “local”, the <localTime> and <timeZone> fields are required. The <localTime> block sets the device time. If <timeMode> is present and set to “NTP”, only the <timeZone> field is required. The device time is set by synchronizing with NTP.	

Time XML Block

```
<Time version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <timeMode>    <!-- req, xs:string, "NTP, manual" -->    </timeMode>
  <localTime>    <!-- req, xs:datetime -->                </localTime>
  <timeZone>    <!-- req, xs:string, POSIX time zone string -->    </timeZone>
</Time>
```

8.1.8LocalTime

/System/time/localTime		General Resource v1.0
GET		Viewer
Description	It is used to get the device local time information.	
Query	None	
Inbound Data	None	
Success Return	ISO 8601 Date-Time String	
PUT		Administrator
Description	It is used to update the device local time information.	
Query	None	
Inbound Data	ISO 8601 Date-Time String	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
An ISO 8601 Date/Time string is accepted and returned. If the date/time value has a time zone, the time is converted into the device's local time zone.		
If the device time mode is set to "ntp" setting this value has no effect.		

8.1.9TimeZone

/System/time/timeZone	General Resource v1.0
-----------------------	-----------------------

GET		Viewer
Description	It is used to get the device time zone information.	
Query	None	
Inbound Data	None	
Success Return	Time zone string	
PUT		Administrator
Description	It is used to udpate the device time zone information.	
Query	None	
Inbound Data	Time zone string	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: Time zones are defined by POSIX 1003.1 section 8.3 time zone notations. Note that the value following the +/- is the amount of time that must be added to the local time to result in UTC. Example: EST+5EDT01:00:00,M3.2.0/02:00:00,M11.1.0/02:00:00 Defines eastern standard time as “EST” with a GMT-5 offset. Daylight savings time is called “EDT”, is one hour later and begins on the second Sunday of March at 2am and ends on the first Sunday of November at 2am. CET-1CEST01:00:00,M3.5.0/02:00:00,M10.5.0/03:00:00 Defines central European time as GMT+1 with a one-hour daylight savings time (“CEST”) that starts on the last Sunday in March at 2am and ends on the last Sunday in October at 3am.		

8.1.10 NtpServers

/System/time/ntpServers		General Resource v1.0
GET		Viewer
Description	It is used to get the configuration of NTP servers for the device.	
Query	None	
Inbound Data	None	
Success Return	NTPServerList	
PUT		Administrator
Description	It is used to update the configuration of NTP servers for the device.	
Query	None	

Inbound Data	NTPServerList
Success Return	hik:ResponseStaus ResponseStatus
POST Administrator	
Description	It is used to add the configuration of a NTP server for the device.
Query	None
Inbound Data	NTPServer
Success Return	hik:ResponseStaus ResponseStatus
DELETE Administrator	
Description	It is used to delete the configuration of NTP servers for the device.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: When the <timeMode> is set to “NTP”, the servers in this list are used to synchronize the device’s system time.	

NTPServerList XML Block

```
<NTPServerList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <NTPServer/> <!-- opt -->
</ NTPServerList>
```

8.1.11 NtpServer

/System/time/ntpServers/ID		General Resource v1.0
GET		Viewer
Description	It is used to get the configuration of a NTP server for the device.	
Query	None	
Inbound Data	None	
Success Return	NTPServer	
PUT		Administrator
Description	It is used to update the configuration of a NTP server for the device.	
Query	None	
Inbound Data	NTPServer	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Administrator
Description	It is used to delete the configuration of a NTP server for the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

Depending on the value of <addressingFormatType>, either the <hostName> or the IP address fields will be used to locate the NTP server.

NTPServer XML Block

```
<NTPServer version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>    <!-- req, xs:integer, "1"-->    </id>
  <addressingFormatType>
    <!-- xs:string, "ipaddress,hostname" -->
  </addressingFormatType>
  <hostName>    <!-- dep, xs:string -->    </hostName>
  <ipAddress>    <!-- dep, xs:string -->    </ipAddress>
  <portNo>    <!-- ro, opt, xs:integer -->    </portNo>
</NTPServer>
```

8.1.12 Log

/System/logging		General Resource	v1.0
GET		Viewer	
Description	It is used to get the log information of the device.		
Query	majorType minorType startTime stopTime		
Inbound Data	None		
Success Return	LogList		
Notes: The value of “majorType” is: 0x1:Alarm 0x2:Exception 0x3:Operation When the value of “majorType” is 0x1, the value of “minorType” is: 0x1: alarm input 0x2: alarm output 0x3: motion detection alarm start 0x4: motion detection alarm stop 0x5: shelter alarm start 0x6: shelter alarm stop When the value of “majorType” is 0x2, the value of “minorType” is: 0x21: video loss 0x22: illegal access 0x23: hard disk full			

0x24: hard disk error

0x25: modem off-line

0x26: ip address conflict

0x27: network not connected

When the value of “majorType” is 0x3, the value of “minorType” is:

0x41: boot

0x42: shutdown

0x43: illegal shut down

0x50: login(local)

0x51: logout(local)

0x52: config parameter(local)

0x53: playback by file name(local)

0x54: playback by time(local)

0x55: start record(local)

0x56: stop record(local)

0x57: PTZ control(local)

0x58: preview(local)

0x59: modify date/time(local)

0x5a: upgrade software(local)

0x70: login(remote)

0x71: logout(remote)

0x72: start record(remote)

0x73: stop record(remote)

0x74: start transparent channel(remote)

0x75: stop transparent channel(remote)

0x76: get parameter(remote)

0x77: config parameter(remote)

0x78: get status(remote)

0x79: on guard(remote)

0x7a: disarm(remote)

0x7b: reboot(remote)

0x7c: start voice talk

0x7d: stop voice talk

0x7e: upgrade software(remote)

0x7f: playback by file name(remote)

0x80: playback by time(remote)

0x81: PTZ control(remote)

The format of “startTime” and “stopTime” is “YYYY-MM-DDThh:mm:ss”.

Devices support up to 2000 log.

LogList XML Block

```
<LogList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
```



```

<Log> <!-- opt -->
  <id> <!-- req, xs:integer --> </id>
  <time> <!-- req, xs:datetime --> </time>
  <majorType> <!-- req, xs:string --> </majorType>
  <minorType> <!-- req, xs:string --> </minorType>
  <netUser> <!-- req, xs:string --> </netUser>
  <hostIPAddress> <!-- req, xs:string --> </hostIPAddress>
  <channel> <!-- req, xs:integer --> </channel>
</Log>
</LogList>

```

8.1.13 Storage

/System/Storage	resource v1.0
Notes: service of Storage	

8.1.13.1 Storage/volumes

/System/Storage/volumes	
GET	
Viewer	
Description	It is used to get the storage volumes and files information on a device
Query	None
Inbound Data	None
Success Return	StorageVolumeList
PUT	
Operator	
Description	It is used to update the storage volumes and files configuration on a device.
Query	None
Inbound Data	StorageVolumeList
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

StorageVolumeList XML Block

```

<StorageVolumeList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <StorageVolume/> <!-- ro, opt -->
</StorageVolumeList>

```

8.1.13.2 Storage/volumes/ID

/System/Storage/volumes/ID	
GET	Viewer
Description	It is used to get a special storage volume information on a device
Query	None
Inbound Data	None
Success Return	StorageVolume
Notes:	

StorageVolume XML Block

```
<StorageVolume version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>    <!-- ro, req, xs:string --> </id>
  <volumeName> <!-- ro, req, xs:string --> </volumeName>
  <volumePath> <!-- ro, opt, xs:string --> </volumePath>
  <volumeDescription><!-- ro, opt, xs:string --> </volumeDescription>
  <volumeType>
    <!-- ro, req, xs:string, "VirtualDisk,RAID0,RAID1,RAID0+1,RAID5", etc -->
  </volumeType>
  <storageDescription>
    <!-- ro, opt, xs:string, "DAS","DAS/USB", etc -->
  </storageDescription>
  <storageLocation>
    <!-- ro, opt, xs:string, "HDD","Flash","SDIO", etc-->
  </storageLocation>
  <storageType>
    <!-- ro, opt, xs:string, "internal,external" -->
  </storageType>
  <capacity>    <!-- ro, req, xs:float, in MB --> </capacity>
  <status> <!--ro, req, xs:string "HD_NORMAL, HD_ERROR, HD_IDLE" --> </status>
</StorageVolume>
```

8.1.13.3 Storage/volumes/ID/status

/System/Storage/volumes/ID/status	
GET	Viewer
Description	It is used to get a special storage volume status on a device
Query	None
Inbound Data	None

Success Return	StorageVolumeStatus
Notes: Query the volume status. Currently only the amount of free space is returned. Devices may extend the XML to allow for querying additional information.	

StorageVolumeStatus XML Block

```
<StorageVolumeStatus                                version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <freeSpace>    <!-- ro, req, xs:float, in MB -->    </freeSpace>
</StorageVolumeStatus>
```

8.1.13.4 Storage/volumes/ID/format

/System/Storage/volumes/ID/format	
PUT	Viewer
Description	It is used to format a storage device
Query	None
Inbound Data	None
Success Return	StorageVolumeStatus
Notes: Formating may take time.	

8.1.13.5 Storage/volumes/ID/isFormat

/System/Storage/volumes/ID/IsFormat	
GET	Viewer
Description	It is used to access the procedure of formating
Query	None
Inbound Data	None
Success Return	StorageVolumeFormatSatus
Notes: formatSatus show the percentage of formatted part of the storage device.	

StorageVolumeStatus XML Block

```
<StorageVolumeFormatSatus                            version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <formatSatus><!-- req, xs:integer,"0--100"--></formatSatus>
</StorageVolumeFormatSatus>
```

8.2 Network

/Network	Service v1.0
Notes: Network configuration.	

8.2.1 Interfaces

/Network/interfaces		General Resource	v1.0
GET		Viewer	
Description	It is used to get the device network interfaces.		
Query	None		
Inbound Data	None		
Success Return	NetworkInterfaceList		
Notes:			
As hardwired system resources, network interfaces cannot be created or destroyed.			

NetworkInterfaceList XML Block

```
<NetworkInterfaceList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <NetworkInterface/> <!-- opt -->
</NetworkInterfaceList>
```

8.2.2 Interface

/Network/interfaces//ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular network interface.	
Query	None	
Inbound Data	None	
Success Return	NetworkInterface	
PUT		Administrator
Description	It is used to update a particular network interface.	
Query	None	
Inbound Data	NetworkInterface	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

NetworkInterface XML Block

```
<NetworkInterface version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>      <!-- req, xs:integer, "1" -->    </id>
  <IPAddress/>  <!-- req -->
  <Discovery/>  <!-- opt -->
  <PPPoE /> <!-- opt -->
  <DDNS /> <!-- opt -->
</NetworkInterface>
```

8.2.3IPAddress

/Network/interfaces/ID/ipAddress		General Resource v1.0
GET		Viewer
Description	It is used to get the ip address of a particular network interface.	
Query	None	
Inbound Data	None	
Success Return	IPAddress	
PUT		Administrator
Description	It is used to update the ip address of a particular network interface.	
Query	None	
Inbound Data	IPAddress	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
If <addressingType> is dynamic, fields below it need not be provided.		
If <addressingType> is dynamic, a DHCP client is used for the device.		
If <addressingType> is static the device IP address is configured manually and the gateway and DNS fields are optional.		
<subnetMask> notation is “xxx.xxx.xxx.xxx”.		

IPAddress XML Block

```
<IPAddress version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ipVersion>      <!-- req, xs:string, "v4" -->    </ipVersion>
  <addressingType>  <!-- req, xs:string, "static,dynamic" -->  </addressingType>
  <ipAddress>      <!-- req, xs:string -->          </ipAddress>
  <subnetMask>      <!-- req, xs:string, subnet mask for IPv4 address -->
  </subnetMask>
  <DefaultGateway>  <!-- dep -->
    <ipAddress>    <!-- req, xs:string -->    </ipAddress>
  </DefaultGateway>
  <PrimaryDNS>      <!-- dep -->
    <ipAddress>    <!-- req, xs:string -->    </ipAddress>
  </PrimaryDNS>
```

</IPAddress>

8.2.4 Wireless

/Network/interfaces/ID/wireless		General Resource v1.0
GET		Viewer
Description	It is used to get the WIFI information of a wireless network interface.	
Query	None	
Inbound Data	None	
Success Return	Wireless	
PUT		Administrator
Description	It is used to update the WIFI information of a wireless network interface.	
Query	None	
Inbound Data	Wireless	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
If the <securityMode> field is "WEP", the <WEP> block must be provided.		
If the <securityMode> field is "WPA" or "WPA2-personal", the <WPA> block must be provided.		
<channel> corresponds to an 802.11g wireless channel number or "auto" for autoconfiguration.		
<wmmEnabled> enables 802.11e, QoS for IEEE 802.11 networks (Wi-Fi Multimedia)		
<defaultTransmitKeyIndex> indicates which encryption key is used for WEP security.		
<encryptionKey> is the WEP encryption key in hexadecimal format.		
<sharedKey> is the pre-shared key used in WPA		

Wireless XML Block

```
<Wireless version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <wirelessNetworkMode>
    <!-- opt, xs:string, "infrastructure,adhoc" -->
  </wirelessNetworkMode>
  <channel> <!-- opt, xs:string, "1-14,auto" --> </channel>
  <ssid> <!-- opt, xs:string --> </ssid>
  <wmmEnabled> <!-- opt, xs:boolean --> </wmmEnabled>
  <WirelessSecurity> <!-- opt -->
    <securityMode>
      <!-- opt, xs:string, "disable,WEP,WPA-personal,WPA2-personal,WPA-RADIUS,
        WPA-enterprise,WPA2-enterprise" -->
    </securityMode>
  </WirelessSecurity>
</Wireless>
```

```

<WEP> <!-- dep, depends on <securityMode> -->
  <authenticationType>
    <!-- req, xs:string, "open,sharedkey,auto" -->
  </authenticationType>
  <defaultTransmitKeyIndex> <!-- req, xs:integer --> </defaultTransmitKeyIndex>
  <wepKeyLength> <!-- opt, xs:integer "64,128,152" --> </wepKeyLength>
  <wepKeyType><!-- opt, xs:string "HEX,ASCII" --> </wepKeyType>
  <EncryptionKeyList>
    <encryptionKey>
      <!-- req, xs: HexBinary string or ASCII string -->
    </encryptionKey>
  </EncryptionKeyList>
</WEP>
<WPA> <!-- dep, depends on <securityMode> -->
  <algorithmType> <!-- req, xs:string, "TKIP,AES,TKIP/AES"--> </algorithmType>
  <sharedKey> <!-- req, xs:string, pre-shared key used in WPA --> </sharedKey>
  <wpaKeyLength><!-- req, xs: integer, "8-63"--></wpaKeyLength>
</WPA>
</WirelessSecurity>
</Wireless>

```

8.2.5DetectedWirelessList

/Network/interfaces/ID/detectedWirelessList		General Resource v1.0
GET		Viewer
Description	It is used to get all detected wireless networks.	
Query	None	
Inbound Data	None	
Success Return	detectedWirelessList	

detectedWireless XML Block

```

<DetectedWirelessList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <DetectedWireless/>
</DetectedWirelessList>

```

8.2.6DetectedWireless

/Network/interfaces/ID/detectedWirelessList/ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get a special detected wireless network.		
Query	None		
Inbound Data	None		
Success Return	detectedWireless		

detectedWirelessList XML Block

```
<DetectedWireless version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer--> </id>
  <wirelessNetworkMode>
    <!-- opt, xs:string, "infrastructure,adhoc" -->
  </wirelessNetworkMode>
  <channel> <!-- opt, xs:string, "1-14,auto" --> </channel>
  <ssid> <!-- req, xs:string --> </ssid>
  <speed> <!-- opt, xs:Integer, in Mbps--></speed>
  <signalStrength><!-- opt, xs:Integer,"0-100">< /signalStrength>
  <securityMode>
    <!-- req, xs:string, "disable,WEP,WPA-personal,WPA2-personal,WPA-RADIUS,
      WPA-enterprise,WPA2-enterprise" -->
  </securityMode>
</DetectedWireless>
```

8.2.7Discovery

/Network/interfaces/ID/discovery		General Resource	v1.0
GET		Viewer	
Description	It is used to get the discovery settings of a particular network interface.		
Query	None		
Inbound Data	None		
Success Return	Discovery		
PUT		Administrator	
Description	It is used to update the discovery settings of a particular network interface.		
Query	None		

Inbound Data	Discovery
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

Discovery XML Block

```
<Discovery version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <UPnP>      <!-- req -->
    <enabled>   <!-- req, xs:boolean -->  </enabled>
  </UPnP>
  <Zeroconf>   <!-- opt -->
    <enabled>   <!-- req, xs:boolean -->  </enabled>
  </Zeroconf>
</Discovery>
```

8.2.8PPPoE

/Network/interfaces/ID/pppoe		General Resource v1.0
GET		Viewer
Description	It is used to get the PPPoE configuration of a particular network interface.	
Query	None	
Inbound Data	None	
Success Return	PPPoE	
PUT		Administrator
Description	It is used to update the PPPoE configuration of a particular network interface.	
Query	None	
Inbound Data	PPPoE	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<password> is a write-only field.		

PPPoE XML Block

```
<PPPoE version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled>     <!-- req, xs:boolean -->  </enabled>
  <userName>    <!-- req, xs:string -->   </userName>
  <password>    <!-- wo, req, xs:string --> </password>
  <dynamicIP>   <!--opt, xs:string -->    </ dynamicIP >
</PPPoE>
```

8.2.9 DDNS

/Network/interfaces/ID/ddns		General Resource v1.0
GET		Viewer
Description	It is used to get DDNS configuration of a particular network interface.	
Query	None	
Inbound Data	None	
Success Return	DDNS	
PUT		Administrator
Description	It is used to update DDNS configuration of a particular network interface.	
Query	None	
Inbound Data	DDNS	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
When <provider> is “IPServer”, <serverIPAddress> is required.		
When <provider> is “DysDNS”, all fields are required except the <portNo>.		
When <provider> is “PeanutHall”, all fields are required except the <serverIPAddress> and <portNo>.		
<password> is a write-only field.		

DDNS XML Block

```
<DDNS version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled>    <!-- req, xs:boolean --> </enabled>
  <provider>    <!-- req, xs:string, "IPServer, DynDNS, PeanutHall" --> </provider>
  <serverIPAddress> <!-- dep, xs:string --> </serverIPAddress>
  <portNo> <!-- dep, xs:integer --> </portNo>
  <domainName> <!-- dep, xs:string --> </domainName>
  <userName> <!-- dep, xs:string --> </userName>
  <password> <!-- wo, dep, xs:string --> </password>
</DDNS>
```

8.2.10 NFSList

/Network/interfaces/ID/NFSList		General Resource v1.0
GET		Viewer
Description	It is used to get the configuration of NFSs for a particular network interface.	
Query	None	

Inbound Data	None
Success Return	NFSList
PUT Administrator	
Description	It is used to update the configuration of NFSs for a particular network interface.
Query	None
Inbound Data	NFSList
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

NFSList XML Block

```
<NFSList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <NFS/>
</ NFSList >
```

8.2.11 NFS

/Network/interfaces//ID/NFSList/ID		General Resource v1.0
GET		Viewer
Description	It is used to get the NFS configuration of a particular network interface.	
Query	None	
Inbound Data	None	
Success Return	NFS	
PUT		Administrator
Description	It is used to update the NFS configuration of a particular network interface.	
Query	None	
Inbound Data	NFS	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

NFS XML Block

```
<NFS version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer --> <id>
  <NFSIPAddress> <!-- req, xs:string --> </ NFSIPAddress >
  <NFSDirectory> <!-- req, xs:string --> </ NFSDirectory >
</ NFS >
```

8.2.12 Adapter

/Network/interfaces/ID/Adapter		General Resource	v1.0
GET		Viewer	
Description	It is used to get the adapter configuration of a particular network interface.		
Query	None		
Inbound Data	None		
Success Return	Adapter		
PUT		Administrator	
Description	It is used to update the adapter configuration of a particular network interface.		
Query	None		
Inbound Data	Adapter		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<mode> identifies the transmission speed mode of network interface card			
The following speed mode are supported:			
10M/half-duplex			
10M/duplex			
100M/half-duplex			
100M/duplex			
auto			

NFS XML Block

```
<Adapter version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <description>    <!-- ro, req, xs:string -->    </description>
  <mode>    <!-- req, xs:string -->    </mode>
</Adapter>
```

8.2.13 Examples

Example: Getting the Network Settings

```
GET /Network/interfaces HTTP/1.1
...
HTTP/1.1 200 OK
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx
```

```
<?xml version="1.0" encoding="UTF-8"?>
<NetworkInterfaceList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <NetworkInterface>
    <id>1</id>
    <IPAddress>
      <ipVersion>v4</ipVersion>
      <addressingType>static</addressingType>
      <ipAddress>172.6.64.7</ipAddress>
      <subnetMask>255.255.255.0</subnetMask>
      <DefaultGateway>
        <ipAddress>172.6.64.1</ipAddress>
      </DefaultGateway>
      <PrimaryDNS>
        <ipAddress>192.0.0.200</ipAddress>
      </PrimaryDNS>
    </IPAddress>
    <Discovery>
      <UPnP>
        <enabled>true</enabled>
      </UPnP>
      <Zeroconf>
        <enabled>true</enabled>
      </Zeroconf>
    </Discovery>
    <PPPoE>
      <enabled>true</enabled>
      <userName>hikvision</userName>
    </PPPoE>
    <DDNS>
      <enabled>true</enabled>
      <provider>PeanutHall</provider>
      <domainName>hikvision.vicp.net</domainName>
      <userName>hikvision</userName>
    </DDNS>
  </NetworkInterface>
</NetworkInterfaceList>
```

Example: Setting the IP Address

```
PUT /Network/interfaces/1/ipAddress HTTP/1.1
```

```
...
```

Content-Type: application/xml; charset="UTF-8"

Content-Length: xxx

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<IPAddress version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
```

```
  <ipVersion>v4</ipVersion>
```

```
  <addressingType>static</addressingType>
```

```
  <ipAddress>172.6.64.16</ipAddress>
```

```
  <subnetMask>255.255.255.0</subnetMask>
```

```
  <DefaultGateway>
```

```
    <ipAddress>172.6.64.1</ipAddress>
```

```
  </DefaultGateway>
```

```
  <PrimaryDNS>
```

```
    <ipAddress>192.0.0.200</ipAddress>
```

```
  </PrimaryDNS>
```

```
</IPAddress>
```

HTTP/1.1 200 OK

...

Content-Type: application/xml; charset="UTF-8"

Content-Length:xxx

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<ResponseStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
```

```
  <requestURL>/Network/interfaces/1/ipAddress</requestURL>
```

```
  <statusCode>1</statusCode>
```

```
  <statusString>OK</statusString>
```

```
</ResponseStatus>
```

8.3 IO

/IO		Service	v1.0
GET		Viewer	
Description	It is used to get the I/O ports information.		
Query	None		
Inbound Data	None		
Success Return	IOPortList		
Notes:			
The allocation of IDs between input and output ports must be unique.			

IOPortList XML Block

```
<IOPortList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IOInputPortList/>    <!-- opt -->
  <IOOutputPortList/>  <!-- opt -->
</IOPortList>
```

8.3.1 Status

/IO/status		General Resource v1.0
GET		Viewer
Description	It is used to get the status of the I/O ports.	
Query	None	
Inbound Data	None	
Success Return	IOPortStatusList	
Notes: <ioPortID> refers to /IO/inputs/ID or /IO/outputs/ID. The port IDs are guaranteed to be unique across input and output ports. <ioState> indicates whether the input port is active or inactive. In most applications, a high signal is considered active.		

IOPortStatus XML Block

```
<IOPortStatusList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IOPortStatus>    <!-- req -->
    <ioPortID>    <!-- req, xs:integer, "1, 2" -->          </ioPortID>
    <ioPortType>  <!-- req, xs:string, "input,output" -->    </ioPortType>
    <ioState>     <!-- req, xs:string, "active,inactive" -->  </ioState>
  </IOPortStatus>
</IOPortStatusList>
```

8.3.2 Inputs

/IO/inputs		General Resource	v1.0
GET		Viewer	
Description	It is used to get the Input ports information.		
Query	None		
Inbound Data	None		
Success Return	IOInputPortList		
Notes:			
IO inputs are hardwired, meaning that the inputs are statically allocated by the device and			

cannot be created or deleted.

IOInputPortList XML Block

```
<IOInputPortList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IOInputPort/>    <!-- opt -->
</IOInputPort>
```

8.3.3 Input

/IO/inputs/ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get particular input port information.		
Query	None		
Inbound Data	None		
Success Return	IOInputPort		
PUT		Operator	
Description	It is used to update particular input port information.		
Query	None		
Inbound Data	IOInputPort		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<triggering> indicates the signal conditions to trigger the input port. High/Low will continuously trigger for the duration of high/low input signal.			

IOInputPort XML Block

```
<IOInputPort version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer -->          </id>
  <triggering>  <!-- req, xs:string, "high,low" --> </triggering>
</IOInputPort>
```

8.3.4 Input status

/IO/inputs/ID/status		General Resource	v1.0
GET		Viewer	
Description	It is used to get the status of a particular input port.		
Query	None		
Inbound Data	None		
Success Return	IOPortStatus		

Notes:

See /IO/status for an explanation of the fields.

8.3.5Outputs

/IO/outputs		General Resource v1.0
GET		Viewer
Description	It is used to get the output ports information.	
Query	None	
Inbound Data	None	
Success Return	IOOutputPortList	
Notes:		
IO outputs are hardwired, meaning that the outputs are statically allocated by the device and cannot be created or deleted.		

IOOutputPortList XML Block

```
<IOOutputPortList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IOOutputPort/>  <!-- opt -->
</IOOutputPort>
```

8.3.6Output

/IO/outputs/ID		General Resource v1.0
GET		Viewer
Description	It is used to get particular output port information.	
Query	None	
Inbound Data	None	
Success Return	IOOutputPort	
PUT		Operator
Description	It is used to update particular output port information.	
Query	None	
Inbound Data	IOOutputPort	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<p><PowerOnState> defines the output port configuration when the device is powered on.</p> <p><defaultState> is the default output port signal when it is not being triggered.</p> <p><outputState> is the output port signal when it is being triggered. Pulse will cause the output port to send a signal (opposite of the <defaultState>) for a duration specified by the</p>		

<pulseDuration> tag.
 <pulseDuration> is the duration of a output port signal when it is being triggered. It must be provided if the <outputState> is “pulse”.

IOOutputPort XML Block

```
<IOOutputPort version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer, "2" -->          </id>
  <PowerOnState>  <!-- req -->
    <defaultState> <!--ro, req, xs:string, "high,low" --> </defaultState>
    <outputState>  <!--ro, req, xs:string, "high,low,pulse" --> </outputState>
    <pulseDuration> <!-- dep, xs:integer, milliseconds --> </pulseDuration>
  </PowerOnState>
</IOOutputPort>
```

8.3.7 Output status

/IO/outputs//ID/status		General Resource	v1.0
GET		Viewer	
Description	It is used to get the status of a particular output port.		
Query	None		
Inbound Data	None		
Success Return	IOPortStatus		
Notes:			
See /IO/status for an explanation of the fields.			

8.3.8 Output trigger

/IO/outputs//ID/trigger		General Resource v1.0
PUT		Operator
Description	It is used to manually trigger a particular output port.	
Query	None	
Inbound Data	IOPortData	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Note that the ID used here MUST correspond to the ID in /IO/outputs/ID.		
The IO output port is toggled to a high or low signal accordingly.		

IOPortData XML Block

```
<IOPortData xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <outputState>    <!-- req, xs:string, "high,low" -->  </outputState>
</IOPortData>
```

8.4 Video

/Video	Service v1.0
Notes:	

8.4.1 Input

/Video/inputs		General Resource	v1.0
GET		Viewer	
Description	It is used to get the video inputs configuration on an IP media device.		
Query	None		
Inbound Data	None		
Success Return	VideoInput		
Notes:			
An IP media device may contain a set of video inputs. These inputs are hardwired by the device, meaning that the IDs can be discovered but not created or deleted.			

VideoInput XML Block

```
<VideoInput version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <VideoInputChannelList/>  <!-- opt -->
</VideoInput>
```

8.4.2 Input channels

/Video/inputs/channels		General Resource	v1.0
GET		Viewer	
Description	It is used to get the video input channels configuration on an IP media device.		
Query	None		
Inbound Data	None		
Success Return	VideoInputChannelList		
Notes:			
Since video input channels are resources that are defined by the hardware configuration			

of the device, they cannot be created or deleted.

VideoInputChannelList XML Block

```
<VideoInputChannelList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <VideoInputChannel/>    <!-- opt -->
</VideoInputChannelList>
```

8.4.3 Input channel

/Video/inputs/channels/ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get a particular video input channel configuration on an IP media device.		
Query	None		
Inbound Data	None		
Success Return	VideoInputChannel		
PUT		Operator	
Description	It is used to update a particular video input channel configuration on an IP media device.		
Query	None		
Inbound Data	VideoInputChannel		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<powerLineFrequencyMode> is used to adjust/correct video image based on different power frequencies.			
<whiteBalanceMode> indicates the white balance operational mode.			
<gainLevel> indicates the gain level percentage value. 0 is low gain, 100 is high gain.			

VideoInputChannel XML Block

```
<VideoInputChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>                <!-- req, xs:integer -->                </id>
  <powerLineFrequencyMode>  <!-- opt, xs:string "50hz, 60hz" -->
</powerLineFrequencyMode>
  <whiteBalanceMode>
    <!-- opt, xs:string, "manual,auto,indoor/incandescent" -->
  </whiteBalanceMode>
  <gainLevel>              <!-- opt, xs:integer, 0..100-->      </gainLevel>
  <brightnessLevel>        <!-- opt, xs:integer, 0..100 -->      </brightnessLevel>
  <contrastLevel>          <!-- opt, xs:integer, 0..100 -->      </contrastLevel>
```

```

<saturationLevel>      <!-- opt, xs:integer, 0..100 -->      </saturationLevel>
<DayNightFilter>      <!-- opt -->
  <dayNightFilterType>
    <!-- opt, xs:string, "day,night,auto" -->
  </dayNightFilterType>
</DayNightFilter>
<VideoInputChannel>

```

8.4.4 Input channel overlay texts

/Video/inputs/channels/ID/overlays/text		General Resource	v1.0
GET		Viewer	
Description	It is used to get the text overlays configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	TextOverlayList		
PUT		Operator	
Description	It is used to update the text overlays configuration for a video input channel.		
Query	None		
Inbound Data	TextOverlayList		
Success Return	hik:ResponseStaus ResponseStatus		
POST		Operator	
Description	It is used to add a text overlay for a video input channel.		
Query	None		
Inbound Data	TextOverlay		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete the text overlays configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
A set of text overlays is managed. They are composited over the video signal in increasing ID-order.			

TextOverlayList XML Block

```

<TextOverlayList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <TextOverlay/>      <!-- opt -->

```

```
</TextOverlayList>
```

8.4.5 Input channel overlay text

/Video/inputs/channels/ID/overlays/text/ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get a particular text overlay configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	TextOverlay		
PUT		Operator	
Description	It is used to update a particular text overlay configuration for a video input channel.		
Query	None		
Inbound Data	TextOverlay		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete a particular text overlay configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<posY> value is a multiple of 16.			

TextOverlay XML Block

```
<TextOverlay version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer, "1-4" -->      </id>
  <enabled>      <!-- req, xs:boolean -->             </enabled>
  <posX>         <!-- req, xs:integer -->             </posX>
  <posY>         <!-- req, xs:integer -->             </posY>
  <message>      <!-- req, xs:string -->              </message>
</TextOverlay>
```

8.4.6 Input channel channelNameOverlay

/Video/inputs/channels/ID/overlays/ channelNameOverlay	General Resource	v1.0
-----------------------------------------------------------	------------------	------

GET		Viewer
Description	It is used to get a particular channel name configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	channelNameOverlay	
PUT		Operator
Description	It is used to update a particular channel name configuration for a video input channel.	
Query	None	
Inbound Data	channelNameOverlay	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular text overlay configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<posY> value is a multiple of 16.		

channelNameOverlay XML Block

```

<channelNameOverlay version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <positionX> <!-- req, xs:integer;coordinate --> </positionX>
  <positionY> <!-- req, xs:integer;coordinate --> </positionY>
  <name> <!--opt, xs:string --> </name>
</channelNameOverlay>

```

8.4.7 Input channel privacyMask

/Video/inputs/channels/ID/privacyMask		General Resource v1.0
GET		Viewer
Description	It is used to get the privacy masking configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	PrivacyMask	

PUT		Operator
Description	It is used to update the privacy masking configuration for a video input channel.	
Query	None	
Inbound Data	PrivacyMask	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Privacy masking can be enabled and the region list configured per channel.		

PrivacyMask XML Block

```
<PrivacyMask version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled>           <!-- req, xs:boolean -->           </enabled>
  <PrivacyMaskRegionList/>  <!-- opt -->
</PrivacyMask>
```

8.4.8 Input channel privacyMask regions

/Video/inputs/channels/ID/privacyMask/regions		General Resource v1.0
GET		Viewer
Description	It is used to get the privacy mask regions configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	PrivacyMaskRegionList	
PUT		Operator
Description	It is used to update the privacy mask regions configuration for a video input channel.	
Query	None	
Inbound Data	PrivacyMaskRegionList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add a privacy mask region for a video input channel.	
Query	None	
Inbound Data	PrivacyMaskRegion	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete the privacy mask regions configuration for a video input channel.	
Query	None	

Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: Privacy masking consists of a set of regions that are combined to grey or black out areas of a video input.	

PrivacyMaskRegionList XML Block

```
<PrivacyMaskRegionList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PrivacyMaskRegion/>  <!-- opt -->
</PrivacyMaskRegionList>
```

8.4.9 Input channel privacyMask region


/Video/inputs/channels//ID/privacyMask/regions//ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get a particular privacy mask region configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	PrivacyMaskRegion		
PUT		Operator	
Description	It is used to update a particular privacy mask region configuration for a video input channel.		
Query	None		
Inbound Data	PrivacyMaskRegion		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete a particular privacy mask region configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
Region coordinates are dependent on normalized screen size.			
For IPC and DVR, the normalized screen size is 4CIF（704*576 under 50Hz ， or 704*480 under 60Hz）			
For IP dome, the normalized screen size is 255*255.			
The computer screen coordinate system is used, which the origin coordinate is on top-left corner , the Y axis is vertical downwards , the X axis horizontal rightwards.			

Only support the rectangular region which will be “drawn” from four coordinates. The four points is counterclockwise direction, and the beginning point is the top-left point. Ordering of <PrivacyMaskRegion> blocks is insignificant.

PrivacyMaskRegion XML Block

```
<PrivacyMaskRegion version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer --> </id>
  <RegionCoordinatesList> <!-- req -->
    <RegionCoordinates> <!-- req -->
      <positionX> <!-- req, xs:integer;coordinate --> </positionX>
      <positionY> <!-- req, xs:integer;coordinate --> </positionY>
    </RegionCoordinates>
  </RegionCoordinatesList>
  <RegionExt> <!--opt-->
    <enabled> <!-- req,xs:boolean --> </enabled>
    <privacymaskName><!-- opt, xs:string--></privacymaskName>
    <maskType><!--opt, xs:string "gray,red,yellow,blue,orange,green,
transparent,half-transparent,mosaic"--></maskType>
  </RegionExt>
</PrivacyMaskRegion>
```

Example for priavacyMask Region:



8.4.10 Input channel shelterAlarm

/Video/inputs/channels//ID/shelterAlarm		General Resource	v1.0
GET		Viewer	
Description	It is used to get the shelter alarm configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	ShelterAlarm		
PUT		Operator	
Description	It is used to update the shelter alarm configuration for a video input channel.		
Query	None		
Inbound Data	ShelterAlarm		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

ShelterAlarm XML Block

```
<ShelterAlarm version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <ShelterAlarmRegionList/> <!-- opt -->
</ShelterAlarm>
```

8.4.11 Input channel shelterAlarm regions

/Video/inputs/channels//ID/shelterAlarm/regions		General Resource	v1.0
GET		Viewer	
Description	It is used to get the shelter alarm regions configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	ShelterAlarmRegionList		
PUT		Operator	
Description	It is used to update the shelter alarm regions configuration for a video input channel.		
Query	None		
Inbound Data	ShelterAlarmRegionList		
Success Return	hik:ResponseStaus ResponseStatus		
POST		Operator	

Description	It is used to add a shelter alarm region for a video input channel.
Query	None
Inbound Data	ShelterAlarmRegion
Success Return	hik:ResponseStaus ResponseStatus
DELETE Operator	
Description	It is used to delete the shelter alarm regions configuration for a video input channel.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

ShelterAlarmRegionList XML Block

```
<ShelterAlarmRegionList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <sensitivityLevel>    <!-- req -->
    <!-- req, xs:string, "low, middle, high"-->
  </sensitivityLevel>
  <ShelterAlarmRegion /> <!-- opt -->
</ShelterAlarmRegionList>
```

8.4.12 Input channel shelterAlarm region

/Video/inputs/channels//ID/shelterAlarm/regions//ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular shelter alarm region configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	ShelterAlarmRegion	
PUT Operator		
Description	It is used to update a particular shelter alarm region configuration for a video input channel.	
Query	None	
Inbound Data	ShelterAlarmRegion	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE Operator		
Description	It is used to delete a particular shelter alarm region configuration for a video input channel.	
Query	None	

Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: Region coordinates are dependent on video resolution. Only support the rectangular region which will be “drawn” from four coordinates. The four points is clockwise direction, and the beginning point is the low-left point. Ordering of <ShelterAlarmRegion> blocks is insignificant.	

ShelterAlarmRegion XML Block

```
<ShelterAlarmRegion version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>                <!-- req, xs:integer, "1" -->                </id>
  <RegionCoordinatesList> <!-- req -->
    <RegionCoordinates> <!-- req -->
      <positionX>        <!-- req, xs:integer;coordinate -->        </positionX>
      <positionY>        <!-- req, xs:integer;coordinate -->        </positionY>
    </RegionCoordinates>
  </RegionCoordinatesList>
</ShelterAlarmRegion>
```

8.4.13 Input channel osdDatetime

/Video/inputs/channels/ID/osdDatetime		General Resource	v1.0
GET		Viewer	
Description	It is used to get the OSD configuration for a video input channel.		
Query	None		
Inbound Data	None		
Success Return	OsdDatetime		
PUT		Operator	
Description	It is used to update the OSD configuration for a video input channel.		
Query	None		
Inbound Data	OsdDatetime		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<posY> value is a multiple of 16.			
<type> is the type of the year month day and should be:			
0: XXXX-XX-XX Y-M-D			
1: XX-XX-XXXX M-D-Y			
4: XX-XX-XXXX D-M-Y			
<displayWeek> means display the week or not.			

<attribute> is the configuration of the OSD, the value should be:

- 1: transparent, flash
- 2: transparent, not flash
- 3: not transparent, flash
- 4: not transparent, not flash

OsdDatetime XML Block

```
<OsdDatetime version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <posX> <!-- req, xs:integer;coordinate --> </posX>
  <posY> <!-- req, xs:integer;coordinate --> </posY>
  <type> <!-- req, xs:integer --> </type>
  <displayWeek> <!-- req, xs:boolean --> </displayWeek>
  <attribute> <!-- req, xs:integer --> </attribute>
</OsdDatetime>
```

8.5 Audio

/Audio	Service v1.0
Notes:	

8.5.1 Channels

/Audio/channels		General Resource v1.0
GET		Viewer
Description	It is used to get the audio channels configuration on an IP media device.	
Query	None	
Inbound Data	None	
Success Return	AudioChannelList	
Notes:		
Since inputs are resources that are defined by the hardware configuration of the device, audio channels cannot be created or deleted.		

AudioChannelList XML Block

```
<AudioChannelList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <AudioChannel/> <!-- opt -->
</AudioChannelList>
```

8.5.2Channel

/Audio/channels/ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular audio channel configuration on an IP media device.	
Query	None	
Inbound Data	None	
Success Return	AudioChannel	
Notes:		
<p><audioMode> is the duplex mode for audio transmission between the client and media device.</p> <p><microphoneVolume> Volume control percentage for device microphone..</p> <p><speakerVolume> Volume control percentage for device speaker.</p>		

AudioChannel XML Block

```
<AudioChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>      <!-- req, xs:integer, "11,12" -->      </id>
  <enabled>  <!-- req, xs:boolean -->                </enabled>
  <audioMode>
    <!-- req, xs:string, "talkonly, talkandlisten" -->
  </audioMode>
  <microphoneEnabled> <!-- req, xs:boolean -->      </microphoneEnabled>
  <microphoneSource>  <!-- req, xs:string, "external" --> </microphoneSource>
  <microphoneVolume>  <!-- req, xs:integer, 0...100 --> </microphoneVolume>
  <speakerEnabled>    <!-- req, xs:boolean -->        </speakerEnabled>
  <speakerVolume>     <!-- req, xs:integer,0...100 --> </speakerVolume>
</AudioChannel>
```

8.6 Two way audio

/TwowayAudio	Service v1.0
Notes:	

8.6.1 Open

/TwowayAudio/open	General Resource v1.0
PUT	Operator

Description	It is used to open intercom.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

8.6.2Close

/TwowayAudio/close		General Resource v1.0
PUT		Operator
Description	It is used to close intercom.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.6.3Send data

/TwowayAudio/sendData		General Resource v1.0
PUT		Operator
Description	It is used to send the intercom data.	
Query	None	
Inbound Data	TwowayAudio Data	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

Example:

```
PUT /TwowayAudio/sendData HTTP/1.1
...
Content-Type: audio/basic
Content-Length: xxx
\r\n
TwowayAudio Data...
```


8.6.4 Receive data

/TwowayAudio/receiveData		General Resource	v1.0
GET		Operator	
Description	It is used to receive the intercom data.		
Query	None		
Inbound Data	None		
Success Return	TwowayAudio Data		
Notes:			

Example:

```
GET /TwowayAudio/receiveData HTTP/1.1
```

```
...
```

```
HTTP/1.1 200 OK
```

```
...
```

```
Content-Type: audio/basic
```

```
Content-Length: xxx
```

```
\r\n
```

```
TwowayAudio Data...
```

8.7 Serial

/Serial	Service v1.0
Notes: Serial port service.	

8.7.1 Ports

/Serial/ports		General Resource	v1.0
GET		Viewer	
Description	It is used to get the list of serial ports supported by the device.		
Query	None		
Inbound Data	None		
Success Return	SerialPorList		
Notes:			
Since serial ports are resources that are defined by the hardware configuration of the device, they cannot be created or deleted.			

SerialPortList XML Block

```
<SerialPortList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <SerialPort/>  <!-- opt -->
</SerialPortList>
```

8.7.2Port

/Serial/ports//ID		General Resource v1.0
GET		Viewer
Description	It is used to get the configuration of a serial port supported by the device.	
Query	None	
Inbound Data	None	
Success Return	SerialPort	
PUT		Operator
Description	It is used to update the configuration of a serial port supported by the device.	
Query	None	
Inbound Data	SerialPort	
Success Return	hik:ResponseSta us ResponseStatus	
Notes:		
<p><serialPortType> set the type of port; RS232, RS485. When <id> value is 1, <serialPortType> value is “RS485”. When <id> value is 3, <serialPortType> value is “RS232”. <serialPortType> value can not set directly.</p>		

SerialPort XML Block

```
<SerialPort version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer, "1, 3" -->          </id>
  <enabled>      <!-- ro, req, xs:boolean -->              </enabled>
  <serialPortType> <!-- req, xs:string, "RS485, RS232" --> </serialPortType>
  <baudRate>     <!-- req, xs:integer -->                  </baudRate>
  <dataBits>     <!-- req, xs:integer -->                  </dataBits>
  <parityType>   <!-- req, xs:string, "none,even,odd" --> </parityType>
  <stopBits>    <!-- req, xs:string, "1,1.5,2" -->        </stopBits>
</SerialPort>
```

8.7.3 Command

/Serial/ports/ <i>ID</i> /command		General Resource v1.0
PUT		Operator
Description	It is used to send a command to a serial port.	
Query	chainNo	
Inbound Data	SerialCommand or Raw Data	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: If the IP device is an analog-to-digital encoder and is connected to analog PTZ-enabled camera(s), it is the device's responsibility to relay the request to the appropriate serial interface based on the <chainNo> tag or query string. If the IP device is itself a PTZ-enabled digital camera, it is the device's responsibility to address the correct serial interface for the corresponding PTZ command. The serial command can either be encapsulated in the <command> field, in which case the data should be encoded in hexadecimal notation, or the data can be uploaded directly as the HTTP payload, in which case the content type should be application/octet-stream.		

SerialCommand XML Block

```
<SerialCommand version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <chainNo>      <!-- req, xs:string -->  </chainNo>
  <command>      <!-- req, xs:string, bytes in hexadecimal -->  </command>
</SerialCommand>
```

8.7.4 Transparent channel open

/Serial/ports/ <i>ID</i> /transChanOpen		General Resource v1.0
PUT		Operator
Description	It is used to open the transparent channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Only support RS485 transparent channel, so <i>ID</i> value in the Resource_URI can only be 1.		

8.7.5 Transparent channel close

/Serial/ports/ <i>ID</i> /transChanClose		General Resource v1.0
PUT		Operator
Description	It is used to close the transparent channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Only support RS485 transparent channel, so <i>ID</i> value in the Resource_URI can only be 1.		

8.7.6 Transparent channel send data

/Serial/ports/ <i>ID</i> /transChanSendData		General Resource v1.0
PUT		Operator
Description	It is used to send data on the transparent channel.	
Query	None	
Inbound Data	Raw Data	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Only support RS485 transparent channel, so <i>ID</i> value in the Resource_URI can only be 1.		

Example:

```
PUT /Serial/ports/1/transChanSendData HTTP/1.1
...
Content-Type: application/binary; charset="UTF-8"
Content-Length: xxx
\r\n
Raw Data...
```

8.7.7 Transparent channel receive data

/Serial/ports/ <i>ID</i> /transChanRecvData		General Resource v1.0
GET		Operator
Description	It is used to receive data on the transparent channel.	
Query	None	
Inbound Data	None	

Success Return	Raw Data
Notes: Only support RS485 transparent channel, so <i>ID</i> value in the Resource_URI can only be 1.	

Example:

```
GET /Serial/ports/1/transChanRecvData HTTP/1.1
...

HTTP/1.1 200 OK
...
Content-Type: application/binary; charset="UTF-8"
Content-Length: xxx
\r\n
Raw Data...
```

8.8 Security

/Security	Service v1.0
Notes:	

8.8.1 Users

/Security/users		General Resource v1.0
GET		Viewer
Description	It is used to get the user list for the device.	
Query	None	
Inbound Data	None	
Success Return	UserList	
PUT		Administrator
Description	It is used to update the user list for the device.	
Query	None	
Inbound Data	UserList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Administrator
Description	It is used to add a user for the device.	
Query	None	
Inbound Data	User	
Success Return	hik:ResponseStaus ResponseStatus	

DELETE Administrator	
Description	It is used to delete the user list for the device.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: A default user account, "admin", must be provided. Its default password is "12345". It has an Administrator user level, and must not be deleted. Passwords can only be uploaded - they are never revealed during GET operations.	

UserList XML Block

```
<UserList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <User/>    <!-- opt -->
</UserList>
```

8.8.2User

/Security/users/ID General Resource v1.0	
GET Viewer	
Description	It is used to get a particular user configuration for the device.
Query	None
Inbound Data	None
Success Return	User
PUT Administrator	
Description	It is used to update a particular user configuration for the device.
Query	None
Inbound Data	User
Success Return	hik:ResponseStaus ResponseStatus
DELETE Administrator	
Description	It is used to delete a particular user for the device.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: <id> of "admin" account is 1. "admin" account must not be deleted. <password> is a write-only field.	

User XML Block

```
<User version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer, "1-16" -->    </id>
```

```

<userName>      <!-- req, xs:string -->      </userName>
<password>      <!-- wo, req, xs:string -->    </password>
<priority> <!-- opt, xs:string; "low, middle, high" --> </priority>
<ipAddress> <!-- opt, xs:string --> </ipAddress>
<macAddress> <!-- opt, xs:string --> </macAddress>
<userLevel> <!-- opt, xs:string, "Administrator, Operator, Viewer" --> </userLevel>
</User>

```

8.8.3 adminAccess

/Security/adminAccess		General Resource v1.0
GET		Viewer
Description	It is used to get administrative access protocol for the device.	
Query	None	
Inbound Data	None	
Success Return	AdminAccessProtocol	
PUT		Administrator
Description	It is used to update administrative access protocol for the device.	
Query	None	
Inbound Data	AdminAccessProtocol	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<protocol> is the protocol name for admin access, i.e. “HTTP”, “HTTPS”, etc.		

AdminAccessProtocol XML Block

```

<AdminAccessProtocol version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <protocol> <!-- req, xs:string; "HTTP, HTTPS" --> </protocol>
  <portNo> <!-- req, xs:integer --> </portNo>
  <netClientPort><!-- req, xs:integer --></netClientPort>
</AdminAccessProtocol>

```

8.9 Streaming

/Streaming	Service v1.0
Notes:	

8.9.1 Status

/Streaming/status		General Resource v1.0
GET		Administrator
Description	It is used to get a device streaming status.	
Query	None	
Inbound Data	None	
Success Return	StreamingStatus	
Notes:		
This command accesses the status of all device streaming sessions.		

StreamingStatus XML Block

```
<StreamingStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <totalStreamingSessions>      <!-- req, xs:integer -->  </totalStreamingSessions>
  <StreamingSessionStatusList/>  <!-- dep, only if there are sessions -->
</StreamingStatus>
```

8.9.2 Channels

/Streaming/channels		General Resource v1.0
GET		Viewer
Description	It is used to get the properties of streaming channels for the device.	
Query	None	
Inbound Data	None	
Success Return	StreamingChannelList	
PUT		Administrator
Description	It is used to update the properties of streaming channels for the device.	
Query	None	
Inbound Data	StreamingChannelList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Administrator
Description	It is used to add a streaming channel for the device.	
Query	None	
Inbound Data	StreamingChannel	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Administrator
Description	It is used to delete the list of streaming channels for the device.	

Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: Streaming channels may be hardwired, or it may be possible to create multiple streaming channels per input if the device supports it. To determine whether it is possible to dynamically create streaming channels, check the defined HTTP methods in /Streaming/channels/description.	

StreamingChannelList XML Block

```
<StreamingChannelList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <StreamingChannel/>  <!-- opt -->
</StreamingChannelList>
```

8.9.3Channel

/Streaming/channels/ID		General Resource v1.0
GET		Viewer
Description	It is used to get the properties of a particular streaming channel for the device.	
Query	None	
Inbound Data	None	
Success Return	StreamingChannel	
PUT		Administrator
Description	It is used to update the properties of a particular streaming channel for the device.	
Query	None	
Inbound Data	StreamingChannel	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Administrator
Description	It is used to delete a particular streaming channel for the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
To support multi video input devices , the streaming ID in URL should be indicate video input channel number , so it is defined as : straming-Id + video-input-Id *100, for example : /Streaming/channels/101 indicates the first streaming from the first video input /Streaming/channels/202 indicates the second streaming from the second video input		

For IPC, because of only one video input, case is simple, it can accept 1 as the main stream id, 2 as the sub-stream.

<ControlProtocolList> identifies the control protocols that are valid for this type of streaming.

<Unicast> is for direct unicast streaming.

<Multicast> is for direct multicast streaming.

<sourcePortNo> is the unicast source port parameter for the outbound video and audio streams, and the specific port number is device-dependant.

<destPortNo> is the multicast destination port parameter for the outbound video and audio streams, and the specific port number is device-dependant.

<videoInputChannelID> refers to /Video/inputs/channels/ID.

<audioInputChannelID> refers to /Audio/channels/ID. It must be configured as an input channel.

<audioResolution> is the resolution for the outbound audio stream in bits.

<SVC> enables the function to realize temporal scalability, which can drop frames from bitstream according to actual solution.

StreamingChannel XML Block

```
<StreamingChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>      <!-- req, xs:integer, "1, 2" -->    </id>
  <channelName> <!-- ro, req, xs:string -->    </channelName>
  <enabled>    <!-- ro, req, xs:boolean -->    </enabled>
  <Transport>  <!-- req -->
    <rtspPortNo>    <!-- opt, xs:integer -->    </rtspPortNo>
    <maxPacketSize>    <!-- ro, opt, xs:integer -->    </maxPacketSize>
    <sourcePortNo>    <!-- opt, xs:integer -->    </sourcePortNo>
    <ControlProtocolList>    <!-- req -->
      <ControlProtocol>    <!-- opt -->
        <streamingTransport>
          <!-- ro, req, xs:string, "RTSP" -->
        </streamingTransport>
      </ControlProtocol>
    </ControlProtocolList>
    <Unicast>      <!-- opt -->
      <enabled>      <!-- ro, req, xs:boolean, "true" -->    </enabled>
    </Unicast>
    <Multicast>    <!-- opt -->
      <enabled>      <!-- ro, req, xs:boolean, "true" -->    </enabled>
      <destIPAddress>    <!-- opt, xs:string -->    </destIPAddress>
      <destPortNo>    <!-- opt, xs:integer -->    </destPortNo>
    </Multicast>
</StreamingChannel>
```

```

</Transport>
<Video>
  <enabled>          <!-- ro, req, xs:boolean, "true" -->      </enabled>
  <videoInputChannelID>  <!-- req, xs:integer -->      </videoInputChannelID>
  <videoCodecType>
    <!-- ro, opt, xs:string, "H.264,MJPEG" -->
  </videoCodecType>
  <videoScanType>  <!-- ro, opt, xs:string, "progressive" -->  </videoScanType>
  <videoResolutionWidth>  <!-- req, xs:integer -->      </videoResolutionWidth>
  <videoResolutionHeight> <!-- req, xs:integer -->      </videoResolutionHeight>
  <videoQualityControlType>
    <!-- req, xs:string, "CBR,VBR" -->
  </videoQualityControlType>
  <constantBitRate>  <!-- opt, xs:integer, in kbps -->      </constantBitRate>
  <fixedQuality>    <!-- opt, xs:integer, percentage, "0-100" -->  </fixedQuality>
  <maxFrameRate>    <!-- req, xs:integer, maximum frame rate x100 -->
  </maxFrameRate>
  <keyFrameInterval> <!-- opt, xs:integer-->  </keyFrameInterval>
  <BPFrameInterval> <!-- opt, xs:integer --> </BPFrameInterval>
  <mirrorStatus> <!-- opt, xs:string, "OFF,UpToDown,LeftToRight"--> </mirrorStatus>
  <rotationDegree> <!-- opt, xs: integer,"0,180 "--> </rotationDegree>
  <snapShotImageType> <!-- ro, opt, xs:string, "JPEG" -->  </snapShotImageType>
  <SVC>
    <enabled>  <!-- opt, xs:boolean -->  </enabled>
  <SVC>
</Video>
<Audio>
  <enabled>          <!-- ro, req, xs:boolean, "true,false" -->      </enabled>
  <audioInputChannelID>  <!-- ro, req, xs:integer -->      </audioInputChannelID>
  <audioCompressionType>
    <!-- ro,opt, xs:string, "G.711ulaw" -->
  </audioCompressionType>
</Audio>
</StreamingChannel>

```

Example: Getting Streaming Channel Properties

The following is an example of a GET on the streaming parameters of a particular channel that has been preconfigured by the IP media device. Depending on the device, some streaming channels may be already preconfigured or the device while other may require that channels be manually configured before use.

```
GET /Streaming/channels/1 HTTP/1.1
```

```
...
```

HTTP/1.1 200 OK

Content-Type: application/xml; charset="UTF-8"

Content-Length: xxx

```
<?xml version="1.0" encoding="UTF-8"?>
<StreamingChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>1</id>
  <channelName>Input 1 H.264</channelName>
  <enabled>true</enabled>
  <Transport>
    <rtspPortNo>554</rtspPortNo>
    <maxPacketSize>1000</maxPacketSize>
    <sourcePortNo>8200</sourcePortNo>
    <ControlProtocolList>
      <ControlProtocol>
        <streamingTransport>RTSP</streamingTransport>
      </ControlProtocol>
    </ControlProtocolList>
    <Unicast>
      <enabled>true</enabled>
    </Unicast>
    <Multicast>
      <enabled>true</enabled>
      <destIPAddress>224.16.74.1</destIPAddress>
      <destPortNo>8600</destPortNo>
    </Multicast>
  </Transport>
  <Video>
    <enabled>true</enabled>
    <videoInputChannelID>1</videoInputChannelID>
    <videoCodecType>H.264</videoCodecType>
    <videoScanType>progressive</videoScanType>
    <videoResolutionWidth>640</videoResolutionWidth>
    <videoResolutionHeight>480</videoResolutionHeight>
    <videoQualityControlType>CBR</videoQualityControlType>
    <constantBitRate>3072</constantBitRate>
    <fixedQuality>80</fixedQuality>
    <maxFrameRate>2500</maxFrameRate>
    <keyFrameInterval>25</keyFrameInterval>
    <BPFrameInterval>0</BPFrameInterval>
    <mirrorStatus>OFF</mirrorStatus>
    <rotationDegree>180</rotationDegree>
    <snapShotImageType>JPEG</snapShotImageType>
```

```

    <SVC>
      <enabled>true</enabled>
    </SVC>
  </Video>
  <Audio>
    <enabled>true</enabled>
    <audioInputChannelID>11</audioInputChannelID>
    <audioCompressionType>G.711ulaw</audioCompressionType>
  </Audio>
</StreamingChannel>

```

Example: Getting Streaming Capabilities

```

GET /Streaming/channels/1/capabilities HTTP/1.1
...
HTTP/1.1 200 OK
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>

<StreamingChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id opt="1,2">1</id>
  <channelName min="0" max="64">Input 1 H.264</channelName>
  <enabled opt="true">true</enabled>
  <Transport>
    <rtspPortNo min="0" max="65535" def="554">554</rtspPortNo>
    <maxPacketSize opt="1000">1000</maxPacketSize>
    <sourcePortNo min="0" max="65535" def="8200">8200</sourcePortNo>
    <ControlProtocolList>
      <ControlProtocol>
        <streamingTransport opt="RTSP">RTSP</streamingTransport>
      </ControlProtocol>
    </ControlProtocolList>
    <Unicast>
      <enabled opt="true" def="true">true</enabled>
    </Unicast>
    <Multicast>
      <enabled opt="true" def="true">true</enabled>
      <destIPAddress min="8" max="16">224.16.74.1</destIPAddress>
      <destPortNo min="0" max="65535" def="8600">8600</destPortNo>
    </Multicast>
  </Transport>

```

```

<Video>
  <enabled opt="true">true</enabled>
  <videoInputChannelID opt="1">1</videoInputChannelID>
  <videoCodecType opt="H.264,MJPEG">H.264</videoCodecType>
  <videoScanType opt="progressive">progressive</videoScanType>
  <videoResolutionWidth opt="640*480">640</videoResolutionWidth>
  <videoResolutionHeight opt="640*480">480</videoResolutionHeight>
  <videoQualityControlType opt="CBR,VBR">CBR</videoQualityControlType>
  <constantBitRate min="32" max="4000">3072</constantBitRate>
  <fixedQuality opt="1,20,40,60,80,100">80</fixedQuality>
  <maxFrameRate
    opt="2500,2200,2000,1800,1600,1500,1200,1000,800,600,400,200,100,50,25,
    12,6">2500</maxFrameRate>
  <keyFrameInterval min="1", max="400">25</keyFrameInterval>
  <BPFrameInterval opt="0, 1, 2">0</BPFrameInterval>
  <mirrorStatus opt="OFF,UpToDown,LeftToRight">OFF</mirrorStatus>
  <rotationDegree opt="0,180">180</rotationDegree>
  <snapShotImageType opt="JPEG" def="JPEG">JPEG</snapShotImageType>
  <SVC>
    <enabled opt="ture,false">true</enabled>
  </SVC>
</Video>
<Audio>
  <enabled opt="true,false">true</enabled>
  <audioInputChannelID opt="11,12">11</audioInputChannelID>
  <audioCompressionType opt="G.711ulaw">G.711ulaw</audioCompressionType>
</Audio>
</StreamingChannel>

```

8.3.1 Dynamic capabilities

/Streaming/channels/ID/dynamicCap		General Resource	v2.0
GET			
Description	Get dynamic capabilities, different resolutions have different frame rates; different audio compression types have different audio bit rate.		
Query	None		
Inbound Data	None		
Success Return	DynamicCap		
Notes:			

DynamicCap XML Block

```
<DynamicCap version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ResolutionAvailableDescriptorList>
    <ResolutionAvailableDescriptor>
      <videoResolutionWidth> <!-- req, xs:integer --> </videoResolutionWidth>
      <videoResolutionHeight> <!-- req, xs:integer --> </videoResolutionHeight>
      <supportedFrameRate> <!-- req, xs:string --> </supportedFrameRate>
    </ResolutionAvailableDescriptor>
  </ResolutionAvailableDescriptorList>
  <AudioDescriptorList>
    <audioCompressionType>
      <!-- req, xs:string,
      " G.711alaw,G.711ulaw,G.726,G.729,G.729a,G.729b,PCM,MP3,AC3,AAC,ADPCM,
      MP2L2"-->
    </audioCompressionType>
  </AudioDescriptorList>
</DynamicCap>
```

Example: Getting the Dynamic Capabilities

```
GET /Streaming/Channels/101/dynamicCap HTTP/1.1
...
HTTP/1.1 200 OK
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>
<DynamicCap version="2.0" xmlns="http://www.hikvision.org/ver20/XMLSchema">
  <ResolutionAvailableDescriptorList>
    <ResolutionAvailableDescriptor>
      <videoResolutionWidth>176</videoResolutionWidth>
      <videoResolutionHeight>144</videoResolutionHeight>
      <supportedFrameRate>2500,6,12,25,50,100,200,400,600,800,1000,1200,1500,16
00,1800,2000,2200</supportedFrameRate>
    </ResolutionAvailableDescriptor>
    <ResolutionAvailableDescriptor>
      <videoResolutionWidth>352</videoResolutionWidth>
      <videoResolutionHeight>288</videoResolutionHeight>
      <supportedFrameRate>2500,6,12,25,50,100,200,400,600,800,1000,1200,1500,16
00,1800,2000,2200</supportedFrameRate>
    </ResolutionAvailableDescriptor>
    <ResolutionAvailableDescriptor>
      <videoResolutionWidth>704</videoResolutionWidth>
      <videoResolutionHeight>576</videoResolutionHeight>
```

```

    <supportedFrameRate>2500,6,12,25,50,100,200,400,600,800,1000,1200,1500,16
00,1800,2000,2200</supportedFrameRate>
  </ResolutionAvailableDescriptor>
</ResolutionAvailableDescriptorList>
  <AudioDescriptorList>
    <audioCompressionType
SupportedAudioBitRate="32,64,128">MP2L2</audioCompressionType>
  </AudioDescriptorList>
</DynamicCap>

```

8.9.4 Channel status

/Streaming/channels/{ID}/status		General Resource	v1.0
GET		Administrator	
Description	It is used to get the list of streaming sessions associated with a particular channel.		
Query	None		
Inbound Data	None		
Success Return	StreamingSessionStatusList		
Notes:			

StreamingSessionStatusList XML Block

```

<StreamingSessionStatusList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <StreamingSessionStatus>
    <clientAddress> <!-- req -->
      <ipAddress> <!-- req, xs:string --> </ipAddress>
    </clientAddress>
  </StreamingSessionStatus>
</StreamingSessionStatusList>

```

8.9.5 Picture

/Streaming/channels/ID/picture		General Resource v1.0
GET		Operator
Description	It is used to get a snapshot of the current image.	
Query	videoResolutionWidth videoResolutionHeight snapShotImageType	

Inbound Data	None
Success Return	Picture over HTTP
Notes: All devices must support <snapShotImageType> of “JPEG”. Only support the main stream channel snapshot. To determine the format of the picture returned, either the parameters in <Video> or the query string values are used, or, if the Accept: header field is present in the request and the server supports it, the picture is returned in that format. For supported values, query /Streaming/channels/ <i>ID</i> /picture/capabilities. Examples: GET /Streaming/channels/1/picture?snapShotImageType=JPEG ... GET /Streaming/channels/1/picture Accept: image/jpeg ...	

8.9.6 Request keyframe

/Streaming/channels/{ID}/requestKeyFrame		General Resource v1.0
PUT		Operator
Description	It is used to request that the device issue a key frame on a particular channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: The key frame that is issued should include everything necessary to initialize a video decoder, i.e. parameter sets for H.264.		

8.10 Motion Detection

/MotionDetection		Service v1.0
GET		Viewer
Description	It is used to get the motion detection configuration for all video input channels.	
Query	None	
Inbound Data	None	

Success Return	MotionDetectionList
Notes: If motion detection is supported by the device, a motion detection ID will be allocated for each video input channel ID. The motion detection ID must correspond to the video input channel ID.	

MotionDetectionList XML Block

```
<MotionDetectionList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <MotionDetection/>      <!-- opt -->
</MotionDetectionList >
```

8.10.1 One channel motion detection

/MotionDetection/ID		General Resource v1.0
GET		Viewer
Description	It is used to get the motion detection configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	MotionDetection	
PUT		Operator
Description	It is used to update the motion detection configuration for a video input channel.	
Query	None	
Inbound Data	MotionDetection	
Success Return	hik:ResponseStatus ResponseStatus	
Notes:		
Note that the ID used here MUST correspond to the video input ID.		
The interface supports grid-based motion detection.		
Grid-based motion detect divides the image into a set of fixed “bins” that delimit the motion detection area boundaries.		

MotionDetection XML Block

```
<MotionDetection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>      <!-- req, xs:integer -->      </id>
  <enabled>  <!-- req, xs:boolean -->      </enabled>
  <regionType> <!-- ro, req, xs:string, "grid" --> </regionType>
  <Grid>    <!-- req -->
    <rowGranularity> <!-- ro, req, xs:integer --> </rowGranularity>
```

```

    <columnGranularity> <!-- ro, req, xs:integer --> </columnGranularity>
  </Grid>
  <MotionDetectionRegionList/> <!-- req -->
</MotionDetection>

```

8.10.2 Motion detection regions

/MotionDetection/ID/regions		General Resource v1.0
GET		Viewer
Description	It is used to get the motion detection regions configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	MotionDetectionRegionList	
PUT		Operator
Description	It is used to update the motion detection regions configuration for a video input channel.	
Query	None	
Inbound Data	MotionDetectionRegionList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add a motion detection region for a video input channel.	
Query	None	
Inbound Data	MotionDetectionRegion	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete the motion detection regions configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
All motion detection regions share a sensitivity level.		
It is possible to define mask regions that are subtracted from other regions.		

MotionDetectionRegionList XML Block

```

<MotionDetectionRegionList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <sensitivityLevel> <!-- req -->
    <!-- req, xs:integer, "0-5", 0 is least sensitive -->

```

```

</sensitivityLevel>
<MotionDetectionRegion/> <!-- opt -->
</MotionDetectionRegionList>

```

8.10.3 Motion detection region

/MotionDetection/ID/regions/ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular motion detection region configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	MotionDetectionRegion	
PUT		Operator
Description	It is used to update a particular motion detection region configuration for a video input channel.	
Query	None	
Inbound Data	MotionDetectionRegion	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular motion detection region configuration for a video input channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
The region detection coordinate space depends on the value of <regionType>. Only support the rectangular region which will be “drawn” from four coordinates. The four points is clockwise direction, and the beginning point is the low-left point.		

MotionDetectionRegion XML Block

```

<MotionDetectionRegion version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer, "1-16" --> </id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <maskEnabled> <!-- req, xs:boolean --> </maskEnabled>
  <RegionCoordinatesList> <!-- req -->
    <RegionCoordinates> <!-- Note: at least four coordinates are required -->
      <positionX> <!-- req, xs:integer --> </positionX>
      <positionY> <!-- req, xs:integer --> </positionY>
    
```

```

</RegionCoordinates>
</RegionCoordinatesList>
</MotionDetectionRegion>


```

8.10.4 Motion Detection Example

Set up Motion Detection

The following command configures two rectangular detection regions, with one “masked” region on video input channel ID 1. Example assumes a resolution of 1600x1200 and a grid motion detection algorithm:

- Motion detection is enabled with a granularity of a 22x18 grid – this means the detection region coordinates will ultimately be defined by a grid of 396 regions. For a resolution of 1600x1200, this means that each “granule” will be 1600/22 x 1200/18 pixels. (If a coordinate doesn’t exactly match the configured granularity, it should be mapped internally to the nearest possible point).
- Two detection regions are defined, the second containing an inner/overlapping region that is disabled. Region 1 occupies the bottom-left 16 granules. Region 2 occupies the middle 16 granules, with the top-right-most corner granule (region 3) disabled by use of the <maskEnabled> tag.



```

PUT /MotionDetection/1 HTTP/1.1
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>
<MotionDetection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">

```

```

<id>1</id>
<enabled>true</enabled>
<MotionDetectionRegionList>
  <sensitivityLevel>2</sensitivityLevel>
  <MotionDetectionRegion>
    <id>1</id>
    <enabled>true</enabled>
    <maskEnabled>>false</maskEnabled>
    <RegionCoordinatesList>
      <RegionCoordinates>
        <positionX>0</positionX>
        <positionY>0</positionY>
      </RegionCoordinates>
      <RegionCoordinates>
        <positionX>0</positionX>
        <positionY>4</positionY>
      </RegionCoordinates>
      <RegionCoordinates>
        <positionX>4</positionX>
        <positionY>4</positionY>
      </RegionCoordinates>
      <RegionCoordinates>
        <positionX>4</positionX>
        <positionY>0</positionY>
      </RegionCoordinates>
    </RegionCoordinatesList>
  </MotionDetectionRegion>
  <MotionDetectionRegion>
    <id>2</id>
    <enabled>true</enabled>
    <maskEnabled>>false</maskEnabled>
    <RegionCoordinatesList>
      <RegionCoordinates>
        <positionX>8</positionX>
        <positionY>8</positionY>
      </RegionCoordinates>
      <RegionCoordinates>
        <positionX>8</positionX>
        <positionY>12</positionY>
      </RegionCoordinates>
      <RegionCoordinates>
        <positionX>12</positionX>
        <positionY>12</positionY>
      </RegionCoordinates>
    </RegionCoordinatesList>
  </MotionDetectionRegion>
</MotionDetectionRegionList>

```

```

</RegionCoordinates>
<RegionCoordinates>
  <positionX>12</positionX>
  <positionY>8</positionY>
</RegionCoordinates>
</RegionCoordinatesList>
</MotionDetectionRegion>
<MotionDetectionRegion>
  <id>3</id>
  <enabled>true</enabled>
  <maskEnabled>true</maskEnabled>
  <RegionCoordinatesList>
    <RegionCoordinates>
      <positionX>11</positionX>
      <positionY>11</positionY>
    </RegionCoordinates>
    <RegionCoordinates>
      <positionX>11</positionX>
      <positionY>12</positionY>
    </RegionCoordinates>
    <RegionCoordinates>
      <positionX>12</positionX>
      <positionY>12</positionY>
    </RegionCoordinates>
    <RegionCoordinates>
      <positionX>12</positionX>
      <positionY>11</positionY>
    </RegionCoordinates>
  </RegionCoordinatesList>
</MotionDetectionRegion>
</MotionDetectionRegionList>
</MotionDetection>

```

8.10.5 /MotionDetectionExt/<ID>

/MotionDetectionExt/ID		Service v2.0
GET		
Description	It is used to get the motion detection configuration for all video input channels.	
Query	None	
Inbound Data	None	
Success Return	MotionDetectionExt	

PUT	
Description	It is used to update the motion detection configuration for a video input channel.
Query	None
Inbound Data	MotionDetectionExt
Success Return	ResponseStatus
Notes: If motion detection is supported by the device, a motion detection ID will be allocated for each video input channel ID. The motion detection ID must correspond to the video input channel ID. <activeMode> indicates current effective motion detection mode, <activeMode> will switch to “Normal” mode automatically when using /MotionDetection/<ID>/regions to configure motion detection; <activeMode> will switch to “expert” mode automatically when using /MotionDetectionExt/<ID>	

MotionDetectionExt XML Block

```

<MotionDetectionExt version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean -->    </enabled>
  <minObjectSize>
    <!-- opt, xs:integer, min number of pixels per object -->
  </minObjectSize>
  <maxObjectSize>
    <!-- opt, xs:integer, max number of pixels per object -->
  </maxObjectSize>
  <ROI>
    <!-- dep, required if <motionType> is "roi" -->
    <minHorizontalResolution> <!-- req, xs:integer -->    </minHorizontalResolution>
    <minVerticalResolution>    <!-- req, xs:integer -->    </minVerticalResolution>
  </ROI>
  <highlightsenabled><!-- opt, xs:boolean -->    </highlightsenabled>
  <MotionDetectionSwitch/>
  <activeMode> <!-- ro, xs:string, "normal,expert"> <activeMode>
  <MotionDetectionRegionList/> <!-- req -->
</MotionDetectionExt>

```

8.10.6 /MotionDetectionExt/<ID>/switch

/MotionDetectionExt/ID/switch

General Resource v2.0

GET	
Description	It is used to get the motion detection switch day and night settings.
Query	None
Inbound Data	None
Success Return	MotionDetectionSwitch
PUT	
Description	It is used to update the motion detection switch day and night settings.
Query	None
Inbound Data	MotionDetectionSwitch
Success Return	ResponseStatus
Notes: If motion detection is supported by the device, a motion detection ID will be allocated for each video input channel ID. The motion detection ID must correspond to the video input channel ID.	

MotionDetectionSwitch XML Block

```
<MotionDetectionSwitch version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <type>
    <!-- opt, xs:string, "off,auto,schedule"-->
  </type>
  <Schedule> <!--dep-->
    <scheduleType><!--req,xs:string,"day,night"></scheduleType>
    <TimeRange> <!-- req -->
      <beginTime> <!-- req, xs:time, ISO8601 time --> </beginTime>
      <endTime> <!-- req, xs:time, ISO8601 time --> </endTime>
    </TimeRange>
  </Schedule>
</MotionDetectionSwitch>
```

8.10.7 /MotionDetectionExt/<ID>/regions

/MotionDetectionExt/ID/regions	General Resource v2.0
GET	

MotionDetectionRegionList XML Block

```
<MotionDetectionRegionList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <MotionDetectionRegion/> <!-- opt -->
```

</MotionDetectionRegionList>

8.10.8 /MotionDetectionExt/<ID>/regions/<ID>

/MotionDetectionExt/ID/regions/ID		General Resource v2.0
GET		
Description	It is used to get the motion detection configuration for all video input channels.	
Query	None	
Inbound Data	None	
Success Return	MotionDetectionRegion	
PUT		
Description	It is used to update the motion detection configuration for a video input channel.	
Query	None	
Inbound Data	MotionDetectionRegion	
Success Return	ResponseStatus	
Notes:		
If motion detection is supported by the device, a motion detection ID will be allocated for each video input channel ID. The motion detection ID must correspond to the video input channel ID.		

MotionDetectionRegion XML Block

```
<MotionDetectionRegion version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:string;id --></id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <maskEnabled> <!-- opt, xs:boolean --> </maskEnabled>
  <daySensitivityLevel> <!-- opt -->
    <!-- req, xs:integer, 0..100, 0 is least sensitive -->
  </daySensitivityLevel>
  <nightSensitivityLevel> <!-- opt -->
    <!-- req, xs:integer, 0..100, 0 is least sensitive -->
  </nightSensitivityLevel>
  <sensitivityLevel> <!-- opt -->
    <!-- req, xs:integer, 0..100, 0 is least sensitive -->
  </sensitivityLevel>
  <dayObjectSize> <!-- opt -->
    <!-- req, xs:integer, 0..100, 0 is least sensitive -->
  </dayObjectSize>
```

```

<nightObjectSize> <!-- opt -->
  <!-- req, xs:integer, 0..100, 0 is least sensitive -->
</nightObjectSize>
<objectSize> <!-- opt -->
  <!-- req, xs:integer, 0..100, 0 is least sensitive -->
</objectSize>
<detectionThreshold> <!-- req -->
  <!-- req, xs:integer, 0..100, percentage-->
</detectionThreshold>
<RegionCoordinatesList> <!-- req -->
  <RegionCoordinates> <!-- Note: at least two coordinates are required -->
    <positionX> <!-- req, xs:integer --> </positionX>
    <positionY> <!-- req, xs:integer --> </positionY>
  </RegionCoordinates>
</RegionCoordinatesList>
</MotionDetectionRegion>

```

8.11 Event

/Event		Service v1.0
GET		Viewer
Description	It is used to get the configuration of the device event behavior, scheduling and notifications.	
Query	None	
Inbound Data	None	
Success Return	EventNotification	
PUT		Operator
Description	It is used to update the configuration of the device event behavior, scheduling and notifications.	
Query	None	
Inbound Data	EventNotification	
Success Return	hik:ResponseStatus ResponseStatus	
Notes:		
The event trigger list defines the set of device behaviors that trigger events.		
The event schedule defines when event notifications are active.		
The event notification methods define what types of notification (e-mail) are supported.		

EventNotification XML Block

```

<EventNotification version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <EventTriggerList/> <!-- opt -->

```

```
<EventSchedule/>          <!-- opt -->
<EventNotificationMethods/> <!-- opt -->
</EventNotification>
```

8.11.1 Triggers

/Event/triggers		General Resource v1.0
GET		Viewer
Description	It is used to get the list of event triggers.	
Query	None	
Inbound Data	None	
Success Return	EventTriggerList	
PUT		Operator
Description	It is used to update the list of event triggers.	
Query	None	
Inbound Data	EventTriggerList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add an event trigger.	
Query	None	
Inbound Data	EventTrigger	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete the list of event triggers.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Event triggering defines how the device reacts to particular events, such as video loss or motion detection.		

EventTriggerList XML Block

```
<EventTriggerList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <EventTrigger/>  <!-- opt -->
</EventTriggerList>
```

8.11.2 Trigger

/Event/triggers/{ID}		General Resource v1.0
GET		Viewer
Description	It is used to get a particular event trigger configuration.	
Query	None	
Inbound Data	None	
Success Return	EventTrigger	
PUT		Operator
Description	It is used to update a particular event trigger configuration.	
Query	None	
Inbound Data	EventTrigger	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular event trigger.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<p>An event trigger determines how the device reacts when a particular event is detected.</p> <p>The following types are supported:</p> <ul style="list-style-type: none">IO: trigger when an input IO port changes state.VMD: trigger on video motion detection.Video loss: trigger when the input video signal cannot be detected.Shelter alarm: trigger when shelter is set. <p>The “ID” in the URI is the sequence number of a trigger , the max value of <id> is depend on device. The first trigger id is 1.</p> <p><inputIOPortID> is only required if <eventType> is “IO”.</p>		
<p>The trigger ID in URL is defined as :</p> <ul style="list-style-type: none">1 to N are assigned for alarm input port 1 to NN+1 is assigned for VMD eventN+2 is assigned for video-loss eventN+3 is assigned for Shelter alarm eventN+4 is assigned for field detection eventN+5 is assigned for audio exception detection eventN+6 is assigned for defocus detection eventN+7 is assigned for scene change detection eventN+8 is assigned for face detection <p>Example: For an IPC that with three alarm input ports, trigger 1 is alarm input 1 , trigger 3 is for alarm input 3, trigger 4 is for VMD, trigger 5 is for Video loss , trigger 6 is for shelter</p>		

alarm.

EventTriggerList XML Block

```
<EventTrigger version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>                <!-- req, xs:integer-->                </id>
  <eventType>          <!-- req, xs:string, "IO,VMD,videoloss,shelteralarm, fieldddetection,
audioexception,defocus,scenechangedetection,facedetection" -->  </eventType>
  <eventDescription>    <!-- ro, req, xs:string -->            </eventDescription>
  <inputIOPortID>       <!-- ro, req, xs:string -->            </inputIOPortID>
  <EventTriggerNotificationList/> <!-- req -->
</EventTrigger>
```

8.11.3 Trigger notifications

/Event/triggers/ID/notifications		General Resource v1.0
GET		Viewer
Description	It is used to get the list of notification methods and behaviors for an event trigger.	
Query	None	
Inbound Data	None	
Success Return	EventTriggerNotificationList	
PUT		Operator
Description	It is used to update the list of notification methods and behaviors for an event trigger.	
Query	None	
Inbound Data	EventTriggerNotificationList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add a notification method and behavior for an event trigger.	
Query	None	
Inbound Data	EventTriggerNotification	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete the list of notification method and behavior for an event trigger.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	

Notes:

This section determines the kinds of notifications that are supported for a particular event trigger and their recurrences and behaviors.

EventTriggerNotificationList XML Block

```
<EventTriggerNotificationList version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <EventTriggerNotification/>  <!-- opt -->
</EventTriggerNotificationList>
```

8.11.4 Trigger notification

/Event/triggers//ID/notifications//ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular notification method and behavior for an event trigger.	
Query	None	
Inbound Data	None	
Success Return	EventTriggerNotification	
PUT		Operator
Description	It is used to update a particular notification method and behavior for an event trigger.	
Query	None	
Inbound Data	EventTriggerNotification	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular notification method and behavior for an event trigger.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
The first “ID” in the URI is the sequence number of a trigger , the max value of <id> is depend on device. The first trigger id is 1.		
The second “ID” in the URI is the sequence number a notification , the max value of <id> is depend on device. The first notification id is 1.		
<outputIOPortID> is only required if the <notifiocationMethod> is “IO”.		
<ptzAction> is only required if the <notifiocationMethod> is “PTZ”.		

EventTriggerNotification XML Block

```
<EventTriggerNotification version="1.0"
```

```

xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>                <!-- req, xs:integer -->                </id>
  <notificationMethod><!--req,xs:string,"email,IO,record,HTTP,FTP,ptz"--></notificationMetho
d>
  <notificationRecurrence> <!-- ro, req, xs:string, "beginning" -->
  </notificationRecurrence>
  <outputIOPortID>      <!-- ro, dep, xs:integer -->          </outputIOPortID>
  <ptzAction> <!-- dep -->
    <ptzChannelID> <!--req, xs:string; id -->  </ptzChannelID>
    <actionName> <!-- req, xs:string, "preset, pattern, patrol" --> </actionName>
    <actionNum> <!-- dep, xs:integer> </actionNum>
  </ptzAction>
</EventTriggerNotification>

```

8.11.5 Schedule

/Event/schedule		General Resource v1.0
GET		Viewer
Description	It is used to get event schedules.	
Query	None	
Inbound Data	None	
Success Return	EventSchedule	
PUT		Operator
Description	It is used to update event schedules.	
Query	None	
Inbound Data	EventSchedule	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Defines the schedule. The schedule is defined as a set of time blocks that define when the events are active.		
The schedule is always valid.		
It only supports one TimeBlock every day now.		

EventSchedule XML Block

```

<EventSchedule version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <TimeBlockList> <!-- req -->
    <TimeBlock>
      <dayOfWeek>
        <!-- opt, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
      </dayOfWeek>
    </TimeBlock>
  </TimeBlockList>
</EventSchedule>

```



```

    <TimeRange>      <!-- req -->
      <beginTime>    <!-- req, xs:time, ISO8601 time --> </beginTime>
      <endTime>      <!-- req, xs:time, ISO8601 time --> </endTime>
    </TimeRange>
  </TimeBlock>
</TimeBlockList>
</EventSchedule>

```

8.11.6 Schedule/ID

/Event/Schedule/ID		General Resource v1.0
GET		Viewer
Description	It is used to get event schedules.	
Query	None	
Inbound Data	None	
Success Return	EventSchedule	
PUT		Operator
Description	It is used to update event schedules.	
Query	None	
Inbound Data	EventSchedule	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
This is a new resource, may be some old firmware isn't supported.		
Old url is : /Custom/HIKCGI/Event/schedule/ID		
New firmware will support both of them.		
ID is defined as TypeName. If the event type is IO, the ID is IO_IN_PortNumber/ the ID is IO_OUT_PortNumber.		
Examples :		
VMD : Video Motion Detection		
videoloss : Video Loss		
shelteralarm : Shelter Alarm		
fielddetection : Field Detection		
audioexception : Audio Exception		
scenechangedetection : Scene Change Detection		
IO_IN_1 :the first IO input port		
IO_OUT_2 : the second IO output port		

EventSchedule XML Block

```

<EventSchedule version= "1.0" xmlns= "http://www.hikvision.com/ver10/XMLSchema" >
  <eventType>      <!-- req -->

```

```

<!-- req, xs:string,
“IO,VMD,videoloss,shelteralarm,fielddetection,audioexception,scenechangedetection”
-->
</eventType>
<inputIOPortID>      <!-- dep, xs:string -->      </inputIOPortID>
<outputIOPortID>     <!-- dep, xs:string -->      </inputIOPortID>
<TimeBlockList> <!-- req -->
  <TimeBlock>
    <dayOfWeek>
      <!-- opt, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
    </dayOfWeek>
    <TimeRange>      <!-- req -->
      <beginTime>     <!-- req, xs:time, ISO8601 time --> </beginTime>
      <endTime>       <!-- req, xs:time, ISO8601 time --> </endTime>
    </TimeRange>
  </TimeBlock>
</TimeBlockList>
</EventSchedule>

```

8.11.7 Notification

/Event/notification		General Resource v1.0
GET		Viewer
Description	It is used to get event notifications configuration.	
Query	None	
Inbound Data	None	
Success Return	EventNotificationMethods	
PUT		Operator
Description	It is used to update event notifications configuration.	
Query	None	
Inbound Data	EventNotificationMethods	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
E-mail notification type is supported.		
E-mail: a mail with relevant information is sent in an e-mail to a list of servers.		

EventNotificationMethods XML Block

```

<EventNotificationMethods version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">

```

```
<MailingNotificationList/>    <!-- opt -->
<EmailFormat>                <!-- opt -->
    <senderEmailAddress>      <!-- req, xs:string --> </senderEmailAddress>
    <receiverEmailAddress>    <!-- req, xs:string --> </receiverEmailAddress>
</EmailFormat>
</EvenNotificationMethods>
```

8.11.8 Mails notification

/Event/notification/ mailing		General Resource v1.0
GET		Viewer
Description	It is used to get the list of E-mail notifications.	
Query	None	
Inbound Data	None	
Success Return	MailingNotificationList	
PUT		Operator
Description	It is used to update the list of E-mail notifications.	
Query	None	
Inbound Data	MailingNotificationList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add an E-mail notification.	
Query	None	
Inbound Data	MailingNotification	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete the list of E-mail notifications.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
When the notification is triggered, an e-mail with relevant information is mailed to the each of the addresses in the mailing list.		

MailingNotificationList XML Block

```
<MailingNotificationList version="1.0"
    xmlns="http://www.hikvision.com/ver10/XMLSchema">
    <MailingNotification/>    <!-- opt -->
</MailingNotificationList>
```

8.11.9 Mail notification

/Event/notification/mailing/ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular E-mail notification configuration.	
Query	None	
Inbound Data	None	
Success Return	MailingNotification	
PUT		Operator
Description	It is used to update a particular E-mail notification configuration.	
Query	None	
Inbound Data	MailingNotification	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular E-mail notification.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<p>Depending on the value of <addressingFormatType>, either the <hostName> or the IP address fields will be used to locate the SMTP server.</p> <p><authenticationMode> determines the authentication requirements for sending an email from the device.</p> <p><portNo> is the port number of the SMTP server entry.</p> <p><accountName> is the user account name for the SMTP server.</p>		

MailingNotification XML Block

```
<MailingNotification version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:integer, "1" -->    </id>
  <authenticationMode>
    <!-- req, xs:string, "SMTP,none" -->
  </authenticationMode>
  <addressingFormatType>
    <!-- req, xs:string, "ipaddress,hostname" -->
  </addressingFormatType>
  <hostName>      <!-- dep, xs:string -->      </hostName>
  <ipAddress>     <!-- dep, xs:string -->      </ipAddress>
  <portNo>        <!-- ro, req, xs:integer -->   </portNo>
  <accountName>   <!-- req, xs:string -->      </accountName>
  <password>      <!-- req, xs:string -->      </password>
  <attachmentEnable> <!-- opt, xs:Boolean,"true,false" --> </attachmentEnable>
```

```

<attachmentInterval> <!-- opt, xs:integer --> </attachmentInterval>
<sslEnable> <!-- opt, xs:Boolean, "true,false" --> </sslEnable>
<EmailFormatExt> <!-- opt"-->
<senderEmailAddress> <!-- req, xs:string --> </senderEmailAddress>
<receiverEmailAddressList>
<receiverEmailAddress>
<id> <!-- req, xs:integer --> </id>
<EmailAddress> <!-- req, xs:string --> </EmailAddress>
</receiverEmailAddress>
</receiverEmailAddressList>
</EmailFormatExt>
</MailingNotification>

```

8.11.10 HTTP Hosts

/Event/notification/httpHost		General Resource	v2.0
GET			
Description	It is used to get the configuration of e-mail.		
Query	None		
Inbound Data	None		
Success Return	HttpHostNotificationList		
PUT			
Description	It is used to set the configuration of e-mail.		
Query	None		
Inbound Data	HttpHostNotificationList		
Success Return	ResponseStatus		
Notes:			

HttpHostNotificationList XML Block

```

<HttpHostNotificationList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <HttpHostNotification/> <!-- opt -->
</HttpHostNotificationList>

```

8.11.11 HTTP Host

/Event/notification/httpHost/ID		General Resource v2.0
GET		
Description	It is used to get the configuration of a particular e-mail.	

Query	None
Inbound Data	None
Success Return	HttpHostNotification
PUT	
Description	It is used to set the configuration of a particular e-mail.
Query	None
Inbound Data	HttpHostNotification
Success Return	ResponseStatus
Notes:	

HttpHostNotification XML Block

```

<HttpHostNotification version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:string;id --> </id>
  <url> <!-- req, xs:string --> </url>
  <protocolType><!-- req, xs:string, "HTTP,HTTPS" --> </protocolType>
  <parameterFormatType>
    <!-- req, xs:string, "XML,querystring" -->
  </parameterFormatType>
  <addressingFormatType>
    <!-- req, xs:string, "ipaddress,hostname" -->
  </addressingFormatType>
  <hostName> <!-- dep, xs:string --> </hostName>
  <ipAddress> <!-- dep, xs:string --> </ipAddress>
  <ipv6Address> <!-- dep, xs:string --> </ipv6Address>
  <portNo> <!-- opt, xs:integer --> </portNo>
  <userName> <!-- dep, xs:string --> </userName>
  <password> <!-- dep, xs:string --> </password>
  <httpAuthenticationMethod>
    <!-- req, xs:string, "MD5digest,none" -->
  </httpAuthenticationMethod>
</HttpHostNotification>

```

8.11.12 Notification alertStream

/Event/notification/alertStream		General Resource v1.0
GET		Viewer
Description	It is used to get the event notification data stream through HTTP server push.	
Query	None	

Inbound Data	None
Success Return	Stream of <EventNotificationAlert>

Notes:

This function is used to get an event notification alert stream from the media device via HTTP or HTTPS. This function does not require that a client/VMS system be added as an HTTP(S) destination on the media device. Instead, the client/VMS system can call this API to initialize a stream of event information from the device. In other words, a connection is established with the device when this function is called, and stays open to constantly receive event notifications.

This API uses HTTP server-push with the MIME type multipart/mixed defined in RFC 2046.

<protocol> is the protocol name, i.e. "HTTP" or "HTTPS".

<channelID> is present for video and analytics events.

<activePostCount> is the sequence number of current notification for this particular event. It starts at 1. Useful for recurring notifications of an event. Each event maintains a separate post count.

EventNotificationAlert XML Block

```
<EventNotificationAlert version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ipAddress>      <!-- dep, xs:string -->    </ipAddress>
  <portNo>         <!-- opt, xs:integer -->    </portNo>
  <protocol>       <!-- opt, xs:string -->     </protocol>
  <macAddress>     <!-- opt, xs:string;MAC -->  </macAddress>
  <channelID>      <!-- dep, xs:string -->     </channelID>
  <dateTime>       <!-- req, xs:datetime -->   </dateTime>
  <activePostCount> <!-- req, xs:integer -->    </activePostCount>
  <eventType>      <!-- req, xs:string, "IO,VMD,videoloss, shelteralarm" --> </eventType>
  <eventState>     <!-- req, xs:string, "active,inactive" --> </eventState>
  <eventDescription> <!-- req, xs:string -->    </eventDescription>
  <inputIOPortID>  <!-- dep, xs:integer, if <eventType> is "IO" --> </inputIOPortID>
  <DetectionRegionList> <!-- dep, if <eventType> is "VMD" -->
    <DetectionRegionEntry> <!-- req -->
      <regionID>         <!-- req, xs:string -->    </regionID>
      <sensitivityLevel>  <!-- req, xs:integer, 0..100 --> </sensitivityLevel>
    </DetectionRegionEntry>
  </DetectionRegionList>
</EventNotificationAlert>
```

Example

The following is an example of an HTTP event stream that pushes a VMD event from video channel 1.

```
GET /Event/notification/alertStream HTTP/1.1
...
HTTP/1.1 200 OK
MIME-Version: 1.0
Content-Type: multipart/mixed; boundary="<boundary>"
--<boundary>
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>
<EventNotificationAlert version="1.0"
  xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ipAddress>172.6.64.7</ipAddress>
  <portNo>80</portNo>
  <protocol>HTTP</protocol>
  <macAddress>01:17:24:45:D9:F4</macAddress>
  <channelID>1</channelID>
  <dateTime>2009-11-14T15:27Z</dateTime>
  <activePostCount>1</activePostCount>
  <eventType>VMD</eventType>
  <eventState>active</eventState>
  <eventDescription>Motion alarm</eventDescription>
  <DetectionRegionList>
    <DetectionRegionEntry>
      <regionID>2</regionID>
      <sensitivityLevel>4</sensitivityLevel>
    </DetectionRegionEntry>
  </DetectionRegionList>
</EventNotificationAlert>
--<boundary>
...
```

8.11.13 Event Triggering Examples

Example: Trigger Events on IO Port

The command below enables detection for input port 1. When the input signal is detected according to <inputIOPortID>, two event notification responses are used – output port 2 will be triggered for the duration of the input signal detection, and an SMTP server will be notified with the “E-mail Event Notification Alert”. The behavior of this notification is as follows:

- A SMTP notification is sent at detection time, and every some seconds after while

the signal is present. This is denoted by the <notificationRecurrence> tags. These APIs will have an <eventState> of “active”.

- When the input port 1 signal detection stops, one last E-mail notification is sent to the server with an <eventState> of “active”.
- After the signal detection stops for input port 1, the device will wait some seconds before starting to detect the signal again for this port.

```
PUT /Event/triggers HTTP/1.1
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>
<EventTrigger version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>1</id> <!-- "eventType: IO" -->
  <EventTriggerNotificationList>
    <EventTriggerNotification>
      <id>1</id> <!-- "notificationMethod: email" -->
    </EventTriggerNotification>
    <EventTriggerNotification>
      <id>2</id> <!-- "notificationMethod: IO" -->
    </EventTriggerNotification>
  </EventTriggerNotificationList>
</EventTrigger>
```

Example: Schedule event detection and triggering

The command below schedules event detection and triggering from 7:00 am to 5:00 pm. every Tuesday.

```
PUT /Event/schedule HTTP/1.1
Content-Type: application/xml; charset="UTF-8"
Content-Length: xxx

<?xml version="1.0" encoding="UTF-8"?>
<EventSchedule version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <TimeBlockList>
    <TimeBlock>
      <dayOfWeek>2</dayOfWeek>
      <TimeRange>
        <beginTime>07:00:00</beginTime>
        <endTime>17:00:00</endTime>
      </TimeRange>
    </TimeBlock>
  </TimeBlockList>
</EventSchedule>
```

8.12 PTZ

/PTZ	Service v1.0
Notes: PTZ control service.	

8.12.1 Channels

/PTZ/channels		General Resource	v1.0
GET		Viewer	
Description	It is used to get the list of PTZ channels for the device.		
Query	None		
Inbound Data	None		
Success Return	PTZChannelList		
PUT		Operator	
Description	It is used to update the list of PTZ channels for the device.		
Query	None		
Inbound Data	PTZChannelList		
Success Return	hik:ResponseStaus ResponseStatus		
POST		Operator	
Description	It is used to add a PTZ channel for the device.		
Query	None		
Inbound Data	PTZChannel		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete the list of PTZ channels for the device.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
PTZ channels may be hardwired, or it may be possible to create channels if the device supports it. To determine whether it is possible to dynamically PTZ channels, check the defined HTTP methods in /PTZ/channels/description.			

PTZChannelList XML Block

```
<PTZChannelList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZChannel/>    <!-- opt -->
</PTZChannelList>
```

8.12.2 Channel

/PTZ/channels/ID		General Resource	v1.0
GET		Viewer	
Description	It is used to get a particular PTZ channel configuration for the device.		
Query	None		
Inbound Data	None		
Success Return	PTZChannel		
PUT		Operator	
Description	It is used to update a particular PTZ channel configuration for the device.		
Query	None		
Inbound Data	PTZChannel		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete a particular PTZ channel for the device.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<videoInputID> links the PTZ channel to a video channel.			
<controlProtocol> indicates the control protocol to be used for PTZ.			

PTZChannel XML Block

```

<PTZChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer --> </id>
  <videoInputID> <!-- req, xs:integer --> </videoInputID>
  <controlProtocol> <!-- req, xs:string --> </controlProtocol>
  <controlAddress> <!-- req, xs:integer --> </controlAddress>
  <PresetIDList> <!-- opt -->
    <PresetID> <!-- opt -->
      <id> <!-- ro, req, xs:integer, "1-128" --> </id>
      <enabled> <!-- req, xs:boolean --> </enabled>
    </PresetID>
  </PresetIDList>
  <PatrolIDList> <!-- opt -->
    <PatrolID> <!-- opt -->
      <id> <!-- ro, req, xs:integer, "1-16" --> </id>
      <enabled> <!-- req, xs:boolean --> </enabled>

```

```

    </PatrolID>
  </PatrolIDList >
  <PatternIDList> <!-- opt -->
    <PatternID> <!-- opt -->
      <id> <!-- ro, req, xs:integer, "1-16" --> </id>
      <enabled> <!-- req, xs:boolean --> </enabled>
    </PatternID>
  </PatternIDList>
</PTZChannel>

```

8.12.3 Patrols

/PTZ/channels/ID/patrols		General Resource	v1.0
GET		Viewer	
Description	It is used to get the list of patrols for a PTZ channel.		
Query	None		
Inbound Data	None		
Success Return	PTZPatrolList		
Notes:			

PTZPatrolList XML Block

```

<PTZPatrolList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZPatrol> <!-- opt -->
</ PTZPatrolList >

```

8.12.4 Patrol

/PTZ/channels/ID/patrols/ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular patrol configuration for a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PTZPatrol	
PUT		Operator
Description	It is used to update a particular patrol configuration for a PTZ channel.	
Query	None	
Inbound Data	PTZPatrol	

Success Return	hik:ResponseStaus ResponseStatus
Notes:	

PTZPatrol XML Block

```
<PTZPatrol version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>    <!-- req, xs:integer -->    </id>
  <PatrolPointList />    <!--opt -->
</ PTZPatrol>
```

8.12.5 Patrol keyPoints

/PTZ/channels//ID/patrols//ID/keyPoints		General Resource	v1.0
GET		Viewer	
Description	It is used to get the list of key points of a particular patrol for a PTZ channel.		
Query	None		
Inbound Data	None		
Success Return	PatrolPointList		
PUT		Operator	
Description	It is used to update the list of key points of a particular patrol for a PTZ channel.		
Query	None		
Inbound Data	PatrolPointList		
Success Return	hik:ResponseStaus ResponseStatus		
POST		Operator	
Description	It is used to add a key point of a particular patrol for a PTZ channel.		
Query	None		
Inbound Data	PatrolPoint		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete the list of key points of a particular patrol for a PTZ channel.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

PatrolPointList XML Block

```
<PatrolPointList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
```

```
<PatrolPoint /> <!--opt -->
</PatrolPointList>
```

8.12.6 Patrol keyPoint

/PTZ/channels//ID/patrols//ID/keyPoints//ID		General Resource v1.0
GET		Viewer
Description	It is used to get a particular key point of a particular patrol for a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PatrolPoint	
PUT		Operator
Description	It is used to update a particular key point of a particular patrol for a PTZ channel.	
Query	None	
Inbound Data	PatrolPoint	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular key point of a particular patrol for a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<presetNo> is Preset's series number.		
<speed> is Patrol speed.		
<dwelTime> is the stay time for the patrol point, the unit is second		

PatrolPoint XML Block

```
<PatrolPoint version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer --> </id>
  <presetNo> <!-- req, xs:integer --> </ presetNo>
  <speed> <!--opt, xs:integer --> </speed>
  <dwelTime> <!--opt, xs:integer --> </dwelTime>
</PatrolPoint>
```

8.12.7 PTZControl

/PTZ/channels//ID/PTZControl		General Resource v1.0
PUT		Operator
Description	It is used to control PTZ.	
Query	command presetNo patrolNo mode speed	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: The value of command is: LIGHT: Light WIPER: Wiper FAN: Fan HEATER: Heater. AUX1: auxiliary equipment 1. AUX2: auxiliary equipment 2 SET_PRESET: Set preset CLE_PRESET: Clear preset. ZOOM_IN: Zoom in the specified speed. ZOOM_OUT: Zoom out in the specified speed. FOCUS_NEAR: focus near in the specified speed. FOCUS_FAR: focus far in the specified speed. IRIS_OPEN: IRIS is open in the specified speed IRIS_CLOSE: IRIS is cloesd in the specified speed TILT_UP: PTZ is tilt up in the specified speed TILT_DOWN: PTZ is tilt down in the specified speed PAN_LEFT: PTZ is pan left in the specified speed PAN_RIGHT: PTZ is pan right in the specified speed UP_LEFT: PTZ is up-left in the specified speed UP_RIGHT: PTZ is up-right in the specified speed DOWN_LEFT: PTZ is down-left in the specified speed DOWN_RIGHT: PTZ is down-right in the specified speed PAN_AUTO: PTZ scans pan with the specified speed. MEM_PATTERN: memory pattern. RUN_PATTERN: Start pattern. PATROL: patrol. GOTO_PRESET: Go to preset.		

“mode” value is “start” and “stop”. It indicates the “start” or “stop” of some actions for PTZ, or the “turn on” or “turn off” of external equipment power for PTZ. The default is “start”.

In addition to the “SET_PRESET”, “CLE_PRESET”, “RUN_PATTERN” and “GOTO_PRESET” command, all commands require the “mode” query parameters.

“speed” range is 1-7.

When the command is “ZOOM_IN”, “ZOOM_OUT”, “FOCUS_NEAR”, “FOCUS_FAR”, “IRIS_OPEN”, or “IRIS_CLOSE”, the default is 1.

When the command is “TILT_UP”, “TILT_DOWN”, “PAN_LEFT”, “PAN_RIGHT”, “UP_LEFT”, “UP_RIGHT”, “DOWN_LEFT”, “DOWN_RIGHT”, “PAN_AUTO”, the default is 3.

8.13 PTZCtrl

/PTZCtrl	Service v1.0
Notes: PTZCtrl control service.	

8.13.1 /PTZCtrl/channels

/PTZCtrl/channels		General Resource v1.0
GET		Viewer
Description	It is used to get the list of PTZ channels for the device	
Query	None	
Inbound Data	None	
Success Return	PTZChannelList	
PUT		Operator
Description	It is used to update the list of PTZ channels for the device.	
Query	None	
Inbound Data	PTZChannelList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator
Description	It is used to add a PTZ channel for the device.	
Query	None	
Inbound Data	PTZChannel	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Administrator

Description	It is used to delete the list of PTZ channels for the device.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: PTZ channels may be hardwired, or it may be possible to create channels if the device supports it. To determine whether it is possible to dynamically PTZ channels, check the defined HTTP methods in /PTZCtrl/channels/description.	

PTZChannelList XML Block

```
<PTZChannelList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZChannel/>    <!-- opt -->
</PTZChannelList>
```

8.13.2 /PTZCtrl/channels/<ID>

/PTZCtrl/channels/<ID>		General Resource v1.0
GET		Viewer
Description	It is used to get a particular PTZ channel configuration for the device.	
Query	None	
Inbound Data	None	
Success Return	PTZChannel	
PUT		Operator
Description	It is used to update a particular PTZ channel configuration for the device.	
Query	None	
Inbound Data	PTZChannel	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular PTZ channel on a device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<videoInputID> links the PTZ channel to a video channel.		
<presetSpeed> indicates the movement speed level about calling preset		
<autoScanSpeed> indicates the movement speed level about park function		
<keyPadControlSpeed> indicates the movement speed level to be controlled by keyboard		
<controlProtocol> indicates the control protocol to be used for PTZ.		
< controlAddress> indicates the soft address (enabled means soft address is used)		

PTZChannel XML Block

```
<PTZChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer --> </id>
  <enabled> <!--ro,req, xs:boolean --> </enabled>
  <videoInputID> <!-- req, xs:integer --> </videoInputID>
  <panMaxSpeed> <!--ro,opt, xs:integer, degrees/sec --> </panMaxSpeed>
  <tiltMaxSpeed> <!--ro,opt, xs:integer, degrees/sec --> </tiltMaxSpeed>
  <presetSpeed> <!--opt, xs:integer 1..8 --> </presetSpeed>
  <autoPatrolSpeed> <!-- opt, xs:integer, 0..100 --> </autoPatrolSpeed>
  <keyBoardControlSpeed>
    <!-- opt, xs:string, "low, normal, high">
  </keyBoardControlSpeed>
  <controlProtocol> <!-- opt, xs:string, "pelco-d,... " --> </controlProtocol>
  <controlAddress> <!--opt -->
    <enabled> <!-- req, xs:boolean --> </enabled>
    <Address> <!--opt, xs:string 1-255 --> </Address>
  </controlAddress><
  <defaultPresetID> <!-- opt, xs:string;id --> </defaultPresetID>
  <panSupport> <!--ro,opt, xs:boolean --> </panSupport>
  <tiltSupport> <!--ro,opt, xs:boolean --> </tiltSupport>
  <zoomSupport> <!--ro,opt, xs:boolean --> </zoomSupport>
</PTZChannel>
```

8.13.3 /PTZCtrl/channels/<ID>/homeposition

/PTZCtrl/channels/<ID>/homeposition		General Resource v1.0
PUT		Operator
Description	It is used to set the current horizontal position as horizontal coordinate zero point for the device	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete system horizontal coordinate zero point and restore default zero point for the device (The photoelectric detection location)	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.4 /PTZCtrl/channels/<ID>/homeposition/goto

/PTZCtrl/channels/<ID>/homeposition/goto		General Resource v1.0
PUT		Operator
Description	It is used to move a particular PTZ channel to horizontal coordinate zero point position for the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.5 /PTZCtrl/channels/<ID>/continuous

/PTZCtrl/channels/<ID>/continuous		General Resource v1.0
PUT		Operator
Description	It is used to control PTZ move around and zoom for the device.	
Query	pan, tilt, zoom	
Inbound Data	PTZData	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

PTZData XML Block

```
<PTZData version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <pan> <!-- opt, xs:integer, -100..100 --> </pan>
  <tilt> <!-- opt, xs:integer, -100..100 --> </tilt>
  <zoom> <!-- opt, xs:integer, -100.. 100--> </zoom>
</PTZData>
```

8.13.6 /PTZCtrl/channels/<ID>/momentary

/PTZCtrl/channels/<ID>/momentary		General Resource v1.0
PUT		Operator
Description	It is used to control PTZ move around and zoom in a period of time for the device.	
Query	pan, tilt, zoom, duration	
Inbound Data	PTZData	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

PTZData XML Block

```
<PTZData version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <pan> <!-- opt, xs:integer, -100..100 --> </pan>
  <tilt> <!-- opt, xs:integer, -100..100 --> </tilt>
  <zoom> <!-- opt, xs:integer, -100.. 100--> </zoom>
  <Momentary>
    < duration> <!--opt , xs:integer, milliseconds --> </duration>
  </Momentary>
</PTZData>
```

8.13.7 /PTZCtrl/channels/<ID>/relative

/PTZCtrl/channels/<ID>/relative		General Resource	v1.0
PUT		Operator	
Description	Pans, tilts, and/or zooms the device relative to the current position.		
Query	positionX, positionY, relativeZoom		
Inbound Data	PTZData		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
Mouse clicking function			

PTZData XML Block

```
<PTZData version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <Relative>
    <positionX> <!-- opt, xs:integer --> </positionX>
    <positionY> <!-- opt, xs:integer --> </positionY>
    <relativeZoom> <!-- opt, xs:integer, -100.. 100--> </relativeZoom>
  </Relative>
</PTZData>
```

8.13.8 /PTZCtrl/channels/<ID>/absolute

/PTZCtrl/channels/<ID>/absolute		General Resource v1.0
PUT		Operator
Description	It is used to move a particular PTZ channel to a absolute position which is defined by Absolute for the device.	
Query	elevation, azimuth, absoluteZoom	
Inbound Data	PTZData	
Success Return	hik:ResponseStaus ResponseStatus	

Notes:

Absolute position function

<AbsoluteHigh> is high precision positioning which is accurate to a bit after the decimal point; For example elevation -900..2700 is corresponding to vertical -90.0-270.0 degree, and azimuth 0..3600 is corresponding to horizontal 0.0-360.0 degree, absoluteZoom is corresponding to zoom 0.0..100.0;

PTZData XML Block

```
<PTZData version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <AbsoluteHigh>
    <elevation> <!-- opt, xs:integer, -900..2700 --> </elevation>
    <azimuth> <!-- opt, xs:integer, 0..3600 --> </azimuth>
    <absoluteZoom> <!-- opt, xs:integer,0.. 1000---> </absoluteZoom>
  </AbsoluteHigh>
</PTZData>
```

8.13.9 /PTZCtrl/channels/<ID>/digital

/PTZCtrl/channels/<ID>/digital		General Resource v1.0
PUT		Operator
Description	It is used to move the position number which is defined by positionX, position to the screen center and digital zoom for the device.	
Query	position, positionY, digitalZoomLevel	
Inbound Data	PTZData	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: Digital zoom function digitalZoomLevel: 0 indicates that maintain the original image ratio.		

PTZData XML Block

```
<PTZData version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <Digital>
    <positionX> <!-- opt, xs:integer --> </positionX>
    <positionY> <!-- opt, xs:integer --> </positionY>
    <digitalZoomLevel> <!-- opt, xs:integer, 0.. 100---> </digitalZoomLevel>
  </Digital>
</PTZData>
```

8.13.10 /PTZCtrl/channels/<ID>/status

/PTZCtrl/channels/<ID>/status		General Resource v1.0
GET		Viewer
Description	It is used to get currently PTZ coordinate position for the device.	
Query	None	
Inbound Data	None	
Success Return	PTZStatus	
Notes: <AbsoluteHigh> is high precision positioning which is accurate to a bit after the decimal point; For example elevation -900..2700 is corresponding to vertical -90.0-270.0 degree, and azimuth 0..3600 is corresponding to horizontal 0.0-360.0 degree, absoluteZoom is corresponding to zoom 0.0..100.0;		

PTZStatus XML Block

```
< PTZStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <AbsoluteHigh>
    <elevation> <!-- opt, xs:integer, -900..2700 --> </elevation>
    <azimuth> <!-- opt, xs:integer, 0..3600 --> </azimuth>
    <absoluteZoom> <!-- opt, xs:integer,0.. 1000---> </absoluteZoom>
  </AbsoluteHigh>
</PTZStatus>
```

8.13.11 /PTZCtrl/channels/<ID>/presets

/PTZCtrl/channels/<ID>/presets		General Resource v1.0
GET		Viewer
Description	It is used to get preset configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	None	
Success Return	PTZPresetList	
PUT		Operator
Description	It is used to update preset configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	PTZPresetList	
Success Return	hik:ResponseStaus ResponseStatus	
POST		Operator

Description	It is used to add preset configuration information of a particular PTZ channel for the device.
Query	None
Inbound Data	PTZPreset
Success Return	hik:ResponseStaus ResponseStatus
DELETE Administrator	
Description	It is used to delete preset configuration information of a particular PTZ channel for the device.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

PTZPresetList XML Block

```
<PTZPresetList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZPreset> <!-- opt -->
</PTZPresetList>
```

8.13.12 /PTZCtrl/channels/<ID>/presets/<ID>

/PTZCtrl/channels/<ID>/presets/<ID>		General Resource v1.0
GET		Viewer
Description	It is used to get particular preset configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	None	
Success Return	PTZPreset	
PUT		Operator
Description	It is used to update particular preset configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	PTZPreset	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete particular preset configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	

Notes:

<id> indicates the preset number.

<presetName> indicates the preset name

Enable is used to indicate whether preset have been set.

PUT is used to set preset and update title of new preset. (Enable value import to **PTZPreset** should be 1 when PUT)

PTZPreset XML Block

```
<PTZPreset version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <id> <!-- req, xs:string;id --> </id>
  <presetName> <!-- req, xs:string --> </presetName>
</PTZPreset>
```

8.13.13 /PTZCtrl/channels/<ID>/presets/<ID>/goto

/PTZCtrl/channels/<ID>/presets/<ID>/goto		General Resource v1.0
PUT		Operator
Description	It is used to move a particular PTZ channel to a ID preset position for the device.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.14 /PTZCtrl/channels/<ID>/patrols

/PTZCtrl/channels/<ID>/patrols		General Resource v1.0
GET		Viewer
Description	It is used to get patrol configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	None	
Success Return	PTZPatrolList	
PUT		Operator
Description	It is used to update patrol configuration information of a particular PTZ channel for the device.	
Query	None	
Inbound Data	PTZPatrolList	

Success Return	hik:ResponseStaus ResponseStatus
POST Operator	
Description	It is used to add a patrol point configuration for a particular PTZ channel.
Query	None
Inbound Data	PTZPatrol
Success Return	hik:ResponseStaus ResponseStatus
DELETE Administrator	
Description	It is used to delete patrol configuration for a particular PTZ channel.
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: It is similar with preset.	

PTZPatrolList XML Block

```
<PTZPatrolList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZPatrol> <!-- opt -->
</PTZPatrolList>
```

8.13.15 /PTZCtrl/channels/<ID>/patrols/<ID>

/PTZCtrl/channels/<ID>/patrols/<ID> General Resource v1.0	
GET Viewer	
Description	It is used to get a particular patrol route configuration of a particular PTZ channel.
Query	None
Inbound Data	None
Success Return	PTZPatrol
PUT Operator	
Description	It is used to update a particular patrol configuration of a particular PTZ channel.
Query	None
Inbound Data	PTZPatrol
Success Return	hik:ResponseStaus ResponseStatus
DELETE Operator	
Description	It is used to delete a particular patrol route configuration of a particular PTZ channel
Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus

Notes:

<PatrolSequence> indicates the patrol point.

< presetID > indicates the preset number

<seqSpeed> indicates the patrol speed

<delay> indicates the dwell time, in seconds

PTZPatrol XML Block

```
<PTZPatrol version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <id> <!-- req, xs:string;id --> </id>
  <patrolName> <!-- req, xs:string --> </patrolName>
  <resumeType> <!-- opt, xs:string, "relative,absolute" --> </resumeType>
  <PatrolSequenceList> <!-- req, at least one entry -->
    <PatrolSequence> <!-- req -->
      <id> <!-- req, xs:string;id --> </id>
      <presetID> <!-- req, xs:string;id --> </presetID>
      <seqSpeed> <!-- req, xs:string;id --> </seqSpeed>
      <delay> <!-- req, xs:integer, milliseconds --> </delay>
    </PatrolSequence>
  </PatrolSequenceList>
</PTZPatrol>
```

8.13.16 /PTZCtrl/channels/<ID>/patrols/<ID>/start

/PTZCtrl/channels/<ID>/patrols/<ID>/start		General Resource v1.0
PUT		Operator
Description	It is used to start running particular patrol route of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.17 /PTZCtrl/channels/<ID>/patrols/<ID>/stop

/PTZCtrl/channels/<ID>/patrols/<ID>/stop		General Resource v1.0
PUT		Operator
Description	It is used to stop running particular patrol route of a particular PTZ channel.	
Query	None	

Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: It is available to stop the patrol route which is in running state or in pause state.	

8.13.18 /PTZCtrl/channels/<ID>/patrols/<ID>/pause

/PTZCtrl/channels/<ID>/patrols/<ID>/pause		General Resource v1.0
PUT		Operator
Description	It is used to pause particular patrol route which is in running state of a particular channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Patrolstart is used to restart patrol route.		
It doesn't support dome at this moment.		

8.13.19 /PTZCtrl/channels/<ID>/patrols/<ID>/status

/PTZCtrl/channels/<ID>/patrols/<ID>/status		General Resource	v1.0
GET		Viewer	
Description	It is used to get particular patrol route state of a particular PTZ channel.		
Query	None		
Inbound Data	PTZPatrolStatus		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
It doesn't support dome at this moment!!			

PTZPatrolStatus XML Block

```
<PTZPatrol version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZPatrolStatus>    <!--opt -->
    <patrolID> <!-- req, xs:string;id --> </patrolID>
    <patrolStatus> <!-- req, xs:string, "running,stopped,pause" --> </patrolStatus>
  </PTZPatrolStatus>
</PTZPatrol>
```

8.13.20 /PTZCtrl/channels/<ID>/patrols/<ID>/schedule

/PTZCtrl/channels/<ID>/patrols/<ID>/schedule		General Resource v1.0
GET		Viewer
Description	It is used to get patrol schedule of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	TimeBlockList	
PUT		Operator
Description	It is used to update patrol schedule of a particular PTZ channel.	
Query	None	
Inbound Data	TimeBlockList	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.21 /PTZCtrl/channels/<ID>/patterns

/PTZCtrl/channels/<ID>/patterns		General Resource v1.0
GET		Viewer
Description	It is used to get pattern configuration of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PTZPatternList	
Notes:		
It is similar to presets!!		
DELETE		Operator
Description	It is used to delete all patterns configuration of a particular PTZ channel	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	

PTZPatternList XML Block

```
<PTZPatternList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <PTZPattern> <!-- opt -->
</ PTZPatternList >
```

8.13.22 /PTZCtrl/channels/<ID>/patterns/<ID>

/PTZCtrl/channels/<ID>/patterns/<ID>		General Resource v1.0
GET		Viewer
Description	It is used to get a particular pattern configuration of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PTZPattern	
PUT		Operator
Description	It is used to update a particular pattern configuration of a particular PTZ channel.	
Query	None	
Inbound Data	PTZPattern	
Success Return	hik:ResponseStaus ResponseStatus	
DELETE		Operator
Description	It is used to delete a particular pattern configuration of a particular PTZ channel	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<space> x% indicates the remaining space for pattern		

PTZPattern XML Block

```
<PTZPattern version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <id> <!-- req, xs:integer --> </id>
  <space> <!-- req, xs:integer, 0..100--> </space>
</PTZPattern>
```

8.13.23 /PTZCtrl/channels/<ID>/patterns/<ID>/recordstart

/PTZCtrl/channels/<ID>/patterns/<ID>/recordstart		General Resource v1.0
PUT		Operator
Description	It is used to start particular pattern information recording of a particular PTZ channel.	
Query	None	

Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus
Notes: Remaining space information will be uploaded in real time during the recording process.	

8.13.24 /PTZCtrl/channels/<ID>/patterns/<ID>/recordstop

/PTZCtrl/channels/<ID>/patterns/<ID>/recordstop		General Resource	v1.0
PUT		Operator	
Description	It is used to stop a particular pattern information recording of a particular PTZ channel		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

8.13.25 /PTZCtrl/channels/<ID>/patterns/<ID>/run

/PTZCtrl/channels/<ID>/patterns/<ID>/run		General Resource v1.0
PUT		Operator
Description	It is used to start a particular pattern of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.26 /PTZCtrl/channels/<ID>/patterns/<ID>/stop

/PTZCtrl/channels/<ID>/patterns/<ID>/stop		General Resource v1.0
PUT		Operator
Description	It is used to stop a particular pattern which is in running status of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

8.13.27 /PTZCtrl/channels/<ID>/PTZOSDDisplay

/PTZCtrl/channels/<ID>/PTZOSDDisplay		General Resource v1.0
GET		Viewer
Description	It is used to get OSD display information of a particular PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PTZOSDDisplay	
PUT		Operator
Description	It is used to update OSD display information of a particular PTZ channel.	
Query	None	
Inbound Data	PTZOSDDisplay	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<zoomlable> indicates the zoom progress bar display		
<azimuth> indicates the azimuth display		
<presetlable> indicates the preset title display		

PTZOSDDisplay XML Block

```

<PTZOSDDisplay version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <zoomlable>
    <!-- req, xs:strings, "2sec, 5sec, 10sec, alwaysclose, alwaysopen"-->
  </zoomlable>
  <azimuth>
    <!-- req, xs:strings, "2sec, 5sec, 10sec, alwaysclose, alwaysopen"-->
  </azimuth>
  <presetlable>
    <!-- req, xs:strings, "2sec, 5sec, 10sec, alwaysclose, alwaysopen"-->
  </presetlable>
</PTZOSDDisplay>

```

8.13.28 /PTZCtrl/channels/<ID>/parkaction

/PTZCtrl/channels/<ID>/parkaction		General Resource v1.0
GET		Viewer
Description	It is used to get park action information of a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	ParkAction	

PUT		Operator
Description	It is used to update park action information of a PTZ channel.	
Query	None	
Inbound Data	ParkAction	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
<Parktime> Time span that will trigger an park action		
<Action> park action		
<ActionNum> park action number. It is used when park action is patrol, pattern or preset.		
For others, it is 0		

ParkAction XML Block

```

<ParkAction version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <Parktime> <!-- req, xs:integer, seconds --> </Parktime>
  <Action>
    <ActionType>
      <!-- req, xs:strings, "atuoscan, framescan, randomscan, panoramascan,
      patrol, pattern, preset" -->
    </ActionType>
    <ActionNum> <!-- req, xs:integer, 0..255--> </ActionNum>
  </Action>
</ParkAction>

```

8.13.29 /PTZCtrl/channels/<ID>/ptzlimiteds

/PTZCtrl/channels/<ID>/ptzlimiteds		General Resource v1.0
GET		Viewer
Description	It is used to get movement limitations of PTZ channels.	
Query	None	
Inbound Data	None	
Success Return	PTZLimitedList	
Notes:		
PUT		Viewer
Description	It is used to set movement limitations of PTZ channels.	
Query	None	
Inbound Data	None	
Success Return	PTZLimitedList	
Notes:		
DELETE		
Description	It is used to clear movement limitations of a PTZ channel.	

Query	None
Inbound Data	None
Success Return	hik:ResponseStaus ResponseStatus

PTZLimitedList XML Block

```
<PTZLimitedList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled><!-- req --></enabled>
  <PTZLimited> <!-- opt -->
</ PTZLimitedList>
```

8.13.30 /PTZCtrl/channels/<ID>/ptzlimiteds/<ID>

/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>		General Resource v1.0
GET		Viewer
Description	It is used to get movement limitations of a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	PTZLimited	
DELETE		
Description	It is used to clear movement limitations of a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
It is used to get or set the parameter that whether movement limitation is enabled or disabled.		
Speed dome add two types of movement limitation.		
<ID>=1 Manual control movement limitation <ID>=2 Panorama scan movement limitation		

PTZLimited XML Block

```
<PTZLimited version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <id> <!-- req, xs:string;id --> </id>
</PTZLimited>
```

8.13.31 /PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/setstart

/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/setstart		General Resource v1.0
PUT		Operator
Description	Set the start position of a movement limitation of a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Only used when movement limitation is enabled.		

8.13.32 /PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/set

/PTZCtrl/channels/<ID>/ptzlimiteds/<ID>/set		General Resource v1.0
PUT		Operator
Description	Set other positions of a movement limitation of a PTZ channel.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: Only used when movement limitation is enabled and setstart already been used. Order of the positions is left→right→up→down. Please save the settings after setup.		

8.13.33 /PTZCtrl/channels/<ID>/saveptzpoweroff

/PTZCtrl/channels/<ID>/saveptzpoweroff		General Resource v1.0
GET		Viewer
Description	It is used to get the PTZ power off memory settings information	
Query	None	
Inbound Data	None	
Success Return	PTZChannel	
PUT		Operator
Description	It is used to update the PTZ power off memory settings information	
Query	None	
Inbound Data	PTZChannel	

Success Return	hik:ResponseStaus ResponseStatus
Notes: <savePtzPoweroff>Power off memory	

savePtzPoweroff XML Block

```
<savePtzPoweroff version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <savePtzPoweroffType>
    <!-- req, xs:integer, "disable, 30sec, 60sec, 300sec, 600sec"-->
  </savePtzPoweroffType>
</savePtzPoweroff>
```

8.13.34 /PTZCtrl/channels/<ID>/timetasks

/PTZCtrl/channels/<ID>/timetasks		General Resource v1.0
GET		Viewer
Description	It is used to get a list of tasks based on a schedule	
Query	None	
Inbound Data	None	
Success Return	TimeTaskList	
PUT		Operator
Description	It is used to update a list of tasks based on a schedule	
Query	None	
Inbound Data	TimeTaskList	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: GET is used to get a list of tasks of a whole week(7) <enabled>Enable all the tasks <Parktime> Time span for a task to resume.		
DELETE		Operator
Description	It is used to delete all lists of tasks	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	

TimeTaskList XML Block

```
<TimeTaskList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <Parktime> <!-- req, xs:integer, seconds --> </Parktime>
  <TimeTaskBlock /> <!-- opt -->
```

</TimeTaskList>

8.13.35 /PTZCtrl/channels/<ID>/timetasks/<ID>

/PTZCtrl/channels/<ID>/timetasks/<ID>		General Resource	v1.0
GET		Viewer	
Description	It is used to get a list of tasks of one day		
Query	None		
Inbound Data	None		
Success Return	TimeTaskBlock		
PUT		Operator	
Description	It is used to update a list of tasks of one day		
Query	None		
Inbound Data	TimeTaskBlock		
Success Return	hik:ResponseStaus ResponseStatus		
DELETE		Operator	
Description	It is used to delete a list of tasks of one day		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
Tasks based on a schedule consist of time blocks ad tasked. This task is enabled always.			
<TimeTaskBlock> get all the time span and tasks of one day			
<dayOfWeek> specify the day of a week, ranging from 1 to 7			
<TimeTaskRange> time span of each task. Up to ten time spans and 10 tasks are supported in one day.			
<beginDateTime> specify the begin time of each task, ranig from 0:0:0-23:59:00, format is consistent to ISO 8601.			
<endDateTime> specify the end time of each task, ranig from 0:0:0-23:59:00, format is consistent to ISO 8601. endDateTime should be larger than or equal to beginDateTime.			
<TaskType> Tasks type			
<TaskNum> Tasks number. Enabled when park action is patrol, pattern, preset or auxoutput, otherwise the value is 0.			

TimeTaskBlock XML Block

```
<TimeTaskBlock version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <dayOfWeek>
    <!-- req, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
  </dayOfWeek>
  <TimeTaskRange>
    <TaskID><!-- req, xs:string;id --></TaskID>
```

```

<beginTime> <!-- req, xs:time, ISO8601 time --> </beginTime>
<endTime> <!-- req, xs:time, ISO8601 time --> </endTime>
<Task>
  <TaskType>
    <!-- req, xs:strings, "disable, atuoscan, framescan, randomscan, panoramascan,
patrol, pattern, preset, tiltscan,periodreboot,periodadjust,auxoutput" -->
  </TaskType>
  <TaskNum><!-- dep, xs:integer, 0.8--></TaskNum>
</Task>
</TimeTaskRange>
</TimeTaskBlock>

```

8.13.36 /PTZCtrl/channels/<ID>/timetasks

/<ID>/copytask

/PTZCtrl/channels/<ID>/timetasks/<ID>/copytask		General Resource	v1.0
GET		Viewer	
Description	It is used to get the default copy time of a tasks list of a specified PTZ channel.		
Query	None		
Inbound Data	None		
Success Return	TimeTaskCopy		
PUT		Operator	
Description	It is used to update the default copy time of a tasks list of a specified PTZ channel.		
Query	None		
Inbound Data	TimeTaskCopy		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
<curDayOfWeek> specify the current day of a week;			
<copyDayOfWeek> specify the days that will have the same settings as the current day;			

TimeTaskCopy XML Block

```

<TimeTaskCopy version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <curDayOfWeek>
    <!-- req, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
  </curDay>
  <copyDayOfWeek>
    <!-- req, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
  </copyDay>

```

</TimeTaskCopy >

8.13.37 /PTZCtrl/channels/<ID>/auxcontrol

/PTZCtrl/channels/<ID>/auxcontrol		General Resource v1.0
GET		Viewer
Description	It is used to get auxillary PTZ control information of a specified PTZchannel.	
Query	command	
Inbound Data	None	
Success Return	PTZAuxStatus	
PUT		Operator
Description	It is used to update auxillary PTZ control information of a specified PTZchannel.	
Query	command	
Inbound Data	PTZAuxStatus	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		
Auxillary PTZ functions:		
Commands:		
LIGHT_PWRON: open light		
WIPER_PWRON: turn on wiper		
FAN_PWRON: turn on fun		
HEATER_PWRON: turn on heater		
<enabled> 1 means turned on, 0 means turned off.		

PTZAuxStatus XML Block

```
<PTZAuxStatus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
</PTZAuxStatus>
```

8.13.38 /PTZCtrl/channels/<ID>/onpushfoucs/start

/PTZCtrl/channels/<ID>/onpushfoucs/start		General Resource v1.0
PUT		Operator
Description	It is used to start focusing by pushing a key.	
Query	None	
Inbound Data	None	
Success Return	hik:ResponseStaus ResponseStatus	

Notes:

8.13.39 /PTZCtrl/channels/<ID>/onpushfoucs/reset

/PTZCtrl/channels/<ID>/onpushfoucs/reset		General Resource	v1.0
PUT		Operator	
Description	IPC Lens initialization		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

8.13.40 /PTZCtrl/channels/<ID>/position3D

/PTZCtrl/channels/<ID>/position3D		General Resource	v1.0
PUT		Operator	
Description	It is used to set 3D zoom of a particular PTZ channel.		
Query	None		
Inbound Data	Position3D		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

Position3D XML Block

```
<Position3D version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <StartPoint><!--0-255-->
    <positionX> <!-- req, xs:integer --> </positionX>
    <positionY> <!-- req, xs:integer --> </positionY>
  </StartPoint>
  <EndPoint>
    <positionX> <!-- req, xs:integer --> </positionX>
    <positionY> <!-- req, xs:integer --> </positionY>
  </EndPoint>
</Position3D>
```

8.14 Image

/Image	Service v1.0
Notes: service of camera Image	

8.14.1 /Image/channels

/Image/channels		General Resource	v1.0
GET		Viewer	
Description	It is used to get the list of channel Image configuration.		
Query	None		
Inbound Data	None		
Success Return	ImageChannellist		
PUT		Operator	
Description	It is used to update Image configuration for all channels.		
Query	None		
Inbound Data	ImageChannellist		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

ImageChannellist XML Block

```
<ImageChannellist version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ImageChannel/> <!--opt-->
</ImageChannellist>
```

8.14.2 /Image/channels/<ID>

/Image/channels/<ID>		General Resource v1.0
GET		Viewer
Description	It is used to get a special channel Image configuration.	
Query	None	
Inbound Data	None	
Success Return	ImageChannel	
PUT		Operator
Description	It is used to update Image configuration for a special channel.	
Query	None	
Inbound Data	ImageChannel	
Success Return	hik:ResponseStaus ResponseStatus	

Notes:

ImageChannellist XML Block

```
<ImageChannel version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id><!-- req, xs:integer --></id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <videoInputID> <!-- req, xs:integer --> </videoInputID>
  <resetImage/><!-- opt -->
  <restoreImageparam/> <!-- opt -->
  <Focus/> <!-- opt -->
  <LensInitialization /> <!-- opt -->
  <ImageFilp/> <!-- opt -->
  <ImageFreeze/> <!-- opt -->
  <proportionalpan/> <!-- opt -->
  <WDR/> <!-- opt -->
  <BLC/> <!-- opt -->
  <NoiseReduce/> <!-- opt -->
  <ImageEnhancement/> <!-- opt -->
  <IrcutFilter/> <!-- opt -->
  <DSS/> <!-- opt -->
  <WhiteBlance/> <!-- opt -->
  <Exposure/> <!-- opt -->
  <Sharpness/> <!-- opt -->
  <Iris/> <!-- opt -->
  <Shutter/> <!-- opt -->
  <Gain/> <!-- opt -->
  <gamaCorrection/> <!-- opt -->
  <powerLineFrequency/> <!-- opt -->
  <Color/> <!-- opt -->
  <NosiseReduceExt/> <!-- opt -->
  <IrcutFilterExt/> <!-- opt -->
  <WDRExt/> <!-- opt -->
  <Scene/> <!-- opt -->
  < EPTZ/ > <!-- opt -->
  < PTZ/> <!-- opt -->
  <EIS/> <!-- opt -->
  <HLC/> <!-- opt -->
  <ChromaSuppress/> <!-- opt -->
  <ZoomLimit/> <!-- opt -->
  <ExpComp/> <!-- opt -->
</ImageChannel>
```

8.14.3 /Image/channels/<ID>/resetImage

/Image/channels/{ID}/resetImage		General Resource	v1.0
PUT		Operator	
Description	It is used to reset an image channel (cut off the power and reboot the speed dome).		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes: Image reset only reboot the camera unit.			

8.14.4 /Image/channels/<ID>/restoreImageparam

/Image/channels/<ID>/restoreImageparam		General Resource	v1.0
PUT		Operator	
Description	It is used to reset the image configure parameter to the factory default.		
Query	None		
Inbound Data	None		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

8.14.5 /Image/channels/<ID>/Focus

/Image/channels/<ID>/Focus		General Resource	v1.0
GET		Viewer	
Description	It is used to get focus parameters of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	Focus		
PUT		Operator	
Description	It is used to update focus parameters of a specified image channel.		
Query	None		
Inbound Data	Focus		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			
AUTO: auto focus			

MANUAL: manual focus

SEMIAUTOMATIC: semi automatic

FocusValue's PUT operator is enabled only when FocusStyle's value is MANUAL.

focusSpeed: focus vector data. Negative numbers focus near, positive numbers focus far.

Numerical value is a percentage of the maximum focus speed of the lens module.

Focus XML Block

```
<Focus version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <FocusStyle/>  <!-- req, xs:string, "AUTO, MANUAL, SEMIAUTOMATIC" -->
  <FocusLimited/>  <!-- req, xs:string, "1cm, 10cm, 30cm, 1m, 1.5m, 3m, 6m,INFINITE"
-->
  <FocusValue/>  <!-- optdep,depends on <FocusStyle>, xs:integer-->
  <focusSpeed>  <!-- opt, xs:integer, -100..100 --> </focusSpeed>
</Focus>
```

8.14.6 /Image/channels/<ID>/LensInitialization

/Image/channels/<ID>/ LensInitialization		General Resource	v1.0
GET		Viewer	
Description	It is used to get the initizlization status of the lens of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	LensInitialization		
PUT		Operator	
Description	It is used to update focus parameters of a specified image channel.		
Query	None		
Inbound Data	LensInitialization		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

LensInitialization XML Block

```
<LensInitialization version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>          <!-- req, xs:boolean -->
</LensInitialization>
```

8.14.7 /Image/channels/<ID>/ImageFlip

/Image/channels/<ID>/ImageFlip		General Resource	v1.0
GET		Viewer	
Description	It is used to get the mirror status of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	ImageFlip		
PUT		Operator	
Description	It is used to update mirror status of a specified image channel.		
Query	None		
Inbound Data	ImageFlip		
Success Return	ResponseStaus ResponseStatus		
Notes:			
ImageFlipStyle is enabled only when enabled value is true.			

ImageFlip XML Block

```
<ImageFlip version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>          <!--req, xs:boolean -->
  <ImageFlipStyle/>   <!--opt, xs:string, "LEFTRIGHT, UPDOWN, CENTER" -->
</ImageFlip>
```

8.14.8 /Image/channels/<ID>/ImageFreeze

/Image/channels/<ID>/ImageFreeze		General Resource v1.0
GET		Viewer
Description	It is used to get ImageFreeze status of a specified Image channel.	
Query	None	
Inbound Data	None	
Success Return	ImageFreeze	
PUT		Operator
Description	It is used to update ImageFreeze status of a specified image channel.	
Query	None	
Inbound Data	ImageFreeze	
Success Return	ResponseStaus ResponseStatus	
Notes:		

ImageFreeze XML Block

```
<ImageFreeze version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>          <!-- req, xs:boolean -->
</ImageFreeze>
```

8.14.9 /Image/channels/<ID>/proportionalpan

/Image/channels/<ID>/proportionalpan		General Resource v1.0
GET		Viewer
Description	It is used to get proportional pan status of a specified image channel.	
Query	None	
Inbound Data	None	
Success Return	proportionalpan	
PUT		Operator
Description	It is used to update proportional pan status of a specified image channel.	
Query	None	
Inbound Data	proportionalpan	
Success Return	ResponseStaus ResponseStatus	
Notes:		

proportionalpan XML Block

```
<proportionalpan version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/> <!--req, xs:boolean -->
</proportionalpan >
```

8.14.10 /Image/channels/<ID>/WDRExt

/Image/channels/<ID>/WDRExt		General Resource v1.5.9
GET		Viewer
Description	It is used to get the value of wide dynamic range for a specified Image channel.	
Query	None	
Inbound Data	None	
Success Return	WDRExt	
PUT		Operator
Description	It is used to configure the value of wide dynamic range for a specified Image channel.	

Query	None
Inbound Data	WDRExt
Success Return	hik:ResponseStaus ResponseStatus
Notes: <WDRLevelExt> is optional; some cameras may use more than one level to control WDR working. <mode> value can be “open”, “close” or “auto” , some cameras may not surpport the “auto” mode . If a camera works in auto mode, WDR would automatically open or close according to scene.	

WDRExt XML Block

```
<WDRExt version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <mode>      <!-- req, xs:string,"open,close,auto"--> </mode>
  <WDRLevel><!--opt,xs:integer,"0--100 "--> </WDRLevel>
  <WDRContrastLevel> <!--opt, xs:integer, "0--100" --> </WDRContrastLevel>
  <WDRLevelExt> <!--opt-->
    <Level2> <!--opt,xs:integer,"0--100 "--> </Level2>
  </WDRLevelExt>
</WDRExt >
```

8.14.11 /Image/channels/<ID>/BLC

/Image/channels/<ID>/BLC		General Resource	v1.0
GET		Viewer	
Description	It is used to get the configuration of backlight compensation for a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	BLC		
PUT		Operator	
Description	It is used to configure the configuration of backlight compensation for a specified image channel.		
Query	None		
Inbound Data	BLC		
Success Return	ResponseStaus ResponseStatus		
Notes:			

BLC XML Block

```
<BLC version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>    <!-- req, xs:boolean -->
  <BLCMode/>    <!--opt, xs:string, "UP, DOWN, LEFT, RIGHT, CENTER,
MULTI-AREA,Region" -->
  <BLCRegionList><!--dep-->
    <BLCRegion>
      <id> <!--req,integer--></id>
      <RegionCoordinatesList/>
    </BLCRegion>
  <BLCRegionList>
</BLC>
```

8.14.12 /Image/channels/<ID>/Imageenhancement

/Image/channels/<ID>/Imageenhancement		General Resource	v1.0
GET		Viewer	
Description	It is used to get the ImageEnhancement's configuration of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	ImageEnhancement		
PUT		Operator	
Description	It is used to configure the ImageEnhancement's configuration of a specified image channel.		
Query	None		
Inbound Data	ImageEnhancement		
Success Return	ResponseStaus ResponseStatus		
Notes:			

Imageenhancement XML Block

```
<ImageEnhancement version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/> <!-- req, xs:boolean -->
  <ImageEnhancementLevel> <!--opt, xs:integer -->
</ImageEnhancement>
```

8.14.13 /Image/channels/<ID>/IrcutFilterExt

/Image/channels/<ID>/IrcutFilterExt		General Resource	v1.5.9
GET		Viewer	

Description	It is used to get the IrcutFilter's configuration of a specified image channel.
Query	None
Inbound Data	None
Success Return	IrcutFilterExt
PUT Operator	
Description	It is used to configure the IrcutFilter's configuration of a specified image channel.
Query	None
Inbound Data	IrcutFilterExt
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

IrcutFilter XML Block

```

<IrcutFilterExt version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IrcutFilterType>
    <!-- opt, xs:string, " auto, day, night,schedule,eventTrigger"-->
  </IrcutFilterType>
  <dayToNightFilterLevel><!--opt, xs:string, "low, normal, high" --></dayToNightFilterLevel>
  <dayToNightFilterTime> <!--opt xs:integer --> </dayToNightFilterTime>
  <nightToDayFilterLevel><!--opt,xs:string, "low, normal, high" --></nightToDayFilterLevel>
  <nightToDayFilterTime> <!--opt xs:integer --></nightToDayFilterTime>
  <Schedule> <!--dep-->
    <scheduleType><!--req,xs:string,"day,night"></scheduleType>
    <TimeRange> <!-- req -->
      <beginTime> <!-- req, xs:time, ISO8601 time --> </beginTime>
      <endTime> <!-- req, xs:time, ISO8601 time --> </endTime>
    </TimeRange>
  </Schedule>
  <EventTrigger> <!--dep-->
    <eventType><!--req,xs:string,"IO,VMD"></eventType>
    <IrcutFilterAction> <!--req,xs:string,"day,night"> </ IrcutFilterAction >
  </EventTrigger>
</IrcutFilterExt>

```

8.14.14 /Image/channels/<ID>/NoiseReduceExt

/Image/channels/<ID>/NoiseReduceExt General Resource v1.5.9	
GET Viewer	
Description	It is used to get 3D noise-reduce parameters of a specified Image

	channel.
Query	None
Inbound Data	None
Success Return	NoiseReduceExt
PUT Operator	
Description	It is used to configure 3D noise-reduce parameter of a specified Image channel.
Query	None
Inbound Data	NoiseReduceExt
Success Return	hik:ResponseStatus ResponseStatus
Notes: 3D noise-reduce method is related to 2D noise reduce. 2D noise-reduce method is a noise-reduce method that try to reduce the noise in the frame. 3D noise reduce method can reduce noise in the frame and the noise between every adjacent two frames. 3D noise-reduce depend on FrameNoiseReduceLevel and InterFrameNoiseReduceLevel, FrameNoiseReduceLevel affects noise-reduce between frames, InterFrameNoiseReduceLevel affects noise-reduce in the frame. If the GeneralMode was chosen, the generalLevel will be used, then the FrameNoiseReduceLevel and InterFrameNoiseReduceLevel would be set to the same value as generalLevel.	

NoiseReduceExt XML Block

```

<NoiseReduceExt version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <mode><!--req,xs:string,"close, general, advanced"--></mode>
  <GeneralMode> <!--dep,depends on <mode> -->
    <generalLevel><!--req,xs:integer"0-100"--></generalLevel>
  </GeneralMode>
  <AdvancedMode>
    <FrameNoiseReduceLevel><!--req,xs:integer"0-100"--></FrameNoiseReduceLevel>
    <InterFrameNoiseReduceLevel><!--req,xs:integer"0-100"--></InterFrameNoiseReduceLevel>
  </AdvancedMode>
</NoiseReduceExt>

```

8.14.15 /Image/channels/<ID>/DSS

/Image/channels/<ID>/DSS	General Resource v1.0
GET	Viewer

Description	It is used to get the the configuration of digital slow shutter for a specified Image channel.
Query	None
Inbound Data	None
Success Return	DSS
PUT Operator	
Description	It is used to configure the configuration of digital slow shutter for a specified Image channel.
Query	None
Inbound Data	DSS
Success Return	ResponseStaus ResponseStatus
Notes: DSSLevel is only enabled when enabled value is true.	

DSS XML Block

```
<DSS version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>          <!-- req, xs:boolean -->
  <DSSLevel/>  <!--opt, xs:string, "low, normal, high" -->
</DSS>
```

8.14.16 /Image/channels/<ID>/WhiteBlance

/Image/channels/<ID>/WhiteBlance		General Resource v1.0
GET		Viewer
Description	It is used to get the WhiteBlance value of a specified ilmage channel.	
Query	None	
Inbound Data	None	
Success Return	WhiteBlance	
PUT		Operator
Description	It is used to configure the WhiteBlance value of a specified ilmage channel.	
Query	None	
Inbound Data	WhiteBlance	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: WhiteBlanceRed and WhiteBlanceBlue's PUT operator is enabled only when WhiteBlanceStyle's value is manual.		

WhiteBlance XML Block

```
<WhiteBlance version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <WhiteBlanceStyle/> <!-- req, xs:string, "auto, manual, indoor, outdoor, autotrace, onece,
    sodiumlight, mercurylight" -->
  <WhiteBlanceRed/> <!--dep, depends on <WhiteBlanceStyle>,xs:integer,"0--100" -->
  <WhiteBlanceBlue/> <!--dep, depends on <WhiteBlanceStyle>,xs:integer,"0--100" -->
</WhiteBlance>
```

8.14.17 /Image/channels/<ID>/Exposure

/Image/channels/<ID>/Exposure		General Resource	v1.0
GET		Viewer	
Description	It is used to get the exposure mode of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	Exposure		
PUT		Operator	
Description	It is used to configure the exposure mode of a specified image channel.		
Query	None		
Inbound Data	Exposure		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

hik:Exposure XML Block

```
<Exposure version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ExposureType/> <!--req, xs:string, "auto, IrisFirst, ShutterFirst, gainFirst, manual" -->
  <OverexposeSuppress> <!--opt-->
    <enabled> <!--req, xs:boolean --> </enabled>
  <OverexposeSuppress>
</Exposure>
```

8.14.18 /Image/channels/<ID>/Sharpness

/Image/channels/<ID>/Sharpness		General Resource	v1.0
GET		Viewer	
Description	It is used to get the sharpness's value of a specified image channel.		
Query	None		
Inbound Data	None		

Success Return	Sharpness
PUT	
Operator	
Description	It is used to configure the sharpness's value of a specified image channel.
Query	None
Inbound Data	Sharpness
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

Sharpness XML Block

```
<Sharpness version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <SharpnessLevel/>  <!--req, xs:integer,"0--100" -->
  <SharpnessMode><!--opt, xs:string,"manual,auto" --></ SharpnessMode >
</Sharpness>
```

8.14.19 /Image/channels/<ID>/Iris

/Image/channels/<ID>/Iris		General Resource	v1.0
GET		Viewer	
Description	It is used to get the iris's value of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	Iris		
PUT		Operator	
Description	It is used to configure the iris's value of a specified image channel.		
Query	None		
Inbound Data	Iris		
Success Return	hik:ResponseStaus ResponseStatus		
Notes: Iris's PUT operate is enabled only when <ExposureType> is IrisFirst irisSpeed: negative numbers close iris, positive numbers open iris. Numerical value is a percentage of the maximum iris speed of the lens module.			

hik:IrisValue XML Block

```
<Iris version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IrisLevel/>
    <!--dep, depends on <ExposureType>, xs:string, "f1.4, f1.6, f2.0, f2.4, f2.8, f3.4, f4.0,
      f4.8, f5.6, f6.8, f8.0, f9.6, f11, f14, f16, f19, f22,close" -->
  <irisSpeed>  <!-- opt, xs:integer, -100..100 -->  </irisSpeed>
</Iris>
```

8.14.20 /Image/channels/<ID>/Shutter

/Image/channels/<ID>/Shutter		General Resource	v1.0
GET		Viewer	
Description	It is used to get the Shutter value of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	Shutter		
PUT		Operator	
Description	It is used to configure the Shutter value of a specified image channel.		
Query	None		
Inbound Data	Shutter		
Success Return	hik:ResponseStaus ResponseStatus		
Notes: Shutter's PUT operate is enabled only when <ExposureType> is ShutterFirst			

hik:ShutterValue XML Block

```
<Shutter version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ShutterLevel/>
  <!--dep,depends on <ExposureType>, xs:string, "1/1, 1/2, 1/3, 1/6, 1/12, 1/25, 1/50,
    1/75, 1/100, 1/120, 1/150, 1/215, 1/300, 1/425, 1/600, 1/1000, 1/1250, 1/1750,
    1/2500, 1/3500, 1/6000, 1/10000" -->
</Shutter>
```

8.14.21 /Image/channeles/<ID>/Gain

/Image/channels/<ID>/Gain		General Resource	v1.0
GET		Viewer	
Description	It is used to get the gain configuration of a specified Image channel.		
Query	None		
Inbound Data	None		
Success Return	Gain		
PUT		Operator	
Description	It is used to configure the gain configuration of a specified Image channel.		
Query	None		
Inbound Data	Gain		
Success Return	hik:ResponseStaus ResponseStatus		
Notes: Gain’s PUT operate is enabled only when <ExposureType> is gainFirst.			

hik:gain XML Block

```
<Gain version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <GainLevel/> <!--dep,depends on <ExposureType>, xs:integer,"0--100" -- -->
  <GainWindow><!-- opt -->
  <RegionCoordinatesList> <!-- opt -->
  <RegionCoordinates><!-- opt -->
  <positionX><!-- req, xs:integer;coordinate --></positionX>
  <positionY><!-- req, xs:integer;coordinate --></positionY>
  </RegionCoordinates>
  </RegionCoordinatesList>
  </GainWindow>
</Gain>
```

8.14.22 /Image/channels/<ID>/GamaCorrection

/Image/channels/<ID>/gamaCorrection		General Resource	v1.0
GET		Viewer	
Description	It is used to get the gama correction of a specified Image channel.		
Query	None		
Inbound Data	None		
Success Return	gammaCorrection		
PUT		Operator	
Description	It is used to configure the gama correction of a specified Image channel.		
Query	None		
Inbound Data	gammaCorrection		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

hik:gammaCorrection XML Block

```
<gammaCorrection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <gammaCorrectionEnabled> <!-- opt, xs:boolean --> </gammaCorrectionEnabled>
  <gammaCorrectionLevel> <!-- opt, xs:integer, 0--100 --> </gammaCorrectionLevel>
</gammaCorrection>
```

8.14.23 /Image/channels/<ID>/powerLineFrequency

/Image/channels/<ID>/powerLineFrequency	General Resource	v1.0
-----------------------------------------	------------------	------

GET		Viewer
Description	It is used to get the powerLineFrequency value of a specified Image channel.	
Query	None	
Inbound Data	None	
Success Return	powerLineFrequency	
PUT		Operator
Description	It is used to configure the powerLineFrequency value of a specified Image channel.	
Query	None	
Inbound Data	powerLineFrequency	
Success Return	hik:ResponseStaus ResponseStatus	
Notes: Configure the powerlineFrequency requires to reboot the camera.		

hik:powerlineFrequency XML Block

```
<powerLineFrequency version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <powerLineFrequencyMode> <!-- opt, xs:string "50hz, 60hz" -->
</powerLineFrequencyMode>
</powerLineFrequency >
```

8.14.24 /Image/channels/<ID>/Color

/Image/channels/<ID>/Color		General Resource	v1.0
GET		Viewer	
Description	It is used to get the color's value of a specified Image channel.		
Query	None		
Inbound Data	None		
Success Return	Color		
PUT		Operator	
Description	It is used to configure the color's value of a specified Image channel.		
Query	None		
Inbound Data	Color		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

color XML Block

```
<Color version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <brightnessLevel>      <!-- opt, xs:integer, 0--100 -->      </brightnessLevel>
  <contrastLevel>        <!-- opt, xs:integer, 0--100 -->      </contrastLevel>
  <saturationLevel>      <!-- opt, xs:integer, 0--100 -->      </saturationLevel>
  <hueLevel><!-- opt, xs:integer, 0--100 -->      </ hueLevel >
  <grayScale>
    <grayScaleMode> <!-- opt, xs:string, "indoor,outdoor"--><grayScaleMode>
  <grayScale>
</Color>
```

8.14.25 /Image/channels/<ID>/Scene

/Image/channels/<ID>/Scene		General Resource	v1.0
GET		Viewer	
Description	It is used to get sene mode of a camera.		
Query	None		
Inbound Data	None		
Success Return	Scene		
PUT		Operator	
Description	It is used to set sene mode of a camera.		
Query	None		
Inbound Data	Scene		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

Scene XML Block

```
<Scene>
  <mode><!--req,xs:string,"indoor, outdoor, default,dimlight"--></mode>
</Scene>
```

8.14.26 /Image/channels/<ID>/EPTZ

/Image/channels/<ID>/EPTZ		General Resource	v1.0
GET		Viewer	
Description	It is used to get electronic PTZ enabled status.		
Query	None		
Inbound Data	None		

Success Return	EPTZ
PUT	Operator
Description	It is used to get electronic PTZ enabled status.
Query	None
Inbound Data	EPTZ
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

EPTZ XML Block

```
< EPTZ>
  <enabled><!--req,xs:boolean,"true, false"--></enabled >
< /EPTZ>
```

8.14.27 /Image/channels/<ID>/PTZ

/Image/channels/<ID>/PTZ	General Resource v1.0
GET	Viewer
Description	It is used to get PTZ status. if a camera support PTZ, enabled tag value is true , otherwise is false
Query	None
Inbound Data	None
Success Return	PTZ

PTZ XML Block

```
< PTZ>
  <enabled><!--ro,xs:boolean,"true, false"--></enabled >
< /PTZ >
```

8.14.28 /Image/channels/<ID>/EIS

/Image/channels/<ID>/EIS	General Resource v1.0
GET	Viewer
Description	It is used to get the electronic-image-stabilizer configuration of a specified image channel.
Query	None
Inbound Data	None
Success Return	EIS

PUT		Operator
Description	It is used to set the the electronic-image-stabilizer configuration of a specified image channel.	
Query	None	
Inbound Data	EIS	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

EIS XML Block

```
<EIS version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <EISLevel> <!-- opt, xs:integer,"0--100" --> </EISLevel>
</EIS>
```

8.14.29 /Image/channels/<ID>/HLC

/Image/channels/<ID>/HLC		General Resource v1.0
GET		Viewer
Description	It is used to get the high-light-compensation configuration of a specified image channel.	
Query	None	
Inbound Data	None	
Success Return	HLC	
PUT		Operator
Description	It is used to set the high-light-compensation configuration of a specified image channe.	
Query	None	
Inbound Data	HLC	
Success Return	hik:ResponseStaus ResponseStatus	
Notes:		

HLC XML Block

```
<HLC version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <HLCLevel> <!-- opt, xs:integer, 0--100 --> </HLCLevel>
</HLC>
```

8.14.30 /Image/channels/<ID>/ChromaSuppress

/Image/channels/<ID>/ChromaSuppress		General Resource	v1.0
GET		Viewer	
Description	It is used to get the chroma-suppress configuration of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	ChromaSuppress		
PUT		Operator	
Description	It is used to set the chroma-suppress configuration of a specified image channel.		
Query	None		
Inbound Data	ChromaSuppress		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

ChromaSuppress XML Block

```
<ChromaSuppress version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <ChromaSuppressLevel> <!-- opt, xs:integer, 0--100 --> </ChromaSuppressLevel>
</ChromaSuppress>
```

8.14.31 /Image/channels/<ID>/ZoomLimit

/Image/channels/<ID>/ZoomLimit		General Resource	v1.0
GET		Viewer	
Description	It is used to get the zoomlimitconfiguration of a specified Image channel.		
Query	None		
Inbound Data	None		
Success Return	ZoomLimit		
PUT		Operator	
Description	It is used to set the zoomlimit value of the camera		
Query	None		
Inbound Data	ZoomLimit		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

ZoomLimit XML Block

```
<ZoomLimit version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ZoomLimitRatio> <!--opt xs:integer --> </ZoomLimitRatio>
</ZoomLimit >
```

8.14.32 /Image/channels/<ID>/ExpComp

/Image/channels/<ID>/ExpComp		General Resource	v1.0
GET		Viewer	
Description	It is used to get the value of exposure compensation for a specified Image channel.		
Query	None		
Inbound Data	None		
Success Return	ExpComp		
PUT		Operator	
Description	It is used to configure the value of exposure compensation for a specified Image channel.		
Query	None		
Inbound Data	ExpComp		
Success Return	hik:ResponseStaus ResponseStatus		
Notes:			

ExpComp XML Block

```
<ExpComp version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/> <!--req, xs:boolean -->
  <ExpCompLevel/> <!--opt, xs:integer, "0-100" -->
</ExpComp>
```

8.14.33 /Image/channels/<ID>/IrLight

/Image/channels/<ID>/IrLight		General Resource v1.0
GET		Viewer
Description	It is used to get the IR Light configuration for a specified Image channel.	
Query	None	
Inbound Data	None	

Success Return	IrLight
PUT Operator	
Description	It is used to configure IR Light for a specified Image channel.
Query	None
Inbound Data	IrLight
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

IrLight XML Block

```
<IrLight version="1.5.9" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <mode>      <!--req, xs:string,"auto,manual" --> </mode>
  <brightnessLevel>  <!--dep, xs:integer, "0-100" --> </brightnessLevel>
  <sensitivityLevel> <!--dep, xs:integer, "0-100" --><sensitivityLevel>
</IrLight >
```

8.14.34 /Image/channels/<ID>/WDR(1.5.8 old version)

/Image/channels/<ID>/WDR General Resource v1.0	
GET Viewer	
Description	It is used to get the value of wide dynamic range for a specified Image channel.
Query	None
Inbound Data	None
Success Return	WDR
PUT Operator	
Description	It is used to configure the value of wide dynamic range for a specified Image channel.
Query	None
Inbound Data	WDR
Success Return	ResponseStaus ResponseStatus
Notes: The range of WDRLevel's value is needed according to the capbilites of devices.	

WDR XML Block

```
<WDR version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>      <!-- req, xs:boolean -->
  <WDRLevel/><!--opt,xs:string,"0,1,2...100,B0,B1,B2...B100"-->
  <WDRContrastLevel/>  <!--opt, xs:integer, "0--100" -->
</WDR>
```

8.14.35 /Image/channels/<ID>/NoiseReduce(1.5.8 old version)

/Image/channels/<ID>/NoiseReduce		General Resource	v1.0
GET		Viewer	
Description	It is used to get the NoiseReduce's value of a specified image channel.		
Query	None		
Inbound Data	None		
Success Return	NoiseReduce		
PUT		Operator	
Description	It is used to configure the NoiseReduce's value of a specified image channel.		
Query	None		
Inbound Data	NoiseReduce		
Success Return	ResponseStaus ResponseStatus		
Notes:			

NoiseReduce XML Block

```
<NoiseReduce version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled/>          <!-- req, xs:boolean -->
  <NoiseReduceLevel> <!--opt, xs:string, "low, normal, high" -->
</NoiseReduce>
```

8.14.36 /Image/channels/<ID>/IrcutFilter(1.5.8 old version)

/Image/channels/<ID>/IrcutFilter		General Resource v1.0
GET		Viewer
Description	It is used to get the IrcutFilter's configuration of a specified image channel.	
Query	None	
Inbound Data	None	
Success Return	IrcutFilter	
PUT		Operator
Description	It is used to configure the IrcutFilter's configuration of a specified image channel.	

Query	None
Inbound Data	IrcutFilter
Success Return	ResponseStaus ResponseStatus
Notes:	

IrcutFilter XML Block

```
<IrcutFilter version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <IrcutFilterType/>    <!-- opt, xs:string, " auto, day, night,"-->
  <IrcutFilterLevel/>    <!--opt, xs:string, "low, normal, high" -->
  <IrcutFilterTime/>    <!--opt xs:integer -->
</IrcutFilter>
```

8.15 /Record

/Record	Service v1.0
Notes: service of Recording	

8.15.1 /Record/Schedule

/Record/schedule	
GET	
	Viewer
Description	It is used to get recording time range.
Query	None
Inbound Data	None
Success Return	RecordSchedule
PUT	
	Operator
Description	It is used to update recording time range.
Query	None
Inbound Data	RecordSchedule
Success Return	hik:ResponseStaus ResponseStatus
Notes:	

RecordSchedule XML Block

```
<RecordSchedule version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enalbled><!-- req, xs:boolean --> <enalbled/>
  <RecordDelayTime><!-- req, xs:integer --></ RecordDelayTime>
  <PreRecordTime><!-- req, xs:integer --></PreRecordTime>
  <TimeBlockList> <!-- req -->
```

```

<TimeBlock>
  <recordType> <!-- req, xs:string, "Alarm, Motion, Timing, ..." --> </recordType>
  <dayOfWeek>
    <!-- opt, xs:integer, ISO8601 weekday number, 1=Monday, ... -->
  </dayOfWeek>
  <TimeRange> <!-- req -->
    <beginTime> <!-- req, xs:time, ISO8601 time --> </beginTime>
    <endTime> <!-- req, xs:time, ISO8601 time --> </endTime>
  </TimeRange>
</TimeBlock>
</TimeBlockList>
</RecordSchedule>

```

8.16 Smart

8.16.1 /Smart/Capabilities

/Smart/capabilities		General Resource	v2.0
GET			
Description	It is used to get Smart capability.		
Query	None		
Inbound Data	None		
Success Return	<SmartCap>		
Notes:			

SmartCap XML Block

```

<SmartCap version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <isSupportROI> <!-- opt, xs:boolean --> </isSupportROI>
  <isSupportFaceDetect> <!-- opt, xs:boolean --> </isSupportFaceDetect>
  <isSupportIntelliTrace> <!-- opt, xs:boolean --> </isSupportIntelliTrace>
  <isSupportFieldDetection> <!-- opt, xs:boolean --> </isSupportFieldDetection>
  <isSupportDefocusDetection> <!-- opt, xs:boolean --> </isSupportDefocusDetection>
  <isSupportAudioDetection> <!-- opt, xs:boolean --> </isSupportAudioDetection>
  <isSupportSceneChangeDetection> <!-- opt, xs:boolean -->
</isSupportSceneChangeDetection>
</SmartCap>

```


8.16.2 /Smart/ROI/channels/ID

/Smart/ROI/channels/ID		General Resource	v2.0
GET			
Description	Access and configure the ROI for a special channel.		
Query	None		
Inbound Data	None		
Success Return	ROI		
PUT			
Description	Access and configure the ROI for a special channel.		
Query	None		
Inbound Data	ROI		
Success Return	ResponseStatus		
DELETE			
Description	Access and configure the ROI for a special channel.		
Query	None		
Inbound Data	None		
Success Return	ResponseStatus		
Notes:			
normalizedScreenSize: the size of normalized screen			
ROIRegionList:the list of ROI region			
<ID> should be consistent with <ID> of streaming.			
<enabled/> <!-- req, xs:string --> if the value of this tag is “disable”, all of regions are invalid.			

ROI XML Block

```

<ROI version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id/> <!-- req, xs:string, id -->
  <enabled/> <!-- req, xs:string -->
  <normalizedScreenSize> <!--req-->
    <normalizedScreenWidth> <!-- req, xs:integer --></normalizedScreenWidth>
    <normalizedScreenHeight> <!-- req, xs:integer --></normalizedScreenHeight>
  </normalizedScreenSize>
  <ROIRegionList/> <!--dep-->
  <FaceTrace/> <!--dep-->
  <ObjectTrace/> <!--dep-->
</ROI>

```

8.16.3 /Smart/ROI/channels/<ID>/regions

/Smart/ROI/channels/ID/regions		General Resource	v1.0
GET			
Description	Access and configure the ROI regions for a special channel.		
Query	None		
Inbound Data	None		
Success Return	ROIRegionsList		
PUT			
Description	Access and configure the ROI regions for a special channel		
Query	None		
Inbound Data	ROIRegionsList		
Success Return	ResponseStatus		
Notes:			

ROIRegionsList XML Block

```
<ROIRegionsList version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <ROI/> <!-- opt -->
</ROIRegionsList>
```

8.16.4 /Smart/ROI/channels/<ID>/regions/<ID>

/Smart/ROI/channels/ID/regions/ID		General Resource	v1.0
GET			
Description	Access and configure one ROI region for a special channel.		
Query	None		
Inbound Data	None		
Success Return	ROIRegion		
PUT			
Description	Access and configure one ROI region for a special channel		
Query	None		
Inbound Data	ROIRegion		
Success Return	ResponseStatus		
DELETE			
Description	Access and configure one ROI region for a special channel		
Query	None		
Inbound Data	None		
Success Return	ResponseStatus		

Notes:

qualityLevel:quality level of a region
RegionCoordinatesList:coordinate of ROI

ROIRegion XML Block

```
<ROIRegion version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:integer--> </id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <name> <!-- opt, xs:string --> </name>
  <qualityLevelOfROI> <!-- req, xs:integer "1-6"--> </qualityLevelOfROI>
  <RegionCoordinatesList/>
</ROIRegion>
```

8.16.5 /Smart/ROI/channels/<ID>/facettrace

/Smart/ROI/channels/ID/facetrace		General Resource	v1.0
GET			
Description	Access and configure the ROI regions for a special channel.		
Query	None		
Inbound Data	None		
Success Return	FaceTrace		
PUT			
Description	Access and configure the ROI regions for a special channel		
Query	None		
Inbound Data	FaceTrace		
Success Return	ResponseStatus		
Notes:			

FaceTrace XML Block

```
<FaceTrace version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean --> </enabled>
  <name> <!-- opt, xs:string --> </name>
  <qualityLevelOfROI> <!-- req, xs:integer--> </qualityLevelOfROI>
</FaceTrace>
```

8.16.6 /Smart/ROI/channels/<ID>/objecttrace

/Smart/ROI/channels/ID/objecttrace		General Resource	v1.0
GET			
Description	Access and configure the ROI regions for a special channel.		
Query	None		
Inbound Data	None		
Success Return	ObjectTrace		
PUT			
Description	Access and configure the ROI regions for a special channel		
Query	None		
Inbound Data	ObjectTrace		
Success Return	ResponseStatus		
Notes:			

objecttrace XML Block

```
<ObjectTrace version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <enabled> <!-- req, xs:boolean -->    </enabled>
  <qualityLevelOfROI>    <!-- req, xs:integer--> </qualityLevelOfROI>
</ObjectTrace>
```

8.16.7 /Smart/FaceDetect/<ID>

/Smart/FaceDetect/ID		General Resource	v1.0
GET			
Description	Access and configure the FaceDetect.		
Query	None		
Inbound Data	None		
Success Return	FaceDetect		
PUT			
Description	Access and configure the FaceDetect.		
Query	None		
Inbound Data	FaceDetect		
Success Return	ResponseStatus		
Notes:			
<ID> stands for channel number			

FaceDetect XML Block

```

<FaceDetect version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id/> <!-- req, xs:string, id -->
  <enabled>          <!-- req, xs:boolean -->    </enabled>
  <minObjectSize>
    <!-- opt, xs:integer, min number of pixels per object -->
  </minObjectSize>
  <maxObjectSize>
    <!-- opt, xs:integer, max number of pixels per object -->
  </maxObjectSize>
  <ROI> <!--opt-->
    <minHorizontalResolution> <!-- req, xs:integer --> </minHorizontalResolution>
    <minVerticalResolution> <!-- req, xs:integer --> </minVerticalResolution>
  </ROI>
  <sensitivityLevel>    <!-- req -->
    <!-- req, xs:integer -->
  </sensitivityLevel>
  <detectionThreshold>    <!-- dep-->
    <!-- req, xs:integer-->
  </detectionThreshold>
  <highlightsenabled><!-- req, xs:boolean -->    </highlightsenabled>
</FaceDetect>

```

8.16.8 /Smart/IntelliTrace/<ID>

/Smart/IntelliTrace/ID		General Resource	v1.0
GET			
Description			
Query	None		
Inbound Data	None		
Success Return	IntelliTrace		
PUT			
Description			
Query	None		
Inbound Data	IntelliTrace		
Success Return	ResponseStatus		
Notes:			

IntelliTrace XML Block

```
<IntelliTrace version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:string; id --> <id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <tracktime> <!-- opt, xs:integer, 0--300--> </tracktime>
</IntelliTrace>
```

8.16.9 /Smart/IntelliTrace/<ID>/ZoomRatial

/Smart/IntelliTrace/ID/ZoomRatial		General Resource	v1.0
PUT			
Description			
Query	None		
Inbound Data	None		
Success Return	ResponseStatus		
Notes:			

8.16.10 /Smart/FieldDetection/<ID>

/Smart/FieldDetection/ID		General Resource	v1.0
GET			
Description	Field detection configuration for a video input channels.		
Query	None		
Inbound Data	None		
Success Return	FieldDetection		
PUT			
Description	Field detection configuration for a video input channels.		
Query	None		
Inbound Data	FieldDetection		
Success Return	ResponseStatus		
Notes:			

FieldDetection XML Block

```
<FieldDetection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:string --> </id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <startTriggerTime> <!-- req, xs:integer, milliseconds --> </startTriggerTime>
```

```

<endTriggerTime> <!-- req, xs:integer, milliseconds --> </endTriggerTime>
<normalizedScreenSize>
  <normalizedScreenWidth> <!-- req, xs:integer --> </normalizedScreenWidth>
  <normalizedScreenHeight> <!-- req, xs:integer --> </normalizedScreenHeight>
</normalizedScreenSize>
<minObjectSize>
  <!-- opt, xs:integer, min number of pixels per object -->
</minObjectSize>
<maxObjectSize>
  <!-- opt, xs:integer, max number of pixels per object -->
</maxObjectSize>
<FieldDetectionRegionList/>
</FieldDetection>

```

8.16.11 /Smart/FieldDetection/<ID>/regions

/Smart/FieldDetection/ID/regions		General Resource	v1.0
GET			
Description	Access the list of regions for Field detection on a particular video input channel.		
Query	None		
Inbound Data	None		
Success Return	FieldDetectionRegionList		
PUT			
Description	Access the list of regions for Field detection on a particular video input channel.		
Query	None		
Inbound Data	FieldDetectionRegionList		
Success Return	ResponseStatus		
POST			
Description	Access the list of regions for Field detection on a particular video input channel.		
Query	None		
Inbound Data	None		
Success Return	FieldDetectionRegion		
DETELE			
Description	Access the list of regions for Field detection on a particular video		

	input channel.
Query	None
Inbound Data	None
Success Return	ResponseStatus
Notes:	

FieldDetectionRegionsList XML Block

```
<FieldDetectionRegionList version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <FieldDetectionRegion/>
</FieldDetectionRegionList>
```

8.16.12 /Smart/FieldDetection/<ID>/regions/<ID>

/Smart/FieldDetection/ID/regions/ID		General Resource	v1.0
GET			
Description	Access the list of regions for Field detection.		
Query	None		
Inbound Data	None		
Success Return	FieldDetectionRegion		
PUT			
Description	Access the list of regions for Field detection.		
Query	None		
Inbound Data	FieldDetectionRegion		
Success Return	ResponseStatus		
DELETE			
Description	Access the list of regions for Field detection.		
Query	None		
Inbound Data	None		
Success Return	ResponseStatus		
Notes:			

FieldDetectionRegion XML Block

```
<FieldDetectionRegion version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:string -->          </id>
  <enabled>      <!-- req, xs:boolean -->          </enabled>
  <sensitivityLevel>
```



```

    <!--req, xs:integer-->
</sensitivityLevel>
<timeThreshold>
    <!--req, xs:integer -->
</timeThreshold>
<objectOccupation>
    <!--req, xs:integer-->
</objectOccupation>
<RegionCoordinatesList>
    <RegionCoordinates> <!-- req, -->
        <positionX> <!-- req, xs:integer;coordinate --> </positionX>
        <positionY> <!-- req, xs:integer;coordinate --> </positionY>
    </RegionCoordinates>
</RegionCoordinatesList>
</FieldDetectionRegion>

```

8.16.13 /Smart/DefocusDetection/<ID>

/Smart/DefocusDetection/ID		General Resource	v1.0
GET			
Description	Defocus detection configuration for a audio input channel.		
Query	None		
Inbound Data	None		
Success Return	DefocusDetection		
PUT			
Description	Defocus detection configuration for a audio input channel.		
Query	None		
Inbound Data	DefocusDetection		
Success Return	ResponseStatus		
Notes:			

DefocusDetection XML Block

```

<DefocusDetection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
    <id> <!-- req, xs:string --> </id>
    <enabled> <!-- req, xs:boolean --> </enabled>
</DefocusDetection>

```

8.16.14 /Smart/AudioDetection/channels/<ID>

/Smart/AudioDetection/channels/ID		General Resource	v1.0
GET			
Description	Audio detection configuration for a audio input channel.		
Query	None		
Inbound Data	None		
Success Return	AudioDetection		
PUT			
Description	Audio detection configuration for a audio input channel.		
Query	None		
Inbound Data	AudioDetection		
Success Return	ResponseStatus		
Notes:			

AudioDetection XML Block

```
<AudioDetection version="1.0" xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>  <!-- req, xs:string;id -->    </id>
  <audioInputException>
    <enabled>    <!-- req, xs:boolean -->    </enabled>
  </audioInputException>
  <soundIntensityMutation>
    <enabled>    <!-- req, xs:boolean -->    </enabled>
    <sensitivityLevel>
      <!--req, xs:integer-->
    </sensitivityLevel>
    <mutationThreshold>
      <!--req, xs:integer -->
    </mutationThreshold>
  </soundIntensityMutation>
</AudioDetection>
```

8.16.15 /Smart/AudioDetection/channels/<ID>/Status

/Smart/AudioDetection/channels/ID/status		General Resource	v1.0
GET			

Description	It is used to get audio strength.
Query	None
Inbound Data	None
Success Return	AudioStrengthStatus
Notes:	

AudioStrengthStatus XML Block

```
<AudioStrengthStatus version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id>          <!-- req, xs:string -->          </id>
  <audioStrength> <!--ro, req, xs:integer--> </audioStrength>
</AudioStrengthStatus>
```

8.16.16 /Smart/SceneChangeDetection/<ID>

/Smart/SceneChangeDetection/ID		General Resource	v1.0
GET			
Description	Scene change detection configuration for a video input channels.		
Query	None		
Inbound Data	None		
Success Return	SceneChangeDetection		
PUT			
Description	Scene change detection configuration for a video input channels.		
Query	None		
Inbound Data	SceneChangeDetection		
Success Return	ResponseStatus		
Notes:			

SceneChangeDetection XML Block

```
<SceneChangeDetection version="1.0"
xmlns="http://www.hikvision.com/ver10/XMLSchema">
  <id> <!-- req, xs:string --> </id>
  <enabled> <!-- req, xs:boolean --> </enabled>
  <sensitivityLevel> <!-- req, xs:integer --> </sensitivityLevel>
</SceneChangeDetection>
```

Annex A (normative):

XML Schema Definition

A.0 hik.xsd

The following XML Schema Document contains XML schema definitions for data structures in this specification.

```
<?xml version="1.0" encoding="UTF-8"?>
<xs:schema xmlns:hik="http://www.hikvision.com/ver10/XMLSchema"
  xmlns:xs="http://www.w3.org/2001/XMLSchema"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xmlns:xlink="http://www.w3.org/1999/xlink"
  targetNamespace="http://www.hikvision.com/ver10/XMLSchema"
  elementFormDefault="qualified">
  <xs:import namespace="http://www.w3.org/1999/xlink" schemaLocation="xlink.xsd"/>
  <xs:annotation>
    <xs:documentation>
      HIK Core XML Schema
    </xs:documentation>
  </xs:annotation>
  <!-- ===== -->
  <!--      Resource Types      -->
  <!-- ===== -->
  <xs:simpleType name="ResourceType">
    <xs:restriction base="xs:string">
      <xs:enumeration value="Special Resource" />
      <xs:enumeration value="Service" />
      <xs:enumeration value="General Resource" />
    </xs:restriction>
  </xs:simpleType>
  <!-- ===== -->
  <xs:complexType name="QueryParameter">
    <xs:sequence>
      <xs:element name="name" type="xs:string" />
      <xs:element name="type" type="xs:string" />
      <xs:element name="description" type="xs:string" minOccurs="0" maxOccurs="1" />
    </xs:sequence>
  </xs:complexType>
```

```

<!-- ===== -->
<xs:complexType name="QueryParameterList">
  <xs:sequence>
    <xs:element name="queryParameter" type="hik:QueryParameter" minOccurs="0"
      maxOccurs="unbounded" />
  </xs:sequence>
</xs:complexType>
<!-- ===== -->
<xs:complexType name="OperationParameter">
  <xs:sequence>
    <xs:element name="description" type="xs:string" />
    <xs:element name="queryParameterList" type="hik:QueryParameterList" />
    <xs:element name="inboundData" type="xs:string" />
    <xs:element name="successReturn" type="xs:string" />
  </xs:sequence>
</xs:complexType>
<!-- ===== -->
<xs:complexType name="ResourceDescription">
  <xs:sequence>
    <xs:element name="name" type="xs:string" />
    <xs:element name="version" type="xs:string" />
    <xs:element name="type" type="hik:ResourceType" />
    <xs:element name="get" type="hik:OperationParameter" minOccurs="0"
      maxOccurs="1" />
    <xs:element name="put" type="hik:OperationParameter" minOccurs="0"
      maxOccurs="1" />
    <xs:element name="post" type="hik:OperationParameter" minOccurs="0"
      maxOccurs="1" />
    <xs:element name="delete" type="hik:OperationParameter" minOccurs="0"
      maxOccurs="1" />
    <xs:element name="notes" type="xs:string" minOccurs="0"
      maxOccurs="1" />
  </xs:sequence>
  <xs:attribute name="version" type="xs:string" use="required" />
</xs:complexType>
<!-- ===== -->
<xs:complexType name="Resource">
  <xs:sequence>
    <xs:element name="name" type="xs:string" />
    <xs:element name="version" type="xs:string" />
    <xs:element name="type" type="hik:ResourceType" />
    <xs:element name="description" type="xs:string" minOccurs="0"
      maxOccurs="1" />
  </xs:sequence>

```

```

    <xs:element name="ResourceList" type="hik:ResourceList" minOccurs="0"
      maxOccurs="1" />
  </xs:sequence>
  <xs:attribute name="version" type="xs:string" use="required" />
<xs:complexType>
  <!-- ===== -->
  <xs:complexType name="ResourceList">
    <xs:sequence>
      <xs:element name="Resource" type="hik:Resource" minOccurs="0"
        maxOccurs="unbounded"/>
    </xs:sequence>
    <xs:attribute name="version" type="xs:string" use="required" />
  </xs:complexType>
  <!-- ===== -->
  <!-- ResponseStatus Types -->
  <!-- ===== -->
  <xs:simpleType name="StatusCode">
    <xs:restriction base="xs:integer">
      <xs:minInclusive value="1" />
      <xs:maxInclusive value="7" />
    </xs:restriction>
    <!-- 1-OK, 2-Device Busy, 3-Device Error, 4-Invalid Operation, 5-Invalid XML Format,
      6-Invalid XML Content, 7-Reboot Required -->
  </xs:simpleType>
  <!-- ===== -->
  <xs:simpleType name="ID">
    <xs:restriction base="xs:integer">
      <xs:minInclusive value="1" id="id.minInclusive" />
    </xs:restriction>
  </xs:simpleType>
  <!-- ===== -->
  <xs:complexType name="ResponseStatus">
    <xs:sequence>
      <xs:element name="requestURL" type="xs:anyURI" />
      <xs:element name="statusCode" type="hik:StatusCode" />
      <xs:element name="statusString" type="xs:string" />
      <xs:element name="id" type="hik:ID" minOccurs="0" maxOccurs="1" />
    </xs:sequence>
    <xs:attribute name="version" type="xs:string" use="required" />
  </xs:complexType>
</xs:schema>

```

Notes:

- For IP Camera, now only support one input channel. <id> associated with the input channel can only be 1.