MNEMONICS TABLE

Mnemonic	Description	Example
TIME	It adds time libraries in the code.	Just type TIME
HWD	It adds • board • digitalio libraries in the code.	Just type HWD
HID	It adds • usb_hid • Keycode • Keyboard • KeyboardLayoutUS libraries in the code.	Just type HID
MOUSE	It adds the Mouse library in the code.	Just type MOUSE
KYBD	It create objects for keycode and keyboard layout in the code.	Just type KYBD
MSE	It create objects for mouse in the code.	Just type MSE
PIN	It add pin declaration in the code.	Just type PIN
LED	It turns on/off the led in the code. Values are • ON • OFF	LED ON
WAIT	It add time in the code. Time is in milliseconds. 1000 ms = 1 second.	WAIT 1000
TYPE	It add text want to type in the code.	TYPE Hello World!

MOVE	It moves the mouse pointer according to the values. Values are • x-axis • y-axis • scroll Values may be • Positive • Negative • ZERO Values in sequence 1. x-axis 2. y-axis 3. scroll	MOVE 36 -78 0
CLICK	It clicks the mouse buttons. Values are • LEFT • MIDDLE • RIGHT	CLICK LEFT
PRESS	It press the mouse buttons and relaese immediately. Values are • LEFT • MIDDLE • RIGHT	PRESS RIGHT