

Patching in the Cabin

LIGHTING PATCH → With the installed rig in the Cabin

When in the cabin, we typically use the smartfade with a preloaded show installed into the memory of the console. If you have to repatch the fixtures for some reason in the cabin, here are the fixture information and addresses for each of the fixtures:

Fixture Type	Universe	Address
ColorBlast 12 TR	2	1-3
ColorBlast 12 TR	2	4-6
ColorBlast 12 TR	2	7-9
ColorBlast 12 TR	2	10-12
ColorBlast 12 TR	2	13-15
ColorBlast 12 TR	2	16-18
S4 LED Lustr+Direct StrFan	2	101-110
S4 LED Lustr+Direct StrFan	2	111-120
S4 LED Lustr+Direct StrFan	2	121-130
S4 LED Lustr+Direct StrFan	2	131-140
S4 LED Lustr+Direct StrFan	2	141-150
Rush Par 2 RGBW Zoom 9 Ch	2	21-29
Rush Par 2 RGBW Zoom 9 Ch	2	30-38
Rush Par 2 RGBW Zoom 9 Ch	2	39-47
Rush Par 2 RGBW Zoom 9 Ch	2	48-56
Rush Par 2 RGBW Zoom 9 Ch	2	57-65
Rush Par 2 RGBW Zoom 9 Ch	2	66-74
Rush Par 2 RGBW Zoom 9 Ch	2	75-83
Rush Par 2 RGBW Zoom 9 Ch	2	84-92

*When using lighting in the cabin, make sure the Crestron Panel Reads Live Look 1

How to Control LEDs

1. Go to Crestron and press the “all off” button
2. Go into the live looks and activate “Live Look 1”
3. No other lighting look will work!

Additional Lighting in the Cabin

Address	Unit Type
47	Chandalier & CFL Over Counter + Chandalier in Stairway
46	CFL Cans Back of Room
44	CFL Cans's Over Stage
45	CFL Cans's Over Balcony
43	Chandalier

How to Run DMX Cables

- Plug the U1 DMX into the house U1 DMX
- Plug the U2 DMX into the house U2 DMX
- To use the PDS-750-TRX
 - Below company switch
 - DMX cable from house output U2 (or U1) to PDS-750-TRX

How to Return House to Normal

1. Go to Crestron and press the “all off” button
Go into any light setting besides “Presentation” and “Live Look 1”

SmartFade Guide - Cabin

1. Power on SmartFade with the power button (top right)
2. Press the menu button (checkmark by the right LCD screen)
3. Use the right scroll wheel to scroll display to “Patch” and press enter
4. Scroll display to “Devices” and press enter
5. Use the right scroll wheel to scroll display to “Patch Wizard” and press enter
6. The left LCD screen will display the “make” option. Choose company of origin
 - a. ColorBlast is in the “Generic” category
7. The right LCD screen will display the fixtures of the companies “make”
 - a. Use right wheel to scroll to the correct fixture. Press enter.
8. On the left LCD screen are three options
 - a. “Device” is what button/fader you want to assign the device to
 - b. The [U1] is the indicator of the universe. Press the “more” key to switch to [U2]
 - c. “DMX” is the address of the fixture. Look at the address guide above
9. On the right LCD screen is the “count” option
 - a. The count is how many fixtures in a row that you want. If you have 6 fixtures in a row, the count will be 6
10. Press the “<<” key to exit all the way out of the menu
11. Select your device number
12. Press the “color” on the middle right of the board
 - a. Select to assign your color

SmartFade Troubleshoot Guide – Cabin

- Turn all room lights off
- Go to live look one
- Master is up
- Blackout key isn't on
- Universe 1 and Universe 2 are plugged in correctly
- Int Devices is selected
- Select Devices is selected
- Patch is correct