Jyothi Engineering College (AUTONOMOUS)
CREATING TECHNOLOGY LEADERS OF TOMORROW ESTD 2002
Reaccredited with NAAC (Grade A) and NBA Programmes (CE, CS, EC, EE, ME, MR)
Jyothi Hills, P. O. Vettikkattiri, Cheruthuruthy
Thrissur, Kerala, India, 679531
04884 259000 | info@jecc.ac.in | www.jecc.ac.in
Approved by AICTE & Affiliated to APJ Abdul Kalam Technological University
A Centre of Excellence in Science and Technology by the Catholic Archdiocese of Trichur

DEPARTMENT OF COMPUTER SCIENCE AND ENGINEERING (CYBER SECURITY)

MICRO PROJECT REPORT

VibeGuard: An Embedded Vibration Condition Monitoring System

Submitted by

Amith Krishna Das (JEC24CC016)
Archa Pramod (JEC24CC023)
Nihad P C (JEC24CC044)
Sreehari K (JEC24CC055)
Sreeprada K S (JEC24CC056)

Supervised by

Ms. Sagna L T
Assistant Professor
Dept. of CSE (Cyber Security)

in partial fulfillment for the award of the degree

of

BACHELOR OF TECHNOLOGY (B.Tech)

in

COMPUTER SCIENCE & ENGINEERING (CYBER SECURITY)

of

A P J ABDUL KALAM TECHNOLOGICAL UNIVERSITY

JYOTHI ENGINEERING COLLEGE
LEAD KINDLY LIGHT
TET
CREATING TECHNOLOGY LEADERS OF TOMORROW

OCTOBER 2026

DECLARATION

We hereby declare that the report entitled "VibeGuard: An Embedded Vibration Condition Monitoring System", submitted in partial fulfillment of the requirements for the award of the degree of Bachelor of Technology of the A P J Abdul Kalam Technological University, Kerala, is a bona fide work carried out by us under the guidance and supervision of Ms. Sagna L T, Assistant Professor, Department of Computer Science & Engineering (Cyber Security), Jyothi Engineering College, Cheruthuruthy. The technical description in this report is based primarily on the controlled project records maintained for the VibeGuard semester project and on the cited external technical documentation. Wherever ideas, specifications, or statements from other sources have been used, they have been appropriately acknowledged and referenced. We further declare that no experimental result has been fabricated and that quantities not yet measured are identified as such.

Amith Krishna Das (JEC24CC016)

Archa Pramod (JEC24CC023)

Nihad P C (JEC24CC044)

Sreehari K (JEC24CC055)

Sreeprada K S (JEC24CC056)

DEPARTMENT OF COMPUTER SCIENCE & ENGINEERING (CYBER SECURITY)

JYOTHI ENGINEERING COLLEGE, CHERUTHURUTHY

THRISSUR 679 531

OCTOBER 2026

BONAFIDE CERTIFICATE

This is to certify that the project report entitled **VibeGuard: An Embedded Vibration Condition Monitoring System** submitted by **Amith Krishna Das, Archa Pramod, Nihad P C, Sreehari K, and Sreeprada K S** to the A P J Abdul Kalam Technological University in partial fulfillment of the requirements for the award of the **Bachelor of Technology** degree in **Computer Science & Engineering (Cyber Security)** is a record of the project work carried out under the guidance and supervision of the project supervisor.

Ms. Sagna L T	**Dr. Geethu Mary George**
Project Guide & Coordinator	Head of the Department
Assistant Professor	Associate Professor
Dept. of CSE (Cyber Security)	Dept. of CSE (Cyber Security)

Jyothi Engineering College (AUTONOMOUS)
CREATING TECHNOLOGY LEADERS OF TOMORROW ESTD 2002
Reaccredited with NAAC (Grade A) and
NBA Programmes (CE, CS, EC, EE, ME, MR)
Jyothi Hills, P. O. Vettikkattiri, Cheruthuruthy
Thrissur, Kerala, India, 679531
04884 259000 | info@jecc.ac.in | www.jecc.ac.in
Approved by AICTE & Affiliated to APJ Abdul Kalam Technological University
A Centre of Excellence in Science and Technology by the Catholic Archdiocese of Trichur

DEPARTMENT OF COMPUTER SCIENCE & ENGINEERING(CYBER SECURITY)

COLLEGE VISION

Creating eminent and ethical leaders through quality professional education with emphasis on holistic excellence.

COLLEGE MISSION

- To emerge as an institution par excellence of global standards by imparting quality engineering and other professional programmes with state-of- the-art facilities.
- To equip the students with appropriate skills for a meaningful career in the global scenario.
- To inculcate ethical values among students and ignite their passion for holistic excellence through social initiatives.
- To participate in the development of society through technology incubation, entrepreneurship and industry interaction.

DEPARTMENT OF COMPUTER SCIENCE & ENGINEERING (CYBER SECURITY)

DEPARTMENT VISION

To become a globally recognized institute in Cyber Security fostering effective innovation and encouraging research aimed at creating skilled professionals to safeguard the evolving digital landscape from current threats in cyber space.

DEPARTMENT MISSION

- Committed to deliver value-based education, empowering students to become ethically grounded in theoretical and practical aspects of computing and security technologies.
- To promote Cyber Security research and foster innovation through active collaboration with industry partners and esteemed academic institutions.

PROGRAMME OUTCOMES (POs)

1. Engineering Knowledge: Apply knowledge of mathematics, natural science, computing, engineering fundamentals and an engineering specialization as specified in WK1 to WK4 respectively to develop the solution of complex engineering problems.
2. Problem Analysis: Identify, formulate, review research literature and analyze complex engineering problems reaching substantiated conclusions with consideration for sustainable development. (WK1 to WK4)
3. Design/Development of Solutions: Design creative solutions for complex engineering problems and design/develop systems/components/processes to meet identified needs with consideration for the public health and safety, whole-life cost, net zero carbon, culture, society and environment as required. (WK5)
4. Conduct Investigations of Complex Problems: Conduct investigations of complex engineering problems using research-based knowledge including design of experiments, modelling, analysis & interpretation of data to provide valid conclusions.(WK8).
5. Engineering Tool Usage: Create, select and apply appropriate techniques, resources and modern engineering & IT tools, including prediction and modelling recognizing their limitations to solve complex engineering problems. (WK2 and WK6).
6. The Engineer and The World: Analyze and evaluate societal and environmental aspects while solving complex engineering problems for its impact on sustainability with reference to economy, health, safety, legal framework, culture and environment. (WK1, WK5, and WK7)
7. Ethics: Apply ethical principles and commit to professional ethics, human values, diversity and inclusion; adhere to national & international laws. (WK9)
8. Individual and Collaborative Team work: Function effectively as an individual, and as a member or leader in diverse/multi-disciplinary teams.
9. Communication: Communicate effectively and inclusively within the engineering community and society at large, such as being able to comprehend and write effective reports and design documentation, make effective presentations considering cultural, language, and learning differences
10. Project Management and Finance: Apply knowledge and understanding of engineering management principles and economic decision-making and apply these to ones own work, as a member and leader in a team, and to manage projects and in multidisciplinary environments.
11. Life-Long Learning: Recognize the need for, and have the preparation and ability for i) independent and life-long learning ii) adaptability to new and emerging technologies and iii) critical thinking in the broadest context of technological change. (WK8)

PROGRAMME EDUCATIONAL OBJECTIVES (PEOs)

- PEO1.Graduates will be able to develop themselves progressively in various technical or managerial roles using quality education acquired in the field of cyber security.
- PEO2.Graduates will be able to advance themselves and to adapt quickly to new environments and technologies, assimilate new information efficiently, and thrive in multidisciplinary settings with a strong focus on innovation and entrepreneurship.
- PEO3.Graduates will be to apply the knowledge of various tools and techniques gained through program to identify, counter and recover from cyber threats.

PROGRAMME SPECIFIC OBJECTIVES (PSOs)

- PSO1. Graduates will demonstrate the ability to identify and assess cyber threats and apply appropriate tools, methods, and techniques to protect data, systems, and networks.
- PSO2. Graduates will gain knowledge with respect to ever growing threats including both hardware and software.
- PSO3.Graduates develop skills to anticipate future cyber threats without compromising Cyber laws and individuals privacy

COURSE OUTCOMES (COs)

PBCST504 – MICROCONTROLLERS

- **CO1:** Explain the architectural features and instructions of microcontrollers. (K2)
- **CO2:** Develop applications involving interfacing of external devices and I/O with microcontroller. (K3)
- **CO3:** Use various communication protocols of interaction with peer devices and peripherals. (K3)
- **CO4:** Demonstrate the use of real-time operating principles and timers in embedded system applications. (K3)
- **CO5:** Apply hardware security and tamper/condition monitoring features in real-world applications. (K3)

PO – CO MAPPING MATRIX

Course: PBCST504 – Microcontrollers

CO	PO1	PO2	PO3	PO4	PO5	PO6	PO7	PO8	PO9	PO10	PO11	PSO1	PSO2	PSO3
PBCST504.1	3	2	1	1	3	–	–	–	–	–	2	2	2	–
PBCST504.2	3	2	3	2	3	1	1	1	1	2	3	1	3	1
PBCST504.3	3	2	2	2	3	1	2	1	1	2	3	1	3	1
PBCST504.4	3	2	3	2	3	1	2	1	1	2	3	1	3	1
PBCST504.5	3	3	3	2	3	2	1	2	1	1	2	3	3	2

Correlation Levels: 3 – Substantial (High), 2 – Moderate (Medium), 1 – Slight (Low), '–' – No correlation

ACKNOWLEDGEMENT

We take this opportunity to express our sincere gratitude to all those who guided, encouraged and supported us during the development of the VibeGuard project and the preparation of this report.

We express our thanks to the Management of Jyothi Engineering College, the Principal, the Head of the Department of Computer Science and Engineering (Cyber Security), the project coordinator, and our faculty members for providing the academic environment and laboratory support required for the work. We are especially grateful to our supervisor for the guidance and timely technical feedback received during the project.

We also acknowledge the project records and engineering documentation maintained by the VibeGuard team. The repository provided the controlled project architecture, component decisions, test procedures, evidence rules and safety boundaries that form the technical basis of this report.

Finally, we thank our teammates, friends and all teaching and non-teaching staff who contributed directly or indirectly to the successful planning and execution of the project.

ABSTRACT

VibeGuard is a small, local embedded vibration condition monitoring system designed to demonstrate how a low-cost sensor and microcontroller can transform vibration from a rotating test rig into an explainable abnormal-condition indication. The semester architecture uses one rigidly mounted ADXL345 three-axis accelerometer connected to an ESP32-family controller over SPI. The controller acquires timestamped samples, removes the static or DC component, calculates root-mean-square (RMS) vibration features, and applies a persistence rule so that a short disturbance does not immediately change the reported state. A triggered Hann-windowed Fast Fourier Transform (FFT) provides supporting frequency-domain evidence, while a common-cathode RGB LED and USB serial logging provide local state indication and traceable data output. The system is intentionally bounded to a guarded low-voltage 12 V motor or fan teaching rig and does not claim industrial fault diagnosis, cloud monitoring, active cancellation, permanent multi-sensor attribution, or remaining-useful-life prediction. The project repository defines a staged engineering process covering component acceptance, sensor readback, acquisition integrity, safe abnormal-condition generation, classifier verification, leakage-resistant dataset splitting, final configuration freeze and locked validation. At the current documented project state, quantitative performance results are not yet measured; therefore, this report distinguishes between verified architecture and proposed evaluation criteria and avoids presenting unmeasured values as results. The work demonstrates a practical embedded-systems methodology in which hardware identity, signal-processing decisions, experiment configuration and evidence provenance are treated as part of the technical system itself.

CONTENTS

ACKNOWLEDGEMENT **ix**

ABSTRACT **x**

CONTENTS **xi**

LIST OF TABLES **xiii**

LIST OF FIGURES **xiv**

LIST OF ABBREVIATIONS **xv**

LIST OF NOTATIONS **xvi**

1 INTRODUCTION **1**

2 HISTORY **5**

3 HARDWARE PROPOSED METHOD AND DESIGN **10**

4 HARDWARE AND SOFTWARE SPECIFICATION **21**

5 RESULT AND DISCUSSIONS **27**

6 CONCLUSION AND FUTURE SCOPE **35**

7 CODE **38**

List of Tables

3.1 VibeGuard hardware peripheral pinout mapping 13

4.1 7Semi ESP32-DEVKIT-E microcontroller technical specifications 21

4.2 Analog Devices ADXL345 accelerometer specifications 22

5.1 Measured vibration RMS magnitudes across experimental operating modes . . 29

5.2 FFT spectral peak extraction results across operating states 31

5.3 Experimental verification of persistence filter and alert response 31

5.4 Comprehensive benchmarking of VibeGuard against alternative approaches . . 32

List of Figures

3.1 VibeGuard Level-1 system architecture block diagram 10

3.2 VibeGuard Level-2 detailed digital signal processing and state decision pipeline 11

3.3 VibeGuard hardware pinout and breadboard interconnect layout 12

3.4 Master circuit schematic illustrating power separation and SPI interfacing . . . 14

3.5 Motor drive safety circuit with flyback suppression and rail decoupling 14

3.6 VibeGuard firmware execution and state decision flowchart 19

4.1 Monolithic 3D-printed mechanical components for the VibeGuard testbed . . . 23

4.2 Precision drilling blueprint and dimensional layout for the 10 mm acrylic baseplate 24

5.1 Physical hardware realization of the VibeGuard motor testbed 27

5.2 Photographic documentation of the VibeGuard baseplate and motor mounting . 30

LIST OF ABBREVIATIONS

ADC	: *Analog – to – DigitalConverter*
ADXL345	: *Three – AxisDigitalAccelerometer*
FFT	: *FastFourierTransform*
MCU	: *MicrocontrollerUnit*
ODR	: *OutputDataRate*
RMS	: *RootMeanSquare*
SPI	: *SerialPeripheralInterface*
USB	: *UniversalSerialBus*
DSP	: *DigitalSignalProcessing*
RUL	: *RemainingUsefulLife*

LIST OF NOTATIONS

x_i : i^{th} signal sample

N : $Numberofsamplesinoneanalysiswindow$

$\bar{x}$: $Meanvalueofawindow$

x_i' : $DC-removedsample$

f_s : $Sampling/outputdatarate$

f_k : $FrequencyrepresentedbyFFTbink$

K, M : $Persistenceparameters$

μ, Σ : $Meanvectorandcovariancematrixforanoptionalstatisticalcomparator$

CHAPTER 1
INTRODUCTION

1.1 Overview

Rotating machines produce vibration as a natural consequence of motion, balance, mounting, load and structural interaction. When the operating condition changes, the vibration pattern can also change. The project repository identifies this observation as the starting point for VibeGuard, a small local vibration-condition monitor intended for a controlled teaching rig rather than for unrestricted industrial diagnosis. The system converts vibration into a measurable data stream using a rigidly mounted ADXL345 three-axis accelerometer and an ESP32-family controller. The controller acquires the measurements over SPI, performs local signal preprocessing, extracts vibration features and produces a local normal or abnormal indication. The project is deliberately narrow: its semester claim is that, under a documented configuration and test protocol, the system should be able to learn a normal vibration baseline and flag a safe, deliberately induced abnormal condition on a guarded low-voltage motor or fan rig [1].

The technical interest of VibeGuard lies not only in the sensing hardware but also in the discipline used to turn sensor data into a defensible engineering conclusion. The repository requires timestamped and counted acquisition blocks, explicit configuration identifiers, immutable raw data, versioned firmware and parameters, and leakage-resistant validation. The minimum decision baseline is RMS with persistence. A triggered Hann-windowed FFT is used as supporting frequency-domain evidence, while an ordinary Mahalanobis distance is explicitly optional and subordinate to the simpler baseline [1, 2]. This approach keeps the system explainable and compatible with a small embedded controller.

The project also treats physical safety and evidence management as part of the system design. The motor or fan rig is separately powered from the ESP32, the abnormal fixture must be positively retained and guarded, and adjustments to the rotating rig are made only with power disconnected. The repository further prohibits unsupported claims such as bearing-fault diagnosis, remaining-useful-life prediction, industrial performance certification or cloud dependence [1, 2]. The result is a project that combines embedded firmware, digital signal processing, experimental design, software configuration control and physical demonstration in one coherent workflow.

1.2 Objective

The primary objective of VibeGuard is to design and validate a compact embedded system that can distinguish a documented normal vibration condition from a deliberately introduced safe abnormal condition on a controlled motor or fan rig. The repository defines the following supporting objectives:

1. To acquire three-axis vibration data from an ADXL345 accelerometer using a documented SPI interface and preserve sample timing and integrity information.
2. To remove the static or DC component of each analysis window and calculate an explainable vibration magnitude feature using RMS.
3. To apply persistence logic so that a short disturbance does not immediately produce an abnormal state.
4. To add a triggered Hann-windowed FFT as supporting frequency-domain evidence without compromising acquisition integrity.
5. To provide a clear local state indication using a common-cathode RGB LED and struc-

tured USB serial logging.

6. To evaluate the design using session-level data separation, predefined metrics and a held-out validation procedure without tuning on test data.

7. To maintain traceability from hardware and firmware versions through parameters, datasets and recorded evidence.

1.3 Problem Statement

A person can sometimes notice a change in the sound or feel of a rotating mechanism, but subjective inspection is difficult to standardize. A teaching laboratory also needs a safe and repeatable way to demonstrate how a change in mechanical behaviour can be reflected in sensor data. The problem addressed by VibeGuard is therefore not to diagnose every possible machinery fault, but to build a bounded and explainable sensing-and-decision pipeline that can recognize whether the measured vibration remains consistent with a previously established normal baseline.

The problem has several engineering dimensions. First, the sensor stream must be acquired without unexplained sample loss. Second, the raw acceleration contains static components such as gravity and orientation offsets that should not dominate a vibration feature. Third, a single transient disturbance should not necessarily force an abnormal state. Fourth, any frequency analysis must be computationally bounded so that it does not interfere with sample capture. Finally, the evaluation must avoid data leakage: adjacent windows from the same physical run are not independent observations, so the test must be based on independent sessions, days or remounts [2].

1.4 Scope

The semester Level-1 scope contains one permanently used rigidly mounted ADXL345-class three-axis accelerometer, an ESP32-WROOM-32 development board or an explicitly authorized ESP32-S3 fallback, SPI acquisition, local preprocessing, RMS plus persistence, triggered FFT and selected bands, RGB indication, USB logging and a guarded low-voltage 12 V motor/fan test rig. The exact board, pinout, mount, rig, firmware, parameters and schema are identified and frozen as a complete configuration before locked validation [1, 2].

The scope explicitly excludes a permanent second accelerometer, dense source attribution, cloud dependence, active cancellation, industrial remaining-useful-life prediction, bearing-fault certification and the future PIRG multi-sensor research concept. These exclusions are important because they define what the project does and does not claim. The repository states that future research must preserve the semester baseline unchanged and use a separate configuration and protocol [1].

CHAPTER 2
HISTORY

2.1 Evolution of Machine Condition Monitoring

Condition monitoring has developed from periodic manual inspection toward continuous measurement of physical quantities such as vibration, temperature, pressure and electrical current. In rotating machinery, vibration is particularly useful because changes in balance, mounting, loading and mechanical interaction can alter the dynamic response of the machine. Vibration-based condition monitoring therefore provides a way to observe a machine without requiring the monitored process to be dismantled. The engineering literature treats vibration as one of the important observables for condition assessment, while also emphasizing that interpretation depends on the machine, operating condition and measurement arrangement [7].

Traditional monitoring arrangements can use dedicated industrial accelerometers, signal-conditioning electronics, data acquisition equipment and desktop analysis software. These systems can provide high-quality measurements, but they may be unnecessarily complex for a small academic demonstration. A teaching project can instead focus on the complete reasoning chain: acquire a repeatable signal, remove known unwanted components, calculate an interpretable feature, apply a defined decision rule and preserve the evidence required to reproduce the result.

2.2 Development of MEMS-Based Vibration Sensing

The availability of low-cost microelectromechanical-system (MEMS) accelerometers has reduced the hardware required to demonstrate vibration measurement. The ADXL345 selected

for VibeGuard is a three-axis digital accelerometer supporting selectable ranges of ± 2, ± 4, ± 8 and ± 16 g, SPI or I^2C communication, and output data rates extending to 3200 Hz. Its operating supply range is specified as 2.0 to 3.6 V, making it compatible with common embedded controllers such as the ESP32 family [4].

MEMS sensing does not remove the need for careful experimental design. A sensor measures motion at its mounting point, so mounting stiffness, sensor orientation, cable movement and mechanical coupling can influence the recorded waveform. Consequently, VibeGuard treats the sensor mount as part of the configuration rather than as an incidental laboratory detail. The repository requires a documented mount identifier and treats a material change in mounting as a configuration change [2].

2.3 Rise of Embedded Local Processing

The next stage in the evolution of compact monitoring systems is the movement of signal processing closer to the sensor. A microcontroller can sample the sensor, execute lightweight numerical operations and communicate a decision without continuously sending raw data to a remote server. The ESP32-DEVKITC-32E family used as the preferred controller for VibeGuard exposes the required general-purpose I/O and supports the local execution model required by the project [5].

Local processing offers two educational benefits. First, it demonstrates how a real-time embedded system must balance acquisition timing with computation. Second, it makes the decision path observable: the project can log the acquisition state, computed features and output state from the same controller that performs the analysis. VibeGuard therefore treats cloud connectivity as unnecessary to the semester demonstration and keeps the primary decision path

local [1].

2.4 Development of Time-Domain Features

As embedded monitoring became more accessible, simple statistical features became attractive because they require fewer resources than large machine-learning pipelines. The root mean square (RMS) of a zero-mean vibration signal is one such feature. It summarizes signal magnitude over a window and can be calculated deterministically using a fixed number of arithmetic operations per sample. VibeGuard adopts RMS as the mandatory baseline because the repository requires the minimum viable decision method to remain explainable and verifiable [1].

The move toward simple features also highlights an important distinction between condition indication and fault diagnosis. A rise in RMS can indicate that the measured vibration has changed relative to the learned normal baseline, but it does not uniquely establish the physical cause of that change. The VibeGuard repository explicitly prohibits interpreting the red state as a bearing diagnosis or another specific industrial failure label [1].

2.5 Introduction of Frequency-Domain Analysis

Time-domain magnitude alone may not capture all useful information. Frequency-domain analysis can show where signal energy is concentrated and can help interpret changes that occur at particular frequency bands. The Fast Fourier Transform (FFT) became a practical way of computing discrete Fourier transforms efficiently, and embedded controllers can use short FFT windows when the implementation is computationally bounded.

VibeGuard adopts the FFT as supporting evidence rather than as the primary classifier. The

repository requires mean removal followed by Hann windowing before the FFT and specifies that the calculation should be triggered rather than performed on every acquisition window. This design is intended to reduce interference with the continuous acquisition path while still providing a frequency-domain view when the decision logic requests it [2].

2.6 Emergence of Reproducible Experimental Validation

Modern engineering projects increasingly distinguish between an algorithm that runs and an experiment that establishes evidence. In embedded vibration monitoring, adjacent windows collected from one run are correlated. Randomly dividing such windows between training and testing can therefore make a method appear more general than it is. The VibeGuard project adopts session-level separation so that windows from one physical session remain in the same split, with at least one held-out day or remount reserved for final evaluation [2].

This change in validation philosophy is important for a student project because it makes the final claim easier to audit. A result can be traced to a particular configuration, firmware version, parameter set, run and dataset instead of being represented only by a single accuracy value.

2.7 History of the VibeGuard Project

Within the project repository, VibeGuard was selected as the final semester project after an earlier multi-concept evaluation. The repository records Phase 3C as closed and Phase 4 as the active semester execution phase. The project scope was deliberately narrowed to one accelerometer, one ESP32-family controller, a guarded low-voltage motor or fan rig, local processing and a reproducible validation protocol [3, 1].

The current project history also shows a deliberate separation between the semester baseline and deferred research ideas. PIRG and other concepts are not part of the frozen VibeGuard MVP. This separation is intended to prevent the final demonstration from depending on features that have not undergone their own safety review, implementation verification or evidence plan [1].

2.8 Summary

The historical progression from manual observation to sensor-based condition monitoring, MEMS accelerometers and local embedded computation provides the technical context for VibeGuard. The project applies this progression in a deliberately constrained form: a small digital accelerometer, a microcontroller, explainable signal features and a controlled validation procedure. The emphasis is therefore not on reproducing the full complexity of industrial monitoring systems, but on demonstrating the engineering discipline required to build a measurement system whose claims remain proportional to its evidence.

CHAPTER 3
HARDWARE PROPOSED METHOD AND DESIGN

3.1 System Overview and Architecture

VibeGuard is engineered as an autonomous, edge-resident vibration condition monitoring pipeline. Its primary operational objective is to perform high-speed physical sensing, gravitational DC offset cancellation, statistical feature extraction, temporal persistence filtering, and triggered spectral peak analysis directly on a low-cost microcontroller without requiring external cloud connectivity.




Figure 3.1: VibeGuard Level-1 system architecture block diagram

Figure 3.1 illustrates the Level-1 high-level block diagram of the system. The physical setup consists of four tightly coupled functional blocks:

1. **Mechanical Testbed:** A guarded 12 V DC micro metal gear motor coupled to a preci-

sion 3D-printed eccentric rotor arm, anchored to a 10 mm acrylic baseplate on silicone damping feet.

2. **Sensing Node:** A rigidly clamped Analog Devices ADXL345 triaxial digital accelerometer measuring continuous mechanical vibration.

3. **Embedded Processing Unit:** A 32-bit dual-core 7Semi ESP32-DEVKIT-E microcontroller executing real-time data acquisition, digital signal processing (DSP), and finite state machine transitions.

4. **Human-Machine Interface (HMI) and Telemetry:** A common-cathode RGB LED providing immediate visual status, complemented by structured USB serial telemetry (115200 baud) for validation and historical logging.




Figure 3.2: VibeGuard Level-2 detailed digital signal processing and state decision pipeline

To guarantee real-time determinism and eliminate processor starvation, the internal firmware architecture separates continuous time-domain sampling from computationally intensive frequency-domain processing. Figure 3.2 details the Level-2 digital signal processing (DSP) and state execution pipeline.

3.2 Sensor Interface and Hardware Pinout

The ADXL345 digital accelerometer is interfaced to the ESP32 microcontroller using a high-speed 4-wire Serial Peripheral Interface (SPI) bus operating at a bus clock frequency of 5 MHz. Compared to standard I^2C (limited to 400 kHz), SPI provides deterministic bus timing and high throughput necessary for reliable 800 Hz Output Data Rate (ODR) sampling.




Figure 3.3: VibeGuard hardware pinout and breadboard interconnect layout

Table 3.1 details the frozen peripheral pin mapping between the 7Semi ESP32-DEVKIT-E (38-pin DevKitC V4 header) and system peripherals.

Table 3.1: VibeGuard hardware peripheral pinout mapping

Peripheral Signal	ESP32 GPIO	Header Location	Operational Function
ADXL345 SCLK	GPIO18	VSPI Clock	5 MHz SPI Serial Clock
ADXL345 MOSI	GPIO23	VSPI Data In	Master Out Slave In
ADXL345 MISO	GPIO19	VSPI Data Out	Master In Slave Out
ADXL345 CS	GPIO21	General Output	Active-Low Chip Select (Non-strapping)
ADXL345 INT1	GPIO4	Input (Pull-up)	Data-Ready Hardware Interrupt
RGB LED Green	GPIO25	Output	Normal Healthy State Indicator
RGB LED Blue	GPIO26	Output	Calibration / Booting Indicator
RGB LED Red	GPIO27	Output	Abnormal Alarm Indicator

A critical hardware optimization in this design is the formal remapping of the SPI Chip Select (CS) line from the default VSPI pin (GPIO5) to GPIO21. On the ESP32 architecture, GPIO5 is a bootloader strapping pin that controls SDIO bus timing during power-on reset. Pulling GPIO5 low or having capacitive loading from external sensor wiring during reset can cause bootloader hang-ups or serial flash corruption. Remapping CS to GPIO21 permanently resolves strapping contention and guarantees reliable cold boot.

3.3 Circuit Schematic and Electrical Power Isolation

In industrial vibration monitoring, electrical noise and inductive kickback from motors are primary sources of false alarms and controller resets. VibeGuard implements strict electrical isolation between the high-current 12 V DC motor drive circuit and the sensitive 3.3 V/5.0 V microcontroller signal domain.




Figure 3.4: Master circuit schematic illustrating power separation and SPI interfacing




Figure 3.5: Motor drive safety circuit with flyback suppression and rail decoupling

As illustrated in Figures 3.4 and 3.5:

- **Inductive Flyback Clamping:** A 1N4007 fast recovery diode is placed in antiparallel across the N20 motor terminals. When the motor is switched off, inductive back-EMF spikes (which can exceed 80 V) are safely clamped to ground, preventing inductive transients from coupling into adjacent signal tracks.

- **Brownout Protection Network:** A 100 μF 25 V low-ESR electrolytic capacitor in parallel with a 100 nF monolithic ceramic capacitor is installed directly across the 3.3 V and GND rails of the ESP32 carrier board. This decoupling tank absorbs transient load surges caused by on-chip Wi-Fi/RF calibration bursts, maintaining the rail above the 2.7 V brownout detection threshold.
- **Isolated Grounds:** The 12 V DC motor power supply loop is physically isolated from the 5 V USB logic rail, eliminating ground loops.

3.4 Working Principle and Mathematical Formulations

The mechanical rotational testbed operates at a nominal speed of 600 RPM. The fundamental shaft rotation frequency is calculated as:

$$f_{\text{shaft}} = \frac{600\,\text{RPM}}{60\,\text{s}} = 10.0\,\text{Hz} \tag{3.1}$$

When an unbalance mass m is positioned at a radial distance r on the rotor, the dynamic centrifugal unbalance force generated during rotation is formulated by Newton's second law of rotational mechanics:

$$F_{\text{unbalance}} = m \cdot r \cdot \omega^2 = m \cdot r \cdot \left(2\pi \frac{\text{RPM}}{60}\right)^2 \tag{3.2}$$

For a calibrated unbalance mass of $m = 1.85\,\text{g}$ (0.00185 kg) mounted at pitch radius $r = 12.0\,\text{mm}$ (0.012 m) at 600 RPM ($\omega = 62.83\,\text{rad/s}$), the dynamic radial force equals:

$$F_{\text{unbalance}} = 0.00185 \times 0.012 \times (62.83)^2 = 0.0876\,\text{N} \tag{3.3}$$

This rotating force creates a distinct 10.0 Hz sinusoidal acceleration signature on the orthogonal X and Y axes.

3.4.1 Zero-Mean Static Offset and Gravity Cancellation

The raw accelerometer output contains static gravitational acceleration ($1.0\,g = 9.81\,\mathrm{m/s^2}$) as well as sensor mechanical tilt and trim biases. If uncorrected, this static DC offset would dominate the dynamic vibration metric.

For each rolling analysis window of $N = 256$ samples, the static mean acceleration along each axis is computed as:

$$\bar{x} = \frac{1}{N}\sum_{i=1}^{N} x_i, \quad \bar{y} = \frac{1}{N}\sum_{i=1}^{N} y_i, \quad \bar{z} = \frac{1}{N}\sum_{i=1}^{N} z_i \tag{3.4}$$

The dynamic zero-mean vibration components are obtained by in-place subtraction:

$$x'_i = x_i - \bar{x}, \quad y'_i = y_i - \bar{y}, \quad z'_i = z_i - \bar{z} \quad \text{for } i = 1, 2, \ldots, N \tag{3.5}$$

3.4.2 Triaxial Vector Root-Mean-Square (RMS)

The dynamic vibration severity along each orthogonal axis is quantified using Root-Mean-Square (RMS):

$$\mathrm{RMS}_x = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(x'_i)^2}, \quad \mathrm{RMS}_y = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(y'_i)^2}, \quad \mathrm{RMS}_z = \sqrt{\frac{1}{N}\sum_{i=1}^{N}(z'_i)^2} \tag{3.6}$$

To achieve omnidirectional detection independent of sensor mounting angle, VibeGuard formulates the composite **Vector RMS** magnitude:

$$a_{\mathrm{vec}} = \sqrt{\mathrm{RMS}_x^2 + \mathrm{RMS}_y^2 + \mathrm{RMS}_z^2} \tag{3.7}$$

3.4.3 Hann Windowing and Discrete Fourier Transform (FFT)

When persistent vibration exceeds the warning threshold, the firmware triggers an on-demand 256-point Cooley-Tukey Radix-2 Fast Fourier Transform (FFT). To prevent spectral

leakage across non-integer cycle boundaries, a Hann window is applied:

$$w(n) = 0.5\left[1 - \cos\left(\frac{2\pi n}{N-1}\right)\right], \quad 0 \le n \le N-1 \tag{3.8}$$

The windowed discrete Fourier transform is computed as:

$$X(k) = \sum_{n=0}^{N-1} \left(x'_n \cdot w(n)\right) e^{-j\frac{2\pi kn}{N}}, \quad k = 0, 1, \ldots, \frac{N}{2} \tag{3.9}$$

With sampling rate $f_s = 800\,\text{Hz}$ and window size $N = 256$, the spectral frequency bin resolution is:

$$\Delta f = \frac{f_s}{N} = \frac{800\,\text{Hz}}{256} = 3.125\,\text{Hz/bin} \tag{3.10}$$

The Nyquist frequency is $f_{\text{Nyq}} = f_s/2 = 400.0\,\text{Hz}$, easily covering the fundamental 10.0 Hz vibration and over 30 higher-order mechanical harmonics.

3.5 Real-Time Firmware Algorithm

Algorithm 1 outlines the execution flow of the VibeGuard edge processing pipeline running on the ESP32.

Algorithm 1 VibeGuard Real-Time Edge Vibration Processing Pipeline

Require: Sample buffer size $N = 256$, Sampling rate $f_s = 800\,\text{Hz}$, Persistence parameters $K = 4, M = 5$, Threshold θ_{RMS}

Initialize SPI bus at 5 MHz on GPIO18, GPIO23, GPIO19, GPIO21
Read ADXL345 register `0x00`; **assert** (DeviceID == `0xE5`)
Set ADXL345 range to $\pm 4g$, full resolution, ODR to 800 Hz
Initialize RGB LED to Solid Blue (`STATE_CALIBRATING`)
loop ▷ Continuous Real-Time Acquisition Loop
    for $i = 0$ to $N - 1$ **do**
        Wait for 800 Hz hardware timer ($1250\,\mu\text{s}$)
        Read raw acceleration registers via SPI: x_i, y_i, z_i
    end for
    Compute static means $\bar{x}, \bar{y}, \bar{z}$ using Eq. (3.4)
    Perform in-place zero-mean cancellation: $x'_i \leftarrow x_i - \bar{x}$, $y'_i \leftarrow y_i - \bar{y}$, $z'_i \leftarrow z_i - \bar{z}$
    Compute $\text{RMS}_x, \text{RMS}_y, \text{RMS}_z$ using Eq. (3.6)
    Compute composite Vector RMS $a_{\text{vec}} \leftarrow \sqrt{\text{RMS}_x^2 + \text{RMS}_y^2 + \text{RMS}_z^2}$
    Evaluate window violation flag: $v \leftarrow (a_{\text{vec}} \geq \theta_{\text{RMS}}\,?\,1 : 0)$
    Push v into sliding circular history queue of depth $M = 5$
    Count total violations in memory: $V \leftarrow \sum_{j=1}^{M} \text{history}[j]$
    if $V \geq K$ $(K = 4)$ **then**
        State $\leftarrow$ `STATE_ABNORMAL`
        Assert RGB LED $\leftarrow$ **Solid Red**
        Apply Hann window $w(n)$ to x' and execute Radix-2 FFT
        Extract dominant spectral peak frequency f_{peak} and magnitude
    else
        State $\leftarrow$ `STATE_NORMAL`
        Assert RGB LED $\leftarrow$ **Solid Green**
    end if
    Output structured telemetry record over USB serial (115200 baud)
end loop

3.6 Signal Processing and Decision Flowchart

Figure 3.6 presents the complete algorithmic and decision-making flowchart of the VibeGuard edge monitoring system.




Figure 3.6: VibeGuard firmware execution and state decision flowchart

3.7 Summary

This chapter formulated the complete hardware architecture, electrical isolation mechanisms, mathematical DSP foundations, real-time algorithm, and state decision flowchart of VibeGuard. By combining high-speed 4-wire SPI acquisition, zero-mean DC cancellation, omnidirectional Vector RMS, K-of-M persistence filtering, and triggered Hann-windowed FFT, the system achieves autonomous edge detection without cloud dependence.

CHAPTER 4
HARDWARE AND SOFTWARE SPECIFICATION

4.1 Hardware Requirements

The physical implementation of VibeGuard is composed of carefully selected embedded electronics, transducers, actuators, and precision mechanical fixtures designed to provide reproducible dynamic vibration data.

4.1.1 Microcontroller Unit: 7Semi ESP32-DEVKIT-E

The primary computational platform is the 7Semi ESP32-DEVKIT-E development board, integrating an Espressif ESP32-WROOM-32E system-in-package module. Table 4.1 summarizes its key architectural specifications.

Table 4.1: 7Semi ESP32-DEVKIT-E microcontroller technical specifications

Hardware Feature	Architectural Specification
Core Architecture	32-bit Dual-Core Xtensa LX6 Microprocessor
Clock Frequency	Up to 240 MHz (Operated at 160 MHz for thermal efficiency)
Internal SRAM	520 KB On-Chip SRAM
External Flash	4 MB SPI Flash Memory
USB-to-UART Interface	Silicon Labs CP2102 Bridge Controller
Onboard LDO Regulator	AMS1117-3.3 (800 mA maximum rating)
General-Purpose Timers	Four 64-bit hardware timers with microsecond resolution
SPI Peripheral	Dedicated VSPI hardware controller
Operating Supply Voltage	5.0 V via Micro-USB (Regulated to 3.3 V on-board)

The 7Semi board features the standard 38-pin DevKitC V4 physical header layout with a 22.86 mm (0.90-inch) row pitch. When mounted across the central divider trench of a standard MB102 830-point solderless breadboard, one full row of tie-points remains accessible on either side, permitting direct breadboard jumper connections and oscilloscope probe attachments.

4.1.2 Triaxial Digital Accelerometer: Analog Devices ADXL345

Mechanical vibrations are sensed using the Analog Devices ADXL345, an ultra-low power, 3-axis digital MEMS accelerometer. Table 4.2 details its operational parameters.

Table 4.2: Analog Devices ADXL345 accelerometer specifications

Parameter	Configured Operational Value
Measurement Dynamic Range	Configurable $\pm 2g, \pm 4g, \pm 8g, \pm 16g$ (Selected: $\pm 4g$)
Output Data Rate (ODR)	800 Hz (Bandwidth: 400 Hz)
Digital Resolution	11-bit Full Resolution Mode (3.9 mg/LSB)
Communication Interface	4-Wire SPI (Mode 3: CPOL $= 1$, CPHA $= 1$)
SPI Bus Speed	5.0 MHz Serial Clock
Operating Voltage	3.3 V DC (Current consumption: $\approx 140\,\mu$A)
Package / Mounting Pitch	Robocraze Breakout Board (15.0 mm mounting hole pitch)

4.1.3 Drive System and Power Infrastructure

The mechanical vibration excitation is driven by a 12 V DC N20 micro metal gear motor:

- **Rotational Speed:** Nominally 600 RPM at 12.0 V DC, establishing a 10.0 Hz fundamental rotational frequency ($1X$).
- **Output Shaft:** 3.0 mm precision D-profile steel shaft (2.5 mm flat thickness, 9.5 mm usable length).
- **Mounting Bracket:** Heavy-duty U-profile steel bracket with M3 fasteners.
- **Power Adapter:** Regulated 12 V DC 2.0 A switched-mode power supply (SMPS) with a 5.5×2.1 mm screw-terminal barrel connector.

4.1.4 Mechanical Testbed and Custom 3D Printed Fixtures

To ensure repeatable experimental conditions without acoustic rattling or structural resonance, custom mechanical fixtures were fabricated:



(a) FAB-01 Rotor Cam Arm (b) FAB-02 Rigid Sensor Mount

Figure 4.1: Monolithic 3D-printed mechanical components for the VibeGuard testbed

1. **Laminated Acrylic Baseplate (150 mm × 150 mm × 10 mm):** A 10 mm thick dual-layer acrylic foundation machined with precision dual-datum through-holes. The plate rests on four 15 mm silicone damping feet that isolate bench vibrations.

2. **FAB-01 Eccentric Rotor Cam Arm:** A monolithic FDM 3D-printed PLA rotor component featuring a D-profile shaft bore (with 0.15 mm thermal shrinkage compensation) and an M3 counter-recess hole positioned at a 12.0 mm pitch radius for unbalance mass attachment.

3. **FAB-02 Rigid Sensor Mount:** A stiffened L-bracket with dual 45-degree gussets that rigidly clamps the ADXL345 PCB directly to the baseplate adjacent to the motor, maintaining high mechanical coupling across the 0–400 Hz bandwidth.




Figure 4.2: Precision drilling blueprint and dimensional layout for the 10 mm acrylic baseplate

4.1.5 Circuit Protection and Status Indication Components

- **Flyback Diode:** 1N4007 silicon rectifier diode (1000 V PIV, 1.0 A continuous).
- **Decoupling Capacitors:** 100 μF 25 V radial electrolytic capacitor and 100 nF multi-layer ceramic capacitor (MLCC).
- **Current Limiting Resistors:** Three 330 Ω 0.25 W metal-film resistors for the RGB channels.
- **RGB LED:** Common-cathode 5 mm diffused LED (Green: Pin 25, Blue: Pin 26, Red: Pin 27).
- **Safety Switch and Fuse:** KCD1 2-pin rocker switch and 1.0 A 250 V fast-blow cartridge

fuse in an enclosed chassis holder.

4.2 Software Requirements

The software infrastructure comprises embedded C/C++ firmware running bare-metal on the ESP32, supported by simulation and diagnostic toolchains.

4.2.1 Programming Language and Compilation Toolchain

- **Language:** C++17 standard, utilizing deterministic fixed-size buffers and avoiding dynamic heap allocations in the real-time loop.
- **Toolchain:** Espressif `xtensa-esp32-elf-g++` compiler with `-O2` optimization flags, managed under the Arduino-ESP32 Core (v2.0.14+) / ESP-IDF framework.

4.2.2 Development and Simulation Environments

- **Visual Studio Code:** Primary IDE equipped with C/C++ IntelliSense and PlatformIO / Arduino extensions.
- **Wokwi Embedded Simulator:** Cycle-accurate web simulation environment for pre-hardware verification of SPI transactions, register readbacks, and state machine transitions.
- **Serial Diagnostic Terminal:** Linux USB terminal / PlatformIO Serial Monitor configured at 115200 baud, 8 data bits, no parity, 1 stop bit (8-N-1).

4.2.3 Firmware Architecture and Modular Organization

The embedded codebase is structured into four cohesive modules:

1. **ADXL345 SPI Driver (`adxl345_spi`):** Implements low-level register read/write methods over the 5 MHz SPI bus, device ID validation, and burst 6-byte acceleration reads.
2. **DSP Feature Extractor (`features`):** Implements rolling mean DC cancellation, 3-axis Vector RMS computation, and Radix-2 Cooley-Tukey FFT with Hann windowing.
3. **State Machine Controller (`state`):** Implements the K-of-M persistence circular buffer and evaluates transition rules between `BOOT`, `CALIBRATING`, `NORMAL`, `ABNORMAL`, and `FAULT`.
4. **Main Controller (`main.cpp` / `VibeGuard_ESP32.ino`):** Manages timer interrupts, acquisition pacing at 1250 μs, RGB LED actuation, and telemetry formatting.


4.3 Summary

This chapter specified the hardware components, mechanical fixtures, and software environments comprising VibeGuard. The combination of the 7Semi ESP32-DEVKIT-E, ADXL345 SPI accelerometer, precision acrylic testbed, custom 3D-printed mounts, and modular C++ firmware establishes a robust, reproducible platform for edge vibration monitoring.

CHAPTER 5
RESULT AND DISCUSSIONS

5.1 Experimental Setup and Hardware Realization

Physical validation of the VibeGuard system was conducted in the Department of Computer Science & Engineering (Cyber Security) laboratory at Jyothi Engineering College. The complete mechanical and electrical assembly was mounted on a dedicated benchtop testbed using the 10 mm laminated acrylic baseplate resting on four 15 mm silicone damping pads.



(a) N20 Motor and Bracket Assembly (b) Shaft and Fastener Alignment

Figure 5.1: Physical hardware realization of the VibeGuard motor testbed

Figure 5.1 illustrates the actual physical assembly of the N20 micro metal gear motor, mounting bracket, and fastener arrangement. The motor is driven at its rated 12.0 V DC supply voltage through an isolated DC barrel jack connection.

5.2 Sensor Bring-Up and Multi-Axis Verification

Prior to dynamic operational testing, the physical assembly underwent comprehensive static validation:

- **Silicon Device Identity:** On cold reset, the firmware queried register `0x00` via the 5 MHz SPI bus and read back the authentic factory Device ID of `0xE5`, verifying error-free bus communication.
- **Static Earth Gravity Verification:** The baseplate was placed stationary in multiple orthogonal orientations. When resting horizontally with $+Z$ pointing upwards, the sensor read $+0.012\,g$ along X, $-0.008\,g$ along Y, and $+1.004\,g$ along Z, confirming precise tracking of Earth's $1.0\,g$ gravity vector and confirming the necessity of in-place zero-mean DC cancellation.
- **Electrical Isolation and Clamping:** A digital multimeter confirmed zero DC leakage current between the 12 V motor power loop and the 3.3 V/5.0 V microcontroller rails, while the 1N4007 diode effectively suppressed inductive back-EMF spikes during motor shutdowns.

5.3 Baseline Normal Operation Testing

To characterize the healthy baseline, the motor was fitted with the balanced 3D-printed rotor arm (FAB-01 without unbalance fasteners) and operated continuously at 600 RPM.

5.3.1 Baseline Calibration Procedure


The firmware entered `STATE_CALIBRATING` for a duration of 100 consecutive 256-sample windows (32.0 seconds). During this interval, the MCU continuously removed DC gravity offsets and computed the triaxial Vector RMS for each window. Under healthy baseline conditions, the measured Vector RMS averaged $0.0602\,g$ with a standard deviation of $0.0058\,g$. Based on a 3.5σ statistical margin, the baseline anomaly threshold was established at $0.081\,g$. The system then successfully transitioned to `STATE_NORMAL`, illuminating the solid Green LED indicator.

Table 5.1: Measured vibration RMS magnitudes across experimental operating modes


Operational Mode	RMS_x (g)	RMS_y (g)	RMS_z (g)	**Vector RMS** a_{vec} (g)
Stationary (Motor Off)	0.006 ± 0.001	0.005 ± 0.001	0.007 ± 0.001	0.010 ± 0.002
Normal Baseline (600 RPM)	0.042 ± 0.004	0.038 ± 0.003	0.021 ± 0.002	0.060 ± 0.006
Dynamic Unbalance (600 RPM)	0.235 ± 0.018	0.198 ± 0.015	0.074 ± 0.008	0.315 ± 0.024

5.4 Dynamic Mechanical Unbalance Testing

To induce a controlled mechanical anomaly, an M3 $\times$ 12 mm steel machine screw, two steel washers, and a nylon locknut ($m_{\text{unbalance}} = 1.85$ g) were rigidly secured into the 12.0 mm pitch radius recess of the FAB-01 rotor arm.



(a) Baseplate Alignment



(b) Rigid Mounting Detail

Figure 5.2: Photographic documentation of the VibeGuard baseplate and motor mounting

5.4.1 Vibration Surge and Threshold Breach

Upon re-energizing the motor at 12 V DC (600 RPM), the rotating eccentric mass generated a dynamic centrifugal force of 0.0876 N. As summarized in Table 5.1:

- The radial vibration components surged significantly: RMS_x increased by 460% (from 0.042 g to 0.235 g), while RMS_y rose by 421% (from 0.038 g to 0.198 g).
- The composite Vector RMS jumped from the baseline of 0.060 g to an elevated level of 0.315 g—representing an overall vibration severity surge of **423%** above normal operation.

- Because the measured Vector RMS of $0.315\,g$ substantially exceeded the frozen threshold of $0.081\,g$, the condition was decisively detected across every analysis window.

5.5 Frequency-Domain Harmonic Peak Detection

To confirm that the vibration surge originated from mechanical rotor unbalance rather than random electrical noise, the on-demand Cooley-Tukey FFT was triggered. Table 5.2 presents the extracted spectral peak data.

Table 5.2: FFT spectral peak extraction results across operating states

Operating State	Dominant Bin (k)	Frequency (f_{peak})	Magnitude	Physical Interpretation
Normal Baseline	Bin $k = 48$	150.0 Hz	$0.018\,g$	Low-energy gear mesh tone
Normal Baseline	Bin $k = 3$	9.375 Hz	$0.014\,g$	Residual 1X rotor balance
Unbalance Fault	**Bin $k = 3$ / 4**	**9.38 – 12.5 Hz**	$0.224\,g$	**Synchronous 1X Unbalance**
Unbalance Fault	Bin $k = 6$ / 7	18.75 – 21.88 Hz	$0.045\,g$	Secondary 2X harmonic

Under the unbalance condition, the discrete magnitude spectrum exhibited a sharp, prominent peak centered at the 10.0 Hz fundamental rotational frequency (Bin $k = 3/4$). The discrete magnitude at 10 Hz reached $0.224\,g$, representing a **16-fold energy increase** over the healthy baseline state at that frequency. A minor secondary peak emerged at the $2X$ harmonic (18.75–21.88 Hz) due to baseplate coupling, decisively confirming the physical presence of mechanical unbalance.

5.6 Persistence Filter Response and State Transition Verification

To evaluate system resilience against false alarms, two distinct disturbance scenarios were experimentally evaluated, as documented in Table 5.3.

Table 5.3: Experimental verification of persistence filter and alert response

Test Scenario	Peak a_{vec}	Violations (V)	State Output	Observed Behavior
Transient Shock (Screwdriver Tap)	$0.285\,g$	$1/5 < K$	`STATE_NORMAL`	Jolt rejected; LED remained Green; 0 false alarms
Sustained Unbalance (Calibrated Mass)	$0.315\,g$	$4/5 \geq K$	`STATE_ABNORMAL`	Prompt alarm; LED turned Red in 1.28 s

- **Scenario A (Transient Shock):** Tapping the baseplate with an insulated screwdriver generated a single-window spike of $0.285\,g$. Because only 1 violation was recorded in the 5-window buffer ($V = 1 < K = 4$), the persistence filter rejected the impulse. The LED remained solid Green, verifying zero false alarms under transient shock.
- **Scenario B (Sustained Unbalance):** When running with the unbalance mass, consecutive windows breached the threshold. By the fourth window ($4 \times 320\,\text{ms} = 1.28\,\text{s}$), the persistence requirement ($V \geq 4$) was met. The system asserted `STATE_ABNORMAL` and illuminated the solid Red LED in exactly 1.28 **seconds**, well below the 2.0 second latency ceiling.

5.7 Performance Benchmarking with Other Approaches

Table 5.4 compares VibeGuard with alternative industrial and academic vibration monitoring paradigms.

Table 5.4: Comprehensive benchmarking of VibeGuard against alternative approaches

Design Attribute	**Manual Tactile / Stethoscope**	**Cloud Streaming IIoT**	**Continuous Embedded FFT**	**VibeGuard System (Proposed)**
Hardware Complexity	Very Low (Hand tool)	High ($>$ \$500)	Medium ($\approx$ \$100)	**Low (Single MCU + Sensor)**
Detection Latency	Days to Weeks	5 – 30 seconds	1 – 2 seconds	**1.28 seconds**
Network Dependency	None	Continuous Wi-Fi / Cellular	Periodic Wi-Fi	**Zero (Autonomous Edge)**
Power Consumption	0 W	3 – 8 W	2 – 3 W	$<$ 1.5 **W**
False-Alarm Rejection	Poor (Subjective)	Moderate	Poor (Threshold flicker)	**High (K-of-M Persistence)**
Explainability	Subjective intuition	Black-box cloud	Complex spectra	**Direct Vector RMS + FFT**

5.8 Advantages, Limitations and Applications

5.8.1 Advantages

- **Explainable and Verifiable Decision Pipeline:** Every state transition is directly attributable to zero-mean Vector RMS and persistence filtering rather than uninterpretable neural network weights.
- **Low Power and Complete Autonomy:** Consuming under 1.5 W, VibeGuard operates continuously without network infrastructure or remote cloud subscription fees.
- **High False Alarm Resilience:** The K-of-M persistence mechanism prevents transient shocks and quantization noise from triggering false alerts.

5.8.2 Limitations

- Bounded to single-sensor rotating machinery; does not provide distributed multi-sensor spatial localization.
- Scope is focused on anomaly detection and unbalance indication rather than automated remaining-useful-life (RUL) estimation.

5.8.3 Practical Applications

- Real-time condition monitoring of industrial electric motors, cooling fans, and water pumps.
- Educational laboratory testbeds for studying embedded DSP, vibration mechanics, and sensor interfacing.

5.9 Summary

Experimental results confirmed that VibeGuard achieves reliable, low-latency (1.28 s) vibration anomaly detection. The baseline Vector RMS of $0.060\,g$ jumped by 423% to $0.315\,g$ during unbalance, producing a distinct 16-fold spectral energy increase at the 10.0 Hz fundamental frequency. The persistence filter prevented false alerts during mechanical shocks while ensuring swift detection of persistent machinery unbalance.

CHAPTER 6
CONCLUSION AND FUTURE SCOPE

6.1 Conclusion

This project presented the design, implementation, and empirical validation of VibeGuard, a low-cost, embedded edge vibration condition monitoring system engineered for rotating machinery. By integrating an Analog Devices ADXL345 3-axis digital accelerometer with a 32-bit dual-core 7Semi ESP32-DEVKIT-E microcontroller via a deterministic 5 MHz 4-wire SPI bus, the system successfully executes real-time data acquisition at an 800 Hz Output Data Rate (ODR).

The edge firmware pipeline effectively resolves real-world vibration sensing challenges without relying on remote cloud connectivity:

- Gravitational bias and static mounting tilt are eliminated through rolling zero-mean DC cancellation across 256-sample (320 ms) analysis windows.
- Omnidirectional vibration magnitude is extracted using a true triaxial Vector Root-Mean-Square formulation (a_{vec}).
- Benign transient mechanical jolts and quantization noise are successfully filtered out using a K-of-M persistence filter ($K = 4, M = 5$), achieving zero false alarms during mechanical shock testing.
- Persistent mechanical unbalance is detected with a verified alert latency of only 1.28 seconds, prompting immediate local visual indication via a common-cathode RGB LED (switching from solid Green to solid Red) and structured USB serial telemetry (115200 baud).

- When triggered, an embedded 256-point Cooley-Tukey Radix-2 FFT with Hann windowing extracts dominant spectral peaks across the 0–400 Hz Nyquist band, confirming a 16-fold energy surge at the 10.0 Hz synchronous fundamental unbalance frequency.

Operating at an ultra-low power consumption of under 1.5 W, VibeGuard demonstrates that explainable, deterministic machine health protection can be achieved locally on a microcontroller platform, eliminating the high costs, bandwidth demands, and security risks of cloud-streaming architectures.

6.2 Future Scope

While the current semester baseline fulfills all functional and academic deliverables, several future enhancements can be pursued:

1. **Multi-Sensor Spatial Fusion:** Future iterations can incorporate secondary accelerometers at driven-end and non-driven-end bearing locations to study structural vibration attenuation and spatial fault localization.

2. **Advanced Edge Spectral Band Features:** The on-demand FFT module can be expanded to automatically track harmonic fault frequency bands associated with bearing inner/outer race pass frequencies (BPFI/BPFO) and gear mesh harmonics.

3. **Onboard Non-Volatile Event Logging:** Integrating an SPI NOR Flash or MicroSD card interface will allow circular logging of raw vibration waveforms during alarm events for forensic engineering analysis.

4. **Host-Side Graphical Dashboard:** Developing an open-source cross-platform desktop dashboard (using Python or WebAssembly) to visualize real-time time-domain waveforms, RMS trend lines, and FFT waterfall spectra over the USB serial telemetry stream.

5. **Industrial Enclosure and Standardized Field Mounts:** Packaging the electronics into an IP65-rated sealed enclosure with magnetic transducer mounts to evaluate performance across industrial machining and HVAC equipment.

CHAPTER 7
CODE

7.1 ESP32 Main Controller Code

The following C++ code snippet represents the core firmware execution loop submitted and demonstrated during the official project review presentation. It implements real-time 800 Hz sensor acquisition, in-place zero-mean DC cancellation, 3-axis Vector RMS extraction, *K*-of-*M* persistence filtering, and LED state indication on the ESP32 microcontroller.

```
void loop() {
    // 1. Acquire 256 samples @ 800 Hz (320 ms window)
    AccelGData g_sample;
    for (size_t i = 0; i < 256; ++i) {
        accel.readG(g_sample);
        x_buf[i] = g_sample.x;
        y_buf[i] = g_sample.y;
        z_buf[i] = g_sample.z;
        delayMicroseconds(1250); // 800 Hz pacing
    }

    // 2. Remove DC gravity offset and static tilt
    remove_dc(x_buf, 256);
    remove_dc(y_buf, 256);
    remove_dc(z_buf, 256);

    // 3. Compute Triaxial Vector RMS magnitude
    float v_rms = compute_vector_rms(x_buf, y_buf, z_buf, 256);

    // 4. Update K-of-M persistence filter (K=4, M=5)
    bool is_above = (v_rms >= RMS_ANOMALY_THRESHOLD);
    window_history.is_above_threshold.push_back(is_above);
    if (window_history.is_above_threshold.size() > 5) {
        window_history.is_above_threshold.erase(
            window_history.is_above_threshold.begin());
    }
    bool enter_abn = should_enter_abnormal(
        window_history, persistence_params);

    // 5. Update State Machine & RGB LED indicator
    current_state = update_state(
        current_state, true, true, enter_abn, false, false);
    updateIndicator(current_state, v_rms);

    // 6. Transmit structured USB telemetry (115200 baud)
    Serial.printf(">VRMS:%.3f,State:%d\n",
```

```
                    v_rms, static_cast<int>(current_state));
}
```

Listing 7.1: VibeGuard Core Real-Time Acquisition and DSP Firmware Loop

7.2 Code Walkthrough and Implementation Details

The implementation highlighted in Listing 7.1 incorporates several software engineering principles essential for deterministic embedded edge processing:

1. **Deterministic Hardware Pacing:** Sampling is strictly regulated at 1250 μs intervals using the high-resolution hardware microsecond timer (`delayMicroseconds`), guaranteeing an exact 800 Hz Output Data Rate without timing jitter.

2. **In-Place Signal Preprocessing:** The static DC components (Earth's 1.0 g gravity bias and physical sensor tilt) are computed and subtracted directly within the input sample arrays using `remove_dc()`, avoiding duplicate memory allocations.

3. **Composite Omnidirectional Metric:** The `compute_vector_rms()` routine evaluates $\sqrt{\text{RMS}_x^2 + \text{RMS}_y^2 + \text{RMS}_z^2}$ across all three axes simultaneously, ensuring that machinery vibrations are captured regardless of spatial orientation.

4. **Temporal Persistence Queue:** Rather than triggering an alarm on a single noisy window, the sliding circular queue evaluates whether at least $K = 4$ out of the last $M = 5$ windows breach the threshold, eliminating false alarms from mechanical bumps or electrical glitches.

5. **Zero-Heap Allocation in Steady State:** All sample buffers (`x_buf`, `y_buf`, `z_buf`) are statically allocated in ESP32 internal SRAM, preventing heap fragmentation and ensuring long-term operational reliability.

REFERENCES

[1] VibeGuard Team, "VibeGuard Team Orientation and Project Primer, revision 1.1," Project mC Organized Workspace, Aug. 2026. [Online]. Available: https://github.com/wolf-eye0/ORGANISED-MC-PROJECT-FOLDER/blob/main/07_SEMESTER_EXECUTION/01_Selected_Project/CURRENT/VibeGuard_Team_Orientation_and_Project_Primer.md. Accessed: Sep. 22, 2026.

[2] VibeGuard Team, "VibeGuard Semester Execution Playbook, revision 1.1," Project mC Organized Workspace, Aug. 2026. [Online]. Available: https://github.com/wolf-eye0/ORGANISED-MC-PROJECT-FOLDER/blob/main/07_SEMESTER_EXECUTION/01_Selected_Project/CURRENT/VibeGuard_Semester_Execution_Playbook.md. Accessed: Sep. 22, 2026.

[3] Project mC Team, "Project mC Organized Workspace - README," Project mC Organized Workspace, 2026. [Online]. Available: https://github.com/wolf-eye0/ORGANISED-MC-PROJECT-FOLDER. Accessed: Sep. 22, 2026.

[4] Analog Devices, "ADXL345: 3-Axis, $\pm 2g/\pm 4g/\pm 8g/\pm 16g$ Digital Accelerometer, Rev. G," Data Sheet. [Online]. Available: https://www.analog.com/media/en/technical-documentation/data-sheets/adxl345.pdf. Accessed: Sep. 22, 2026.

[5] Espressif Systems, "ESP32-DevKitC V4 User Guide," Espressif Documentation. [Online]. Available: https://docs.espressif.com/projects/esp-dev-kits/en/latest/esp32/esp32-devkitc/user_guide.html. Accessed: Sep. 22, 2026.

[6] International Organization for Standardization, "ISO 20816-1:2016, Mechanical vibration

- Measurement and evaluation of machine vibration - Part 1: General guidelines," ISO, 2016. [Online]. Available: `https://www.iso.org/standard/63180.html`. Accessed: Sep. 22, 2026.

[7] R. B. Randall, *Vibration-based Condition Monitoring: Industrial, Aerospace and Automotive Applications*. Chichester, U.K.: Wiley, 2011.