

SigmStar SSD202 wifi configuration and testing

原创 Hikil Posted at 2021-11-05 10:51:05 153 collect

copyright

Article tags: linux embedded

After executing the following commands in sequence, you can connect to the wifi whose account is Xiaomi_Clk

0. Environmental preparation

0. Execute sequentially

```
export LD_LIBRARY_PATH=$LD_LIBRARY_PATH:/customer/lib:/customer/libdns:/lib:/config/wifi/
```

```
/config/wifi/ssw01bInit.sh
```

1. Start wifi

```
/config/wifi/wpa_supplicant -i wlan0 -Dnl80211 -c/appconfigs/wpa_supplicant.conf -B
```

2. Scan ap

```
/config/wifi/wpa_cli -i wlan0 scan -p /tmp/wifi/run/wpa_supplicant/
```

3. Obtain the scan results (check whether there is a wifi to be connected to, and check the signal strength, if it is too weak, you may not be able to connect)

```
/config/wifi/wpa_cli -i wlan0 scan_result -p /tmp/wifi/run/wpa_supplicant
```

```
# /config/wifi/wpa_cli -i wlan0 scan_result -p /tmp/wifi/run/wpa_supplicant
bssid / frequency / signal level / flags / ssid
3c:cd:57:e7:1d:97 2457 -2 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][WPS][ESS] Xiaomi_1006
ec:41:18:ec:46:c1 2452 -38 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][WPS][ESS] Xiaomi_Clk
94:d9:b3:28:f6:9f 2462 -49 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][ESS] SMC
fe:01:7c:9f:95:fe 2437 -53 [WPA2-PSK-CCMP][WPS][ESS] DIRECT-fe-HP M130 LaserJet
ec:b9:70:37:62:40 2462 -52 [WPA2-PSK-CCMP][WPS][ESS] joydee
30:42:40:bc:53:f0 2422 -54 [WPA-PSK-CCMP][WPA2-PSK-CCMP][WPS][ESS] ChinaNet-311
32:42:40:bc:53:f0 2422 -53 [WPA-PSK-CCMP][WPA2-PSK-CCMP][ESS]
d8:32:5a:b7:50:a1 2417 -56 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][WPS][ESS] ChinaNet-cd6A
54:75:95:70:00:db 2442 -59 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][ESS] aoyun2021A2.4G
b8:3a:08:87:e0:d1 2432 -56 [WPA-PSK-CCMP][WPA2-PSK-CCMP][WPS][ESS] miin
fe:01:7c:57:34:1a 2437 -60 [WPA2-PSK-CCMP][WPS][ESS] DIRECT-1a-HP M130 LaserJet
be:54:fc:9d:52:72 2422 -66 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][ESS] YHH310-2.4G
88:11:96:1b:d3:7b 2412 -65 [WPA2-PSK-CCMP][ESS] \x00\x00\x00\x00\x00\x00\x00\x00
9e:ae:d3:ab:83:7d 2412 -68 [WPA2-PSK-CCMP][WPS][ESS] DIRECT-D3AB037D
38:17:c3:0c:1d:60 2412 -66 [WPA2-PSK-CCMP][ESS] Unisound-Guest
38:17:c3:0c:1d:62 2412 -65 [WPA2-PSK-CCMP][ESS] Unisound-Dev
14:69:a2:22:46:b9 2427 -66 [WPA-PSK-CCMP+TKIP][WPA2-PSK-CCMP+TKIP][ESS] CU_NQ9C
0a:0f:9f:eb:5d:c1 2432 -67 [WPA2-PSK-CCMP][ESS] Redmt CSDN @Hikil
```

4. Add a network - must remember that the return value is useful later (assuming the return value is 0)

```
/config/wifi/wpa_cli -i wlan0 add_network -p /tmp/wifi/run/wpa_supplicant/
```

5. Set the ssid

network to be connected to 0, obtained just now. Xiaomi_Clk is ssid (wifi name)

```
/config/wifi/wpa_cli -i wlan0 set_network 0 ssid "Xiaomi_Clk" -p /tmp/wifi/run/wpa_supplicant/
```

6. Set the wifi password

network to be connected to 0, just obtained. 12345678 is the wifi password

```
/config/wifi/wpa_cli -i wlan0 set_network 0 psk "smc@2020" -p /tmp/wifi/run/wpa_supplicant/
```

7. Select the network,

```
/config/wifi/wpa_cli -i wlan0 select_network 0 -p /tmp/wifi/run/wpa_supplicant/
```

8. Enable the network

```
/config/wifi/wpa_cli -i wlan0 enable_network 0 -p /tmp/wifi/run/wpa_supplicant/
```

9. Turn on wifi dhcp to automatically connect to get ip

```
udhcpc -q -i wlan0 -s /etc/init.d/udhcpc.script &
```

10. Save the configuration just now

```
/config/wifi/wpa_cli -i wlan0 save_config -p /tmp/wifi/run/wpa_supplicant/
```

11. Check whether the connection to wifi is successful

```
ifconfig
```

```
/ # ifconfig
wlan0      Link encap:Ethernet  HWaddr DC:29:19:07:03:CB
           inet addr:192.168.31.212  Bcast:192.168.31.255  Mask:255.255.255.0
           UP BROADCAST RUNNING MULTICAST  MTU:1500  Metric:1
           RX packets:11776  errors:0  dropped:207  overruns:0  frame:0
           TX packets:5  errors:0  dropped:0  overruns:0  carrier:0
           collisions:0  txqueuelen:1000
           RX bytes:555683 (542.6 KiB)  TX bytes:1042 (1.0 KiB)
```



Hikil

focus on



0



0



0



MStar 702 datasheet

10-12

n Video Decoder Supports NTSC, PAL and SECAM video input formats 2D NTSC and PAL comb-filte...

mStar 6A648 双 WiFi 所使用的8188eu.ko

10-10

mStar 6A648 双 WiFi 所使用的8188eu.ko 完整说明见这里: <https://blog.csdn.net/kangear/article/details/83...>

参与评论

您还未登录, 请先 [登录](#) 后发表或查看评论

RK 从SD卡更新LCD屏幕参数的说明

11-07

RK 从SD卡更新LCD屏幕参数的说明

目标检测算法SSD用于行人检测 (二) : 训练和测试SSD网络

sunshine_zkf的博客

3842

将Caltech数据集转化为caffe的输入数据格式LMDB请参考上一篇文章: https://blog.csdn.net/sunshine_zkf/...

as ssd 测试软件得分少,教大家AS SSD Benchmark如何测试硬盘... weixin_28837817的博客

3381

近日有关于AS SSD Benchmark如何测试硬盘性能的问题受到了很多网友们的关注, 大多数网友都想要知...

SSD202开发笔记 | 01- 东山Pi壹号开发板快速上手 (原厂S... Mculover666的博客 (嵌入式)

1580

本文中我使用Ubuntu 18.04, 阿里源。安装必要的包 `sudo apt-get install -y libc6-dev-i386 lib32z1 lib32nc...`

启明云端分享| sigmastar SSD201/SSD202D/SSD210/SSD212开机动画启... ami82的博客

871

作为Espressif (乐鑫科技) 大中华区合作伙伴及sigmastar (厦门星辰) VAD合作伙伴, 我们不仅用心整理...

小明分享|sigmastar SSD201/SSD202 针对RGB的LCD屏配置操作说明分享

ami82的博客

939

SSD20X 平台 LCD 屏的配置主要涉及两个结构体 :MI_PANEL_ParamConfig_t、MI_PANEL_Mipi...

星辰科技(sigmastar) SSD20x (SSD201、SSD202、SSD203) 、SSD21... Flying的博客

1349

SSD系列应用demo 项目地址 <https://gitee.com/mFlying/ssd2xx-demo>; 一、概要 二、目录 三、使用说明...

SSD202系统刷成功后第一个UI界面,并给大家带来一个非常好用... weixin_49938318的博客

666

8ms平台设计GUI 1.免开发环境搭建, 省时省力, 香! 8ms.xyz开发平台, 无论是给初学者还是给有着丰富...

SigmaStar智能显示--SSD201/SSD202D芯片, H.264/265解码... weixin_44281973的博客

3410

(SigmaStar智能显示芯片--SSD201、SSD202) SSD201/SSD202芯片主要芯片规格如下: A7双核1.2Ghz...

固态硬盘测试软件有哪些,SSD测试软件有哪些? SSD测试软件... weixin_32616931的博客

6557

在购买了固态硬盘(SSD)后, 如果对商家或官方给出的诸如读写速度等关键性数据存在质疑的话, 最好的解...

Windows上利用Caffe-SSD进行训练和测试

仰望星空的博客

3751

本文利用SSD: Single Shot MultiBoxDetector这种目标检测方法对视频目标检测数据集VOC2007和VOC201...

SSD读写速度测试

micklf的博客

7577

测试环境在EXSI上, 基于PCIE SSD和普通的SSD磁盘, 创建了2个规格一样的虚拟机: 2*2 cpu, 4GB me...

- SigmaStar SSD201 测试笔记

SHH_1064994894的博客 100

测试U盘 echo UDISK > /dev/udisk_4g mount -o remount rw / cd /;fdisk -l mkdir usb mount /dev/sda1 /usb/ ...
- SSD202 驱动WIFI-ssw01b的STA模式 最新发布

淡定的小龟 233

1 电路相关 复位芯片方法1 echo ON > /dev/wifi_reset echo OFF > /dev/wifi_reset 复位芯片方法2 echo 71 ...
- 小明分享|sigmstar SSD201/SSD202 针对MIPI的LCD屏配置操作说明分享...ami82的博客 1253

SSD20X 平台 LCD 屏的 配置 主要 涉及 两个 结构 体 :MI_PANEL_ParamConfig_t、 MI_PANEL_Mipi...
- mStar 6A648 双 WiFi

Android/Linux的专栏 3504

替换 8188 驱动 将 8188eu.ko,替换到系统/system/lib/modules/8188eu.ko。 替换后的文件大小为 1471470...
- sigmstar SSD201/SSD202 openwrt--应用支持分享

ami82的博客 2313

sigmstar SSD201/SSD202 openwrt 原由 近期启明云端对sigmstar SSD201/SSD202 做了openwrt的开源, ...
- 启明云端分享 | SSD201_自动升级固件与烧录MAC地址

ami82的博客 630

Functions 1. Automatically upgrade firmware from SD card when booting; 2. Automatically burn MAC addr...
- ©2022 CSDN Skin Theme: Swimming-White Designer: My name is Bai Xiaopang Return to the home page



Hikll

Code age 2

No certificatio...

40

170,000+

40,000+

10,000+



original

Weekly

Overall

access

grade

Rank

ranking

440

173

7

2

68

integral

fan

Liked

Comment

collect









Private letter

focus on

Search blogger articles



popular articles

- FFMPGE

2777

Configuring the process of porting Raspberry Pi

1744

virtualbox network configuration

1512

Raspberry Pi based face recognition access control system

1498

Raspberry Pi kernel configuration

1176

Category column

- 

CMake

1 article

latest comment

- Face Recognition Access Control Syste...

Burning Bee: I'm also learning this recently, the blog post is really well written, I feel ...

Face Recognition Access Control Syste...

Dream Eraser: Just started, especially need such articles to nourish, highly recomi ...

latest articles

- The memory model of the program - a detailed explanation of the four areas of memory

Embedded GUI using Linux framebuffer
device with LVGL

Simple CMake compilation example under
Linux

9 articles in 2022 13 articles in 2021
23 articles in 2020

content