

Q: Are all of these enough to get full marks in the exam?

A: NO. This is a practice sheet. Meaning, you can practice all you want using the questions from this sheet. However, doing well in exams depends upon your ability to understand a question, formulate an answer, and express it correctly. You see, these are humane skills which cannot be guaranteed by completing a practice sheet only. But yeah, Best of luck anyway.

Chapter 2 (Instructions: Language of the Computer)

Question - 1:

Construct the equivalent RISC-V code of the following C code. Once you have the RISC-V code, identify type of each instruction and encode them accordingly.

$$\begin{aligned} A[7] &= A[2] + A[B[8]] + 10; \\ B[i] &= A[3] - 8; \end{aligned}$$

Base addresses of array A and B are in register X_{20} and X_{21} and i is in register X_{22}

Question - 2:

Construct the equivalent RISC-V code of the following C code.

```
for (i = 8; i > 0 ; i--) {  
    if ( A[i] == i){  
        A[2] = A [B[3]] ;  
    }  
}
```

Base addresses of array A and B are in register X_{20} and X_{21} . Also consider i is in register X_{22} .

Question - 3:

Construct the equivalent RISC-V code of the following C code.

```
if ( A[i] < i){  
    A[2] = A [B[3]] ;  
}
```

Base addresses of array A and B are in register X_{20} and X_{21} . Also consider i is in register X_{22} .

Question - 4:

Construct the equivalent RISC-V code of the following C code.

```
if ( A[3] != A[6]){  
    if (A[3] == 0) {  
        A[3] = A[3] + 2;  
    }else{  
        A[6] = A[6] / 16;  
    }  
}else{  
    A[6] = A[6] * 8  
}
```

Base addresses of array A and B are in register X_{20} and X_{21} .

Question - 5:

Construct the equivalent RISC-V code of the following C code.

```
Main () {  
    int x = 0;  
    int y = 9;  
    int z = addition(x, y);  
}
```

```

int addition (int a, int b) {
    int c = a + b;
    return c;
}

```

Variables x, y, z are stored in X_{20} , X_{21} and X_{22} registers. Argument x, y are passed using register X_{13} , X_{14}

Variable c from the addition function also uses register X_{21}

Question - 6:

Write RISC-V assembly code that checks if the number stored in register X_{25} is **even** or not. If **even** then store **1** in register X_{26} otherwise store **0**.

Question - 7:

ADD X_{25} , X_{25} , X_0 . Can you make this instruction faster? If yes, Write the updated instruction?

Question - 8:

Memory Location	Code	Line Number	Machine Code
	ADDI X_5 , X_0 , 5	1	
	ADDI X_6 , X_0 , 1	2	
	ADDI X_{25} , X_0 , 0	3	
	Loop: BLT X_5 , X_6 , loopBreak	4	_____XXX_____XXXXXXXX
	ADDI X_{25} , X_{25} , 1	5	
#7080	ADDI X_5 , X_5 , -1	6	
	BEQ X_0 , X_0 , Loop	7	_____XXX_____XXXXXXXX
	loopBreak:	8	

- What is the value of **PC** while executing line2? Answer: _____
- Fill up the machine codes corresponding to line4 and line7 in the table above.

Question - 9:

Memory Location	Code	Line Number
	Loop:	
	SLLI X_{10} , X_{22} , 3	1
	ADD X_{10} , X_{10} , X_{25}	2
	LD X_9 , 0(X_{10})	3
	BNE X_9 , X_{24} , Exit	4
#80016	ADDI X_{22} , X_{22} , 1	5
	BEQ X_0 , X_0 , Loop	6
	Exit:	

- Fill up the memory locations.
- Find the SB-type instructions from the above code and encode them accordingly.
Given,
I. opcode = $(103)_{10}$, funct3 = $(000)_2$ opcode for BEQ
II. opcode = $(103)_{10}$, funct3 = $(001)_2$ opcode for BNE

Question - 10:

Write necessary RISC-V instructions to store the value $(1111\ 1111\ 0000\ 1111\ 11)_2$ in X_{20} register.

Question - 11:

Show how the value 0xabcdef12 would be arranged in memory in RISC-V machine.

Question - 12:

For the RISC-V assembly instructions below, what is the corresponding C/high level statement?

slli x30, x5, 3 add x30, x10, x30 slli x31, x6, 3	Assume that the variables f, g, h, i, and j are assigned to registers x5, x6, x7,
---	---

<pre> add x31, x11, x31 ld x5, 0(x30) addi x12, x30, 8 ld x30, 0(x12) add x30, x30, x5 sd x30, 0(x31) </pre>	x28, and x29, respectively. Assume that the base address of the Arrays A and B are in registers x10 and x11, respectively.
--	--

Newly added problems:

[Solutions available]

Question - 13:

Construct the equivalent RISC-V code **without using the multiplication operation** of the following C code:

```
int n = (a * 19)
```

Assume: n in x21, a in x22 [Hint: use slli]

Question - 14:

Construct the equivalent RISC-V code of the following C code:

```

int n = 0;
for(int i = 5; i <= n; i--) {
    if(A[i] > 0 && A[i] < n){
        A[i] = A[i] - 1;
    }
}

```

Assume : A base address in x20, n in x21, i in x22

Question - 15:

3. Translate the following assembly to equivalent C code.

Assume : A base in x21, B base in x20, i in x22

```

slli x10, x22, 3
add x10, x10, x20

```

```
ld x5, 0(x10)
addi x5, x5, 1
sd x5, 24(x21)
```

Question - 16:

```
bge x22, x21, Exit          \\ 0x015B1A67
    slli x5, x22, 3
    add x5, x20, x5
    ld x10, 0(x5)
    addi x10, x10, -1
    sd x10, 0(x5)
    addi x22, x22, 1
```

The machine code of the first instruction is given beside the instruction. Based on that, deduce where should the label “Exit” be put?

Question - 17:

Construct the equivalent RISC-V code of the following C code:

```
int max (int a, int b){
    if(a>b) return a;
    else return b;
}

int main(){
    int x = max(1000, 6000);
}
```

Assume x is in x21.

Question - 18:

Construct the equivalent **RISC-V assembly** for the following C statement:

```
A[5] = A[i] * 12 + B[i];
```

Assume, Base addresses of **A** and **B** are in **x20** and **x21** respectively. The value of ‘i’ is in **x22** and data size is 4 bytes.

Question - 19:

Assume the value:

0xCAFEBAFE12345678

is stored starting at memory address 0x2000. Show the byte order in memory for both little endian and big endian

Question - 20:

Given the following RISC-V instructions, write their **32-bit machine code** in binary. Put **Don't care(X)** where necessary (As opcode, funct3 or funct7 value is not given).

BEQ x6, x0, target1 (Assume target1 is 32 bytes ahead of the current PC.)

BNE x10, x11, target2 (Assume target2 is 64 bytes before the current PC.)

Question - 21:

Translate the following **C code** into **RISC-V assembly**. You must use the **LUI instruction**.

int x = 0x12345083;

int y = 25;

int z;

z = x + y;

Question - 22:

Translate the following **C code** into **RISC-V assembly**.

```
int multiply_add(int a, int b) {  
    int c;  
    c = a * 4;  
    return c + b;  
}
```

```
int main() {  
    int x = 6;  
    int y = 9;
```

```
int z;  
z = multiply_add_stack(x, y);  
}
```

Assume:

$x \rightarrow x20$

$y \rightarrow x21$

$z \rightarrow x22$

Function arguments $\rightarrow x10, x11$

Return value $\rightarrow x10$

Stack pointer $\rightarrow x2$

$a \rightarrow x13$

$b \rightarrow x14$

$c \rightarrow x15$

NB: Store and restore $x13-x15$ in stack during procedure