

REGISTER		Register Name	BIT-N								DEFAULT Value		
No	Hex		7	6	5	4	3	2	1	0	HEX	BIN	
0	0x00	ES8388_CONTROL1	SCPRReset	LRCM	DACMCLK	SameFs	SeqEn	EnRef	VMIDSEL		0x06	00000110	
1	0x01	ES8388_CONTROL2			LPVcmMod	LPVrefBuf	PdnAna	PdnIbiasgen	VrefrLo	PdnVrefbuf	0x5C	01011100	
2	0x02	ES8388_CHIPPOWER	adc_DigPDN	dac_DigPDN	adc_stm_rst	dac_stm_rst	ADCDLL_PDN	DACDLL_PDN	adcVref_PDN	dacVref_PDN	0xC3	11000011	
3	0x03	ES8388_ADCPOWER	PdnAINL	PdnAINR	PdnADCL	PdnADCR	PdnMICB	PdnADCBiasgen	flashLP	int1LP	0xFC	11111100	
4	0x04	ES8388_DACPOWER	PdnDACL	PdnDACR	LOUT1	ROUT1	LOUT2	ROUT2			0xC0	11000000	
5	0x05	ES8388_CHIPLOPOW1	LPDACL	LPDACR	LPLOUT1		LPLOUT2				0x00	00000000	
6	0x06	ES8388_CHIPLOPOW2	LPPGA	LPLMIX					LPADCvrp	LPDACvrp	0x00	00000000	
7	0x07	ES8388_ANAVOLMANAG		VSEL							0x7C	01111100	
8	0x08	ES8388_MASTERMODE	MSC	MCLKDIV2	BCLK_INV	BCLKDIV					0x80	10000000	
9	0x09	ES8388_ADCCONTROL1	MicAmpL				MicAmpR				0x00	00000000	
10	0x0A	ES8388_ADCCONTROL2	LINSEL		RINSEL		DSSEL	DSR			0x00	00000000	
11	0x0B	ES8388_ADCCONTROL3	DS			MONOMIX		TRI			0x02	00000010	
12	0x0C	ES8388_ADCCONTROL4	DATSEL		ADCLRP	ADCWL			ADCFORMAT		0x00	00000000	
13	0x0D	ES8388_ADCCONTROL5			ADCFsMode	ADCFsRatio					0x06	00000110	
14	0x0E	ES8388_ADCCONTROL6	ADC_invL	ADC_invR	ADC_HPF_L	ADC_HPF_R					0x30	00110000	
15	0x0F	ES8388_ADCCONTROL7	ADCRampRate	ADCSoftRamp	ADCLeR	ADCMute					0x20	00100000	
16	0x10	ES8388_ADCCONTROL8	LADCVOL								0xC0	11000000	
17	0x11	ES8388_ADCCONTROL9	RADCVOL								0xC0	11000000	
18	0x12	ES8388_ADCCONTROL10	ALCSEL		MAXGAIN			MINGAIN			0x38	00111000	
19	0x13	ES8388_ADCCONTROL11	ALCLVL				ALCHLD				0xB0	10110000	
20	0x14	ES8388_ADCCONTROL12	ALCDCY				ALCATK				0x32	00110010	
21	0x15	ES8388_ADCCONTROL13	ALCMODE	ALCZC	TIME_OUT	WIN_SIZE					0x06	00000110	
22	0x16	ES8388_ADCCONTROL14	NGTH					NGG		NGAT	0x00	00000000	
23	0x17	ES8388_DACCONTROL1	DACLRSWAP	DACLRP	DACWL			DACFORMAT			0x00	00000000	
24	0x18	ES8388_DACCONTROL2			DACFsMode	DACFsRatio					0x06	00000110	
25	0x19	ES8388_DACCONTROL3	DACRampRate		DACSoftRamp		DACLeR	DACMute			0x22	00100010	
26	0x1A	ES8388_DACCONTROL4	DACVolumeL (LDACVOL)								0xC0	11000000	
27	0x1B	ES8388_DACCONTROL5	DACVolumeR (RDACVOL)								0xC0	11000000	
28	0x1C	ES8388_DACCONTROL6	DeemphasisMode		DAC_invL	DAC_invR	ClickFree				0x08	00001000	
29	0x1D	ES8388_DACCONTROL7	ZeroL	ZeroR	Mono	SE			Vpp_scale		0x00	00000000	
30	0x1E	ES8388_DACCONTROL8			Shelving_a[29:24]							0x1F	00011111
31	0x1F	ES8388_DACCONTROL9	Shelving_a[23:16]								0xF7	11110111	
32	0x20	ES8388_DACCONTROL10	Shelving_a[15:8]								0xFD	11111101	
33	0x21	ES8388_DACCONTROL11	Shelving_a[7:0]								0xFF	11111111	
34	0x22	ES8388_DACCONTROL12			Shelving_b[29:24]							0x1F	00011111
35	0x23	ES8388_DACCONTROL13	Shelving_b[23:16]								0xF7	11110111	
36	0x24	ES8388_DACCONTROL14	Shelving_b[15:8]								0xFD	11111101	
37	0x25	ES8388_DACCONTROL15	Shelving_b[7:0]								0xFF	11111111	
38	0x26	ES8388_DACCONTROL16			LMIXSEL			RMIXSEL			0x00	00000000	
39	0x27	ES8388_DACCONTROL17	LD2LO	LI2LO	LI2LOVOL						0x38	00111000	

