

MODULATION DESIGN IN AMPLIFY-AND-FORWARD TWO-WAY RELAY HARQ CHANNEL

Author(s) Name(s)

Author Affiliation(s)

ABSTRACT

As a practical transmission enhancement technique for relay and HARQ system, Modulation Diversity (MoDiv) uses distinct mappings to the same constellation for different (re)transmissions. In this work, we study the MoDiv optimization in a Amplify-and-Forward (AF) Two-Way Relay Channel (TWRC). The design of MoDiv to minimize the bit-error rate (BER) is formulated into a successive Koopmans-Beckmann Quadratic Assignment Problem (QAP), which is solved sequentially with a robust taboo search method. The performance gain of our MoDiv scheme over retransmission without remapping and a heuristic MoDiv scheme is demonstrated with numerical results.

Index Terms— Modulation diversity, two-way relay, amplify-and-forward, HARQ, QAP

1. INTRODUCTION

As an advanced technique to improve the robustness of high-rate wireless transmissions against poor channel conditions, Hybrid Automatic Repeat reQuest (HARQ) has found its application in various communication systems [1]. HARQ works on both PHY layer and MAC sublayer to mitigate packet loss due to channel fading and link-adaptation accuracy. Recently, substantial research interest has been drawn to HARQ in Two-Way Relay Channel (TWRC) [2-4]. In [2], the average throughput of naive Type-I HARQ policy for both Amplify and Forward (AF) and Decode and Forward (DF) TWRC schemes have been analyzed. The energy-delay tradeoff, and the diversity-multiplexing tradeoff of type-II HARQ policy, also known as full Incremental Redundancy (IR), for AF TWRC scheme have been studied in [3] and [4], respectively. Related works about TWRC with ARQ for different relay schemes and retransmission policies can also be found in [5, 6, 7] and the references therein.

Apart from the naive Type-I HARQ and HARQ-IR, Type-I HARQ with maximal ratio combining (MRC), also known as HARQ-Chase Combining (HARQ-CC) [8], is another simple and practical HARQ scheme supported by such standards as HSPA [9], LTE [10] and so forth. As practical transmissions often admit linear modulations of finite-alphabet con-




Fig. 1. Two-way relay channel with analog network coding.

stellation (e.g. Q-ary QAM), the performance of HARQ-CC can be improved with Modulation Diversity (MoDiv) [11], in which a same group of $\log_2 Q$ bits are mapped to different symbols in a same constellation in different round of (re)transmissions. MoDiv has been studied for HARQ [12], relay networks [13, 14] and relay-HARQ systems [15, 16].

In this paper, we study the MoDiv design for the TWRC under a simple AF scheme and HARQ-CC protocol. We first derive an approximation for the uncoded bit-error rate (BER) of TWRC-AF channel under the Rayleigh fading condition, given M different mapping schemes corresponding to each (re)transmission. Based on this approximation, we formulate a successive BER minimization MoDiv design into a series of Quadratic Assignment Problem (QAP) in Koopmans-Beckmann (KB) form [17]. Although QAP is NP-hard, efficient numerical algorithms have been extensively researched [18], some of which have shown extremely high performance over QAPLIB [19]. We adopt a taboo search algorithm [20] to solve each QAP in our formulation. Moreover, the coefficients of QAP problem can be also be computed efficiently in a successive manner based on the solution to the preceding QAP problem. Our numerical results demonstrate significant BER reduction over both non-MoDiv and a simple heuristic MoDiv retransmission scheme for 16-QAM, 32-QAM and 64-QAM constellation, even under mismatching design parameters.

The paper is organized as follows. Section 2 introduces the TWRC-AF model and the HARQ protocol we are using. Section 3 presents the successive BER minimization MoDiv design problem. In Section 4, we present the numerical results to show the performance gain of our MoDiv scheme. Finally, Section 5 concludes the paper.

2. SYSTEM MODEL

Consider a TWRC with analog network coding (ANC) protocol [3], a generalization the AF protocol, as shown in Fig. 1.

the relay node R is totally unaware of the HARQ procedure and simply performs ANC. Each round of ANC transmission is composed of two phases. In the multiple access (MAC) phase, the two source nodes S_1 and S_2 transmit to R simultaneously. In the broadcast (BC) phase, R amplify and broadcast the signal received during the MAC phase to both S_1 and S_2 . Denote the uplink channel from S_s to R and downlink channel from R to S_s as h_s and g_s , respectively, where $s = 1, 2$. We assume that all the channels follow Rayleigh distribution, i.e. $h_s \sim \mathcal{CN}(0, \beta_{h_s})$ and $g_s \sim \mathcal{CN}(0, \beta_{g_s})$, $s = 1, 2$. Denote the transmitted symbol from S_s as x_s whose average power $\mathbb{E}[|x_s|^2] = P_s$. Then the signal received by R during the MAC phase is

$$y_R = h_1 x_1 + h_2 x_2 + n_R, \quad (1)$$

where $n_R \sim \mathcal{CN}(0, \sigma_R^2)$ is the received noise at R . Assuming that the relay R has an expected power constraint of P_R , and that S_1 and S_2 perform perfect self-interference cancellation (SIC), then the received signal at S_s after SIC is

$$y_s = \alpha g_s y_R + n_s, \quad s = 1, 2, \quad (2)$$

where $n_s \sim \mathcal{CN}(0, \sigma_s^2)$ is the received noise at S_s , and

$$\alpha = \sqrt{\frac{P_R}{|h_1|^2 P_1 + |h_2|^2 P_2 + P_R}} \quad (3)$$

is the power normalization factor at R .

On top of this settings, S_1 and S_2 performs the HARQ-CC protocol in an unsynchronized manner. Consequently, the MoDiv design at S_1 and S_2 can be handled independently. Without loss of generality, we study the HARQ transmission from S_1 to S_2 . Denote \mathcal{C} as the constellation used by S_1 whose cardinality equals $Q = |\mathcal{C}|$. As a convention, during the initial transmission of a packet, S_1 converts a bit sequence of length $\log_2 Q$ into symbols with Gray mapping $\psi_0 : \{0, \dots, Q-1\} \rightarrow \mathcal{C}$. The bit sequence is labeled by its decimal equivalence $p \in \{0, \dots, Q-1\}$. What distinct HARQ-CC with MoDiv from conventional HARQ-CC is that, during the m -th retransmission, S_1 is allowed to use a mapping function $\psi_m \neq \psi_0$ to remap the same label p . We assume $m \leq M$ where M is the maximum number of retransmissions. According to Eq. (1)(2), the signal received by S_2 after SIC during the m -th (re)transmission of p is

$$y_2^{(m)} = \alpha^{(m)} g_2^{(m)} h_1^{(m)} \psi_m[p] + \alpha^{(m)} g_2^{(m)} n_R^{(m)} + n_2^{(m)}, \quad (4)$$

where $X^{(m)}$ is the m -th realization of random variable X .

Assume that S_2 acquires perfect channel state information (CSI). After the m -th retransmission, it attempts to demodulate the received symbols by identifying label p with $y_2^{(0)}, \dots, y_2^{(m)}$ via the maximum likelihood (ML) detection:

$$p^* = \arg \min_p \sum_{k=0}^m \frac{|y_2^{(k)} - \alpha^{(k)} g_2^{(k)} h_1^{(k)} \psi_k[p]|^2}{\sigma_2^2 + (\alpha^{(k)})^2 \sigma_R^2 |g_2^{(k)}|^2}. \quad (5)$$

3. SUCCESSIVE CONSTELLATION MAPPING DESIGN FOR MODULATION DIVERSITY

In this section, we first derive an closed-form approximation of the reception bit-error rate in our TWRC channel with HARQ-CC. Based on this result, we formulate the BER-minimization MoDiv design into a successive QAP (S-QAP).

3.1. A BER approximation

Assume that the label p follows a uniform distribution. The BER of the ML demodulator after the m -th retransmission can be upper-bounded and approximated with the pair-wise error probability (PEP) [12]:

$$P_{BER}^{(m)} = \sum_{p=0}^{Q-1} \sum_{q=0}^{Q-1} \frac{B[p, q]}{Q} P_{PEP}^{(m)}(q|p), \quad (6)$$

where $B[p, q]$ represents the Hamming distance between the binary representation of p and q normalized by $\log_2 Q$, and $P_{PEP}^{(m)}(q|p)$ is the probability that the ML demodulator prefer q over p conditioned on the transmission of p . From Eq. (5), we have

$$P_{PEP}^{(m)}(q|p) = \mathbb{E} \left[Q \left(\sqrt{\sum_{k=0}^m \frac{(\alpha^{(k)})^2 \epsilon_k[p, q] \gamma_2^{(k)} \delta_1^{(k)}}{2(\tilde{\sigma}_2^{(k)})^2}} \right) \right], \quad (7)$$

where $\gamma_2^{(k)} = \|g_2^{(k)}\|^2$, $\delta_1^{(k)} = \|h_1^{(k)}\|^2$, $\epsilon_k[p, q] = \|\psi_k[p] - \psi_k[q]\|^2$, and $(\tilde{\sigma}_2^{(k)})^2 = \sigma_2^2 + (\alpha^{(k)})^2 \sigma_R^2 \gamma_2^{(k)}$ is the instantaneous variance of the noise received by S_2 . By adopting the Chernoff upper bound $Q(x) \leq e^{-x^2/2}/2$ [21], an approximation to $P_{PEP}^{(m)}(q|p)$ is

$$\tilde{P}_{PEP}^{(m)}(q|p) = \frac{1}{2} \prod_{k=0}^m \mathbb{E} \left[\exp \left(-\frac{(\alpha^{(k)})^2 \epsilon_k[p, q] \gamma_2^{(k)} \delta_1^{(k)}}{4(\tilde{\sigma}_2^{(k)})^2} \right) \right]. \quad (8)$$

Although the Chernoff bound is a rather rough approximation, it enables efficient iterative computation of $P_{PEP}^{(m)}(q|p)$ as m varies. Moreover, as shown in Section 3.2, this approximation results in a simple KB-form QAP. Nevertheless, the Chernoff bound can be replaced with a more accurate approximation as in Eq.(14) of [22], As will be explained in Section 3.2, however, this will lead to a more complex general-form QAP.

Denote $E_k[p, q]$ as the expectation in Eq.(8), which can be evaluated as follows:

Proposition 1. An approximation to $E_k[p, q]$ is

$$\tilde{E}_k[p, q] = \frac{4\sigma_R^2 + \beta_{h_1} \epsilon_k[p, q] v \exp(v) Ei(v)}{u} \quad (9)$$

where

$$u = 4\sigma_R^2 + \beta_{h_1}\epsilon_k[p, q], \quad (10a)$$

$$v = \frac{4\sigma_2^2}{\tilde{\alpha}^2\beta_{g_2}u}, \quad (10b)$$

$$\tilde{\alpha} = \sqrt{\frac{P_R}{\beta_{h_1}P_1 + \beta_{h_2}P_2 + P_R}}, \quad (10c)$$

and $Ei(x) = \int_x^\infty e^{-t}/t dt$ is the exponential integral function [23].

Proof. See Appendix. \square

3.2. The Successive Quadratic Assignment Problem

Our MoDiv design is based on the approximated BER minimization criterion. As it is impossible to know the number of actual retransmission m in advance, we formulate a sequence of M optimization problems as in [12], in which ψ_m is optimized to minimize the approximated BER given $\psi_1, \dots, \psi_{m-1}$ without expecting future retransmissions. The

$$\min_{\psi^{(m)}|\psi^{(k)}, k=0, \dots, m-1} \tilde{P}_{BER}^{(m)}, \quad m = 1, \dots, M \quad (11)$$

where $\tilde{P}_{BER}^{(m)}$ denotes the approximated version of Eq.(6) evaluated with Eq.(8)(9).

In order to rewrite Eq.(11) into a S-QAP formulation, we denote $\mathbf{x}^{(m)} = \{x_{pi}^{(m)}|p, i = 0, \dots, Q-1\}$ as the permutation matrix representing ψ_m :

$$x_{pi}^{(m)} = \begin{cases} 1, & \text{if } \psi_m[p] = \psi_0[i] \\ 0, & \text{otherwise.} \end{cases} \quad (12)$$

Denote the constraint sets

$$\mathcal{P} = \left\{ \mathbf{x} : \sum_{p=0}^{Q-1} x_{pi} = 1, x_{pi} \in \{0, 1\} \right\}, \quad (13a)$$

$$\mathcal{I} = \left\{ \mathbf{x} : \sum_{i=0}^{Q-1} x_{pi} = 1, x_{pi} \in \{0, 1\} \right\}. \quad (13b)$$

Then the MoDiv design problems in Eq.(11) can be formulated into a S-QAP as follows:

$$\begin{aligned} \min_{\mathbf{x}^{(m)}} & \sum_{p=0}^{Q-1} \sum_{i=0}^{Q-1} \sum_{q=0}^{Q-1} \sum_{j=0}^{Q-1} f_{pq}^{(m)} d_{ij} x_{pi}^{(m)} x_{qj}^{(m)}, \\ \text{s.t. } & \mathbf{x}^{(m)} \in \mathcal{P} \cap \mathcal{I}. \end{aligned} \quad (14a)$$

in which the “flow” matrix $f_{pq}^{(m)}$ and the “distance” matrix d_{ij} are defined as

$$f_{pq}^{(m)} = \frac{B[p, q]}{Q} \tilde{P}_{PEP}^{(m-1)}(q|p) \quad (15a)$$

$$d_{ij} = \tilde{E}_0[i, j] \quad (15b)$$

Note that here we assume all channel and noises to be stationary across all retransmissions, so d_{ij} only needs to be evaluated once. On the other hand, $f_{pq}^{(m)}$ can be computed recursively along solving the S-QAP, since

$$\tilde{P}_{PEP}^{(m)}(q|p) = \sum_{i=0}^{Q-1} \sum_{j=0}^{Q-1} \tilde{P}_{PEP}^{(m-1)}(q|p) d_{ij} \hat{x}_{pi}^{(m)} \hat{x}_{qj}^{(m)} \quad (16a)$$

$$\tilde{P}_{PEP}^{(-1)}(q|p) = \frac{1}{2} \quad (16b)$$

where $\hat{\mathbf{x}}^{(m)}$ is the solution to Eq.(14a).

In our S-QAP formulation, each KB-form QAP is defined with two Q -by- Q matrices, and only one of them needs to be updated. Should we adopt the more accurate approximation [22] in Eq.(7), each QAP would be in general-form which is defined with one Q^4 matrix. Although this 4-dimensional matrix can still be updated iteratively using a few Q -by- Q matrices in a sequential manner, the solution to the general-form QAP is usually more complicated. With the S-QAP in KB form, we are able to handle much larger constellation with an efficient robust taboo search algorithm [20]. Other numerical approaches to solve KB-QAP include simulated annealing (SA) [24], ant-colony [25] and so forth. Finally, we note that the MoDiv design can be precomputed offline and stored in S_1 and S_2 as it depends only on statistical CSI.

4. NUMERICAL RESULTS

5. CONCLUSION

6. APPENDIX: PROOF OF PROPOSITION 1

The proof of Proposition 1 is generally based on Eq.(43) of [26]. Firstly, by adopting the heuristic approximation in [27], the random variable $\alpha^{(k)}$ is replaced with constant $\tilde{\alpha}$ in $E_k[p, q]$, then we have

$$\begin{aligned} E_k[p, q] & \approx \mathbb{E}_{\gamma_2} \left[\mathbb{E}_{\delta_1|\gamma_2} \left[\exp \left(-\frac{\tilde{\alpha}^2 \epsilon_k[p, q] \gamma_2 \delta_1}{4(\sigma_2^2 + \tilde{\alpha}^2 \sigma_R^2 \gamma_2)} \right) \right] \right] \\ & = \mathbb{E}_{\gamma_2} \left[\left(1 + \frac{\tilde{\alpha}^2 \epsilon_k[p, q] \beta_{h_1} \gamma_2}{4(\sigma_2^2 + \tilde{\alpha}^2 \sigma_R^2 \gamma_2)} \right)^{-1} \right]. \end{aligned} \quad (17)$$

As δ_1, γ_2 both follow exponential distribution, Eq.(9) is derived by evaluating the above expectation with Eq.(3.352.4) of [23].

7. REFERENCES

- [1] A.M. Cipriano, P. Gagneur, G. Vivier, and S. Sezginer, “Overview of ARQ and HARQ in beyond 3G systems,” in *Personal, Indoor and Mobile Radio Communications Workshops (PIMRC Workshops), 2010 IEEE 21st International Symposium on*, Sept 2010, pp. 424–429.

- [2] F. Iannello and O. Simeone, "Throughput analysis of type-i harq strategies in two-way relay channels," in *Information Sciences and Systems, 2009. CISS 2009. 43rd Annual Conference on*, March 2009, pp. 539–544.
- [3] Jinho Choi, Duc To, Ye Wu, and Shugong Xu, "Energy-delay tradeoff for wireless relay systems using harq with incremental redundancy," *Wireless Communications, IEEE Transactions on*, vol. 12, no. 2, pp. 561–573, February 2013.
- [4] Kun Xu, Yuanyuan Gao, Youyun Xu, and Weiwei Yang, "Diversity-multiplexing tradeoff analysis of a two-way relaying channel with hybrid arq over rayleigh fading channels," *Vehicular Technology, IEEE Transactions on*, vol. 63, no. 3, pp. 1504–1510, March 2014.
- [5] P. Popovski and H. Yomo, "Wireless network coding by amplify-and-forward for bi-directional traffic flows," *Communications Letters, IEEE*, vol. 11, no. 1, pp. 16–18, Jan 2007.
- [6] Zhenyuan Chen, Qiushi Gong, Chao Zhang, and Guo Wei, "Arq protocols for two-way wireless relay systems: Design and performance analysis," *International Journal of Distributed Sensor Networks*, vol. 2012, pp. 980 241–1–980 241–13, 2012.
- [7] Wei Guan and K.J.R. Liu, "Two-way network-coded relaying with delay constraint," *Wireless Communications, IEEE Transactions on*, vol. 14, no. 1, pp. 191–204, Jan 2015.
- [8] D. Chase, "Code combining—a maximum-likelihood decoding approach for combining an arbitrary number of noisy packets," *Communications, IEEE Transactions on*, vol. 33, no. 5, pp. 385–393, May 1985.
- [9] 3GPP TS25.308, "UMTS HSDPA Overall description; Stage 2 (Release 12)," Jan. 2015, v12.2.0.
- [10] Stefania Sesia, Issam Toufik, and Matthew Baker, *LTE: the UMTS long term evolution*, Wiley Online Library, 2009.
- [11] G. Benelli, "A new method for the integration of modulation and channel coding in an ARQ protocol," *IEEE Trans. Commun.*, vol. 40, no. 10, pp. 1594–1606, Oct 1992.
- [12] Harvind Samra, Zhi Ding, and P.M. Hahn, "Symbol mapping diversity design for multiple packet transmissions," *IEEE Trans. Commun.*, vol. 53, no. 5, pp. 810–817, May 2005.
- [13] K.G. Seddik, A.S. Ibrahim, and K.J.R. Liu, "Transmodulation in wireless relay networks," *IEEE Commun. Lett.*, vol. 12, no. 3, pp. 170–172, Mar 2008.
- [14] M.N. Khormuji and E.G. Larsson, "Rate-optimized constellation rearrangement for the relay channel," *IEEE Commun. Lett.*, vol. 12, no. 9, pp. 618–620, Sep 2008.
- [15] Jin Woo Kim, H.S. Lee, J.Y. Ahn, and C.G. Kang, "Design of signal constellation rearrangement (CoRe) for multiple relay links," in *Proc. IEEE GLOBECOM*, Nov 2009, pp. 1–6.
- [16] Hyun-Seok Ryu, Jun-Seok Lee, and C.G. Kang, "BER analysis of constellation rearrangement for cooperative relaying networks over Nakagami- m fading channel," in *Proc. IEEE Int. Commun. Conf. (ICC)*, Jun 2011, pp. 1–5.
- [17] Tjalling C Koopmans and Martin Beckmann, "Assignment problems and the location of economic activities," *Econometrica: journal of the Econometric Society*, pp. 53–76, 1957.
- [18] Una Benlic and Jin-Kao Hao, "Memetic search for the quadratic assignment problem," *Expert Systems with Applications*, vol. 42, no. 1, pp. 584–595, 2015.
- [19] Rainer E Burkard, Stefan E Karisch, and Franz Rendl, "QAPLIB—a quadratic assignment problem library," *Journal of Global optimization*, vol. 10, no. 4, pp. 391–403, 1997.
- [20] E Taillard, "Robust taboo search for the quadratic assignment problem," *Parallel computing*, vol. 17, no. 4, pp. 443–455, 1991.
- [21] John G Proakis, "Digital communications. 1995," *McGraw-Hill, New York*.
- [22] M. Chiani, D. Dardari, and Marvin K. Simon, "New exponential bounds and approximations for the computation of error probability in fading channels," *Wireless Communications, IEEE Transactions on*, vol. 2, no. 4, pp. 840–845, July 2003.
- [23] Daniel Zwillinger, *Table of integrals, series, and products*, Elsevier, 2014.
- [24] David T. Connolly, "An improved annealing scheme for the {QAP}," *European Journal of Operational Research*, vol. 46, no. 1, pp. 93 – 100, 1990.
- [25] L. M. Gambardella, D Taillard, and M. Dorigo, "Ant colonies for the quadratic assignment problem," *The Journal of the Operational Research Society*, vol. 50, no. 2, pp. 167–176, 1999.
- [26] Yang Han, See Ho Ting, Chin Keong Ho, and Woon Hau Chin, "Performance bounds for two-way amplify-and-forward relaying," *Wireless Communications, IEEE Transactions on*, vol. 8, no. 1, pp. 432–439, Jan 2009.

- [27] Yindi Jing and B. Hassibi, "Distributed space-time coding in wireless relay networks," *Wireless Communications, IEEE Transactions on*, vol. 5, no. 12, pp. 3524–3536, December 2006.