

Advanced Engineering Analysis of Grounded Copper Supercoil Systems: Electromagnetic Properties, Winding Geometries, and Safety Architectures

Geometry and Topology of Supercoil and Helical Copper Windings

The architectural design of electrical machine windings and electromagnetic inductors relies fundamentally on the spatial arrangement of conductive pathways. Advanced winding topologies—ranging from traditional orthocyclic and continuous layer configurations to double-helix supercoil and sine-shaped helical structures—dictate the ultimate limits of power density, thermal dissipation, volumetric fill factor, and parasitic reactive elements.

In a conventional helical coil winding, insulated wire is wound uniformly around a cylindrical or conical former in successive layers. The direction of coil progression alternates between right-handed and left-handed helices across adjacent layers, allowing the conductors of an upper layer to rest within the natural inter-turn troughs formed by the underlying layer. While this structural interlocking provides mechanical stability, it introduces periodic crossover zones where the conductor must step across previous turns. These winding steps can occupy up to 60° of the coil circumference on round bobbins and congregate predominantly on the smaller face of rectangular bobbins, creating localized mechanical stress and non-uniform electromagnetic field distributions.

For maximum space utilization in constrained winding windows, orthocyclic winding represents the theoretical upper efficiency limit for round conductors. In an orthocyclic arrangement, wires form a hexagonal close-packed array where each upper turn rests precisely within the groove of two lower turns for over 300° of the coil circumference. In contrast, standard helical winding layers alternate between right-handed and left-handed lay directions, causing conductors to cross over one another and creating periodic inter-layer air gaps or voids. The orthocyclic dense packing structure achieves copper fill factors (K_{fill}) reaching up to 90%. This high fill factor maximizes the magnetic flux density B for a given window area according to Ampère's Law:

$$\oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 \mu_r I_{\text{enclosed}} = \mu_0 \mu_r (J \cdot A_{\text{window}} \cdot K_{\text{fill}})$$

where J is the current density, A_{window} is the stator or core window area, and K_{fill} is the copper fill factor. However, the thermal resistance of an orthocyclic winding increases along the radial axis because the dense wire packing leaves minimal voids for dielectric fluid circulation or convective heat removal.

To resolve the thermal and spatial constraints associated with conventional end-windings, advanced helical supercoil windings employ a double-helix geometry. In a double-helix supercoil, the winding comprises two sets of helical conductors progressing axially in opposite directions around a central axis, effectively functioning as skewed conductive bars with a skew angle equivalent to 180 electrical degrees, or one full pole-pitch.

The primary operational advantage of this topology is the complete elimination of passive end-windings. In traditional slotted electrical machines, end-windings account for up to 30% to 50% of the total phase resistance and copper weight without contributing to electrodynamic torque generation. By utilizing a continuous skewed double helix, the end-connections are integrated directly into the active axial length of the structure.

The electromagnetic behavior of a double-helix winding is governed by its skew factor (k_{skew}), phasebelt distribution factor (k_d), and phase count. The classical skew factor for a 180-degree electrical skew is expressed mathematically as:

$$k_{\text{skew}} = \frac{\sin(\pi / 2)}{\pi / 2} = \frac{2}{\pi} \approx 0.6366$$

The total fundamental winding factor k_w is the product of k_{skew} and k_d :

$$k_w = k_{\text{span}_61}(\text{start_span})(\text{span}_61)(\text{end_span})d \cdot k_{\text{skew}} = k_d \cdot \left(\frac{2}{\pi} \right)$$

Increasing the phase count suppresses higher-order space harmonics in the air-gap magnetomotive force (MMF) wave. Transitioning from a 3-phase to a 6-phase double-helix architecture yields approximately a 3.5% increase in the net fundamental winding factor due to the narrower phasebelt width, partially offsetting the lower intrinsic skew factor.

Winding Topology	Copper Fill Factor (K_{fill})	Relative End-Winding Resistance	Primary Thermal Dissipation Mechanism	Structural & Electromagnetic Strengths	Primary Operational Limitations
Orthocyclic Winding	80% – 90%	High (Standard passive overhangs)	Conductive through inter-turn insulation to outer surfaces	Highest magnetic field strength per unit volume; highly uniform mechanical profile.	Extreme manufacturing precision required; poor internal fluid circulation.
Helical Double-Helix (Supercoil)	45% – 60% (Air-gap/Slots)	Zero (Passive end-windings eliminated)	Direct axial and radial convection via integrated oil channels	Total elimination of end-turn copper mass; reduced R_{phase} ; low synchronous inductance.	Lower fundamental winding factor ($k_{\text{skew}} \approx 0.6366$); requires air-gap construction.
Screw / Helical Multi-Strand	50% – 65%	Moderate	Forced convective cooling via oil ducts between parallel strands	Superior thermal endurance under high continuous current densities.	Higher leakage inductance; complex axial transposition requirement.
Disk / Pie Winding	60% – 70%	High	Radial oil channels between stacked annular disks	High mechanical withstand against axial short-circuit	High inter-disk voltage stress; pronounced capacitive inter-turn

Winding Topology	Copper Fill Factor (K_{fill})	Relative End-Winding Resistance	Primary Thermal Dissipation Mechanism	Structural & Electromagnetic Strengths	Primary Operational Limitations
				impulse forces.	coupling.
Twisted Multi-Wire	55% – 65%	High	Oil-immersed convective transfer	Extreme surge insulation resistance (110–1200 kV applications).	Complex automated twisting machinery; low volumetric efficiency.
Wild / Random Winding	30% – 50%	Variable	Uncontrolled conduction through irregular wire voids	Low cost, rapid automated assembly for small wire gauges.	Non-uniform hot-spot generation; unpredictable inter-turn voltage stress.

Electromagnetic Dynamics, Loss Mechanisms, and Power Density Optimization

In high-power density applications—such as slotless partially superconducting electric machines for megawatt-class aviation propulsion—the interaction between copper supercoil windings and the surrounding magnetic circuit diverges substantially from conventional iron-core machines. Slotless architectures intentionally eliminate stator teeth to eliminate magnetic core saturation and cogging torque, placing the copper supercoil directly within the main air-gap magnetic path. The absence of stator slots exposes the copper conductors directly to the unshielded rotating magnetic field of the rotor, subjecting the copper turns to severe alternating cross-flux. The radial attenuation of flux in an air-gap machine is inversely proportional to the radius raised to the power of the pole-pair count plus one. Consequently, a two-pole machine experiences a modest quadratic radial flux attenuation, retaining substantial magnetic coupling across the entire radial depth of the supercoil, whereas high pole-count machines suffer from steep flux decay that starves the outer winding layers of usable flux linkage. This spatial distribution of the air-gap magnetic flux density $B(r, \theta)$ attenuating radially from the rotor surface is modeled by:

$$B(r) = B_{\text{rotor}} \left(\frac{r_{\text{rotor}}}{r} \right)^{p+1}$$

where p is the pole-pair count and r is the radial position within the air-gap. For $p=1$ (a 2-pole machine), $B(r)$ decays as r^{-2} , whereas for $p=4$ (an 8-pole machine), it decays as r^{-5} , causing a severe reduction in flux linkage across the outer turns of the winding.

The electrical performance of the double-helix supercoil is further dictated by skin and proximity effects operating under elevated fundamental frequencies. The skin depth δ of copper as a function of operating frequency f , permeability μ , and electrical conductivity σ is defined as:

$$\delta = \frac{1}{\sqrt{\pi f \mu \sigma}}$$

When the individual conductor thickness exceeds 2δ , high-frequency AC current is restricted to the outer periphery of the wire, drastically increasing the effective AC resistance R_{ac} and generating parasitic eddy losses. In planar magnetic components, flat copper foils

are positioned horizontally between ferrite core halves separated by a discrete air gap. The localized magnetic fringing field emanating from the gap penetrates the broad face of the copper foil perpendicularly, inducing intense intra-conductor eddy current loops unless attenuated by localized foil tapering or active geometry shaping.

To mitigate these losses, advanced manufacturing techniques utilize variable-thickness helical foil geometries and additive manufacturing to create optimized "sine-shaped" helical windings.

To combat high-frequency edge losses in gapped-core planar transformers, the conductor thickness of the helical foil is contoured along its axial path, thinning the foil in regions subjected to intense fringing cross-flux near the core gap to minimize local eddy current generation while maintaining full conductor cross-section in regions dominated by pure axial transport. The local skew angle α for a helical machine with stack length L and pole count p is defined as:

$$\alpha = \frac{\alpha_p \cdot p}{4}$$

where α_p is the physical angle of twist along the axial length L .

In slotless partially superconducting motor topologies—such as 2 MW aircraft propulsion motors operating at elevated stator voltages—the double-helix supercoil provides extremely low phase resistance and minimal leakage inductance due to the absence of slot-leakage pathways. The total synchronous inductance L_s is given by:

$$L_s = L_{\text{airgap}} + L_{\text{end}} \approx L_{\text{airgap}}$$

Because the end-winding inductance $L_{\text{end}} \approx 0$, the machine exhibits low electrical time constants ($\tau = L/R$), facilitating high-bandwidth vector control and high dynamic response, while requiring precise fault-current limiting strategies during system-level short circuits.

Grounding Safety Design, Stray Capacitance, and Transient Protection

Designing grounded copper supercoils and high-voltage coil assemblies requires systematic management of distributed parasitic capacitances, internal insulation stress, and transient ground-fault currents. Electrically, a grounded coil operates as a lumped ladder network comprising series turn inductances shunted by distributed inter-turn and inter-layer capacitances, with distinct capacitive paths routed to the grounded structural frame.

Stray capacitance within a grounded copper supercoil manifests through three primary physical mechanisms:

- **Inter-turn capacitance (C_{tt}):** Distributed capacitive coupling occurring between adjacent conductive turns within the same winding layer.
- **Inter-layer capacitance (C_{ll}):** Capacitance across dielectric insulation barriers separating concentric or stacked winding layers.
- **Coil-to-ground capacitance (C_{sg}):** Capacitance formed between the conductive turns and the grounded metallic structural frame, stator core, or outer shield enclosure.

The net equivalent stray capacitance C_s creates an LC parallel resonant frequency ($\omega_0 = 1/\sqrt{L C_s}$). When high di/dt switching transients—such as those generated by Silicon Carbide (SiC) or Gallium Nitride (GaN) solid-state power converters—impinge on the coil terminals, the high-frequency voltage stress distributes non-uniformly across the turns. The initial voltage surge distribution is governed by the capacitive distribution factor α_{cap} :

$$\alpha_{\text{cap}} = \sqrt{\frac{C_{\text{sg}}}{C_{\text{tt}}}}$$

When $\alpha_{\text{cap}} \gg 1$, over 80% of the terminal surge voltage drops across the initial input turns adjacent to the line terminal, concentrating extreme dielectric stress across the turn-to-turn enamel insulation rather than establishing a linear gradient across the full turn length.

Establishing solid ground bonds provides an explicit, low-impedance reference path that safely discharges these high-frequency parasitic displacement currents to Earth, preventing dangerous potential buildup on floating conductive structures.

Grounding secondary circuits and coil enclosures must strictly comply with established industry standards, including IEEE C57 series guides, IEC safety directives, and Underwriters Laboratories (UL) specifications. Standard ground safety architectures employ low-impedance copper ground straps sized to carry maximum prospective short-circuit currents without exceeding the thermal melting limits of the conductor.

During a line-to-ground fault event, the short-circuit current (I_{sc}) flowing through the grounded supercoil can exceed nominal operational ratings by multiple orders of magnitude. To prevent catastrophic thermal degradation and destructive electrodynamic forces (which scale quadratically with current, $F \propto I_{sc}^2$), current-limiting reactors (CLRs) are placed in series with grounding or power supply lines. These air-core or oil-immersed reactors introduce controlled inductive reactance (X_L

$=\omega L_{CLR}$) to limit the peak fault current below the rated interrupting capacity ($I_{interrupt}$) of the upstream protection hardware:

$$I_{sc, \text{ limited}} = \frac{V_{\text{system}}}{\sqrt{R_{\text{total}}^2 + (X_{\text{system}} + X_{CLR})^2}}$$

System Voltage Class	Target Insulation System & Dielectric Media	Primary Stray Capacitance Mechanisms	Standard Grounding Configuration	Compliance Standards
Low Voltage (< 1 kV AC / 1.5 kV DC)	Enamel (Polyurethane / Polyamide-imide), Paper Wrapping	High inter-turn (C_{tt}); low ground capacitance (C_{sg})	Solid grounding / Direct Earth bond	IEEE Secondary Grounding / UL 508C
Medium Voltage (1 kV – 35 kV)	Cast Epoxy Resin, Nomex/Mylar, Oil-immersed channels	Balanced inter-layer (C_{ll}) and frame capacitance (C_{sg})	Low-resistance grounding (LRG) or neutral grounding reactor	IEEE C57.13 / IEC 60076-3
High / Ultra-High Voltage (110 kV – 1200 kV)	Multi-strand twisted wire, Kraft paper, Transformer Oil	Dominant coil-to-tank ground capacitance (C_{sg})	Solid multi-point grounding with current-limiting reactors	IEC 60076-5 / IEEE C57.12.00
Cryogenic / Superconducting Systems	Kapton/Polyimide tape, Vacuum Insulation, Liquid Helium/Nitrogen	Inter-coil and cryostat vacuum-barrier capacitive coupling	High-Impedance Active Grounding with Quench Protection Dump Resistors	IEC 61788 / IEEE Trans. Applied Superconductivity

In high-power transformer and supercoil reactor implementations, the insulation architecture combines physical paper wrapping around high-purity copper conductors with circulating dielectric oil. The oil serves a dual functional role: it acts as a high-dielectric breakdown barrier exceeding 30 kV/mm and circulates through engineered axial screw or helical channels to

evacuate heat directly from the conductor surfaces.

High-Density Applications and Advanced Manufacturing

The specialized electromagnetic properties and thermal characteristics of grounded copper supercoils have led to their adoption across multiple high-performance electrical engineering sectors. The operational domain of grounded supercoils spans medical charged-particle steering gantries requiring ultra-precise dipole fields, aerospace electric propulsion systems demanding slotless megawatt-class power density, and utility-scale power electronics utilizing planar filter inductors and high-voltage transformers.

Medical Accelerators and Charged Particle Therapy

In modern proton and heavy-ion (carbon) cancer therapy systems, charged particle beams must be focused and steered along curvilinear trajectories using precise magnetic fields.

Conventional resistive magnets require multi-story gantries weighing over 100 tons to achieve the bending forces required for high-energy particle beams. By deploying high-field double-helix supercoil configurations—frequently combining high-temperature superconductors with high-purity copper stabilizer matrixes—the overall physical envelope and mass of the beam-steering magnets are dramatically reduced.

The precise spatial modulation of the skew angle in double-helix windings eliminates unwanted higher-order multipole field errors, producing clean, uniform dipole or quadrupole steering fields within a compact assembly. This structural miniaturization enables charged particle therapy gantries to be deployed within standard clinical treatment facilities, lowering installation costs and expanding patient access.

Aircraft Propulsion and Slotless Superconducting Machines

Electric aviation propulsion systems require power-to-weight ratios exceeding 10 kW/kg at megawatt scales. Partially superconducting machines address this requirement by pairing superconducting rotor field windings with high-conductivity copper helical stator supercoils. Because iron teeth are removed to minimize weight, the stator relies on self-supporting, sine-shaped additive-manufactured copper windings.

These windings are optimized via continuous spatial skew variations that equalize the current distribution across the conductor profile. Utilizing additive manufacturing allows internal cooling channels to be integrated directly into the copper structure, enabling direct liquid cooling at heat flux rates exceeding 100 W/cm^2 .

Planar Helical Power Electronics

At the circuit component level, planar helical foil windings are widely utilized in high-frequency inductors and power transformers for renewable energy inverters and aerospace power converters. In planar components, flat copper foils are stacked on printed circuit boards or gapped ferrite cores. By applying variable conductor thickness shaping, designers counteract localized flux concentrations caused by core gaps, reducing total copper losses (I^2R_{dc} +

P_{AC}) by up to 40% compared to uniform-thickness foil designs.

Precision Manufacturing and Quality Control Standards

The industrial fabrication of copper supercoils requires strict quality control across every stage of production:

- **Raw Rod Extrusion & Slitting:** Oxygen-free high-conductivity (OFHC) copper rods are extruded and slit into rectangular or circular profiles matching exact window cross-sections.
- **Precision Enameling and Paper Wrapping:** Conductors are coated with multi-layer synthetic enamels (e.g., polyimide) or wrapped with high-density paper tapes to achieve target dielectric withstand voltages.
- **Automated Winding with Dynamic Tensioning:** Automated CNC winding machinery maintains closed-loop tension control to prevent insulation degradation or micro-fissuring during orthocyclic or helical layering.
- **Vacuum Pressure Impregnation (VPI) & Oil Filling:** Completed coil assemblies undergo VPI with dielectric resins or are submerged in vacuum-degassed transformer oil to eliminate internal air voids, suppressing partial discharge during operation.
- **Quality Control Verification:** Finished assemblies undergo electrical testing, including high-potential (Hi-Pot) dielectric testing, surge impulse comparison, precision LCR meter inter-turn capacitance profiling, and calorimetric loss verification.

Engineering Synthesis and Strategic Trade-Off Analysis

Designing and integrating grounded copper supercoil systems requires balancing interdependent electromagnetic, thermal, mechanical, and safety parameters. System optimization demands balancing electromagnetic performance, thermal dissipation, and safety isolation. Elevating current density increases electrodynamic output but requires dedicated liquid channels that reduce the geometric fill factor, while strengthening dielectric isolation against transient surge voltages increases physical spacing and parasitic ground capacitance. Maximizing the copper fill factor ($K_{fill} \approx 90\%$) through orthocyclic winding minimizes nominal DC conduction losses (I^2R_{dc}) within a given core volume. However, the dense consolidation of conductors eliminates internal cooling channels, increasing thermal resistance and creating internal hot spots. Conversely, double-helix supercoils and multi-strand screw windings introduce dedicated axial oil channels that reduce the effective fill factor ($K_{fill} \approx 45\% - 65\%$), but increase the maximum allowable continuous current density (J_{max}) due to direct convective heat removal.

Furthermore, the double-helix supercoil completely eliminates end-winding copper mass and its associated passive I^2R losses, significantly reducing total active mass. However, because the double-helix geometry requires a slotless, air-gap stator construction, the effective magnetic gap between the rotor poles and the stator iron is significantly enlarged. This expanded air gap decreases the fundamental magnetic flux linkage, requiring higher rotor pole excitation to maintain equivalent electromagnetic torque output.

Finally, placing winding layers in close physical proximity maximizes mutual inductive coupling, which is highly desirable for compact energy storage. However, this spatial proximity elevates inter-turn and inter-layer stray capacitance (C_{tt} , C_{ll}). Under fast inverter switching

transients (dV/dt), high stray capacitance induces non-linear voltage stress distributions across the initial turns and drives displacement currents into the ground system. Incorporating grounded electrostatic shields or increasing dielectric insulation thickness mitigates capacitive voltage surges, protecting the assembly from breakdown while slightly reducing net power density.

Grounded copper supercoils represent an optimized convergence of advanced winding geometry, electromagnetic field control, and high-voltage safety design. Whether implemented in megawatt-class electric aircraft motors, miniaturized particle therapy magnets, or high-frequency grid inductors, managing the trade-offs between winding topology, current density, parasitic capacitance, and standards-compliant grounding ensures optimal performance, thermal stability, and operational reliability.

Quellenangaben

1. The Basics of Coil Winding - Custom Coils, Inc., <https://ccoils.com/blog/the-basics-of-coil-winding/>
2. Coil winding technology - Wikipedia, https://en.wikipedia.org/wiki/Coil_winding_technology
3. Coil Winding Design Guide: Types, Tips, and Machines [2026], <https://grwinding.com/coil-winding-design/>
4. [No. 48] Helical winding - JMAG, https://www.jmag-international.com/engineers_diary/048/
5. Design of Helical Winding for Slotless Partially Superconducting, https://www.researchgate.net/publication/379742197_Design_of_Helical_Winding_for_Slotless_Partially_Superconducting_Electric_Machines_for_Aircraft_Propulsion
6. US20090206974A1 - Helical Coil Design and Process For Direct, <https://patents.google.com/patent/US20090206974A1/en>
7. Overview of helical foil winding design for planar inductors, <https://ujcontent.uj.ac.za/esploro/outputs/conferencePaper/Overview-of-helical-foil-winding-design/9912445207691>
8. IEEE Guide For Grounding of Instrument Transformer Secondary, <https://pdfcoffee.com/ieee-guide-for-grounding-of-instrument-transformer-secondary-circuits-and-cases-pdf-free.html>
9. IEEE Standard Requirements, Terminology,, <https://ewh.ieee.org/soc/pes/switchgear/minutes/2010-1/S10HVCBa11.pdf>
10. Copper Coil Winding Process Guide | PDF - Scribd, <https://www.scribd.com/presentation/918841966/ko-myo>
11. IEEE Recommended Practice for Powering and Grounding Sensitive, <http://ieeexplore.ieee.org/iel1/2838/5834/00223448.pdf>